

| | |
|--|--|
| Project Title Date Submitted | IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 > MU-MIMO: Demodulation at the Mobile Station 2009-01-05 |
| Source(s) | M. A. (Amir) Khojastepour (amir@nec-labs.com) NEC 4 independence Way, suite 200 Princeton, NJ 08540 |
| Re: Abstract | IEEE C802.16m-08/052 Call for SDD comments and contributions on 802.16m SDD (802.16m-08/003r6) This document proposes that each MU-MIMO user may be informed about some scheduling parameters of other co-scheduled MU-MIMO users, such as their beamforming vectors, power levels and modulations. |
| Purpose Notice Release Patent Policy | Discussion and Decision <i>This document does not represent the agreed views of the IEEE 802.16 Working Group or any of its subgroups.</i> It represents only the views of the participants listed in the "Source(s)" field above. It is offered as a basis for discussion. It is not binding on the contributor(s), who reserve(s) the right to add, amend or withdraw material contained herein. The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16 The contributor is familiar with the IEEE-SA Patent Policy and Procedures: < http://standards.ieee.org/guides/bylaws/sect6-7.html#6 > and < http://standards.ieee.org/guides/opman/sect6.html#6.3 >. Further information is located at < http://standards.ieee.org/board/pat/pat-material.html > and < http://standards.ieee.org/board/pat > . |

MU-MIMO: Demodulation at the Mobile Station

N. Prasad, M. A. Khojastepour, M. Jiang, X. Wang and S. Rangarajan

I. INTRODUCTION

In this document, we consider MU-MIMO where the base station (BS) may schedule several mobile stations on the same resource unit. Each scheduled mobile station (MS) is served only a single stream via beamforming. We examine the various demodulator options that are available to a scheduled MS (or user) depending on the information it has about the beam vectors, power levels and modulations used to serve the co-scheduled users. We assume that each scheduled user is informed about the beam vector, power level as well as the MCS assigned to it by the BS.

Consider the received signal model on any subcarrier at a user terminal k , which is equipped with N receive antennas and where the BS has M transmit antennas,

$$\mathbf{y}_k = \mathbf{H}_k \mathbf{x} + \mathbf{v}_k, \quad (1)$$

where $\mathbf{H}_k \in \mathbb{C}^{N \times M}$ is the channel matrix and $\mathbf{v}_k \sim \mathcal{CN}(\mathbf{0}, \mathbf{I})$ is the additive noise. The signal vector \mathbf{x} transmitted by the BS can be expanded as

$$\mathbf{x} = \sum_{k \in \mathcal{S}} \mathbf{g}_k s_k \quad (2)$$

where \mathcal{S} is the set of users that are scheduled on the same resource unit, \mathbf{g}_k is the beamforming vector and s_k is the data symbol corresponding to user $k \in \mathcal{S}$. The beamforming vectors are selected from a codebook \mathcal{C} of unit-norm vectors. The sum power constraint is given by $E[\mathbf{x}^\dagger \mathbf{x}] = \sum_{k=1}^{|\mathcal{S}|} E[|s_k|^2] \leq \rho$.

II. LINEAR COMBINER

A popular linear combiner is the match filter (a.k.a. maximum ratio combiner (MRC)) which is optimal in the absence of interference from the signals intended for the other co-scheduled users. In order to employ this linear combiner, the user of interest (say user 1) does not need to know any information about the co-scheduled users and it can demodulate its own data by completely neglecting the co-channel interference resulting from the transmission intended for the other co-scheduled users. In particular, user 1 employs the unit norm combiner given by,

$$\mathbf{u} = \frac{\mathbf{H}_1 \mathbf{g}_1}{\|\mathbf{H}_1 \mathbf{g}_1\|}. \quad (3)$$

The received signal at user 1 post-combining can now be written as

$$\mathbf{u}_1^\dagger \mathbf{y}_1 = \mathbf{u}_1^\dagger \mathbf{H}_1 \mathbf{g}_1 s_1 + \sum_{k \in \mathcal{S}, k \neq 1} \mathbf{u}_1^\dagger \mathbf{H}_1 \mathbf{g}_k s_k + \tilde{v}_1 \quad (4)$$

and note that due to our normalization $E[|\tilde{v}_1|^2] = 1$. In order to compute the log-likelihood ratios (LLRs) for the coded bits corresponding to the symbol s_1 , the user can completely neglect the interference term $\sum_{k \in \mathcal{S}, k \neq 1} \mathbf{u}_1^\dagger \mathbf{H}_1 \mathbf{g}_k s_k$ and assume the SNR to be $\rho_1 \|\mathbf{H}_1 \mathbf{g}_1\|^2$, where $\rho_1 = E[|s_1|^2]$. Alternatively, an estimate of the true SINR can instead be determined. However, the accuracy of such an estimate depends on the number of sample observations available.

The MRC based demodulator can result in substantial performance degradation when the interference power is not negligible compared to that of the additive noise. This is particularly true at high SNR. In order to design a better linear combiner for such scenarios, a quantization error minimization approach is employed in [1]. In particular, assuming $N < M$, the linear combiner used by the MS is now given by

$$\mathbf{u}_1 = \frac{(\mathbf{g}_1^\dagger \mathbf{H}_1^+)^{\dagger}}{\|\mathbf{g}_1^\dagger \mathbf{H}_1^+\|} \quad (5)$$

where $\mathbf{H}_1^+ = \mathbf{H}_1^\dagger (\mathbf{H}_1 \mathbf{H}_1^\dagger)^{-1}$ denotes the pseudo-inverse. In general, the user can use any linear combiner \mathbf{u}_1 (which could have been pre-computed based only on the channel estimate \mathbf{H}_1). Upon using such a combiner, the resulting model is given by (4) and the LLRs can either be

computed by completely neglecting the interference and using the SNR $\rho_1 \|\mathbf{u}_1^\dagger \mathbf{H}_1 \mathbf{g}_1\|^2$ or by using an estimated SINR.

A. MMSE Linear Combiner

In some scenarios, each scheduled user can also deduce the beamforming vectors and power levels used to serve the other co-scheduled users. In this case, assuming that the transmit power is equally split among all scheduled users, user 1 can determine the optimal minimum mean squared error (MMSE) linear combiner as

$$\mathbf{u}_1 = \left(\mathbf{I} + \tilde{\rho} \sum_{k \in \mathcal{S}, k \neq 1} \mathbf{H}_1 \mathbf{g}_k \mathbf{g}_k^\dagger \mathbf{H}_1^\dagger \right)^{-1} \mathbf{H}_1 \mathbf{g}_1, \quad (6)$$

where $\tilde{\rho} = \frac{\rho}{|\mathcal{S}|}$. The resulting SINR is determined to be

$$\tilde{\rho} \mathbf{g}_1^\dagger \mathbf{H}_1^\dagger \left(\mathbf{I} + \tilde{\rho} \sum_{k \in \mathcal{S}, k \neq 1} \mathbf{H}_1 \mathbf{g}_k \mathbf{g}_k^\dagger \mathbf{H}_1^\dagger \right)^{-1} \mathbf{H}_1 \mathbf{g}_1. \quad (7)$$

III. NON-LINEAR DEMODULATORS

In order to further improve the performance, the user may employ non-linear demodulators. Suppose that the user knows the beamforming vectors and power levels used to serve the other co-scheduled users. Moreover, the user also knows the modulations used to serve some or all of the other co-scheduled users. In particular, let $\mathcal{J} \subseteq \mathcal{S}$ denote the set of users whose corresponding modulations are known to user 1 and clearly $1 \in \mathcal{J}$. Then, user 1 can first design a filter to suppress the interference from the signals intended for the other co-scheduled users not in \mathcal{J} to obtain the model

$$\mathbf{z} \triangleq \left(\mathbf{I} + \tilde{\rho} \mathbf{H}_1 \sum_{k \notin \mathcal{J}} \mathbf{g}_k \mathbf{g}_k^\dagger \mathbf{H}_1^\dagger \right)^{-1/2} \mathbf{y}_1 = \left(\mathbf{I} + \tilde{\rho} \mathbf{H}_1 \sum_{k \notin \mathcal{J}} \mathbf{g}_k \mathbf{g}_k^\dagger \mathbf{H}_1^\dagger \right)^{-1/2} \mathbf{H}_1 \sum_{k \in \mathcal{J}} \mathbf{g}_k s_k + \boldsymbol{\eta}, \quad (8)$$

and note that $E[\boldsymbol{\eta} \boldsymbol{\eta}^\dagger] = \mathbf{I}$. Letting $\mathbf{B} = \left(\mathbf{I} + \tilde{\rho} \mathbf{H}_1 \sum_{k \notin \mathcal{J}} \mathbf{g}_k \mathbf{g}_k^\dagger \mathbf{H}_1^\dagger \right)^{-1/2} \mathbf{H}_1 \mathbf{G}_{\mathcal{J}}$ with $\mathbf{G}_{\mathcal{J}} = [\mathbf{g}_k]_{k \in \mathcal{J}}$ denoting the $N \times |\mathcal{J}|$ matrix formed by the beam vectors employed to serve users in \mathcal{J} and $\mathbf{s}_{\mathcal{J}}$ denoting the $|\mathcal{J}| \times 1$ vector formed by the corresponding symbols transmitted to those

users, the model in (8) can be re-written as

$$\mathbf{z} = \mathbf{B}\mathbf{s}_{\mathcal{J}} + \boldsymbol{\eta}. \quad (9)$$

Now we can employ several suitable non-linear demodulators, such as the soft-output sphere decoder [2] and its recent variants over the model in (9). *The key point to be noted is that the LLRs need to be generated only for the coded bits in the symbol s_1 . Note that in order to generate these LLRs, we do not need any information about the coding rates employed to serve any user in \mathcal{J} . This is particularly useful since there are only three distinct modulations that can be used to serve each scheduled user. Also, no attempt is made to decode the codeword of any other user (apart from user 1) in \mathcal{J} .*

IV. DISCUSSION

It is evident that the linear combiner which requires no information about other co-scheduled users results in the least amount of (feedforward) signaling overhead. Such combiners rely on a large extent on the precoder employed by the transmitter (BS) to mitigate or remove the interference seen by them. If the BS has perfect knowledge of the channel matrix ¹ of each user on each subcarrier, it can employ a zero-forcing based precoder to ensure that each scheduled user sees no interference from transmission to other co-scheduled users. In such a scenario the MRC combiner is optimal.

However, in practical FDD systems with limited feedback, providing such perfect channel knowledge about each user to the BS is not possible, particularly in the wideband OFDMA based downlink, where each user's channel response matrix varies across subcarriers. Consequently, the users may need to employ more sophisticated demodulators to combat residual interference and help the system realize the benefit of multi-user MIMO. These sophisticated demodulators need the knowledge about some scheduling parameters of other co-scheduled users such as their beam vectors, power levels and modulations. Fortunately, such parameters for each scheduled user are anyway transmitted in the user-specific part of the unicast service control channel. The

¹As suggested in [1], each user can use a linear combiner to convert its channel matrix into an effective channel vector and report the latter to the BS.

signaling should be designed in an appropriate manner so that an MU-MIMO user can deduce such parameters of other co-scheduled MU-MIMO users.

REFERENCES

- [1] N.Jindal, "Antenna Combining for the MIMO Downlink Channel," *IEEE Trans. Wireless Communications*, Vol. 7, No. 10, pp. 3834-3844, Oct. 2008.
- [2] B. M. Hochwald and S. ten Brink, "Achieving near-capacity on a multiple-antenna channel," *IEEE Trans. Commun.*, vol. 51, pp. 389-399, Mar. 2003.

PROPOSED TEXT

[Modify the text in section 11.8.1.6.2 “Signaling Support for MU-MIMO”]

In the downlink MU-MIMO, the precoding matrix shall be signaled via explicit signaling if common demodulation pilots are used, or via dedicated pilots. Each scheduled MU-MIMO user may be informed about some scheduling parameters of other co-scheduled MU-MIMO users, such as their beam vectors, power levels and modulations. The exact choice of these scheduling parameters is FFS.