

Improved Support for Four-Sector Deployments in the PHY Structure (Section 15.3.5 and Section 15.3.8)

IEEE 802.16 Presentation Submission Template (Rev. 9)

Document Number:

C80216m-09_2532

Date Submitted:

2009-11-06

Source:

Bill Hillery, Fred Vook, Mark Cudak, Eugene Visotsky, Anup Talukdar

Email: fred.vook@motorola.com

Motorola

*<http://standards.ieee.org/faqs/affiliationFAQ.html>

Venue: Session #64 Atlanta Meeting

Re: P802.16m/D2 comments for LB30a

Area: Section 15.3.5 – DL PHY Structure and Section 15.3.8 – UL PHY Structure.

Purpose:

A large number of existing 802.16e deployments have four sectors. This contribution proposes modifications to the PHY structure to better support four-sector deployments.

Notice:

This document does not represent the agreed views of the IEEE 802.16 Working Group or any of its subgroups. It represents only the views of the participants listed in the “Source(s)” field above. It is offered as a basis for discussion. It is not binding on the contributor(s), who reserve(s) the right to add, amend or withdraw material contained herein.

Release:

The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE’s name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE’s sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.

Patent Policy:

The contributor is familiar with the IEEE-SA Patent Policy and Procedures:

<<http://standards.ieee.org/guides/bylaws/sect6-7.html#6>> and <<http://standards.ieee.org/guides/opman/sect6.html#6.3>>.

Further information is located at <<http://standards.ieee.org/board/pat/pat-material.html>> and <<http://standards.ieee.org/board/pat>>.

Introduction & Problem Statement

- A large number of existing 802.16e deployments are four-sector deployments.
 - Many of these deployments are 1x4x2 reuse (2 RF carriers with 4 sectors)
- The current PHY structure in the D2 draft does not adequately support four-sector deployments
- This contribution proposes changes that will provide support for four-sector deployments
 - Provides support for 2 partitions, which are useful for 4-sector deployments

Text Proposal

- Replace the last line of Tables 771 and 861 (20 MHz bandwidth) with the last two lines of the following:

DFPC	Frequency Partition	FPCT	FPS₀	FPS_i (i>0)
7	0:1:1:0	2	0	$N_{\text{PRU}} * 1/2$ (i=1,2), 0 (i=3)
8–15	<i>Reserved</i>			

Text Proposal (cont.)

- Replace the last line of Tables 772 and 862 (10 MHz bandwidth) with the last two lines of the following:

DFPC	Frequency Partition	FPCT	FPS₀	FPS_i (i>0)
6	0:1:1:0	2	0	$N_{\text{PRU}} * 1/2$ (i=1,2), 0 (i=3)
7	<i>Reserved</i>			

Text Proposal (cont.)

- Replace the last line of Tables 773 and 863 (5 MHz bandwidth) with the last two lines of the following:

DFPC	Frequency Partition	FPCT	FPS₀	FPS_i (i>0)
5	0:1:1:0	2	0	$N_{\text{PRU}} * 1/2$ (i=1,2), 0 (i=3)
6–7	<i>Reserved</i>			

Text Proposal (cont.)

- Modify Eq. 187 to:

$$K_{SB,FP_i} = \begin{cases} K_{SB} - (FPCT - 1)DFPSC & i = 0, FPCT = 4 \\ DFPSC & i > 0, FPCT = 3 \text{ or } 4 \\ K_{SB}/2 & i = 1, 2, FPCT = 2 \\ K_{SB} & i = 0, FPCT = 1 \end{cases}$$

When $FPCT = 2$, $DFPSC$ shall be zero.

- Modify Eq. 238 to:

$$K_{SB,FP_i} = \begin{cases} K_{SB} - (FPCT - 1)UFPSC & i = 0, FPCT = 4 \\ UFPSC & i > 0, FPCT = 3 \text{ or } 4 \\ K_{SB}/2 & i = 1, 2, FPCT = 2 \\ K_{SB} & i = 0, FPCT = 1 \end{cases}$$

When $FPCT = 2$, $UFPSC$ shall be zero.

Text Proposal (cont.)

- In section 15.3.5.3.1, p. 298, lines 46-52, replace “ $FP_i (i>0)$ ” with “ $FP_i (i>0, FPCT \neq 2)$ ” (3 locations)

Text Proposal (cont.)

- In section 15.3.5.3.1, p. 298, add the following paragraph before line 62 (before the paragraph containing Eq. 194):

When $FPCT=2$, $DCAS_{SB,i}$ and $DCAS_{MB,i}$ for $i=1$ and 2 are signaled using the $DCAS_{SB,0}$ and $DCAS_{MB,0}$ fields in the SFH. Since FP_0 and FP_3 are empty, $L_{SB-CRU,FP0} = L_{MB-CRU,FP0} = L_{DRU,FP0} = 0$ and $L_{SB-CRU,FP3} = L_{MB-CRU,FP3} = L_{DRU,FP3} = 0$. For $i=1$ and 2 ,

$$L_{SB-CRU,FPi} = N_1 DCAS_{SB,0}.$$

$L_{MB-CRU,FPi}$ is obtained using the mappings in Tables 774 through 776 for system bandwidths of 20MHz, 10MHz, and 5MHz, respectively.

Text Proposal (cont.)

- In section 15.3.8.3.1, p. 455, lines 49-53, replace “ $FP_i (i>0)$ ” with “ $FP_i (i>0, FPCT \neq 2)$ ” (3 locations)

Text Proposal (cont.)

- In section 15.3.8.3.1, p. 455, add the following paragraph before line 64:

When $FPCT=2$, $UCAS_{SB,i}$ and $UCAS_{MB,i}$ for $i=1$ and 2 are signaled using the $UCAS_{SB,0}$ and $UCAS_{MB,0}$ fields in the SFH. Since FP_0 and FP_3 are empty, $L_{SB-CRU,FP0} = L_{MB-CRU,FP0} = L_{DRU,FP0} = 0$ and $L_{SB-CRU,FP3} = L_{MB-CRU,FP3} = L_{DRU,FP3} = 0$. For $i=1$ and 2 ,

$$L_{SB-CRU,FPi} = N_1 UCAS_{SB,0}.$$

$L_{MB-CRU,FPi}$ is obtained using the mappings in Tables 864 through 866 for system bandwidths of 20MHz, 10MHz, and 5MHz, respectively.