

1

2

NOTICE OF DISCLAIMER AND LIMITATION OF LIABILITY

3

4

5

The document to which this Notice is affixed (the “Document”) has been prepared by one or more Engineering Committees or Formulating Groups of the Telecommunications Industry Association (“TIA”). TIA is not the author of the Document contents, but publishes and claims copyright to the Document pursuant to licenses and permission granted by the authors of the contents.

9

10

11

12

13

14

15

16

17

TIA Engineering Committees and Formulating Groups are expected to conduct their affairs in accordance with the TIA Engineering Manual (“Manual”), the current and predecessor versions of which are available at http://www.tiaonline.org/standards/sfg/engineering_manual.cfm. TIA’s function is to administer the process, but not the content, of document preparation in accordance with the Manual and, when appropriate, the policies and procedures of the American National Standards Institute (“ANSI”). TIA does not evaluate, test, verify or investigate the information, accuracy, soundness, or credibility of the contents of the Document. In publishing the Document, TIA disclaims any undertaking to perform any duty owed to or for anyone.

18

19

20

21

22

23

24

If the Document is identified or marked as a project number (PN) document, or as a standards proposal (SP) document, persons or parties reading or in any way interested in the Document are cautioned that: (a) the Document is a proposal; (b) there is no assurance that the Document will be approved by any Committee of TIA or any other body in its present or any other form; (c) the Document may be amended, modified or changed in the standards development or any editing process.

25

26

27

28

29

30

31

32

33

34

35

36

The use or practice of contents of this Document may involve the use of intellectual property rights (“IPR”), including pending or issued patents, or copyrights, owned by one or more parties. TIA makes no search or investigation for IPR. When IPR consisting of patents and published pending patent applications are claimed and called to TIA’s attention, a statement from the holder thereof is requested, all in accordance with the Manual. TIA takes no position with reference to, and disclaims any obligation to investigate or inquire into, the scope or validity of any claims of IPR. TIA will neither be a party to discussions of any licensing terms or conditions, which are instead left to the parties involved, nor will TIA opine or judge whether proposed licensing terms or conditions are reasonable or non-discriminatory. TIA does not warrant or represent that procedures or practices suggested or provided in the Manual have been complied with as respects the Document or its contents.

37

38

39

40

TIA does not enforce or monitor compliance with the contents of the Document. TIA does not certify, inspect, test or otherwise investigate products, designs or services or any claims of compliance with the contents of the Document.

41

42

43

44

45

46

ALL WARRANTIES, EXPRESS OR IMPLIED, ARE DISCLAIMED, INCLUDING WITHOUT LIMITATION, ANY AND ALL WARRANTIES CONCERNING THE ACCURACY OF THE CONTENTS, ITS FITNESS OR APPROPRIATENESS FOR A PARTICULAR PURPOSE OR USE, ITS MERCHANTABILITY AND ITS NON-INFRINGEMENT OF ANY THIRD PARTY’S INTELLECTUAL PROPERTY RIGHTS. TIA EXPRESSLY DISCLAIMS ANY AND ALL RESPONSIBILITIES FOR THE ACCURACY OF THE

1 CONTENTS AND MAKES NO REPRESENTATIONS OR WARRANTIES
2 REGARDING THE CONTENT'S COMPLIANCE WITH ANY APPLICABLE
3 STATUTE, RULE OR REGULATION, OR THE SAFETY OR HEALTH EFFECTS OF
4 THE CONTENTS OR ANY PRODUCT OR SERVICE REFERRED TO IN THE
5 DOCUMENT OR PRODUCED OR RENDERED TO COMPLY WITH THE
6 CONTENTS.
7

*TIA SHALL NOT BE LIABLE FOR ANY AND ALL DAMAGES, DIRECT OR INDIRECT, ARISING FROM OR RELATING TO ANY USE OF THE CONTENTS CONTAINED HEREIN, INCLUDING WITHOUT LIMITATION ANY AND ALL INDIRECT, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES (INCLUDING DAMAGES FOR LOSS OF BUSINESS, LOSS OF PROFITS, LITIGATION, OR THE LIKE), WHETHER BASED UPON BREACH OF CONTRACT, BREACH OF WARRANTY, TORT (INCLUDING NEGLIGENCE), PRODUCT LIABILITY OR OTHERWISE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. THE FOREGOING NEGATION OF DAMAGES IS A FUNDAMENTAL ELEMENT OF THE USE OF THE CONTENTS HEREOF, AND THESE CONTENTS WOULD NOT BE PUBLISHED BY TIA WITHOUT SUCH LIMITATIONS.*NOTICE

{TIA staff to insert applicable text here.}

TRANSMISSION PERFORMANCE SPECIFICATIONS
FOR
4-PAIR 100 Ω AUGMENTED CATEGORY 6 CABLING

TABLE OF CONTENTS

| | | | |
|----|---------|---|----|
| 1 | 1 | INTRODUCTION..... | 1 |
| 2 | 2 | PURPOSE AND SCOPE..... | 1 |
| 3 | 3 | NORMATIVE REFERENCES | 1 |
| 4 | 4 | DEFINITIONS, ACRONYMS & ABBREVIATIONS | 1 |
| 5 | 4.1 | Definitions | 1 |
| 6 | 4.2 | Acronyms and abbreviations..... | 3 |
| 7 | 5 | TEST CONFIGURATIONS..... | 3 |
| 8 | 5.1 | Component test configurations | 3 |
| 9 | 5.2 | Cabling test configurations..... | 3 |
| 10 | 6 | COMPONENTS..... | 3 |
| 11 | 6.1 | Recognized cable | 3 |
| 12 | 6.1.1 | Horizontal cable | 3 |
| 13 | 6.1.2 | Cable for modular cords | 3 |
| 14 | 6.1.3 | Backbone cable | 4 |
| 15 | 6.1.4 | Bundled and hybrid cable | 4 |
| 16 | 6.2 | Recognized connecting hardware | 4 |
| 17 | 6.3 | Cords..... | 4 |
| 18 | 7 | TRANSMISSION REQUIREMENTS..... | 5 |
| 19 | 7.1 | Insertion loss | 5 |
| 20 | 7.1.1 | Cable insertion loss | 5 |
| 21 | 7.1.2 | Connecting hardware insertion loss | 6 |
| 22 | 7.1.3 | Cabling insertion loss..... | 7 |
| 23 | 7.2 | NEXT loss | 8 |
| 24 | 7.2.1 | Pair-to-pair NEXT loss | 8 |
| 25 | 7.2.1.1 | Cable pair-to-pair NEXT loss..... | 8 |
| 26 | 7.2.1.2 | Connecting hardware pair-to-pair NEXT loss..... | 9 |
| 27 | 7.2.1.3 | Work area, equipment, and patch cord pair-to-pair NEXT loss | 9 |
| 28 | 7.2.1.4 | Cabling pair-to-pair NEXT loss..... | 10 |
| 29 | 7.2.2 | Power sum NEXT loss..... | 10 |
| 30 | 7.2.2.1 | Cable power sum NEXT loss | 11 |
| 31 | 7.2.2.2 | Cabling power sum NEXT loss..... | 12 |
| 32 | 7.3 | ELFEXT and FEXT loss..... | 12 |
| 33 | 7.3.1 | Pair-to-pair ELFEXT | 13 |
| 34 | 7.3.1.1 | Cable pair-to-pair ELFEXT | 13 |
| 35 | 7.3.1.2 | Connecting hardware pair-to-pair FEXT loss | 14 |
| 36 | 7.3.1.3 | Cabling pair-to-pair ELFEXT | 14 |
| 37 | 7.3.2 | Power sum ELFEXT | 15 |
| 38 | 7.3.2.1 | Cable power sum ELFEXT..... | 15 |
| 39 | 7.3.2.2 | Cabling power sum ELFEXT | 16 |

| | | | |
|----|---------|---|-------------------------------------|
| 1 | 7.4 | Return loss | 17 |
| 2 | 7.4.1 | Horizontal cable return loss | 17 |
| 3 | 7.4.2 | Stranded conductor cable return loss | 18 |
| 4 | 7.4.3 | Connecting hardware return loss | 19 |
| 5 | 7.4.4 | Work area, equipment, and patch cord return loss | 19 |
| 6 | 7.4.5 | Cabling return loss | 19 |
| 7 | 7.5 | Propagation delay/delay skew | 21 |
| 8 | 7.5.1 | Cable propagation delay | 21 |
| 9 | 7.5.2 | Cabling propagation delay | 21 |
| 10 | 7.5.3 | Cable propagation delay skew | 21 |
| 11 | 7.5.3 | Cabling propagation delay skew | 21 |
| 12 | 7.6 | Balance | 21 |
| 13 | 7.6.1 | Transverse conversion loss (TCL)..... | 22 |
| 14 | 7.6.1.1 | Cable TCL..... | 22 |
| 15 | 7.6.1.2 | Connecting hardware TCL | 22 |
| 16 | 7.6.2 | Equal Level transverse conversion transfer loss (ELTCTL)..... | 22 |
| 17 | 7.6.2.1 | Cable ELTCTL | 22 |
| 18 | 7.6.2.2 | Connecting hardware TCTL | 22 |
| 19 | 7.7 | Alien NEXT..... | 22 |
| 20 | 7.7.1 | Channel power sum alien NEXT | 22 |
| 21 | A.1 | INTRODUCTION | Error! Bookmark not defined. |
| 22 | A.2 | CONDUIT REQUIREMENTS | Error! Bookmark not defined. |
| 23 | A.3 | MEASUREMENT PROCEDURE..... | Error! Bookmark not defined. |
| 24 | A.4 | MEASURED DATA..... | Error! Bookmark not defined. |
| 25 | A.5 | COMPUTATIONS AND STATISTICS | Error! Bookmark not defined. |
| 26 | A.6 | COMPUTING NUMBER OF CABLES ALLOWED IN A CONDUIT..... | Error! Bookmark not defined. |

LIST OF FIGURES

LIST OF TABLES

1 Table 2 - Augmented category 6 cable insertion loss @ 20 °C ± 3°C (68° F ± 5.5 °F) 6
 2 Table 3 – Augmented category 6 connecting hardware insertion loss 6
 3 Table 4 – Augmented category 6 channel insertion loss 7
 4 Table 5– Augmented category 6 permanent link insertion loss 8
 5 Table 6 - Augmented category 6 cable NEXT loss @ 20 °C ± 3 °C (68 °F ± 5.5° F), worst pair-to-
 6 pair..... 8
 7 Table 7 – Augmented category 6 connecting hardware NEXT loss, worst pair-to-pair 9
 8 Table 8 – Augmented category 6 modular cord NEXT loss, worst pair-to-pair..... 9
 9 Table 9 – Augmented category 6 channel NEXT loss requirements, worst pair-to-pair..... 10
 10 Table 10 – Augmented category 6 channel NEXT loss, worst pair-to-pair values..... 10
 11 Table 11 – Augmented category 6 permanent link NEXT loss requirements, worst pair-to pair.. 10
 12 Table 12 – Augmented category 6 permanent link NEXT loss, worst pair-to pair values..... 10
 13 Table 13 – Augmented category 6 channel power sum NEXT loss requirements 12
 14 Table 14 – Augmented category 6 cable power sum NEXT loss values @ 20 °C ± 3 °C (68 °F ±
 15 5.5 °F)..... 12
 16 Table 15 – Augmented category 6 permanent link power sum NEXT loss requirements 12
 17 Table 16 – Augmented category 6 permanent link power sum NEXT loss values 12
 18 Table 17 - Augmented category 6 cable ELFEXT @ 20 °C ± 3 °C (68 °F ± 5.5 °F), worst pair-to-
 19 pair..... 13
 20 Table 18 – Augmented category 6 connecting hardware FEXT loss, worst pair-to-pair 14
 21 Table 19 – Augmented category 6 channel ELFEXT, worst pair-to-pair..... 14
 22 Table 20 – Augmented category 6 permanent link ELFEXT, worst pair-to-pair requirements 15
 23 Table 21 – Augmented category 6 permanent link ELFEXT, worst pair-to-pair values 15
 24 Table 22 - Augmented category 6 cable power sum ELFEXT @ 20 °C ± 3 °C (68 °F ± 5.5 °F).. 16
 25 Table 23 – Augmented category 6 channel power sum ELFEXT 16
 26 Table 24 – Augmented category 6 permanent link power sum ELFEXT requirements..... 17
 27 Table 25 – Augmented category 6 permanent link power sum ELFEXT values 17
 28 Table 26 - Augmented category 6 horizontal cable return loss requirements @ 20°C ± 3°C (68° F
 29 ± 5.5° F)..... 17
 30 Table 27 - Augmented category 6 solid conductor cable return loss values @ 20 °C ± 3 °C (68 °F
 31 ± 5.5 °F)..... 17
 32 Table 28 - Augmented category 6 stranded conductor cable return loss requirements @ 20 °C ±
 33 3 °C (68 °F ± 5.5 °F)..... 18
 34 Table 29 - Augmented category 6 stranded conductor cable return loss values @ 20 °C ± 3 °C
 35 (68 °F ± 5.5 °F)..... 18
 36 Table 30 – Augmented category 6 connecting hardware return loss requirements 19
 37 Table 31 - Augmented category 6 work area, equipment, and patch cord return loss 19
 38 Table 32 – Category 6 channel return loss requirements 19
 39 Table 33 – Augmented category 6 channel return loss values 20
 40 Table 34 – Augmented category 6 permanent link return loss requirements 20
 41 Table 35 – Augmented category 6 permanent link return loss values 21
 42 Table 36 - Propagation delay and delay skew for augmented category 6 cable @ 20 °C ± 3 °C
 43 (68 °F ± 5.5 °F)..... 21
 44 Table 37 – Augmented category 6 cable TCL..... 22
 45 Table 38 – Augmented category 6 connecting hardware TCL..... 22
 46 Table 39 – Augmented category 6 cable ELTCTL 22
 47 Table 40 – Augmented category 6 connecting hardware TCTL 22
 48 Table 41 – Augmented category 6 channel power sum alien NEXT requirements 23
 49 Table 42 – Augmented category 6 channel PSANEXT @ 20 °C ± 3 °C (68 °F ± 5.5 °F)..... 23

FOREWORD

(This foreword is not part of the Standard)

In 2003, the Telecommunications Industry Association (TIA) developed objectives for augmented category 6 cabling intended to support 10 Gigabit applications over a distance of 100 meters. At the request of the Institute of Electrical and Electronics Engineers (IEEE) 802.3 Committee, TIA agreed to specify augmented category 6 cabling systems and components to 500 MHz in order to support 10GBASE-T. The project was assigned to TR-42.7 under Engineering Committee TR-42. The TR-42.7 Sub-Committee cooperated with several groups related to this activity.

(Note: Stuart plans to submit alternate wording)

- a) TR-42.1 – Commercial Building Telecommunications Cabling Sub-Committee
- b) TR-42.7.1 – Copper Connectors Working Group
- c) TR-42.7.2 – Copper Cable Working Group

TIA standards documents are developed within the Technical Committees of the TIA and the standards coordinating committees of the TIA standards board. Members of the committees serve voluntarily and without commission. The companies that they represent are not necessarily members of the TIA. The standards developed within the TIA represent a consensus of the broad expertise on the subject. This expertise comes from within the TIA as well as those outside of the TIA that have an expressed interest. The viewpoint expressed at the time that this standard was approved was from the contributors' experience and the state of the art at that time. Users are encouraged to verify that they have the latest revision of the standard.

This standard has been prepared by the TR-42.7 Subcommittee and approved by the Engineering Committee TR-42.

There are XXX annexes in this Standard. Annexes YYY are normative and considered a mandatory part of this Standard. Annexes ZZZ are informative and not considered a part of this Standard.

1 INTRODUCTION

2 PURPOSE AND SCOPE

1
2
3
4
5
6
7

To develop cabling and component specifications and test procedures to support the operation of IEEE 802.3 10GBASE-T over 100 meters of structured balanced twisted-pair copper cabling. This addendum includes extending the frequency range and adding requirements to those specified in TIA-568-B.2-1.

3 NORMATIVE REFERENCES

The following standards contain requirements that, through reference in this text, constitute provisions of this Standard. At the time of publication, the editions indicated were valid. All standards are subject to revision; parties to agreements based on this Standard are encouraged to investigate the possibility of applying the most recent editions of the standards indicated. ANSI and TIA maintain registers of currently valid national standards published by them.

Note to editor: Review the reference list before the first ballot.

ANSI/ICEA S-80-576, *Communications Wire and Cable for Wiring Premises*, 1994

ANSI/ICEA S-90-661, *Individually Unshielded Twisted Pair Indoor Cable for Use in Communication Wiring Systems*, 1994

ANSI/TIA/EIA-568-B.1, *Commercial Building Telecommunications Standard Part 1: General Requirements*, 2001

ANSI/TIA/EIA-568-B.2, *Commercial Building Telecommunications Standard Part 2: Balanced Twisted-pair Cabling Components*, 2001

ANSI/TIA/EIA-568-B.2-1, *Commercial Building Telecommunications Standard Part 2: Addendum 1: Transmission Performance Specifications for 4-Pair 100 Ohm category 6 cabling*

ANSI/TIA/EIA-568-B.2-3, *Additional Considerations for Insertion Loss and Return Loss Pass/Fail Determination*, 2002

ANSI/TIA/EIA-568-B.3, *Commercial Building Telecommunications Standard Part 3: Optical Fiber Cabling Components*, 2000

ASTM D 4566-98, *Standard Test Methods for Electrical Performance Properties of Insulations and Jackets for Telecommunications Wire and Cable*, 1998

IEC 60603-7, *Connectors for frequencies below 3 MHz for use with printed boards – Part 7: Detail specification for connectors, 8-way, including fixed and free connectors with common mating features, with assessed quality*, 1996

4 DEFINITIONS, ACRONYMS & ABBREVIATIONS

4.1 Definitions

The generic definitions in this section have been formulated for use by the entire family of telecommunications infrastructure standards. As such, the definitions do not contain mandatory requirements of the Standard. Specific requirements are found in the normative sections of this Standard.

Alien crosstalk : A measure of the unwanted signal coupling from a transmitter into a neighboring pair that is external to the transmitter's cabling channel or part thereof.

Alien near-end crosstalk (ANEXT) loss: A measure of the unwanted signal coupling from a transmitter at the near end into a neighboring pair that is external to the transmitter's cabling channel or part thereof, measured at the near end.

1 **Power sum alien near-end crosstalk (PSANEXT) loss:** A computation of the unwanted signal
2 coupling from multiple transmitters at the near end into a neighboring pair that is external to the
3 transmitters' cabling channels or part thereof, measured at the near end.

4 **Alien far-end crosstalk (AFEXT) loss:** A measure of the unwanted signal coupling from a
5 transmitter at the near end into a neighboring pair that is external to the transmitter's cabling
6 channel or part thereof, measured at the far end

Power sum alien far-end crosstalk (PSAFEXT) loss: A computation of the unwanted signal coupling from multiple transmitters at the near end into a neighboring pair that is external to the transmitters' cabling channels or part thereof, measured at the far end.

4.2 Acronyms and abbreviations

ANEXT Alien Near End Crosstalk

PSANEXT Power Sum Alien Near End Crosstalk

AFEXT Alien Far End Crosstalk

PSAFEXT Power Sum Alien Far End Crosstalk

5 TEST CONFIGURATIONS

5.1 Component test configurations

- 1 Cable test configurations
- 2 Connecting hardware test configurations
- 3 Modular cord test configurations

5.2 Cabling test configurations

- 4 Channel test configurations
- 5 Permanent link test configurations
- 6 (Note: Minimum channel and permanent link configurations are needed. For example, see Annex
- 7 O of B.2.)

6 COMPONENTS

6.1 Recognized cable

6.1.1 Horizontal cable

6.1.2 Cable for modular cords

6.1.3 Backbone cable

6.1.4 Bundled and hybrid cable

6.2 Recognized connecting hardware

6.3 Cords

7 TRANSMISSION REQUIREMENTS

7.1 Insertion loss

7.1.1 Cable insertion loss

Table 2 - Augmented category 6 cable insertion loss @ 20 °C ± 3°C (68° F ± 5.5 °F)

7.1.2 Connecting hardware insertion loss

Table 3 – Augmented category 6 connecting hardware insertion loss

7.1.3 Cabling insertion loss

For all frequencies from 1 MHz to 500 MHz, when measured according to the procedures in annex C of TIA-568-B.2-1, the channel insertion loss shall meet the values determined using equation YY. For the purposes of field measurements, calculated channel limits that result in insertion loss values less than 3 dB revert to a requirement of 3 dB maximum (see ANSI/TIA/EIA-568-B.2-3). Insertion loss values in Table 4 computed from equation YY are provided for information only at certain frequencies of interest.

1 IL $\leq 1.05 * (1.8 * \sqrt{f}) + 0.01f + 0.2 / \sqrt{f}) + 4 * 0.02 * \sqrt{f}$ (YY)
 2

3 It is understood that equation YY includes an ILD allowance.
 4
 5
 6

Table 4 – Augmented category 6 channel insertion loss

| Frequency (MHz) | Insertion Loss (dB) |
|-----------------|---------------------|
| 1.00 | 2.2 |
| 4.00 | 4.1 |
| 8.00 | 5.7 |
| 10.00 | 6.4 |
| 16.00 | 8.1 |
| 20.00 | 9.1 |
| 25.00 | 10.2 |
| 31.25 | 11.4 |
| 62.50 | 16.3 |
| 100.00 | 20.8 |
| 200.00 | 30.0 |
| 250.00 | 33.8 |
| 300.00 | 37.4 |
| 400.00 | 43.7 |
| 500.00 | 49.4 |

7
 8
 9

NOTES,

- 1 A 20 % increase in insertion loss is allowed over category 6 horizontal cable insertion loss for work area and patch cords as shown in equation (TBD).
- 2 The insertion loss of the channel does not take into consideration the 0.1 dB measurement floor of the connecting hardware insertion loss requirement.
- 3 The channel insertion loss requirement is derived using the insertion loss contribution of 4 connections.
- 4 For the purposes of field measurements, calculated channel limits that result in insertion loss values less than 3 dB revert to a requirement of 3 dB maximum (see ANSI/TIA/EIA-568-B.2-3).

10
 11
 12

(Permanent link insertion loss requirements are to be added.)

1
2
3
4

Editor: Need a contribution approved by the task group to implement any technical changes.

Table 5– Augmented category 6 permanent link insertion loss

7.2 NEXT loss

NEXT loss is a measure of the unwanted signal coupling from a transmitter at the near-end into neighboring pairs measured at the near-end. NEXT loss is expressed in dB relative to the transmit signal level. NEXT loss shall be measured for all pair combinations of cables and cabling in accordance with annex C of ANSI/TIA/EIA-568-B.2 and the ASTM D 4566 NEXT loss measurement procedure, except the test fixture shall provide for consistent common and differential mode impedance matching for the unjacketed twisted-pairs between the cable jacket and the balun terminations. Connecting hardware NEXT loss shall be measured for all pair combinations in accordance with annex E. Modular plug cord NEXT loss shall be measured for all pair combinations in accordance with annex J. In addition, since each duplex channel can be disturbed by more than one duplex channel, power sum near-end crosstalk (PSNEXT) loss is also specified for cabling and cables.

7.2.1 Pair-to-pair NEXT loss

7.2.1.1 Cable pair-to-pair NEXT loss

Table 6 - Augmented category 6 cable NEXT loss @ 20 °C ± 3 °C (68 °F ± 5.5° F), worst pair-to-pair

7.2.1.2 Connecting hardware pair-to-pair NEXT loss

Table 7 – Augmented category 6 connecting hardware NEXT loss, worst pair-to-pair

7.2.1.3 Work area, equipment, and patch cord pair-to-pair NEXT loss

Table 8 – Augmented category 6 modular cord NEXT loss, worst pair-to-pair

7.2.1.4 Cabling pair-to-pair NEXT loss

1 For all frequencies from 1 MHz to 500 MHz, augmented category 6 channel pair-to-pair NEXT loss
 2 shall meet the values determined using table 9. Calculations that result in NEXT loss values
 3 greater than 65 dB shall revert to a requirement of 65 dB minimum. The values in table 10 are
 4 provided for information only.
 5

Table 9 – Augmented category 6 channel NEXT loss requirements, worst pair-to-pair

| Frequency (MHz) | NEXT Loss, worst pair-to-pair (dB) |
|---------------------|---|
| $1 \leq f \leq 330$ | $-20 \cdot \log(10^{-(0.05 \cdot (44.3 - 15 \cdot \log(f/100)))}) + 2 \cdot 10^{-(0.05 \cdot (54.0 - 20 \cdot \log(f/100)))}$ {TBD} |
| $330 < f \leq 500$ | $31.0 - 50 \cdot \log(f/330)$ {TBD} |

Table 10 – Augmented category 6 channel NEXT loss, worst pair-to-pair values

7 For all frequencies from 1 MHz to 500 MHz, category 6 permanent link pair-to-pair NEXT loss shall
 8 meet the values determined using table 11. Calculations that result in NEXT loss values greater
 9 than 65 dB shall revert to a requirement of 65 dB minimum. The values in table 12 are provided for
 10 information only.
 11

Table 11 – Augmented category 6 permanent link NEXT loss requirements, worst pair-to pair

| Frequency (MHz) | NEXT Loss, worst pair-to-pair (dB) |
|---------------------|---|
| $1 \leq f \leq 300$ | $-20 \cdot \log(10^{-(0.05 \cdot (44.3 - 15 \cdot \log(f/100)))}) + 2 \cdot 10^{-(0.05 \cdot (54.0 - 20 \cdot \log(f/100)))}$ {TBD} |
| $300 < f \leq 500$ | $34.0 - 48 \cdot \log(f/300)$ {TBD} |

Table 12 – Augmented category 6 permanent link NEXT loss, worst pair-to pair values

7.2.2 Power sum NEXT loss

12 Power sum near-end crosstalk loss takes into account the combined crosstalk (statistical) on a
 receive pair from all near-end disturbers operating simultaneously. The power sum near-end
 crosstalk (PSNEXT) loss is calculated in accordance with ASTM D 4566 as a power sum on a
 selected pair from all other pairs as shown in equation (22) for the case of 4-pair cable.

$$PSNEXT = -10 \log(10^{-X1/10} + 10^{-X2/10} + 10^{-X3/10}) \text{ dB} \tag{22}$$

where:

X1, X2, X3 are the pair-to-pair crosstalk measurements in dB between the selected pair and the other three pairs.

1 NOTE - For channel and permanent link power sum calculations, it is assumed that the pair-to-pair
2 connecting hardware NEXT loss requirements of this Standard are equivalent to a PSNEXT loss
3 performance of $50-20\log(f/100)$ for all frequencies from 1 MHz to 500 MHz. PSNEXT loss for
4 connecting hardware does not need to be separately verified.

5
6

7.2.2.1 Cable power sum NEXT loss

7.2.2.2 Cabling power sum NEXT loss

1 For all frequencies from 1 MHz to 500 MHz, augmented category 6 channel power sum NEXT loss
 2 shall meet the values determined using table 13. Calculations that result in NEXT loss values
 3 greater than 62 dB shall revert to a requirement of 62 dB minimum. The values in table 14 are
 4 provided for information only.
 5

Table 13 – Augmented category 6 channel power sum NEXT loss requirements

| Frequency (MHz) | Power Sum NEXT Loss (dB) |
|---------------------|---|
| $1 \leq f \leq 330$ | $-20 \cdot \log(10^{(-0.05 \cdot (42.3 - 15 \cdot \log(f/100)))} + 2 \cdot 10^{(-0.05 \cdot (50 - 20 \cdot \log(f/100)))})$ {TBD} |
| $330 < f \leq 500$ | $28 - 42 \cdot \log(f/330)$ {TBD} |

Table 14 – Augmented category 6 cable power sum NEXT loss values @ 20 °C ± 3 °C (68 °F ± 5.5 °F)

6 For all frequencies from 1 MHz to 500 MHz, augmented category 6 permanent link power sum
 7 NEXT loss shall meet the values determined using table 15. Calculations that result in NEXT loss
 8 values greater than 62 dB shall revert to a requirement of 62 dB minimum. The values in table 16
 9 are provided for information only.
 10
 11

Table 15 – Augmented category 6 permanent link power sum NEXT loss requirements

| Frequency (MHz) | Power Sum NEXT Loss (dB) |
|---------------------|---|
| $1 \leq f \leq 300$ | $-20 \cdot \log(10^{(-0.05 \cdot (42.3 - 15 \cdot \log(f/100)))} + 2 \cdot 10^{(-0.05 \cdot (50 - 20 \cdot \log(f/100)))})$ {TBD} |
| $300 < f \leq 500$ | $31.4 - 40 \cdot \log(f/300)$ {TBD} |

Table 16 – Augmented category 6 permanent link power sum NEXT loss values

7.3 ELFEXT and FEXT loss

12 FEXT loss is a measure of the unwanted signal coupling from a transmitter at the far-end into
 13 neighboring pairs measured at the near-end. FEXT loss is the ratio of the power coupled from a
 14 disturbing pair into the disturbed pair relative to the input power at the opposite end of the
 15 transmission lines determined from measured voltages. This ratio is expressed in dB. ELFEXT
 16 shall be calculated for all pair combinations of cables and cabling in accordance with annex C of
 17 ANSI/TIA/EIA-568-B.2 and the ASTM D 4566 FEXT loss measurement procedure, except the test
 18 fixture shall provide for consistent common and differential mode impedance matching for the
 19 unjacketed twisted-pairs between the cable jacket and the balun terminations. Connecting
 20 hardware FEXT loss shall be measured for all pair combinations in accordance with annex E of
 21 TIA-568-B.2-1. In addition, since each duplex channel can be disturbed by more than one duplex
 22 channel, power sum equal level far-end crosstalk (PSELFEXT) is also specified for cabling and

1 cables.
2

3 7.3.1 Pair-to-pair ELFEXT

4 FEXT loss is a measure of the unwanted signal coupling from a transmitter at the far-end into
5 neighboring pairs measured at the near-end. FEXT loss is the ratio of the power coupled from a
6 disturbing pair into the disturbed pair relative to the input power at the opposite end of the
7 transmission lines determined from measured voltages. This ratio is expressed in dB. ELFEXT
8 shall be calculated for all pair combinations of cables and cabling in accordance with annex C of
9 ANSI/TIA/EIA-568-B.2 and the ASTM D 4566 FEXT loss measurement procedure, except the test
10 fixture shall provide for consistent common and differential mode impedance matching for the
11 unjacketed twisted-pairs between the cable jacket and the balun terminations. Connecting
12 hardware FEXT loss shall be measured for all pair combinations in accordance with annex E. In
13 addition, since each duplex channel can be disturbed by more than one duplex channel, power
14 sum equal level far-end crosstalk (PSELFEXT) is also specified for cabling and cables.

7.3.1.1 Cable pair-to-pair ELFEXT
For all frequencies from 1 MHz to 500 MHz, augmented category 6 cable ELFEXT, for a length of
100 m (328 ft), shall meet the values determined using equation (26). The values in table 17 are
provided for information only.

$$ELFEXT_{cable} \geq 27.8 - 20 \log(f / 100) \text{ dB} \quad (26)$$

Table 17 - Augmented category 6 cable ELFEXT @ 20 °C ± 3 °C (68 °F ± 5.5 °F), worst pair-to-pair

7.3.1.2 Connecting hardware pair-to-pair FEXT loss

For all frequencies from 1 MHz to 500 MHz, category 6 connecting hardware FEXT loss shall meet the values determined using equation (27). Calculations that result in FEXT loss values greater than 75 dB shall revert to a requirement of 75 dB minimum. The values in table 18 are provided for information only.

$$FEXT_{conn} \geq 43.1 - 20 \log(f / 100) \text{ dB} \quad \{\text{TBD}\} \quad (27)$$

Table 18 – Augmented category 6 connecting hardware FEXT loss, worst pair-to-pair

7.3.1.3 Cabling pair-to-pair ELFEXT

1
2
3
4
5
6

For all frequencies from 1 MHz to 500 MHz the channel ELFEXT shall meet the values determined using the equation XX. Due to measurement considerations, ELFEXT values that correspond to measured FEXT values of greater than 70 dB are for information only. ELFEXT values in Table 16 computed from the equation XX are provided for information only at certain frequencies of interest.

$$ELFEXT_{channel} \geq -20 \log \left(10^{\frac{-ELFEXT_{cable}}{20}} + 4 \cdot 10^{\frac{-FEXT_{conn}}{20}} \right) \text{ dB} \quad (XX)$$

Table 19 – Augmented category 6 channel ELFEXT, worst pair-to-pair

| Frequency (MHz) | ELFEXT (dB) |
|-----------------|-------------|
| 1.00 | 63.3 |
| 4.00 | 51.2 |
| 8.00 | 45.2 |
| 10.00 | 43.3 |
| 16.00 | 39.2 |
| 20.00 | 37.2 |
| 25.00 | 35.3 |
| 31.25 | 33.4 |
| 62.50 | 27.3 |
| 100.00 | 23.3 |
| 200.00 | 17.2 |
| 250.00 | 15.30 |
| 300.00 | 13.7 |
| 400.00 | 11.2 |
| 500.00 | 9.3 |

7
8
9
10
11
12

For all frequencies from 1 MHz to 500 MHz, augmented category 6 permanent link ELFEXT shall meet the values determined using table 20. The values in table 21 are provided for information

1 only.
 2
 3
 4
 5
 6

Table 20 – Augmented category 6 permanent link ELFEXT, worst pair-to-pair requirements

| Frequency (MHz) | ELFEXT worst pair-to-pair (dB) |
|---------------------|--|
| $1 \leq f \leq 500$ | $-20 \cdot \log(10^{(-0.05 \cdot (27.8 - 20 \cdot \log(f/100)))} + 3 \cdot 10^{(-0.05 \cdot (43.1 - 20 \cdot \log(f/100)))})$ {TBD} |

Table 21 – Augmented category 6 permanent link ELFEXT, worst pair-to-pair values

7.3.2 Power sum ELFEXT

Power sum equal level far-end crosstalk loss takes into account the combined crosstalk (statistical) on a receive pair from all far-end disturbers operating simultaneously. The power sum equal level far-end crosstalk (PSELFEXT) loss is calculated in accordance with ASTM D 4566 as a power sum on a selected pair from all other pairs as shown in equation (30) for the case of 4-pair cable.

$$PSELFEXT = -10 \log(10^{-X1/10} + 10^{-X2/10} + 10^{-X3/10}) \text{ dB} \tag{30}$$

where:

X1, X2, X3 are the pair-to-pair crosstalk measurements in dB between the selected pair and the other three pairs.

NOTE - For channel and permanent link power sum calculations, it is assumed that the pair-to-pair connecting hardware FEXT loss requirements of this Standard are equivalent to a PSFEXT loss performance of $40.1 - 20 \log(f/100)$ **{TBD}** for all frequencies from 1 MHz to 500 MHz **{TBD}**. PSFEXT loss for connecting hardware does not need to be separately verified.

7.3.2.1 Cable power sum ELFEXT

For all frequencies from 1 MHz to 500 MHz, augmented category 6 cable power sum ELFEXT, for a length of 100 m (328 ft), shall meet the values determined by equation (31). The values in table 22 are for reference only.

$$PSELFEXT_{cable} \geq 24.8 - 20 \log(f / 100) \text{ dB} \quad (31)$$

Table 22 - Augmented category 6 cable power sum ELFEXT @ 20 °C ± 3 °C (68 °F ± 5.5 °F)

7.3.2.2 Cabling power sum ELFEXT

1 For all frequencies from 1 MHz to 500 MHz the channel PSELFEXT shall meet the values
 2 determined using the equation ZZ. Due to measurement considerations, PSELFEXT values that
 3 correspond to measured FEXT values of greater than 70 dB are for information only. PSELFEXT
 4 values in Table 19 computed from the equation ZZ are provided for information only at certain
 5 frequencies of interest.

$$PSELFEXT_{channel} \geq -20 \log \left(10^{\frac{-PSELFEXT_{cable}}{20}} + 4 \cdot 10^{\frac{-PSFEXT_{conn}}{20}} \right) \text{ dB} \quad (ZZ)$$

Table 23 – Augmented category 6 channel power sum ELFEXT

| Frequency (MHz) | PSELFEXT (dB) |
|-----------------|---------------|
| 1.00 | 60.3 |
| 4.00 | 48.2 |
| 8.00 | 42.2 |
| 10.00 | 40.3 |
| 16.00 | 36.2 |
| 20.00 | 34.2 |
| 25.00 | 32.30 |
| 31.25 | 30.4 |
| 62.50 | 24.3 |
| 100.00 | 20.3 |
| 200.00 | 14.2 |
| 250.00 | 12.30 |
| 300.00 | 10.7 |
| 400.00 | 8.2 |
| 500.00 | 6.3 |

6
 7
 8
 9
 10
 11
 12
 13
 14
 15
 16
 17

For all frequencies from 1 MHz to 500 MHz, augmented category 6 permanent link power sum ELFEXT shall meet the values determined using table 24. The values in table 25 are provided for information only.

Table 24 – Augmented category 6 permanent link power sum ELFEXT requirements

| Frequency (MHz) | Power Sum ELFEXT (dB) |
|---------------------|---|
| $1 \leq f \leq 500$ | $-20 \cdot \log(10^{(-0.05 \cdot (24.8 - 20 \cdot \log(f/100)))} + 3 \cdot 10^{(-0.05 \cdot (40.1 - 20 \cdot \log(f/100)))})$ {TBD} |

Table 25 – Augmented category 6 permanent link power sum ELFEXT values

7.4 Return loss

1 Return loss is a measure of the reflected energy caused by impedance mismatches in the cabling
 2 system and is especially important for applications that use simultaneous bi-directional
 3 transmission. Return loss is the ratio of the reflected signal power to the input power determined
 4 from measured voltages, expressed in dB. Cable and cabling return loss shall be measured in
 5 accordance with annex C of ANSI/TIA/EIA-568-B.2. Connecting hardware return loss shall be
 6 measured in accordance with annex D of ANSI/TIA/EIA-568-B.2 for all pairs. Modular plug cords
 7 shall be measured in accordance with annex J for all pairs.

7.4.1 Horizontal cable return loss

8 For all frequencies from 1 MHz to 500 MHz, augmented category 6 horizontal cable return loss, for
 9 a length of 100 m (328 ft), shall meet the values determined using the equations specified in table
 10 26. The values in table 27 are provided for information only.

**Table 26 - Augmented category 6 horizontal cable return loss requirements @ 20°C ± 3°C
 (68° F ± 5.5° F)
 For a length of 100 m (328 ft)**

| Frequency (MHz) | Return Loss (dB) |
|-------------------|---------------------|
| $1 \leq f < 10$ | $20 + 5 \log(f)$ |
| $10 \leq f < 20$ | 25 |
| $20 \leq f < 500$ | $25 - 7 \log(f/20)$ |

**Table 27 - Augmented category 6 solid conductor cable return loss values @ 20 °C ± 3 °C (68 °F ± 5.5 °F)
 For a length of 100 m (328 ft)**

| Frequency (MHz) | Return Loss (dB) |
|-----------------|------------------|
| 1.0 | 20.0 |
| 4.0 | 23.0 |
| 8.0 | 24.5 |
| 10.0 | 25.0 |
| 16.0 | 25.0 |
| 20.0 | 25.0 |
| 25.0 | 24.3 |
| 31.25 | 23.6 |
| 62.5 | 21.5 |
| 100.0 | 20.1 |
| 200.0 | 18.0 |
| 250.0 | 17.3 |
| 300.0 | 16.8 |
| 400.0 | 15.9 |
| 500.0 | 15.2 |

7.4.2 Stranded conductor cable return loss

1 For all frequencies from 1 MHz to 500 MHz, augmented category 6 stranded patch cable return
 2 loss, for a length of 100 m (328 ft), shall meet the values determined using the equations specified
 3 in table 28. The values in table 29 are provided for information only.
 4

**Table 28 - Augmented category 6 stranded conductor cable return loss requirements @ 20 °C ± 3 °C (68 °F ± 5.5 °F)
 For a length of 100 m (328 ft)**

| Frequency (MHz) | Return Loss (dB) |
|-------------------|-----------------------|
| $1 \leq f < 10$ | $20 + 5 \log(f)$ |
| $10 \leq f < 20$ | 25 |
| $20 \leq f < 500$ | $25 - 8.6 \log(f/20)$ |

**Table 29 - Augmented category 6 stranded conductor cable return loss values @ 20 °C ± 3 °C (68 °F ± 5.5 °F)
 Values For a length of 100 m (328 ft)**

| Frequency (MHz) | Return Loss (dB) |
|-----------------|------------------|
| 1.0 | 20.0 |
| 4.0 | 23.0 |
| 8.0 | 24.5 |
| 10.0 | 25.0 |
| 16.0 | 25.0 |
| 20.0 | 25.0 |
| 25.0 | 24.2 |
| 31.25 | 23.3 |
| 62.5 | 20.7 |
| 100.0 | 19.0 |
| 200.0 | 16.4 |
| 250.0 | 15.6 |
| 300.0 | 14.9 |
| 400.0 | 13.8 |
| 500.0 | 13.0 |

7.4.3 Connecting hardware return loss

1
2

Table 30 – Augmented category 6 connecting hardware return loss requirements

| Frequency (MHz) | Return Loss (dB) |
|-------------------------|----------------------------|
| $1 \leq f < 79$ {TBD} | 30 |
| {TBD} $79 \leq f < 500$ | $28 - 20\log(f/100)$ {TBD} |

3
4
5
6

For the purpose of establishing PL and Channel RL limits, a connection value of $26 - 20\log(f/100)$ (TBD) is assumed to account for the variability of patch cord connections.

7.4.4 Work area, equipment, and patch cord return loss

Table 31 - Augmented category 6 work area, equipment, and patch cord return loss

7.4.5 Cabling return loss

For all frequencies from 1 MHz to 500 MHz, augmented category 6 channel return loss shall meet or exceed the values determined using the equations specified in table 32 up to 500 MHz. The values in table 33 are provided for information only.

Table 32 – Augmented Category 6 channel return loss requirements

| Frequency (MHz) | Return Loss (dB) |
|-------------------|-------------------------------|
| $1 \leq f < 10$ | 19 |
| $10 \leq f < 40$ | $24 - 5\log(f)$ |
| $40 \leq f < 500$ | $32 - 10\log(f)$ 6 dB minimum |

Table 33 – Augmented category 6 channel return loss values

| Frequency (MHz) | Return Loss (dB) |
|-----------------|------------------|
| 1.0 | 19.0 |
| 4.0 | 19.0 |
| 8.0 | 19.0 |
| 10.0 | 19.0 |
| 16.0 | 18.0 |
| 20.0 | 17.5 |
| 25.0 | 17.0 |
| 31.25 | 16.5 |
| 62.5 | 14.0 |
| 100.0 | 12.0 |
| 200.0 | 9.0 |
| 250.0 | 8.0 |
| 300.0 | 7.2 |
| 400.0 | 6.0 |
| 500.0 | 6.0 |

For all frequencies from 1 MHz to 250 MHz, augmented category 6 permanent link return loss shall meet the values determined using the equations specified in table 34. The values in table 35 are provided for information only

Table 34 – Augmented category 6 permanent link return loss requirements

| Frequency (MHz) | Return Loss (dB) |
|-----------------------|---|
| $1 \leq f < 3$ | $21 + 4\log(f/3)$ |
| $3 \leq f < 10$ | 21 |
| $10 \leq f < 40$ | $26 - 5\log(f)$ |
| $40 \leq f \leq 250$ | $34 - 10\log(f)$ |
| $250 \leq f \leq 500$ | $10 - 20\log(f/250)$ {TBD} 6 dB minimum {TBD} |

1

Table 35 – Augmented category 6 permanent link return loss values

| Frequency (MHz) | Return Loss (dB) |
|-----------------|------------------|
| 1.0 | 19.1 |
| 4.0 | 21.0 |
| 8.0 | 21.0 |
| 10.0 | 21.0 |
| 16.0 | 20.0 |
| 20.0 | 19.5 |
| 25.0 | 19.0 |
| 31.25 | 18.5 |
| 62.5 | 16.0 |
| 100.0 | 14.0 |
| 200.0 | 11.0 |
| 250.0 | 10.0 |
| 300.0 | 8.4 |
| 400.0 | 6.0 |
| 500.0 | 6.0 |

7.5 Propagation delay/delay skew

7.5.1 Cable propagation delay

Table 36 - Propagation delay and delay skew for augmented category 6 cable @ 20 °C ± 3 °C (68 °F ± 5.5 °F)

7.5.2 Cabling propagation delay

1 In determining the augmented category 6 channel and permanent link propagation delay, the
 2 propagation delay contribution of each installed mated connection is assumed to not exceed 2.5 ns
 3 from 1 MHz to 500 MHz.

4
 5 The maximum propagation delay for an augmented category 6 channel configuration shall be less
 6 than 555 ns measured at 10 MHz.

7
 8 The maximum propagation delay for an augmented category 6 permanent link configuration shall
 9 be less than 498 ns measured at 10 MHz.

7.5.3 Cable propagation delay skew

7.5.3 Cabling propagation delay skew

In determining the channel and permanent link propagation delay skew, the propagation delay skew of each installed mated connection is assumed not to exceed 1.25 ns.

The maximum propagation delay skew for an augmented category 6 channel configuration shall be less than 50 ns measured at 10 MHz.

10 The maximum propagation delay skew for an augmented category 6 permanent link configuration
 11 shall be less than 44 ns measured at 10 MHz.

12

7.6 Balance

13

7.6.1 Transverse conversion loss (TCL)

7.6.1.1 Cable TCL

Table 37 – Augmented category 6 cable TCL

7.6.1.2 Connecting hardware TCL

Table 38 – Augmented category 6 connecting hardware TCL

7.6.2 Equal Level transverse conversion transfer loss (ELTCTL)

7.6.2.1 Cable ELTCTL

1

Table 39 – Augmented category 6 cable ELTCTL

2

7.6.2.2 Connecting hardware TCTL

3

Table 40 – Augmented category 6 connecting hardware TCTL

4

7.7 Alien NEXT

5

Alien NEXT is the coupling of cross-talk noise at the near end from external cabling pairs into a victim pair of the 4-pair cabling under test. Power sum alien NEXT is the calculated power sum of the alien NEXT from all external cabling pairs into the victim pair.

6

7

7.7.1 Channel power sum alien NEXT

8

For all frequencies from 1 MHz to 500 MHz, when measured according to the procedures in Annex XX, the channel power sum alien NEXT shall meet or exceed the values determined using the equations in Table 36. Calculations that result in PSANEXT values greater than 75 dB TBD shall revert to a requirement of 75 dB TBD minimum. Power sum alien NEXT values in Table 41 computed from the equations in Table 42 are provided for information only at certain frequencies of interest.

9

10

11

12

13

14

15

1

Table 41 – Augmented category 6 channel power sum alien NEXT requirements

2

| Frequency f (MHz) | PSANEXT (dB) |
|-------------------------------|--|
| 1 MHz \geq f \leq 100 MHz | $60 - 10 \cdot \text{Log}_{10}(f/100)$ |
| 100 MHz < f \leq 500 MHz | $60 - 15 \cdot \text{Log}_{10}(f/100)$ |

3

4

5

Table 42 – Augmented category 6 channel PSANEXT @ 20 °C \pm 3 °C (68 °F \pm 5.5 °F)

| Frequency (MHz) | PSANEXT (dB) |
|------------------------|---------------------|
| 1.0 | 75.0 |
| 4.0 | 74.0 |
| 8.0 | 71.0 |
| 10.0 | 70.0 |
| 16.0 | 68.0 |
| 20.0 | 67.0 |
| 25.0 | 66.0 |
| 31.25 | 65.1 |
| 62.5 | 62.0 |
| 100.0 | 60.0 |
| 200.0 | 55.5 |
| 250.0 | 54.0 |
| 300.0 | 52.8 |
| 400.0 | 51.0 |
| 500.0 | 49.5 |

6

7

Inclusion of alien FEXT is TBD.



ANNEX A Reference measurement procedure for ANEXT and AFEXT (normative) (TBD)

A.1 Reference measurement instructions

1. Pull seven to ten (depending on conduit fill) up to 90 meter 4-Pair cables into a conduit with a length of > 30 meters. The conduit shall be sized to ensure a conduit fill of 40 % ± 3.5 %. The conduit fill is calculated as the ratio of $N \cdot (D_{\text{cable}})^2 / (D_{\text{conduit}})^2$ expressed as a percentage. See table below for standard EMT conduit sizes and the number of cables within the fill range specified above.

| N Cables | DIA (in) | 3/4 | 1 | 1 1/4 |
|----------|----------|-----------------|-----------------|----------------|
| | | 0.824 % Fill | 1.047 % Fill | 1.38 % Fill |
| 9 | 0.17 | 38.3% | | |
| 8 | 0.18 | 38.2% | | |
| 7 | 0.19 | 37.2% | | |
| 7 | 0.2 | 41.2% | | |
| 10 | 0.21 | | 40.2% | |
| 9 | 0.22 | | 39.7% | |
| 8 | 0.23 | | 38.6% | |
| 7 | 0.24 | | 36.8% | |
| 7 | 0.25 | | 39.9% | |
| 7 | 0.26 | | 43.2% | |
| 10 | 0.27 | | | 38.3% |
| 9 | 0.28 | | | 37.1% |
| 9 | 0.29 | | | 39.7% |
| 8 | 0.3 | | | 37.8% |
| 8 | 0.31 | | | 40.4% |

2. Pull-out a maximum of 1 meter of cable for attachment to the measurement equipment.
 - Measure NEXT and FEXT between all of the 4-pair cable pair combinations excluding within cable pair combinations.
 - Calculate Power Sum NEXT and ELFEXT
3. Pull-out 5 meters of the 90 meter 4-Pair cables from the conduit and tie-wrap every meter
 - Measure NEXT and FEXT between all of the 4-pair cable pair combinations excluding within cable pair combinations.
 - Calculate Power Sum NEXT and ELFEXT
4. Terminate cable pairs to adjacent Category compatible connecting hardware patch panel positions. Use a 1 meter test cord.
 - Measure NEXT and FEXT between all of the 4-pair cabling pair combinations excluding within cable pair combinations.
 - Calculate Power Sum NEXT and ELFEXT

A.2 Additional ANEXT measurement procedures being discussed

- 2 cables in a conduit
- 2 cables bound together

- 1
 - 2
 - 3
 - 4
 - 5
 - 6
 - 7
- 6 around 1 cables bound together
 - drum accumulator with a spiral groove for 2 cables
 - two cables side by side with fixed spacing
 - connecting hardware ANEXT measurement procedures
 - channel ANEXT and AELFEXT measurement procedures

