

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 00 SC 0 P L # 67
 Anslow, Pete Ciena

Comment Type E Comment Status X

Some hyperlinks to Figures and Tables within the document do not work.

For example:

In 91.5.1, the link to Figure 91-2 does not work
 In 91.5.2.5, the link to Figure 91-3 does not work
 In 91.5.2.8, the link to Figure 91-6 does not work
 In 91.5.3.1, the link to Figure 91-8 does not work
 In 92.7.7, the link to Table 92-6 does not work
 etc.

However, some links do work:

In 91.5.2.1, the link to Figure 82-10 does work

SuggestedRemedy

Fix these links, particularly in the new clauses where they will be incorporated into the next revision without modification.

Proposed Response Response Status O

Cl 00 SC 0 P L # 66
 Anslow, Pete Ciena

Comment Type E Comment Status X

As stated in 1.2.6, "Unless otherwise stated, numerical limits in this standard are to be taken as exact, with the number of significant digits and trailing zeros having no significance."

SuggestedRemedy

In 92.8.3.3, page 170, line 52 change "8.0 dB" to "8 dB"
 In 92.8.3.3, page 170, line 54 change "20.0 dB" to "20 dB"
 In 92.10, page 180, line 14 change "6.0 dB" to "6 dB"
 In 94.4.2, page 279, line 41 change "7.0 GHz" to "7 GHz"

Proposed Response Response Status O

Cl 00 SC 0 P L # 50
 Anslow, Pete Ciena

Comment Type E Comment Status X

The Working Group maintains a list of preferred spellings on its web pages.

Spellings in the draft not in accordance with this list are:

- 6 instances of Gbps instead of Gb/s
- 3 instances of inter-symbol instead of intersymbol
- 3 instances of low frequency instead of low-frequency
- 2 instances of peak to peak instead of peak-to-peak
- 20 instances of steady state instead of steady-state
- 2 instances of signal to noise instead of signal-to-noise
- 5 instances of common mode instead of common-mode (when used as an adjective)
- 3 instances of implementer instead of implementor
- 3 instances of boolean that should be Boolean

SuggestedRemedy

Change all instances to be in accordance with Working Group practice.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 00 SC 0 P L # 39
 Anslow, Pete Ciena

Comment Type E Comment Status X

The valid editing instructions are "change, delete, insert, and replace" as described on page 21 of the draft.

There are many instances of "add" and three instances of "append" used as editing instructions. These should all be "insert".

Also, many of the instructions that should be or are "insert" do not define where in tables new rows should be placed.

SuggestedRemedy

Change "add" and "append" editing instructions to "insert".
 For all "insert" editing instructions, check that the insertion point is defined.

For example:

In 30.2.5, change: "Append the following into Table 30-7:" to "Insert the following at the end of Table 30-7:"

In 45.2.1.7.4, change: "Add the following rows to the bottom of Table 45-9:" to "Insert the following rows at the bottom of Table 45-9:"

In 45.2.1.100, change "Add rows & changed reserved row in Table 45-73 and add the paragraph to the end of 45.2.1.100:" to "Change the reserved row and insert new rows immediately below it in Table 45-73 and insert the new paragraph at the end of 45.2.1.100 as follows:". Do not show the new text in underline font.

In 73.11.4.3, change "Add item LE8a and change LE14, LE15, and LE17 as shown:" to "Insert item LE8a immediately below item LE8 and change LE14, LE15, and LE17 as shown:"

etc.

Proposed Response Response Status O

CI 30 SC 30.5.1.1.17 P 25 L 29 # 40
 Anslow, Pete Ciena

Comment Type E Comment Status X

The modified text says: "For 1000BASE-PX, 10/40/100GBASE-R, 100GBASE-P PHYs, an array ..." which would be better as:
 "For 1000BASE-PX, 10/40/100GBASE-R, and 100GBASE-P PHYs, an array ..."

Same issue in 30.5.1.1.18

SuggestedRemedy

Change:
 "For 1000BASE-PX, 10/40/100GBASE-R, 100GBASE-P PHYs, an array ..." to:
 "For 1000BASE-PX, 10/40/100GBASE-R, and 100GBASE-P PHYs, an array ..."

Make the same change in 30.5.1.1.18

Proposed Response Response Status O

CI 45 SC 2.1.2 P 30 L 43 # 6
 Slavick, Jeff Avago Technologies

Comment Type T Comment Status X

PIASA and PEASA are ability registers, so they should be RO property.

SuggestedRemedy

Change PIASA and PEASA to RO from R/W.

Proposed Response Response Status O

CI 45 SC 2.1.6.a P 31 L 26 # 7
 Slavick, Jeff Avago Technologies

Comment Type T Comment Status X

PIASE and PEASE text states that "or not able to stop the ingres direction AUI signalling" which is refering to the ability registers PIASA and PEASA.

SuggestedRemedy

Change "is not able to stop the ingress direction AUI signaling" to
 "is not able to stop the ingress direction AUI signaling (see 1.1.9)"

Make similar change for 45.2.1.6.b

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 45 SC 2.1.92e P 38 L 2 # 8
 Slavick, Jeff Avago Technologies

Comment Type T Comment Status X
 Lane mappings for RS-FEC are valid when fec_align_status is set to one, but we don't have any MDIO register that shows the status of fec_align_status

SuggestedRemedy
 Add a MDIO register to reflect the state of fec_align_status, maybe as bit 15 of 1.206

Proposed Response Response Status O

Cl 45 SC 2.7.14 P 46 L 35 # 9
 Slavick, Jeff Avago Technologies

Comment Type T Comment Status X
 EEE link partner ability register for LPI modes supported is listed as R/W, should be RO

SuggestedRemedy
 Change R/W to RO for MDIO register 7.61.14 in table 45-191

Proposed Response Response Status O

Cl 45 SC 45.2.1.100 P 40 L 26 # 41
 Anslow, Pete Ciena

Comment Type E Comment Status X
 The paragraph to be added at the end of 45.2.1.100:
 Register field 1.1501.8 enables testing with the JP03A pattern defined in 94.2.11.1. Register field 1.1501.9 enables testing with the JP03B pattern defined in 94.2.11.2. Register field 1.1501.10 enables testing with the QPRBS13 pattern defined in 94.2.11.3. The assertion of register 1.1501.8, 1.1501.9, 1.1501.10 are mutually exclusive. If more than one bit are asserted the behavior is undefined. The assertion of 1.1501.8, 1.1501.9, and 1501.10 works in conjunction with register field 1.1501.3. If 1.1501.3 is not asserted then 1.1501.8, 1.1501.9, and 101501.10 have no effect.

is written using different terms from the text that is already present in this subclause. Since the existing paragraphs are not being changed, change this text to be in line with what is already there.

Also, "if more than one bit are asserted" should be "if more than one bit is asserted", "operates" seems a better word to use than "works" and "101501.10" should be "1.1501.10".

SuggestedRemedy
 Change the paragraph to:
 "Register 1.1501 bit 8 enables testing with the JP03A pattern defined in 94.2.11.1. Register 1.1501 bit 9 enables testing with the JP03B pattern defined in 94.2.11.2. Register 1.1501 bit 10 enables testing with the QPRBS13 pattern defined in 94.2.11.3. The assertion of bits 1.1501.8, 1.1501.9, 1.1501.10 are mutually exclusive. If more than one bit is asserted the behavior is undefined. The assertion of bits 1.1501.8, 1.1501.9, and 1501.10 operates in conjunction with register 1.1501 bit 3. If bit 1.1501.3 is not asserted then bits 1.1501.8, 1.1501.9, and 1.1501.10 have no effect."

Proposed Response Response Status O

Cl 45 SC 45.2.1.92a P 35 L 46 # 70
 Anslow, Pete Ciena

Comment Type E Comment Status X
 The heading row for Table 45-72a contains a blank row above the text i.e. it is two text rows high rather than one.

Same issue for Tables 45-72b, 45-72c, 45-72d, 45-72e, 45-72f, and 45-73

SuggestedRemedy
 remove the blank text row from the headings of Tables 45-72a, 45-72b, 45-72c, 45-72d, 45-72e, 45-72f, and 45-73

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 45 SC 45.2.1.92g P 38 L 47 # 279
 Cideciyan, Roy IBM
 Comment Type ER Comment Status X
 Typographical error
 SuggestedRemedy
 Replace "... identical to that described for FEC lane 0 in 45.2.1.92e." by "... identical to that described for FEC lane 0 in 45.2.1.92f."
 Proposed Response Response Status O

CI 45 SC 45.2.1.92j-k P 39 L 22 # 242
 Pillai, Velu Broadcom
 Comment Type E Comment Status X
 The PCS lane number ranges from 0 to 19. Thus a 5-bit (0-31) register should be sufficient. But the "Table 45-72h" assigns a 6-bit register to it. Same comment applies to the other lanes.
 SuggestedRemedy
 Change the register a 5-bit width. Same remedy applies to the other lanes.
 Proposed Response Response Status O

CI 45 SC 45.2.3.9 P 41 L 14 # 74
 Anslow, Pete Ciena
 Comment Type T Comment Status X
 In Register 3.20, the "LPI modes supported" bit has been inserted in the middle of a range of PHY specific bits. It seems better to use bit 15 for this.
 SuggestedRemedy
 Change "LPI modes supported" to bit 15.
 Change subsequent inserted subclause numbering accordingly.
 Proposed Response Response Status O

CI 45 SC 45.2.3.9 P 41 L 19 # 73
 Anslow, Pete Ciena
 Comment Type E Comment Status X
 The title of Table 45-105 prior to the amendment was just "EEE capability register bit definitions" so "(Register 3.20)" has been added, but is not shown in underline font.
 Also, "R/W = Read/Write," has been added to footnote a without underline
 SuggestedRemedy
 Show the addition of "(Register 3.20)" and the addition to footnote a in underline font
 Proposed Response Response Status O

CI 45 SC 45.2.3.9.e P 42 L 17 # 42
 Anslow, Pete Ciena
 Comment Type E Comment Status X
 "valid for PHYs <40 Gb/s" would be better as "valid for PHYs with rates less than 40 Gb/s"
 Similarly, in 45.2.7.13.a, "for PHYs less than 40 Gb/s" would be better as "for PHYs with rates less than 40 Gb/s"
 SuggestedRemedy
 Change:
 "valid for PHYs <40 Gb/s" to:
 "valid for PHYs with rates less than 40 Gb/s"
 In 45.2.7.13.a, change:
 "for PHYs less than 40 Gb/s" to:
 "for PHYs with rates less than 40 Gb/s"
 Proposed Response Response Status O

CI 45 SC 45.2.7.13 P 44 L 12 # 86
 Healey, Adam LSI Corporation
 Comment Type T Comment Status X
 Clause references and next page bit numbers are TBD for bits 7.60.7 to 7.60.14.
 SuggestedRemedy
 Add clauses references and next page bit numbers for these bits.
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 45 SC 45.2.7.13 P 44 L 12 # 75
 Anslow, Pete Ciena

Comment Type T Comment Status X

In Register 7.60, the "LPI modes supported" bit has been inserted as bit 14, which will be in the middle of a range of PHY specific bits when more PHYs are added. It seems better to use bit 0 for this.

Same issue for Register 7.61

SuggestedRemedy

Change "LPI modes supported" to bit 0.
 Change subsequent inserted subclause numbering accordingly.

Make the equivalent change in Register 7.61

Proposed Response Response Status O

Cl 45 SC 45.2.7.14 P 46 L 35 # 87
 Healey, Adam LSI Corporation

Comment Type T Comment Status X

Clause references and next page bit numbers are TBD for bits 7.61.7 to 7.61.14.

SuggestedRemedy

Add clauses references and next page bit numbers for these bits.

Proposed Response Response Status O

Cl 69 SC 69.2.4 P 53 L 9 # 43
 Anslow, Pete Ciena

Comment Type E Comment Status X

In Table 69-1a the heading for Clause 91 is "100GBASE-R RS-FEC" which is not consistent with the term used elsewhere (and in Table 80-2a)

SuggestedRemedy

Change the heading to "RS-FEC"

Proposed Response Response Status O

Cl 73 SC 73.3 P 54 L 17 # 44
 Anslow, Pete Ciena

Comment Type E Comment Status X

"100GBASE-KR4" is split across two lines. Prevent this from happening by replacing the "-" with a non-breaking hyphen (Esc - h)

SuggestedRemedy

Replace the "-" in "100GBASE-KR4" with a non-breaking hyphen (Esc - h)

Proposed Response Response Status O

Cl 73 SC 73.6.10 P 55 L 7 # 45
 Anslow, Pete Ciena

Comment Type E Comment Status X

The editing instruction is "Replace". This is described on page 21 of the draft as: "Replace is used to make changes in figures or equations by removing the existing figure or equation and replacing it with a new one."
 Therefore the strikeout and underline fonts are not appropriate and the third paragraph of the subclause would not be shown.

Similar issue with 73.7.2

SuggestedRemedy

Change the editing instruction to:
 "Change 73.6.10 as shown:"

Change the editing instruction for 73.7.2 to:
 "Change 73.7.2 as shown:"

Proposed Response Response Status O

Cl 78 SC 5 P 67 L 40 # 2
 Slavick, Jeff Avago Technologies

Comment Type E Comment Status X

Note says to add Figure 78-5 at the end of section 78.5 but the figures below is labeled Figure 78-7

SuggestedRemedy

Change the note to refer to the proper figure number.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 78 SC 5 P 68 L 12 # 10
 Slavick, Jeff Avago Technologies

Comment Type T Comment Status X

Definitions for each of the different case types is needed for Table 78-4.

SuggestedRemedy

Add definotns for the following modes of operation.

FAST WAKE
 DEEP SLEEP
 SCRAMBLER BYPASS

Proposed Response Response Status O

Cl 78 SC 78.2 P 60 L 35 # 49
 Anslow, Pete Ciena

Comment Type E Comment Status X

The editing instruction says:
 "Change table title and column heading and add rows to Table 78-2 to for 100 Gb/s Ethernet:" but the inserted rows include 40G PHYs.

SuggestedRemedy

Change the Table 78-2 editing instruction to:
 "Change table title and column heading and insert rows at the bottom of Table 78-2 as follows:"

Proposed Response Response Status O

Cl 78 SC 78.2 P 61 L 8 # 71
 Anslow, Pete Ciena

Comment Type E Comment Status X

The additional rows in Table 78-2 are formatted differently from the existing rows.

In Table 78-2 of IEEE Std 802.3-2012 numbers above 1000 are shown with a space as a thousands separator. However the new rows do not have this space.

SuggestedRemedy

Change "1700" to "1 700" (7 instances) and change "1800" to "1 800" (7 instances) to match the existing table.

Proposed Response Response Status O

Cl 78 SC 78.4.2.5 P 64 L 3 # 46
 Anslow, Pete Ciena

Comment Type E Comment Status X

The editing instruction says: "Add the following state diagrams at the end of 78.4.2.5" but there is text to be added as well.

Also, Figure 78-6 is the last figure in Clause 78 so they should be numbered Figures 78-7 and 78-8.

SuggestedRemedy

Change the editing instruction to:
 "Insert the following text and state diagrams at the end of 78.4.2.5"

Change the figure numbers to 78-7 and 78-8

Proposed Response Response Status O

Cl 78 SC 78.5 P 67 L 29 # 47
 Anslow, Pete Ciena

Comment Type E Comment Status X

Inserting the text and figure with separate editing instructions is not necessary and is different from the way this has been done elsewhere in the draft.
 There is no reference to the new figure in the text.
 The figure number in the second editing instruction does not match that of the inserted figure.
 The figure number should be 78-9 because two previous figures have been inserted in 78.4.2.5 (see separate comment about those figure numbers)

SuggestedRemedy

Remove the second editing instruction and change the first one to:
 "Insert the following text and figure at the end of 78.5:"
 Add a reference to the new figure in the text.
 Change the figure number to 78-9.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 78 SC 78.5 P 67 L 31 # 81
 Anslow, Pete Ciena

Comment Type T Comment Status X

The text "For PHYs with an operating speed of 40 Gb/s and 100 Gb/s (that implement EEE)" would be better if "40 Gb/s and 100 Gb/s" was changed to "40 Gb/s or 100 Gb/s" since it is not required that PHYs do both.

SuggestedRemedy
 Change "40 Gb/s and 100 Gb/s" to "40 Gb/s or 100 Gb/s"

Proposed Response Response Status O

Cl 78 SC 78.5 P 67 L 32 # 116
 Trowbridge, Steve Alcatel-Lucent

Comment Type T Comment Status X

Given that P802.3bm has adopted an EEE objective to support fast wake operation and assuming that fast wake signaling will be modified to be compatible with the OTN mapper, insert a warning that "Deep Sleep" operation must not be enabled for any 40 Gb/s or 100 Gb/s PHY that is transparently mapped over OTN.

SuggestedRemedy
 Insert the indicated warning.

Proposed Response Response Status O

Cl 78 SC 78.5 P 67 L 37 # 72
 Anslow, Pete Ciena

Comment Type E Comment Status X

There should be a non-breaking space (Ctrl Space) between a number and its unit. "mandatory for 40Gb/s and 100Gb/s PHYs" should be "mandatory for 40 Gb/s and 100 Gb/s PHYs"

SuggestedRemedy
 Change "mandatory for 40Gb/s and 100Gb/s PHYs" to "mandatory for 40 Gb/s and 100 Gb/s PHYs"

Proposed Response Response Status O

Cl 78 SC 78.5 P 67 L 44 # 115
 Trowbridge, Steve Alcatel-Lucent

Comment Type T Comment Status X

Figure 78-7 Refresh phase is not needed for fast wake. This is something that is needed when the transmitter is turned off during the sleep state as a periodic "hello" to check that the link is up. Since the link remains up with continuous signaling, this is not needed for fast wake. Nor is the "Sleep" signaling needed, since FW signaling asserts LPI. Advance warning is needed if the transmitter is to be turned off, but no advance warning is needed to stop sending data and assert LPI. Note that this is one of several comments aimed to allow use of the same "Fast Wake" operation for optical interfaces.

SuggestedRemedy
 Change to the necessary four states: Active, FW signaling, Wake, Active

Proposed Response Response Status O

Cl 78 SC 78.5 P 68 L 1 # 48
 Anslow, Pete Ciena

Comment Type E Comment Status X

The editing instruction says:
 "Add rows to Table 78-4 to for 100 Gb/s Ethernet:"
 The title and heading rows have been changed as well.
 The inserted rows include 40G PHYs

SuggestedRemedy
 Change the editing instruction to:
 "Change table title and column heading and insert rows at the bottom of Table 78-4 as follows:"

Proposed Response Response Status O

Cl 78 SC 78.5 P 68 L 35 # 76
 Anslow, Pete Ciena

Comment Type T Comment Status X

In Table 78-4, the last inserted row is for "CAUI", but in Table 78-2 the entry was "XLAUI/CAUI"

SuggestedRemedy
 Change "CAUI" to "XLAUI/CAUI"

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 78 **SC 78.5.2** **P 68** **L 40** # **77**
 Anslow, Pete Ciena

Comment Type **T** **Comment Status** **X**

The title is "40 Gb/s and 100 Gb/s PHY extension using CAUI" but 40G extension uses XLAUI and this is discussed in the subclause text

SuggestedRemedy
 Change the title to "40 Gb/s and 100 Gb/s PHY extension using XLAUI or CAUI"

Proposed Response **Response Status** **O**

Cl 79 **SC 79.3.6** **P 71** **L 44** # **53**
 Anslow, Pete Ciena

Comment Type **E** **Comment Status** **X**

Figure 79-6a is inserted after Figure 79-6 which is the last figure in Clause 79. This means that it should be numbered Figure 79-7

SuggestedRemedy
 Change the figure number to 79-7

Proposed Response **Response Status** **O**

Cl 79 **SC 79.3** **P 71** **L 6** # **51**
 Anslow, Pete Ciena

Comment Type **E** **Comment Status** **X**

The editing instruction is "Add a row and adjust the reserved row of Table 79-1 as shown:", but "add" and "adjust" are not valid editing instructions.

SuggestedRemedy
 Change editing instruction to:
 "Change the reserved row of Table 79-1 and insert a new row immediately above it as shown:"

Proposed Response **Response Status** **O**

Cl 79 **SC 79.3.a.7** **P 72** **L 1** # **54**
 Anslow, Pete Ciena

Comment Type **E** **Comment Status** **X**

The two subclauses after 79.3.6.1 should be 79.3.6.2 and 79.3.6.1 not 79.3.a.7

SuggestedRemedy
 Fix the numbering of these two subclauses

Proposed Response **Response Status** **O**

Cl 79 **SC 79.3.6** **P 71** **L 26** # **52**
 Anslow, Pete Ciena

Comment Type **E** **Comment Status** **X**

In Figure 79-6a there is "subtype = TBA"
 It would be helpful to show "TBA" in magenta as per other TBDs

SuggestedRemedy
 Show "TBA" in magenta

Proposed Response **Response Status** **O**

Cl 79 **SC 79.4** **P 73** **L 1** # **56**
 Anslow, Pete Ciena

Comment Type **E** **Comment Status** **X**

This is shown as Table 79-7, but it should be Table 79-10

SuggestedRemedy
 Change the table numbering to be Table 79-10

Proposed Response **Response Status** **O**

Cl 79 **SC 79.4.2** **P 72** **L 21** # **55**
 Anslow, Pete Ciena

Comment Type **E** **Comment Status** **X**

The editing instruction is "Change the second paragraph of 79.4.2 and append rows to Tables 79-9 and 79-10 as shown:" but "append" is not a valid editing instruction.

SuggestedRemedy
 Change the editing instruction to "Change the second paragraph of 79.4.2 and insert rows at the end of Tables 79-9 and 79-10 as shown:"

Proposed Response **Response Status** **O**

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 79 SC 79.5.3 P74 L7 # 57
 Anslow, Pete Ciena

Comment Type E Comment Status X

The editing instruction is "Append a row to major capabilities table in 79.5.3 as shown:" but "append" is not a valid editing instruction.

SuggestedRemedy

Change the editing instruction to "Insert a row at the bottom of the major capabilities table in 79.5.3 as shown:"

Proposed Response Response Status O

Cl 80 SC 80.3.2 P80 L8 # 103
 Dawe, Piers IPtronics

Comment Type T Comment Status X

Repeating D1.2 comment 407 in different words:
 Figure 80-3 has nothing to do with Clause 91 FEC (the FEC here has to be Clause 74 FEC), nor with EEE. Therefore nothing in it should change in this project.

SuggestedRemedy

Delete:
 "Change note in Figure 80-3 as shown:
 NOTE 1—OPTIONAL OR OMITTED DEPENDING CONDITIONAL BASED ON PHY TYPE"

Proposed Response Response Status O

Cl 80 SC 80.3.3.4 P81 L44 # 58
 Anslow, Pete Ciena

Comment Type E Comment Status X

This says "Without EEE capability (with the deep sleep mode option), the primitive is never invoked ..." which is rather confusingly written.

Same issue in 80.3.3.7

SuggestedRemedy

Change to "Without EEE deep sleep mode capability, the primitive is never invoked ..."

Make equivalent change in 80.3.3.7

Proposed Response Response Status O

Cl 80 SC 80.4 P84 L26 # 210
 Ran, Adeo Intel

Comment Type TR Comment Status X

The base document says "See 44.3 for the calculation of bit time per meter of fiber or electrical cable."

44.3 includes equation and table which implicitly assume BT = 100 ps (since clause 44 is "Intro to 10 Gb/s"). This is adequate for all 10G PHYs, but not for 40G and 100G PHYs, which are the subject of clause 80.

SuggestedRemedy

Add an instruction to change the sentence
 "See 44.3 for the calculation of bit time per meter of fiber or electrical cable."
 to the following text (adding a new equation 80-1):

<start replacement text>

Equation (80–1) specifies the calculation of cable delay in nanoseconds per meter of fiber or electrical cable, based upon the parameter n, which represents the ratio of the speed of electromagnetic propagation in the fiber or electrical cable to the speed of light in a vacuum, $c = 3 \times 10^8$ m/s.

$$\text{cable delay} = 10^9 / (n \cdot c) [\text{ns/m}] \quad (80-1)$$

The value of n should be available from the fiber or electrical cable manufacturer, but if no value is known then a conservative delay estimate can be calculated using a default value of $n = 0.66$, which yields a default cable delay of 5 ns/m.

<end replacement text>

There is no need to include a table as in 44-3 - this table is a simple arithmetic result of the formula. There is also no need to have separate equations for delays in BT units, since the conversions to BT are described in the notes of table 80-3.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 80 SC 80.4 P 84 L 41 # 204
 Ran, Adee Intel

Comment Type T Comment Status X

Note for 100GBASE-CR4 PMD says "Does not include delay of cable medium". Copper cable PMDs (40GBASE-CR4 100GBASE-CR4) are the only cases where such exclusion is made.

Why should this delay be left for network planners and administrators to calculate? The cable medium delay per meter is known (Based on table 80-3 it is about 10 ns/m). For 5 meters, this is 50 ns, which dominates over the suggested 100GBASE-CR4 PMD delay.

Accounting for the maximum medium delay will make it easier to calculate total network delay in this case (compare to the backplane PMDs whose medium delay is included; see 84.4).

For optical PMD types, table 80-3 includes 2 m of fiber, which is a precedence for including the delay of a functionally comparable medium.

SuggestedRemedy

Change maximum delay for the 100GBASE-CR4 PMD to 16 pause_quanta (and corresponding bit time and ns values).

Change the note to "includes 5 m of cable. see 92.4"

Proposed Response Response Status O

CI 80 SC 80.5 P 86 L 8 # 82
 Healey, Adam LSI Corporation

Comment Type E Comment Status X

In Table 80-4, cross-references for skew allowed at SP0, SP7, RS-FEC transmit, and RS-FEC receive are TBD.

SuggestedRemedy

For SP0 and SP7, refer to 83.5.3.1 and 83.5.3.5 respectively. For RS-FEC transmit and RS-FEC receive, refer to 91.5.2.2 and 91.5.3.1 respectively.

Proposed Response Response Status O

CI 80 SC 80.5 P 87 L 8 # 83
 Healey, Adam LSI Corporation

Comment Type E Comment Status X

In Table 80-5, cross-references for skew variation allowed at SP0, SP7, RS-FEC transmit, and RS-FEC receive are TBD.

SuggestedRemedy

For SP0 and SP7, refer to 83.5.3.1 and 83.5.3.5 respectively. For RS-FEC transmit and RS-FEC receive, refer to 91.5.2.2 and 91.5.3.1 respectively.

Proposed Response Response Status O

CI 81 SC 3a.2.1 P 94 L 21 # 11
 Slavick, Jeff Avago Technologies

Comment Type T Comment Status X

PIASE bit is TBD, but is now assigned

SuggestedRemedy

Change TBD to 1.7.9

Proposed Response Response Status O

CI 81 SC 3a.3.1 P 95 L 44 # 12
 Slavick, Jeff Avago Technologies

Comment Type T Comment Status X

PIASE bit reference is listed as TBD, but it's been assigned.

SuggestedRemedy

Change TBD to 1.7.9

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 81 SC 81.3.1.2 P90 L 10 # 59
 Anslow, Pete Ciena

Comment Type E Comment Status X

The editing instruction says "Change Table 81-3 as follows:" but only one of the rows of the existing table is shown.
 Change this to be in line with other table changes in this draft.

Same issue for Table 81-4

SuggestedRemedy

Change the editing instruction to "Change the first reserved row of Table 81-3 and insert a new row immediately below it as follows:"
 Show only one reserved row with "06" in strikethrough and "05" in underline font.

Change the editing instruction and table for Table 81-4 in the same way.

Proposed Response Response Status O

Cl 81 SC 81.3.4 P91 L 47 # 60
 Anslow, Pete Ciena

Comment Type E Comment Status X

The whole subclause 81.3.4 is shown although only one paragraph is changed.

SuggestedRemedy

Change the editing instruction to:
 "Change the third paragraph of 81.3.4 as follows:"
 and only show the changed paragraph.

Proposed Response Response Status O

Cl 81 SC 81.3a.2.1 P94 L 21 # 84
 Healey, Adam LSI Corporation

Comment Type E Comment Status X

PIASE is mapped to bit 1.TBD.

SuggestedRemedy

Replace 1.TBD with the correct mapping.

Proposed Response Response Status O

Cl 81 SC 81.3a.2.1 P94 L 21 # 78
 Anslow, Pete Ciena

Comment Type T Comment Status X

This says "PMA Ingress AUI Stop Enable (PIASE) bit (1.TBD)"
 The PIASE bit is 1.7.9

Same issue in 81.3a.3.1

SuggestedRemedy

Change "TBD" to "1.7.9" here and in 81.3a.3.1

Proposed Response Response Status O

Cl 81 SC 81.3a.3.1 P95 L 43 # 85
 Healey, Adam LSI Corporation

Comment Type E Comment Status X

PIASE is mapped to bit 1.TBD.

SuggestedRemedy

Replace 1.TBD with the correct mapping.

Proposed Response Response Status O

Cl 82 SC 0 P115 L 36 # 15
 Slavick, Jeff Avago Technologies

Comment Type T Comment Status X

Extra LPI_FW in the FW_TX_WAKE state

SuggestedRemedy

Remove the "LPI_FW" from the FW_TX_WAKE state box.

Proposed Response Response Status O

Cl 82 SC 0 P115 L 40 # 5
 Slavick, Jeff Avago Technologies

Comment Type E Comment Status X

Figure 82-16 extra character in TX_WAKE state for down_count.

SuggestedRemedy

Change "idown_count" in TX_WAKE to be "down_count"

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 82 SC 2.18.3.1 P 107 L 15 # 13
 Slavick, Jeff Avago Technologies

Comment Type T Comment Status X
 Timer durations for scrambler bypass are too short. Minimum amount of time spent in scrambler byass is 5 FEC frames. Clause 74 FEC frame is 2112 bits long, so 40G takes 204.8 ns / FEC frame; 100G takes 409.6 ns / FEC frame.

SuggestedRemedy
 In Table 82-5a
 Set Tbyop to be 1.1 to 1.3 us for 40Gbps operation
 Set Tbyop to be 2.1 to 2.3 us for 100Gbps operation

Proposed Response Response Status O

Cl 82 SC 2.18.3.1 P 107 L 33 # 14
 Slavick, Jeff Avago Technologies

Comment Type T Comment Status X
 There are two entries for Twr 40Gbps in Table 82-5b, but no 100Gbps entry.

SuggestedRemedy
 Change the Twr entry which has a max value of 6.5 in Draft 1.3 to be for 100Gbps instead of 40Gbps

Proposed Response Response Status O

Cl 82 SC 2.18.3.1 P 107 L 35 # 4
 Slavick, Jeff Avago Technologies

Comment Type E Comment Status X
 We have nested if then else structure for the time durations of the Twr timer. Shifting the entries to follow that structure makes it easier to understand.

SuggestedRemedy
 Move the Twr timer when LPI_FW=TRUE to be listed as the first Twr timer in Table 82-5b.

Proposed Response Response Status O

Cl 82 SC 2.8a P 101 L 17 # 3
 Slavick, Jeff Avago Technologies

Comment Type E Comment Status X
 Extra space in the hex character field of PCS lane 12

SuggestedRemedy
 Remove the change "0x B9" to 0xB9

Proposed Response Response Status O

Cl 82 SC 82 P 113 L 1 # 79
 Anslow, Pete Ciena

Comment Type T Comment Status X
 Figures 82-14 and 82-15 have no editing instruction associated with them and no text that refers to them.

SuggestedRemedy
 Add an appropriate editing instruction and some text that refers to these two figures.

Proposed Response Response Status O

Cl 82 SC 82.1.5 P 97 L 52 # 61
 Anslow, Pete Ciena

Comment Type E Comment Status X
 The editing instruction for 82.1.5 only changes Figure 82-2 so there is no need to show the text from 82.1.5

SuggestedRemedy
 Remove the text from 82.1.5.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 82 SC 82.2.18.2.3 P 104 L 42 # 235
Brown, Matthew Applied Micro

Comment Type T Comment Status X

The note is inconsistent with a similar requirement in 49.2.4.4. A PHY that supports EEE or has the EEE capability, is by definition established in 802.3az a PHY that has the EEE implemented and has negotiated EEE.

78.3 states "During Auto-Negotiation, both link partners indicate their EEE capabilities. EEE is supported only if during Auto-Negotiation both the local device and link partner advertise the EEE capability for the resolved PHY type. If EEE is not supported, all EEE functionality is disabled and the LPI client does not assert LPI. If EEE is supported by both link partners for the negotiated PHY type, then the EEE function can be used independently in either direction."

SuggestedRemedy

Change the sentence:

"If EEE has not been negotiated or if the PCS does not support EEE, LPI shall not be transmitted and shall be treated as an error if received."
to...

"If EEE is not supported, LPI shall not be transmitted and shall be treated as an error if received."

Proposed Response Response Status O

CI 82 SC 82.2.18.2.3 P 104 L 42 # 234
Brown, Matthew Applied Micro

Comment Type T Comment Status X

The note is inconsistent with a similar note in the T_TYPE definition (page 105, line 21) and for the R_BLOCK_TYPE definition in Clause 49. A PHY that supports EEE or has the EEE capability, is by definition established in 802.3az a PHY that has the EEE implemented and has negotiated EEE.

78.3 states "During Auto-Negotiation, both link partners indicate their EEE capabilities. EEE is supported only if during Auto-Negotiation both the local device and link partner advertise the EEE capability for the resolved PHY type. If EEE is not supported, all EEE functionality is disabled and the LPI client does not assert LPI. If EEE is supported by both link partners for the negotiated PHY type, then the EEE function can be used independently in either direction."

SuggestedRemedy

Change the note to:

"A PCS that does not support EEE classifies vectors containing one or more /LI/ control characters as type E."

Proposed Response Response Status O

CI 82 SC 82.2.18.3.1 P 106 L 41 # 63
Anslow, Pete Ciena

Comment Type E Comment Status X

"as shown in figures 82-16 and 82-17." should be "as shown in Figure 82-16 and Figure 82-17."

SuggestedRemedy

Change: "as shown in figures 82-16 and 82-17." to: "as shown in Figure 82-16 and Figure 82-17."

Proposed Response Response Status O

CI 82 SC 82.2.3.4 P 99 L 11 # 62
Anslow, Pete Ciena

Comment Type E Comment Status X

The editing instruction says "Insert row in Table 82-1 for LPI coding:"
It is not appropriate to show two other rows of Table 82-1
The editing instruction should say where the row is to be inserted.

SuggestedRemedy

Change the editing instruction to:

"Insert LPI row in Table 82-1 between the idle and start rows:"

Only show the LPI row in the table

Proposed Response Response Status O

CI 82 SC 82.2.8a P 99 L 44 # 117
Trowbridge, Steve Alcatel-Lucent

Comment Type T Comment Status X

Rapid Alignment marker insertion should only be done for the "refresh" and "wake" phases coming out of deep sleep. It should not be used for fast wake. See supporting presentation.

SuggestedRemedy

Separate the description of how "deep sleep" and "fast wake" modes of operation are handled. FW signaling should be done by sending continuous LPI control characters with normal alignment marker spacing (maintaining the alignment with the normal data stream), and transitioning to Idle control characters Tw before sending data resumes.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl **83** SC **83.5.8** P **120** L **13** # **64**
 Anslow, Pete Ciena

Comment Type **E** Comment Status **X**

The modified text says "for 40GBASE-KR4, 40GBASE-CR4, 100BASE-CR10 PMDs, 100GBASE-KR4, and 100GBASE-CR4."
 This has "PMDs in the wrong place."

SuggestedRemedy

Change to "for 40GBASE-KR4, 40GBASE-CR4, 100BASE-CR10, 100GBASE-KR4, and 100GBASE-CR4 PMDs."

Proposed Response Response Status **O**

Cl **83A** SC **83A.3.3.1.1** P **294** L **34** # **69**
 Anslow, Pete Ciena

Comment Type **E** Comment Status **X**

There should be a non-breaking space (Ctrl Space) between a number and its unit.
 Here, "30mV within 500ns" should be "30 mV within 500 ns" and on line 36, "720mV within 500ns" should be "720 mV within 500 ns"

SuggestedRemedy

Change: "30mV within 500ns" to "30 mV within 500 ns" and on line 36, change "720mV within 500ns" to "720 mV within 500 ns"

Proposed Response Response Status **O**

Cl **84** SC **84.7.4** P **123** L **21** # **214**
 Ran, Adeo Intel

Comment Type **TR** Comment Status **X**

"While rx_mode = QUIET, SIGNAL_DETECT changes from FAIL to OK only after a valid ALERT signal is applied to the channel."

This requires the receiver to check the validity of the ALERT signal. What is really required is discrimination of ALERT vs. QUIET; behavior in the "gray area" need not be defined. Reasonable implementations may "detect" various strong signals other than ALERT, but as long as they are not valid QUIET signals, EEE functionality is not impacted.

comment also applies to 85.7.4, page 126, line 22.

SuggestedRemedy

Change the sentence above to read

"While rx_mode = QUIET, SIGNAL_DETECT shall be held at FAIL as long as the signal at the receiver input corresponds to a QUIET tx_mode (see 84.7.6) of the link partner."

Similarly for clause 85.

Proposed Response Response Status **O**

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 91 SC 5.3.3 P 140 L 18 # 18
 Slavick, Jeff Avago Technologies

Comment Type T Comment Status X
 Based on slides 10 & 11 from cideciyan_01_0512.pdf we must always have some form of error protection enabled when sending 256b/257b data streams. So allowing for error indication to be disabled when bypass mode is enabled doesn't allow us to meet MTTFFPA since a single bit error can induce a false packet. (Corrupting a control 257b block that contains both TERM & START into a DATA)
 In gustlin_01a_0712.pdf slides 10 & 11 the statement is that error detection always occurs for option 4 (this is what we based the adoption of always sending TC blocks on). The ability to reach the 5ns latency is based on doing trailing error detection which is implementation dependent and can add complexity.
 So the specification needs to state that we always have some form of error detection/correction enabled.

SuggestedRemedy

Change "When FEC correction bypass is not supported or is disabled, the decoder shall indicate errors to the PCS and the value of FEC_error_indication_enable (see 91.6.2) has no effect. When FEC_correction_bypass is supported and enabled, this feature is enabled by the assertion of the FEC_error_indication_enable variable."
 to:
 "When FEC correction bypass is supported and enabled, the decoder shall indicate errors to the PCS and the value of FEC_error_indication_enable (see 91.6.2) has no effect. When FEC_correction_bypass is not supported or disabled, this feature is enabled by the assertion of the FEC_error_indication_enable variable."

Proposed Response Response Status O

Cl 91 SC 91.5.2.5 P 133 L 4 # 178
 Ran, Adeo Intel

Comment Type ER Comment Status X
 "most recently received block" is not well defined since the four blocks are received into the RS-FEC sublayer in parallel, at separate PCS lanes. Re-ordering can also occur. Please clarify.

SuggestedRemedy

Change "the most recently received block" to "the block received from the highest numbered PCS lane (after lane re-ordering)".

Proposed Response Response Status O

Cl 91 SC 91.5.2.5 P 133 L 46 # 179
 Ran, Adeo Intel

Comment Type ER Comment Status X
 Current text says "For each 257-bit block, bit 0 shall be the first bit transmitted". But the bits in each block are distributed over 4 lanes; if bit 0 s in lane 0, then it is transmitted at the same time as bits 10, 20 and 30 in other lanes.
 Similar bit-order instructions appear toward the end of this subclause, in page 136 lines 24 and 29.
 In fact, the next logical step and the place where bit order matters is packing bits into RS-FEC symbols. The text does not describe how this is done. Notably, the bit order within symbols, and whether the 5-bit pad occupies the 5 LSBs or 5 MBSs of a symbol, are not obvious from the text.

SuggestedRemedy

1. Delete the sentence "For each 257-bit block, bit 0 shall be the first bit transmitted".
2. Change two occurrences of "the first 1285 message bits to be transmitted from..." to "the first 1285 message bits to be packed into 10-bit symbols in..."
2. Add the following in the beginning of 91.5.2.7:
 "The bit stream created by the transcoding and alignment mapping insertion is taken in groups of 10 bits to create 10-bit symbols. The order of symbols is such that bit 0 of each 257-bit block is included in one symbol, bit 10 of the same block is included in the next symbol, and so on. Within each symbol, bit order is such that bit 0 of each 257-bit block has lower significance than bit 1 of the same block"

Editorial license is given and should probably be applied for everything above.

Also, a new figure providing a graphical description of packing bits into symbols would help.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 91 SC 91.5.2.6 P 134 L 29 # 157
 Ran, Adee Intel

Comment Type E Comment Status X

The alignment marker mapping function enables not only lane re-ordering but also RS-FEC frame locking. This fact is not evident at this point in the text - only after the remainder of 91.5.2.6 which follows figures 91-3 and 91-4. The text up to this point seems incomplete.

SuggestedRemedy

1. Move figures 91-3 and 91-4 to the end of 91.5.2.6 to make the text contiguous.
2. Delete the sentence "The RS-FEC receive function uses knowledge of this mapping to determine the FEC lane that is received on a given lane of the PMA service interface"
3. Add the following paragraph at the end of 91.5.2.6 text (but before the figures):

"The RS-FEC receive function uses knowledge of the alignment marker mapping and position to determine the FEC lane that is received on a given lane of the PMA service interface, and to obtain the correct alignment of RS codewords."

Proposed Response Response Status O

Cl 91 SC 91.5.3.3 P 140 L 10 # 111
 Dawe, Piers IPtronics

Comment Type TR Comment Status X

This says "The RS-FEC sublayer shall also be capable of detecting uncorrectable codewords." but doesn't say what constitutes an uncorrectable codeword, so it's toothless. If the FEC were to correct up to 7 symbol errors in a codeword, but pass 8 without comment, then there would be a MTTFPA problem: virtually all errors that got past the FEC would be too much for the CRC's guaranteed detection so would only get its statistical (all but 1 in 2^32) protection. But, I believe this RS code can detect up to 14 symbol errors in a codeword. With 257b coding, the standard needs to require that an implementation detect significantly more than 7, when it's correcting, so that the chance of an undetected error is tiny.

SuggestedRemedy

Define the mandatory level of detection of uncorrectable codewords, e.g. up to 14 symbol errors for 100GBASE-CR4 or 100GBASE-KR4.

Proposed Response Response Status O

Cl 91 SC 91.5.3.3 P 140 L 17 # 241
 Kochuparambil, Beth Cisco Systems

Comment Type TR Comment Status X

Ability to disable error indication leaves vulnerability in the network. Large impact to MTTFPA has been shown if this is not implemented correctly.

SuggestedRemedy

Remove FEC_error_indication_enable variable and adapt language to require bad FEC blocks be marked at all times.

Proposed Response Response Status O

Cl 91 SC 91.5.3.3 P 140 L 17 # 205
 Ran, Adee Intel

Comment Type T Comment Status X

Error marking was declared as mandatory when FEC is enabled during the November 2012 meeting. But disabling FEC decoding completely (to minimize latency) is still possible.

If error marking is optional when FEC_correction_bypass is enabled (creating a totally MTTFPA-unsafe link), it is all the more reasonable to make it optional when FEC_correction_bypass is not enabled (which would have a milder impact on MTTFPA under the same conditions, and is thus safer than turning correction off).

A supporting presentation will be submitted.

SuggestedRemedy

Change this paragraph to read

The Reed-Solomon decoder shall provide the ability to indicate errors to the PCS sublayer by intentionally corrupting 66-bit block synchronization headers. The decoder may provide an option to disable error indication in order to reduce the delay contributed by the RS-FEC sublayer. The presence of this option is indicated by the assertion of the FEC_bypass_indication_ability variable. When the option is provided, it is enabled by the assertion of FEC_bypass_indication_enable variable.

Modify management registers and PIC statements (RF7) accordingly.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 91 SC 91.5.3.3 P 140 L 20 # 280
 Cideciyan, Roy IBM
 Comment Type ER Comment Status X
 Typographical error
 SuggestedRemedy
 Replace "FEC_correction_bypass" by "FEC correction bypass". Same expression "FEC correction bypass" was used in the previous sentence that started on line 18.
 Proposed Response Response Status O

Cl 91 SC 91.5.3.3 P 140 L 20 # 110
 Dawe, Piers IPtronics
 Comment Type TR Comment Status X
 Transmitting in 257-bit transcoded format and not using FEC to identify errors gives a PCS Hamming distance of 1 rather than the 4 provided by 64B/66B. The mean time to false packet acceptance is poor, even at BERs when the link is usable (see cideciyan_01_0512.pdf but note that for short frames, the situation for 257b is about 20 times worse than shown). Warning the reader is not an adequate solution, because the user of Ethernet has to plug what he controls into a wider network that he doesn't control. Something that degrades this disgracefully and dangerously can't be called "Ethernet".
 SuggestedRemedy
 Make the FEC error indication function mandatory, always, for 257b.
 If ultra-low latency really is important, look for another coding solution, sacrificing some throughput.
 Proposed Response Response Status O

Cl 91 SC 91.5.3.3 P 140 L 25 # 281
 Cideciyan, Roy IBM
 Comment Type TR Comment Status X
 Statement on line 25 contradicts the statement in previous paragraph (line 20). It is stated that "when FEC correction bypass is not supported or is disabled, the decoder shall indicate errors to the PCS and the value of FEC_error_indication_enable (see 91.6.2) has no effect." However, the next paragraph states that "the error indication function ... or contains errors but was not corrected (when the bypass correction feature is not supported or not enabled), it shall ensure that, for every other 257-bit block within the codeword starting with the first (1st, 3rd, 5th, etc.), ..." It is not possible that the error indication function has "no effect" and "ensures" at the same time.

SuggestedRemedy
 Change sentence starting on line 23 to: "When the decoder determines that a codeword contains errors (when the bypass correction feature and the error indication function are enabled) or contains errors but was not corrected (when the bypass correction feature is not supported or not enabled), for every other 257-bit block within the codeword starting with the first (1st, 3rd, 5th, etc.), the synchronization header for the first 66-bit block at the output of the 256B/257B to 64B/66B transcoder, rx_coded_0<1:0>, is set to 11."
 Proposed Response Response Status O

Cl 91 SC 91.5.3.4 P 140 L 37 # 180
 Ran, Adee Intel
 Comment Type ER Comment Status X
 Bits are received on four lanes in parallel. Bit 0 is received at the same time as bits 10, 20, and 30 (assuming correct alignment).
 This comment applies also to subclause 91.5.3.5, line 51 of the same page.
 SuggestedRemedy
 Change "bit 0 is the first bit received" to "bit 0 is the first bit received on FEC lane 0" in both places.
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 91 SC 91.5.3.5 P 141 L 47 # 243
 Pillai, Velu Broadcom
 Comment Type ER Comment Status X
 Insert
 rx_coded_j<65:2> = rx_payloads<(64j+63):64j> for j=0 to 3
 above Step (C)
 SuggestedRemedy
 Proposed Response Response Status O

CI 91 SC 91.5.3.7 P 142 L 13 # 211
 Ran, Adeel Intel
 Comment Type TR Comment Status X
 5-bit pad is not used when re-inserting AM and can safely be ignored. The current numbers don't add up.
 Applies also to line 15 on the same page.
 SuggestedRemedy
 Change "am_rxmapped<1284:0>" to "am_rxmapped<1279:0>" (twice).
 Proposed Response Response Status O

CI 91 SC 91.5.4.2.1 P 145 L 49 # 1
 Kvist, Bengt Ericsson AB
 Comment Type E Comment Status X
 Missing word?
 "received on at 2 PCS lanes"
 SuggestedRemedy
 "received on at least 2 PCS lanes"
 or possibly "received on 2 PCS lanes"
 Proposed Response Response Status O

CI 91 SC 91.5.4.2.1 P 145 L 49 # 80
 Anslow, Pete Ciena
 Comment Type T Comment Status X
 The definition of ram_valid says "the 66-bit blocks concurrently received on at 2 PCS lanes..." which doesn't make sense.
 SuggestedRemedy
 Change "on at 2 PCS lanes" to "on at least 2 PCS lanes" to be consistent with the definition of ramps_valid
 Proposed Response Response Status O

CI 91 SC 91.5.4.2.3 P 147 L 23 # 65
 Anslow, Pete Ciena
 Comment Type E Comment Status X
 "between 2 and 2.8 ms" should be "between 2 ms and 2.8 ms" according to the style manual.
 Also, on line 26, "between 1.8 and 2 ms" should be "between 1.8 ms and 2 ms"
 SuggestedRemedy
 Change "between 2 and 2.8 ms" to "between 2 ms and 2.8 ms"
 On line 26, change "between 1.8 and 2 ms" to "between 1.8 ms and 2 ms"
 Proposed Response Response Status O

CI 91 SC 91.5.4.3 P 148 L 37 # 244
 Pillai, Velu Broadcom
 Comment Type T Comment Status X
 While in 2_GOOD, if the AMP changes due to BER or other reasons and FEC alignment state diagram (Fig91-9) still in LOSS_OF_ALIGNMENT state due to large skews, there is no way to restart the FEC synchronization state diagram (fig 91-8). Or in other words this statemachine will be in a stuck state (2_GOOD).
 SuggestedRemedy
 Add the following:
 1. AMP_COMPARE in 2_GOOD state
 2. one arc for "lamp_match" going from 2_GODD to SLIP
 3. Self loop for "amp_match" keeping it in 2_GOOD
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 91 SC 91.5.4.3 P 148 L 45 # 98
 Gustlin, Mark Xilinx

Comment Type T Comment Status X

Figure 91-8 is called the "FEC synchronzation state diagram"
 But in reality it is really performing a Alignment marker lock function, that happens to get you to FEC lock once you have all 4 FEC lanes AM locked, Figure 91-9 is the FEC alingment state diagram which makes sense.
 In addition, the block in figure 91-2 that refers to what this state machine performs and what 91-9 does is called: Aligment lock and deskew, so there is a disconnect between the SM and the functional diagram.

SuggestedRemedy

Change the title of figure 91-8 to: "Aligment marker lock state diagram"
 Note that this is the same as Figure 82-11, but how it is achieved is quite different.
 Also change the reference to 91-8 in subclause 91.5.3.1.

Proposed Response Response Status O

Cl 91 SC 91.6 P 151 L 50 # 101
 Dawe, Piers IPtronics

Comment Type E Comment Status X

PMD clauses put the MDIO function mapping early in the clause, typically "n.6 PMD MDIO function mapping" while here "RS-FEC management" and in Clause 83 "PMA MDIO function mapping" it comes last, in Clause 82 in the middle, and Clause 94 (two clauses in one) has one subclause early and another at the end.
 It would help the reader if we were consistent in subclause name and position.

SuggestedRemedy

As MDIO is there to support the sublayer not the other way round, I suggest have the MDIO section at the end, just before the PICS.

Proposed Response Response Status O

Cl 91 SC 91.6 P 152 L 11 # 158
 Ran, Adeel Intel

Comment Type E Comment Status X

Variable name should suggest the ability/option to disable error indication (which is enabled by default), similar to the option of bypassing correction.

SuggestedRemedy

Change FEC_error_indication_enable to FEC_bypass_indication_enable here and elsewhere (rename and negate logically).
 Rename MDIO control variable accordingly.
 Change description in 91.6.2 as well.

Proposed Response Response Status O

Cl 91 SC 91.6.3 P 152 L 42 # 212
 Ran, Adeel Intel

Comment Type TR Comment Status X

If the optional ability to bypass correction is declared in a status variable, so should be the optional ability to bypass error indication.

SuggestedRemedy

Add a "bypass error indication ability" variable in a new subclause, and in table 91-3.

Proposed Response Response Status O

Cl 91 SC 91.6.5 P 153 L 8 # 247
 Dudek, Mike QLogic

Comment Type T Comment Status X

Is the intent of this counter to be for all uncorrected FEC codewords including all those that don't have errors or is it intended just for uncorrected FEC codewords that have errors?

SuggestedRemedy

Clarify.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 91 SC 91.7.4.1 P 156 L 25 # 181
 Ran, Adee Intel

Comment Type ER Comment Status X

Value/comment field in TF7 and TF8 is not stated clearly.

SuggestedRemedy

Change TF7 comment field to read:
 "First 1285 message bits in every 4096th codeword are mapped alignment markers followed by a 5-bit pad".

Change TF8 comment field to read:
 "First 1285 message bits in every other codeword are mapped alignment markers followed by a 5-bit pad".

Proposed Response Response Status O

CI 91 SC 91.7.4.1 P 156 L 34 # 213
 Ran, Adee Intel

Comment Type TR Comment Status X

The 100GBASE-KP4 code has a larger "n" than the 100GBASE-KR4/CR4 code.

SuggestedRemedy

Change TF10 value from RS(528,514) to RS(544,514).

Proposed Response Response Status O

CI 91 SC 91.7.4.2 P 157 L 12 # 159
 Ran, Adee Intel

Comment Type E Comment Status X

In RF3, "capable of" makes sense, since there is an option to bypass error correction; but the behavior of actually correcting the errors (not just "being capable") is not stated. Compare to the error indication function which is clearly stated in RF6.

In RF4, there is no option to bypass, so "capable of" is should be replaced by the expected behavior.

SuggestedRemedy

Change RF3 to read:
 "When enabled, corrects any combination of up to t=7 symbol errors in a codeword"

And change RF4 to read:

"Corrects any combination of up to t=15 symbol errors in a codeword"

Editorial license granted.

Proposed Response Response Status O

CI 92 SC 10.4 P 183 L 48 # 125
 Ghiasi, Ali Broadcom

Comment Type TR Comment Status X

Equation 92-15 has discontinuity of 0.45 dB at 4.1 GHz

SuggestedRemedy

Please repalce 16.5 with 16.05 in the 1st part of the equation

Proposed Response Response Status O

CI 92 SC 10.4 P 183 L 48 # 126
 Ghiasi, Ali Broadcom

Comment Type TR Comment Status X

Equation 92-15 has an error in the 2nd part

SuggestedRemedy

Please repalce "1" prior to log with "10"

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 92 SC 8.3 P 168 L # 22
 Le Cheminant, Greg Agilent Technologies
 Comment Type E Comment Status X
 The correct spelling of Thompson (sic) is Thomson:
 (http://en.wikipedia.org/wiki/Bessel_filter)
 SuggestedRemedy
 Use Thomson
 Proposed Response Response Status O

Cl 92 SC 8.3 P 168 L 28 # 25
 Le Cheminant, Greg Agilent Technologies
 Comment Type T Comment Status X
 I believe the intent of the statement "A fourth order 33 GHz Bessel Thomson filter is to be used for all transmitter signal measurements" is that the entire test system have this response. Placing a 33 GHz filter in front of an oscilloscope will have a system response less than 33 GHz, possibly much less depending on the oscilloscope frequency response.
 SuggestedRemedy
 Replace with: A test system with a fourth-order Bessel-Thomson low-pass response (-3dB at 33 GHz) is to be used for all transmitter signal measurements
 Proposed Response Response Status O

Cl 92 SC 8.3 P 169 L 28 # 120
 Ghiasi, Ali Broadcom
 Comment Type TR Comment Status X
 Random jitter is defined without defining if the limit p-p and/or how many sigma
 SuggestedRemedy
 Assuming the definition is at BER 1E-12 or 14 sigma for p-p, please add sigma to the random jitter
 Proposed Response Response Status O

Cl 92 SC 8.3 P 169 L 30 # 124
 Ghiasi, Ali Broadcom
 Comment Type TR Comment Status X
 Total jitter is defined without defining if the limit p-p and/or how many sigma
 SuggestedRemedy
 Assuming the definition is at BER 1E-12 or 14 sigma for p-p, please add sigma to the random jitter.
 This comment maybe overtaken if we exclude random jitter from Total Jitter
 Proposed Response Response Status O

Cl 92 SC 8.3 P 169 L 31 # 119
 Ghiasi, Ali Broadcom
 Comment Type TR Comment Status X
 Current transmitter output allows total jitter excluding DDJ to be 0.28 UI. In cases transmitter have very low RJ then TJ which in this case can be all PJ could approach 0.28 UI, which will be more harmful to the transmitter.
 Current draft is incomplete as no test method has been provided to measure total jitter excluding DDJ, current test method would require real time scope with long record.
 Comment 306 was submitted on D1.1 but without consensus to make the change
 SuggestedRemedy
 Due to lack of test method and the fact total jitter could end up to be all PJ the proposed resolution is to replace Total jitter excluding DDJ with "Total Jitter excluding DDJ and Random Jitter" which can easily be measured by capturing PRBS9 waveform per test method of 85.8.3.3.
 Replace 0.28 UI with 0.15 UI for value of Total Jitter Excluding DDJ and Random Jitter
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 92 SC 8.3 P 169 L 35 # 136
 Ghiasi, Ali Broadcom
 Comment Type TR Comment Status X
 Min transition time is missing from the table
 SuggestedRemedy
 Add minimum transition to the table with value of 9.5 ps for 20-80%.
 Transmit equalization is adjusted to get 0 dB de-emphasis at TP2.
 Proposed Response Response Status O

CI 92 SC 8.3.3 P 171 L 12 # 26
 Le Cheminant, Greg Agilent Technologies
 Comment Type T Comment Status X
 Assuming that the square wave pattern referenced has sequential runs of 1's and 0's and not a 10101010 pattern (could not find 83.5.10 which has the pattern specs), a 1 UI wide histogram is appropriate to measure the noise as long as 1) the 1 UI wide histogram is positioned away from the 1-0 or 0-1 transition and 2) the use of the term noise is intended to mean any amplitude fluctuation from ideal including both random and deterministic components. (If deterministic components of the histogram are significant compared to the random, the histogram will have an RMS value that will not represent only the standard deviation of the random noise). If the square wave is a 10101010 pattern, the histogram window should be significantly less than 1 UI. (I don't believe this is the case and likely no correction is required). If the intent of the measurement is to determine the random noise, then the measurement process is the dual to jitter separation analysis, where the various amplitude interference components are determined. (This is available in oscilloscope solutions from multiple vendors) If the intent was to determine the RMS of the aggregate amplitude interferers, no change is required
 SuggestedRemedy
 Assuming the square wave pattern has long runs of 1's and 0's, and the measurement is intended to capture all amplitude interference (not just random noise) no change is required
 Proposed Response Response Status O

CI 92 SC 8.3.6 P 174 L 32 # 23
 Le Cheminant, Greg Agilent Technologies
 Comment Type E Comment Status X
 I could not find 83.5.10 to define the square wave pattern doing a document search of "83.5.10". Maybe it is being added later?
 SuggestedRemedy
 Include correct reference to the square wave pattern
 Proposed Response Response Status O

CI 92 SC 8.4.1 P 176 L 27 # 134
 Ghiasi, Ali Broadcom
 Comment Type TR Comment Status X
 Receiver input return loss has unrealistic shape and high frequency is too tight and limit stop at low a frequency.
 See comment 230 against D1.2
 SuggestedRemedy
 Propose to use EQ 92-1 from section 92.8.3.2 as I assume these are the same chip anyway
 $RL = 12 - 0.5f$ from $0.05 = f = 8$
 $= 5.65 - 9.71 \log(f / 14) 8 \leq f \leq 25 \text{ GHz (dB) (92-1)}$
 see ghiasi_01_0113
 Proposed Response Response Status O

CI 92 SC 92 P 159 L 1 # 100
 Dawe, Piers IPtronics
 Comment Type E Comment Status X
 The normal order of PMD clauses is short to long (see 802.3ae, 802.3ba).
 SuggestedRemedy
 Put the 100GBASE-KR4 clause before the 100GBASE-CR4 clause. This makes sense anyway, as 100GBASE-CR4 is made with 100GBASE-KR4 ICs.
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 92 SC 92.1 P 159 L 10 # 236
 Kochuparambil, Beth Cisco Systems

Comment Type E Comment Status X

The following sentence doesn't flow or seem to make sense:
 When forming a complete Physical Layer, a PMD shall be connected to the appropriate PMA as shown in Table 92-1, to the medium through the MDI and the management functions that are optionally accessible through the management interface defined in Clause 45, or equivalent.

SuggestedRemedy
 Perhaps change sentence to "When forming a complete Physical Layer, a PMD shall connect the appropriate PMA [...]" or similar phrasing.

Proposed Response Response Status O

Cl 92 SC 92.1 P 159 L 43 # 183
 Ran, Adeee Intel

Comment Type ER Comment Status X

BER cannot be measured or defined on differential signals, only on bits, given the reference bit sequence.

SuggestedRemedy
 Change
 "are received with a BER less than 10^{-5} "
 to
 "shall appear at the PMD sublayer service interface as the input bits into the transmitter, with a BER less than 10^{-5} ".

Proposed Response Response Status O

Cl 92 SC 92.1 P 159 L 14 # 182
 Ran, Adeee Intel

Comment Type ER Comment Status X

superfluous period (or full stop) after "apply"..

SuggestedRemedy
 delete one.

Proposed Response Response Status O

Cl 92 SC 92.1 P 159 L 45 # 184
 Ran, Adeee Intel

Comment Type ER Comment Status X

"For a complete Physical Layer, this specification is considered to be satisfied by a frame error ratio less than 1.7×10^{-10} for 64 octet frames with minimum inter-packet gap."

1. This is an incomplete description (see suggested remedy)
 2. Missing dash between 64 and octet.

SuggestedRemedy
 Change to

"For a complete Physical Layer (including the RS-FEC sublayers), this specification is considered to be satisfied by a frame error ratio less than 1.7×10^{-10} at the MAC/PLS service interface, for 64-octet frames with minimum inter-packet gap."

Proposed Response Response Status O

Cl 92 SC 92.1 P 159 L 39 # 160
 Ran, Adeee Intel

Comment Type E Comment Status X

The first paragraph following table 92-1 deals with EEE which is optional. It should be placed after the next two paragraphs which are more general.

SuggestedRemedy
 Re-order paragraphs.

Proposed Response Response Status O

Cl 92 SC 92.10.2 P 181 L 11 # 255
 Dudek, Mike QLogic

Comment Type T Comment Status X

With the changes made to draft 1.3 the maximum allowed coefficients do not correspond to the maximum insertion loss at Nyquist.

SuggestedRemedy
 Replace "corresponding to" with "and"

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 92 SC 92.10.2 P 181 L 14 # 195
 Ran, Adee Intel

Comment Type ER Comment Status X

The text suggests that figure 92-9 uses the maximum values of fitting coefficients, but note (a) of table 92-11 says that would exceed the max IL limit. I assume the graph in figure 92-9 shows a fitted IL that does not exceed the limit.

Also, missing period at end of sentence

Also the "Meets equation constraints" label in the figure suggests that this line is a limit line, which isn't the case. The only constraint that can be shown to be met on the graph is the IL at 12.8906 GHz.

SuggestedRemedy

Change the text from
 "The fitted insertion loss corresponding to one example of the maximum insertion loss at 12.8906 GHz and the maximum allowed values of a1, a2, and a4 are illustrated in figure 92-9"
 to
 "One example of the fitted insertion loss corresponding to the maximum insertion loss at 12.8906 GHz and allowed values of a1, a2, and a4 is illustrated in figure 92-9".

Consider adding the coefficient values that are used in this example to figure 92-9 caption or within the text.

Change figure 92-9 caption to read "Example of cable assembly fitted insertion loss".

In the graph, mark the IL at 12.8906 GHz to show that it meets the requirements. The "Meets equation constraints" label should be changed to "Meets max loss" with an arrow pointing to this marker, or just be deleted.

Proposed Response Response Status O

CI 92 SC 92.10.2 P 182 L 28 # 196
 Ran, Adee Intel

Comment Type ER Comment Status X

Figure 92-10 is not mentioned or referred to in the text. I assume it's an example that meets the 8 dB minimum, but it isn't clear (doesn't say "example", and the values that were used to create it are not specified).

SuggestedRemedy

Add an appropriate description.

Proposed Response Response Status O

CI 92 SC 92.10.3 P 182 L 8 # 112
 Dawe, Piers IPtronics

Comment Type TR Comment Status X

The ILD limit is near to double the 40GBASE-CR4 limit (scaled for signalling rate). I don't believe this draft spec works, even with FEC, unless the ICs are much better than needed for 100GBASE-KR4. This draft is not "without technical issues".

SuggestedRemedy

If cables are going to have this much ILD, reflection and so on, change the maximum loss to something more realistic. Show that the spec has technical feasibility (i.e. will work without requiring better-than-KR4 ICs).

Proposed Response Response Status O

CI 92 SC 92.10.3 P 183 L 7 # 166
 Ran, Adee Intel

Comment Type E Comment Status X

Equations 92-13 and 92-14 can be merged into one equation using an absolute value. That would be shorter and clearer.

SuggestedRemedy

Merge into one equation:

$$|ILD(f)| \leq 0.7 + 0.176 f$$

Proposed Response Response Status O

CI 92 SC 92.10.4 P 183 L 43 # 167
 Ran, Adee Intel

Comment Type E Comment Status X

The equation defines limits, not exact values, so "meet the values" is inadequate.

SuggestedRemedy

change "meet the values" to "be within the limits".

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 92 SC 92.10.5 P 184 L 44 # 168
 Ran, Adeo Intel

Comment Type E Comment Status X

The descriptions of NL_i(f), and of i ("is the 0 to 3 (pair-to-pair combination)"), is unclear and possibly wrong. "Combination" suggests all NEXT aggressor/victim pair combinations, and there are 16 of these, not 4.

SuggestedRemedy

Change description of NL_i(f) to "is the NEXT loss at frequency f from transmit lane i into the victim receive lane, in dB".

Change description of i to "is the transmit lane index".

Proposed Response Response Status O

CI 92 SC 92.10.6 P 185 L 9 # 197
 Ran, Adeo Intel

Comment Type ER Comment Status X

The descriptions of NL_i(f), and of i ("is the 0 to 2 (pair-to-pair combination)"), is unclear and possibly wrong. "Combination" suggests all FEXT aggressor/victim pair combinations, and there are 12 of these, not 3.

Also, NL_i(f) suggests that this is NEXT loss, but here FEXT is discussed.

SuggestedRemedy

Change NL_i to FL_i in equation 92-17 and the text below.

Change description of FL_i(f) to "is the FEXT loss at frequency f from neighbor receive lane i into the victim receive lane, in dB".

Change description of i to "is the receive lane neighbor index (out of the 3 receive lanes that are not the victim lane)".

Proposed Response Response Status O

CI 92 SC 92.10.7 P 186 L 25 # 171
 Ran, Adeo Intel

Comment Type E Comment Status X

"crosstalk RMS noise voltage" is awkward. The term "RMS" does not appear in the definitions of equations 92-20 to 92-22 or in table 92-12.

Also, equation 92-23 label suggests that this limit applies to the cable assembly. This is adequate, since the same equations are used later for the mated test fixture. It should be stated.

SuggestedRemedy

Change
 "The total integrated crosstalk RMS noise voltage"
 to
 "The total integrated crosstalk noise voltage of the cable assembly".

Proposed Response Response Status O

CI 92 SC 92.11.1.2 P 187 L 48 # 169
 Ran, Adeo Intel

Comment Type E Comment Status X

How should the differences be accounted for? This suggests some form of de-embedding, but to a non-flat baseline, which is uncommon.

If we allow a tester to modify the result in some way, we'd better to specify exactly how and to what extent. Otherwise, any "accounting" can be done and anything can be made to pass or fail.

comment also applies to 92.11.2, page 188, line 13.

SuggestedRemedy

Preferably, delete this sentence.

Otherwise add an editor's note that this accounting should be specified in more detail.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 92 SC 92.11.2 P 188 L 27 # 256
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 Equation 92-25 has the 1.17dB loss at 12.8906GHz there is no need to keep the editors note.
 SuggestedRemedy
 Delete the editor's note.
 Proposed Response Response Status O

Cl 92 SC 92.11.2 P 188 L 28 # 92
 Healey, Adam LSI Corporation
 Comment Type T Comment Status X
 The editor's note states the test fixture printed circuit board insertion loss at 12.89 GHz that is defined by Annex 92A. Since editor's notes are removed prior to final publication, this information should be added to the subclause text if it to be kept.
 SuggestedRemedy
 Move the information from the editor's note to the subclause text if it is to be kept. Delete the editor's note.
 Proposed Response Response Status O

Cl 92 SC 92.11.2 P 188 L 37 # 170
 Ran, Adee Intel
 Comment Type E Comment Status X
 "4x" label above cable assembly is not needed. It does not appear in any of the similar diagrams.
 SuggestedRemedy
 Delete label.
 Proposed Response Response Status O

Cl 92 SC 92.11.3.1 P 189 L 43 # 93
 Healey, Adam LSI Corporation
 Comment Type T Comment Status X
 The editor's note states that Annex 92A assumes the mated test fixture insertion loss is 4.11 dB at 12.89 GHz. Since editor's notes are removed prior to final publication, this information should be added to the subclause text if it to be kept.
 SuggestedRemedy
 Move the information from the editor's note to the subclause text if it is to be kept. Delete the editor's note.
 Proposed Response Response Status O

Cl 92 SC 92.11.3.3 P 191 L 37 # 257
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 The Conversion loss isn't the return loss
 SuggestedRemedy
 Change "return loss" to "conversion loss"
 Proposed Response Response Status O

Cl 92 SC 92.11.3.3 P 191 L 37 # 152
 Ran, Adee Intel
 Comment Type TR Comment Status X
 Return loss is wrong here, it's conversion loss.
 SuggestedRemedy
 Change the description of conversion_loss(f) to "is the common-mode to differential-mode conversion loss at frequency f".
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 92 SC 92.11.3.4 P 192 L 25 # 258
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 The test fixtures need to meet the common mode return loss from both ends.
 SuggestedRemedy
 Change "either" to "each"
 Proposed Response Response Status O

Cl 92 SC 92.11.3.5 P 193 L 25 # 172
 Ran, Adee Intel
 Comment Type E Comment Status X
 "RMS" is awkward and redundant here. See previous comment on 92.10.7.
 SuggestedRemedy
 Delete the word "RMS".
 Proposed Response Response Status O

Cl 92 SC 92.11.3.4 P 192 L 29 # 259
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 It would be better to not use the name "return loss" when the "common mode return loss" is meant.
 SuggestedRemedy
 Change "return loss" to "common mode return loss" here and in two places on line 35.
 Proposed Response Response Status O

Cl 92 SC 92.12 P 193 L 41 # 173
 Ran, Adee Intel
 Comment Type E Comment Status X
 Why is the PMD "per 92.7" here? 92.7 is labeled "functional specifications".
 There is only one PMD and one cable assembly defined in this clause, so their identities are implicit, without need to refer to 92.7 and 92.10.
 It is suggested to refer to figure 92-2 for illustration instead.
 SuggestedRemedy

Cl 92 SC 92.11.3.4 P 192 L 35 # 208
 Ran, Adee Intel
 Comment Type T Comment Status X
 Better note that this is common mode return loss.
 SuggestedRemedy
 Change the description of return_loss(f) to "is the common-mode return loss at frequency f".
 Proposed Response Response Status O

Change
 "The 100GBASE-CR4 PMD, as per 92.7, is coupled to the cable assembly, as per 92.10, by the MDI"
 to
 "The 100GBASE-CR4 PMD is coupled to the cable assembly by the MDI, as illustrated in figure 92-2".
 Also, delete "of 92.7" and "of 92.10" in line 47.
 Proposed Response Response Status O

Cl 92 SC 92.11.3.4 P 192 L 37 # 260
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 Incorrect figure reference
 SuggestedRemedy
 Change 92-18 to 92-20
 Proposed Response Response Status O

Cl 92 SC 92.12.1 P 193 L 48 # 198
 Ran, Adee Intel
 Comment Type ER Comment Status X
 "interface" is redundant after "MDI".
 SuggestedRemedy
 delete "interface".
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 92 SC 92.12.1.1 P 194 L 10 # 175
 Ran, Adee Intel
 Comment Type E Comment Status X
 Two periods ending sentence..
 SuggestedRemedy
 Leave only one.
 Proposed Response Response Status O

Cl 92 SC 92.12.1.1 P 194 L 6 # 174
 Ran, Adee Intel
 Comment Type E Comment Status X
 Rephrase "matching that".
 SuggestedRemedy
 change "matching that" to "that are listed".
 Proposed Response Response Status O

Cl 92 SC 92.12.1.1 P 195 L 1 # 199
 Ran, Adee Intel
 Comment Type ER Comment Status X
 Paragraph is broken by table 92-14. Also, reference to table 92-13 (line 31) should be to 92-14.
 SuggestedRemedy
 Merge paragraph and correct reference.
 Proposed Response Response Status O

Cl 92 SC 92.12.1.1 P 195 L 18 # 261
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 Table 92-14 for Style 1 connector (QSFP) doesn't include power and auxiliary signal connections whereas Table 92-15 (CFP4) does. It would be good to be consistent.
 SuggestedRemedy
 Add the power and auxiliary connections to Table 92-14.
 Proposed Response Response Status O

Cl 92 SC 92.12.1.2 P 195 L 38 # 200
 Ran, Adee Intel
 Comment Type ER Comment Status X
 Wrong figure and table references.
 Also, rephrase "matching that".
 SuggestedRemedy
 Change "figure 92-21" to "figure 92-24".
 Change "matching that" to "that are listed".
 Change "table 92-14" to "table 92-15".
 Proposed Response Response Status O

Cl 92 SC 92.12.1.2 P 195 L 39 # 262
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 Incorrect reference
 SuggestedRemedy
 Change from table 92-14 to Table 92-15. Also on page 197 line 54.
 Proposed Response Response Status O

Cl 92 SC 92.12.1.2 P 196 L 2 # 201
 Ran, Adee Intel
 Comment Type ER Comment Status X
 Too many periods at end of sentence..
 SuggestedRemedy
 Leave one.
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 92 SC 92.12.1.2 P 197 L 1 # 202
 Ran, Adee Intel
 Comment Type ER Comment Status X
 Paragraph is broken by table 92-15. Also, reference to table 92-15 (line 54) should be to 92-15.
 SuggestedRemedy
 Merge paragraph and correct reference.
 Proposed Response Response Status O

Cl 92 SC 92.14.3 P 200 L 15 # 153
 Ran, Adee Intel
 Comment Type TR Comment Status X
 CR4 is the only PMD; there are no group options as in clause 85. It should be mandatory.
 Assuming it is, then items MDC1 and MDC2 in 92.14.4.6 need not depend on it being implemented.
 SuggestedRemedy
 Change status from "O.1" to "M".
 Delete "CR4*" from items MDC1 and MDC2.
 Proposed Response Response Status O

Cl 92 SC 92.14.3 P 200 L 34 # 203
 Ran, Adee Intel
 Comment Type ER Comment Status X
 CA401 and CA402 suggest 40G vs. 100G, but we are now 100G with no 40G option. Also, PICS item CA15 (in 92.14.4.5) refers to CA100, which does not exist.
 SuggestedRemedy
 Rename these items to CAST1 and CAST2, to match the MDI items following.
 Change status in items CA13 to CA16 (in 92.14.4.5) accordingly.
 Proposed Response Response Status O

Cl 92 SC 92.14.4 P 201 L 2 # 156
 Ran, Adee Intel
 Comment Type TR Comment Status X
 Types left over from clause 85.
 SuggestedRemedy
 Change "type 40GBASE-CR4 and 100GBASE-CR10" to "type 100GBASE-CR4".
 Proposed Response Response Status O

Cl 92 SC 92.14.4.1 P 201 L 10 # 209
 Ran, Adee Intel
 Comment Type T Comment Status X
 Functional specifications items for optional EEE, like the ones added to 85.13.4.1, are missing.
 SuggestedRemedy
 Add items similar to those added to 85.13.4.1 to this table.
 Proposed Response Response Status O

Cl 92 SC 92.14.4.1 P 201 L 10 # 154
 Ran, Adee Intel
 Comment Type TR Comment Status X
 Comment of PF1 allows four or ten electricals. Also, electrical signals, not streams, here and in PF4.
 SuggestedRemedy
 Change PF1 comment to read
 "Converts four logical bit streams into four separate electrical signals"
 Change PF4 comment to read
 "Converts four electrical signals from the MDI into four logical bit streams"
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 92 SC 92.14.4.3 P 204 L 24 # 155
 Ran, Adeo Intel
 Comment Type TR Comment Status X
 TC8 to TC11 are required only if EEE with deep sleep is supported.
 Status of all these should be "LPI:M" or "LPI_DS:M", not "O".
 SuggestedRemedy
 Rephrase these item comments to include deep sleep and update status.
 Proposed Response Response Status O

Cl 92 SC 92.14.4.3 P 205 L 31 # 176
 Ran, Adeo Intel
 Comment Type E Comment Status X
 "shall be" is uncommon in PICS.
 SuggestedRemedy
 Delete it.
 Proposed Response Response Status O

Cl 92 SC 92.14.4.4 P 206 L 20 # 177
 Ran, Adeo Intel
 Comment Type E Comment Status X
 RC7 and RC8 are included in RC6 (table 92-9 summarizes interference tolerance test parameters).
 SuggestedRemedy
 Delete RC7 and RC8.
 Proposed Response Response Status O

Cl 92 SC 92.14.4.4 P 206 L 26 # 151
 Ran, Adeo Intel
 Comment Type TR Comment Status X
 There are two PICS items for AC coupling, this one is incorrect - it isn't part of the receiver. Oddly, the other PICS item, CA17, points to subclause 92.8.4.5 which discusses the receiver (I submitted another comment to move this subclause), and also lacks the "CBL" modifier that makes it relevant only for cable manufacturer. it is the only item in this table which has these features.
 SuggestedRemedy
 Delete RC10.

Add "CBL:" to CA17, and make sure points to the right place.
 Proposed Response Response Status O

Cl 92 SC 92.3 P 161 L 13 # 191
 Ran, Adeo Intel
 Comment Type ER Comment Status X
 Is the text in this subclause sufficient (and/or necessary) for the 100G case? If the PCS is co-located with the AN and PMD then support of AN_LINK.indication probably goes without saying. What happens if the PCS is in another device connected through CAUI? Is there an interface through the PMA and RS-FEC sublayers? if not, how can this primitive be implemented?
 SuggestedRemedy
 Either delete this subclause, or clarify how a non-co-located PCS should communicate, or both.
 Proposed Response Response Status O

Cl 92 SC 92.4 P 161 L 22 # 215
 Ran, Adeo Intel
 Comment Type TR Comment Status X
 If delay through medium is not included (per previous comment), "medium" should be replaced by "MDI", and 2048 ns should be corrected to 20.48 ns. Hopefully this should be OBE due to another comment.
 SuggestedRemedy
 Correct according to comment.
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 92 SC 92.4 P 161 L 22 # 206
 Ran, Adee Intel

Comment Type T Comment Status X

"medium" can be interpreted as the cable assembly but seems to refer only to the MDI. It would be better to include the cable delay as well, and increase the total, as the cable delay is dominant.

Assuming cable delay is included, the total delay should be increased by 60 ns (from the original 20.48 ns), and rounded to 16 pause_quanta.

SuggestedRemedy

Change this paragraph to read:

"The sum of the transmit and the receive delays at one end of the link contributed by the 100GBASE-CR4 PMD, AN, and MDI, plus the delay through medium in one direction, shall be no more than 8192 bit times (16 pause_quanta or 81.92 ns). It is assumed that the one way delay through the medium is no more than 6000 bit times (60 ns)."

Proposed Response Response Status O

CI 92 SC 92.5 P 161 L 32 # 248
 Dudek, Mike QLogic

Comment Type T Comment Status X

With the Transcoding and FEC encoding I don't think that PCS lanes always tranverse the same physical lane with or without skew.

SuggestedRemedy

Delete the sentence "The Skew variation must also be limited"

Proposed Response Response Status O

CI 92 SC 92.5 P 161 L 38 # 141
 Ran, Adee Intel

Comment Type TR Comment Status X

According to comment #60 on D1.2, skew at SP3 should have been 54 ns, not 45 ns.

SuggestedRemedy

Correct.

Proposed Response Response Status O

CI 92 SC 92.7.1 P 163 L 30 # 237
 Kochuparambil, Beth Cisco Systems

Comment Type E Comment Status X

Simple word change could make the sentence flow better.
 "Unless specified otherwise, all receiver measurements and tests defined in 92.8.4 are made at TP3 utilizing the test fixture specified in 92.11.1."

SuggestedRemedy

Change made to executed.

Proposed Response Response Status O

CI 92 SC 92.7.1 P 163 L 35 # 161
 Ran, Adee Intel

Comment Type E Comment Status X

Paragraph includes long complex compound sentences. Commas should be inserted for readability and correct punctuation.

SuggestedRemedy

1. Insert a comma between "the cable assembly insertion loss" and "as illustrated in Figure 92-2".
2. Insert a comma between "The cable assembly test fixture of Figure 92-15" and "or its equivalent,".

Proposed Response Response Status O

CI 92 SC 92.7.1 P 163 L 45 # 162
 Ran, Adee Intel

Comment Type E Comment Status X

Is there a page break here? paragraph ends in an orphan line in the next page.

SuggestedRemedy

Merge last line with paragraph.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 92 SC 92.7.1 P 164 L 10 # 238
 Kochuparambil, Beth Cisco Systems
 Comment Type E Comment Status X
 Table 92-6 of Transmitter Characteristics seems somewhat disjointed from the descriptions that follow.
 SuggestedRemedy
 Perhaps incorporate abbreviations/variables into the table (ex: Vdi, Vcmi, etc)
 Proposed Response Response Status O

Cl 92 SC 92.7.2 P 165 L 3 # 185
 Ran, Adeo Intel
 Comment Type ER Comment Status X
 Multiple issues with this paragraph:
 1. lane numbers denoted both in numbers (in an unclear manner) and with the letter i (without defining the range of i).
 2. "electrical streams" should be "electrical signals".
 3. convoluted definition of differential voltage.
 Similar comments apply to the text in 92.7.3.
 SuggestedRemedy
 Change this paragraph to read:
 The PMD transmit function shall convert the four bit streams requested by the PMD service interface messages PMD:IS_UNITDATA_i.request (i=0 to 3) into four separate electrical signals. The four electrical signals shall then be delivered to the MDI, all according to the transmit electrical specifications in 92.8.3. A positive differential output voltage (SLi<p> minus SLi<n>) shall correspond to tx_bit = one.
 Change 92.7.3 to read:
 The PMD receive function shall convert the four electrical signals from the MDI into four bit streams for delivery to the PMD service interface using the messages PMD:IS_UNITDATA_i.indication (i=0 to 3). A positive differential input voltage (DLi<p> minus DLi<n>) shall correspond to rx_bit = one.
 Proposed Response Response Status O

Cl 92 SC 92.7.2 P 165 L 9 # 186
 Ran, Adeo Intel
 Comment Type ER Comment Status X
 Paragraph includes long complex compound sentences. Rephrasing is suggested.
 comment also applies to 93.7.2, page 214, line 4.
 SuggestedRemedy
 Change this paragraph to read:
 "If the optional EEE capability is supported, the following requirements apply. When tx_mode is set to ALERT, the PMD transmit function shall transmit a periodic sequence, where each period of the sequence consists of 8 ones followed by 8 zeros, on each lane, with the transmit equalizer coefficients set to the preset values (see 92.7.12 and 92.8.3.4). When tx_mode is not set to ALERT, the transmit equalizer coefficients are set to the values determined via the start-up protocol (see 92.7.12)."
 Change 93.7.2 similarly with respective cross references.
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 92 SC 92.7.5 P 165 L 41 # 142
 Ran, Adee Intel

Comment Type TR Comment Status X

This requirement is too restrictive. In a real system, the exit from LPI is caused by an ALERT signaling from the TX and through the channel that the RX was trained on. It's not any "channel meeting the requirements of 92.9" and "output amplitude of 720 mV" - the cable and transmitter cannot be replaced!

The current requirement precludes setting the voltage thresholds dynamically per case (TX and channel) - which is a more robust choice and possibly easier to implement than a fixed, "worst-case" threshold.

The updated text in clauses 84 and 85 does not have this problem.

Comment also applies to 93.7.5.

SuggestedRemedy

rephrase (based on new text in 84.7.4 and 85.7.4):

When rx_mode is set to QUIET, PMD_signal_detect_i shall be set to one within 500 ns following the application of a signal at the receiver input that corresponds to an ALERT tx_mode (see 92.7.2) of the link partner. PMD_signal_detect_i shall be held at zero as long as the signal at the receiver input corresponds to a QUIET tx_mode (see 92.7.6) of the link partner.

Change 93.7.5 similarly with the respective cross references.

Proposed Response Response Status O

CI 92 SC 92.7.6 P 165 L 50 # 143
 Ran, Adee Intel

Comment Type TR Comment Status X

Global_PMD_transmit_disable function is mandatory if EEE deep sleep is implemented.

Comment applies also to 93.7.6.

SuggestedRemedy

Based on accepted change to 84.7.6 and 85.7.6:

Insert "mandatory if EEE with the deep sleep mode option is supported and is otherwise" between "is" and "optional".

Change 93.7.6 similarly.

Proposed Response Response Status O

CI 92 SC 92.8 P 168 L 9 # 108
 Dawe, Piers IPtronics

Comment Type TR Comment Status X

The following items are needed for a viable spec (technical completeness):

- Host common-mode output return loss
 - Absorbs common-mode energy
- Host mixed-mode output return loss or termination mismatch
 - Limits conversion of reflected common-mode signal into interfering differential signal
- Cable common-mode return loss
 - Absorbs common-mode energy
- Integrated common-mode conversion noise or differential to common mode through loss
 - Limits conversion into common mode that would otherwise exceed the AC common-mode output voltage spec - relevant to low loss cables in particular

These items are present in the recently issued InfinBand FDR spec.

SuggestedRemedy

Add specs:

- Host common-mode output return loss, -2 dB, 50 MHz to 19 GHz
- Host common mode to differential output return loss, 16-1.22f, 50 MHz to 19 GHz
- Cable common-mode return loss, -2 dB, 50 MHz to 19 GHz
- Integrated common-mode conversion noise, 40 mV.

Proposed Response Response Status O

CI 92 SC 92.8.3 P 168 L 29 # 187
 Ran, Adee Intel

Comment Type ER Comment Status X

Filter inventor's name is misspelled here and in 5 other places in the document (pages 168, 175, 218, 227, 269, and 279).

SuggestedRemedy

Change Thompson to Thomson, six times.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 92 SC 92.8.3 P 168 L 29 # 188
 Ran, Adee Intel
 Comment Type ER Comment Status X
 missing space between period (or full stop) and "The".
 SuggestedRemedy
 Add a space.
 Proposed Response Response Status O

Cl 92 SC 92.8.3 P 169 L 12 # 102
 Dawe, Piers IPtronics
 Comment Type E Comment Status X
 See D1.0 comment:
 Cl 93 SC 93.8.1.2 P132 L 2 # 144 Comment Type E
 Use consistent order of words. Base document uses "AC common-mode" or "ac commonmode" 20 times, 8 "common-mode AC" or "common-mode ac". Similar proportions on the internet: 6,470 to 3,830.
 SuggestedRemedy
 Change "common-mode AC" to "AC common-mode" throughout (5 changes). For consistency, do the same for "common-mode DC output voltage"
 ACCEPT.
 SuggestedRemedy
 Implement the comment fully, please. Here, Table 94-14 (3 changes), 94.3.12.3 (2 changes).
 Proposed Response Response Status O

Cl 92 SC 92.8.3 P 169 L 13 # 189
 Ran, Adee Intel
 Comment Type ER Comment Status X
 Amplitude is typically half of peak-to-peak voltage, so there's a contradiction in terms here, leading to possible confusion. Also, the fact that this is a differential voltage is not mentioned.
 This text originally appears in clause 85, table 85-5. However, in clause 72, the corresponding parameter in table 72-6 is called "Differential peak-to-peak output voltage (max.)" which is more adequate.

SuggestedRemedy
 Change parameter name to "differential peak-to-peak voltage (max)".
 If a change in clause 85 is within scope, change table 85-5 similarly.
 Proposed Response Response Status O

Cl 92 SC 92.8.3.1 P 169 L 44 # 163
 Ran, Adee Intel
 Comment Type E Comment Status X
 Paragraph is split (in mid-word) by what seems to be a page break, leaving an orphan line on the next page.
 SuggestedRemedy
 Merge this paragraph.
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 92 SC 92.8.3.1 P 170 L 23 # 207
 Ran, Adeel Intel

Comment Type T Comment Status X

Text in this paragraph is somewhat confusing. Rephrasing is suggested.

Also, propose replacing the TBD ns to 1100 ns, which is the minimum time spent in TX_ALERT state according to table 82-5a.

SuggestedRemedy

Change this paragraph to read:

If the optional EEE capability with deep sleep is supported, the following requirements also apply:

When tx_mode is changed from DATA to QUIET, the peak-to-peak differential output voltage shall be less than 30 mV within 500 ns of the transmitter being disabled. The DC common-mode output voltage shall be maintained to within ±150 mV of the value for the enabled transmitter.

When tx_mode is changed from QUIET to ALERT, the peak-to-peak differential output voltage shall be greater than 720 mV within 500 ns of the transmitter being enabled and shall meet the requirements of 92.8.1 within 1100 ns of the transmitter being enabled.

Proposed Response Response Status O

CI 92 SC 92.8.3.1 P 170 L 24 # 250
 Dudek, Mike QLogic

Comment Type T Comment Status X

There is no reason to have the transmitter amplitude lower in EEE than in normal Tx disabled mode.

SuggestedRemedy

Change the value from 30mV to 35mV.

Proposed Response Response Status O

CI 92 SC 92.8.3.1 P 170 L 25 # 239
 Kochuparambil, Beth Cisco Systems

Comment Type E Comment Status X

One sentence in this paragraph doesn't make sense.

"When the transmitter is disabled, the peak-to-peak differential output voltage shall be greater than 720mV within 500ns of the transmitter being enabled [...]"

SuggestedRemedy

Use editorial license to correct grammar to clarify the meaning of the sentence. Such as "When waking from EEE mode, [...]"

Proposed Response Response Status O

CI 92 SC 92.8.3.1 P 170 L 25 # 275
 Dudek, Mike QLogic

Comment Type TR Comment Status X

The peak to peak amplitude of the signal at TP2 is unlikely to be 720mV with 10.37dB loss between TP0 and TP2. This is an un-realistically large voltage to be achieved.

SuggestedRemedy

Either

a) Preferably reduce the requirement from 720mV to 220mV

or

b) change the test point to TP0 by adding "at TP0" between "differential output voltage" and "Shall be greater than 720mV".

Proposed Response Response Status O

CI 92 SC 92.8.3.1 P 170 L 26 # 88
 Healey, Adam LSI Corporation

Comment Type T Comment Status X

When the transmitter is disabled, it shall meet the requirements of 92.8.1 within TBD ns of the transmitter being enabled. TBD should be replaced with a value.

SuggestedRemedy

Replace "TBD ns" with 1 microsecond. Update PICS TC10 accordingly.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 92 SC 92.8.3.1 P 170 L 26 # 249
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 Incorrect reference. Subclause 92.8.1 does not give the requirements for the trasmitter.
 SuggestedRemedy
 Change reference from 92.8.1 to 92.8.3
 Proposed Response Response Status O

Cl 92 SC 92.8.3.1 P 170 L 26 # 251
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 The time to be within specification after turning on in EEE is not defined (TBD)
 SuggestedRemedy
 Use the same time as is used for 10GBASE-KR. Replace TBD with 5us.
 Proposed Response Response Status O

Cl 92 SC 92.8.3.2 P 170 L 36 # 190
 Ran, Adeo Intel
 Comment Type ER Comment Status X
 Missing period or full stop after "Ohm"
 SuggestedRemedy
 Add it.
 Proposed Response Response Status O

Cl 92 SC 92.8.3.2 P 171 L 17 # 146
 Ran, Adeo Intel
 Comment Type TR Comment Status X
 By definition, the measurement includes the measurement system noise. If it should be excluded or calibrated, then the text should describe how it should be done.
 Comment applies also to clause 93.8.1.7 (which only refers back to 85.8.3.2). and to 85.8.3.2 (which may be out of scope).

The test implicitly assumes measurement system noise comparable to or below 1 mV RMS, otherwise the TX noise is under the noise floor. This may not be the case in all 25G measurement setups. It should at least be noted as a recommendation.

SuggestedRemedy
 Change item (8) to read
 "The transmitter under test is turned off and the RMS noise of the measurement system is calculated. Denote sigma_0l and sigma_0h as this RMS value for the low-loss and high-loss cable assembly, respectively. For accurate measurement, sigma_0l and sigma_0h should be lower than 1 mV."

Add the measurement noise term to equation 92-2:

$$RMSI_dev \leq \sqrt{\sigma_{l}^2 + \sigma_{0l}^2 + 2^2}$$

 Change equation 92.3 accordingly.
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 92 SC 92.8.3.3 P 171 L 12 # 145
Ran, Adeo Intel

Comment Type TR Comment Status X

Square wave test pattern is from 83.5.10 which is optional to implement. A 100GBASE-CR4 PMD is likely integrated with a PMA. If the PMA does not implement this optional feature then this test cannot be performed.

Comment also applies to 93.8.1.7 although the test pattern is not explicitly referenced there. It also applies to clause 85.8.3.2.

SuggestedRemedy

Further discussion is required, but for the time being, add editor's notes that this text should be changed to make sure the test can be performed.

Some options for rectification (neither is perfect):

1. Change 83 to make the square wave pattern mandatory
2. Add a mandatory square wave pattern function in the PMD management
3. Change the TX noise test to use a different pattern and method (e.g. distortion analysis as done in clause 94).
4. (recommended) specify that a CR4 PMD must be attached to a PMA which supports the optional square wave test pattern.

Proposed Response Response Status O

Cl 92 SC 92.8.3.4.1 P 172 L 43 # 147
Ran, Adeo Intel

Comment Type TR Comment Status X

If peak value of p(k) is 0.5 of v_f, it means that the rise time of a step at TP2 (in preset setting) is 2 UI. This is not reasonable; the TXFFE coefficients won't be able to compensate for the combination of such a slow TX and a long cable.

For comparison, clause 85 value is 0.63 of "TX DC amplitude" (which is equivalent to v_f) with the same TXFFE coefficient range, and similar insertion loss assumption for both cable and host board.

SuggestedRemedy

Change requirement to 0.63 x v_f here and in table 92-6, also update PICS item TC16 accordingly.

Proposed Response Response Status O

Cl 92 SC 92.8.3.4.2 P 172 L 50 # 148
Ran, Adeo Intel

Comment Type TR Comment Status X

The linear fit error requirement is based on the measurement procedure defined in 85.8.3.3. This procedure does not address measurement noise (it only recommends "averaging multiple waveform captures", which may reduce noise to its mean, but not below).

It is possible that limited resolution of scopes and other measurement noises dominate the measurement results and prevent achieving the required normalized error.

To measure the TX characteristics, one should be allowed to measure the noise and calibrate the measurement accordingly. One way of doing that is to connect a precision sine wave generator in place of the DUT, generate a sine wave with the same amplitude as the TX, capture the waveform, calculate a sinusoidal fit, and measure the fitting error. The noise correction obtained from this procedure should be limited in order to ensure meaningful results.

SuggestedRemedy

My proposed change is a detailed description. Editorial license is granted.

Change this paragraph to read:

The linear fit noise shall be limited by the following procedure (using definitions in 85.8.3.3).

1. Denote E_RMS as the RMS of e(k).
2. Connect a sine wave generator in place of the DUT and set its frequency to 12.9806 GHz and its amplitude to the peak value of p(k).
3. Capture the waveform of the sine wave signal, with the same method and settings used to capture y(k). Denote the result as y_cal(k).
4. Denote Y_cal(n) the two-sided FFT of y_cal(k).
5. Calculate the normalized measurement noise N_RMS_norm as the result of:

$$N_POWER = \sum (f \text{ from } 0 \text{ to } M \cdot f_{\text{Baud}}) (\text{abs}(f) \wedge 2) - 2 \cdot \sum (f \text{ from } 12.85 \text{ GHz to } 13.11 \text{ GHz}) (\text{abs}(f) \wedge 2)$$

$$N_RMS_norm = \sqrt{N_POWER} / \text{peak}(p(k))$$

For meaningful measurements, it is recommended that N_RMS_norm be less than 0.01.

6. Denote E_cal_RMS as $\sqrt{(E_RMS / \text{peak}(p(k)) \wedge 2 - \min(N_RMS_norm, 0.01) \wedge 2)}$ (to exclude calibrated measurement noise up to 0.01 of peak(p(k))).

e_cal_RMS shall be less than 0.037.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 92 SC 92.8.3.5 P 173 L 40 # 252
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 The insertion loss is not required to be a specific value.
 SuggestedRemedy
 Change "insertion loss" to "recommended maximum insertion loss"
 Proposed Response Response Status O

Cl 92 SC 92.8.3.5 P 173 L 40 # 164
 Ran, Adeo Intel
 Comment Type E Comment Status X
 I assume the "Note" refers to the recommended maximum insertion loss, rather than the actual value.
 SuggestedRemedy
 insert "recommended maximum" between "the" and "insertion".
 Proposed Response Response Status O

Cl 92 SC 92.8.3.5 P 174 L 5 # 192
 Ran, Adeo Intel
 Comment Type ER Comment Status X
 Y axis label says "Max and Min" but only maximum is defined and shown.
 SuggestedRemedy
 Change the y-axis label to "Max Insertion Loss - Tx or Rx PCB (dB)".
 Proposed Response Response Status O

Cl 92 SC 92.8.3.6.1 P 174 L 37 # 149
 Ran, Adeo Intel
 Comment Type TR Comment Status X
 Comment also applies to 93.8.1.8.

Current definition of Even-odd jitter is based on the polarity of the pulses (compare positive pulses and negative pulses). This can bias the results due to any effect that causes positive/negative width difference rather than the even/odd that we actually want to limit. One such effect is difference between rise and fall times, but there may be others as well.

The combined effect of even/odd and positive/negative jitter can lead to inconsistent results (depending on whether they add or cancel each other).

If the test pattern is two periods of an odd-length base pattern (such as PRBS9), then the positive pulses occur at even indices in one period and at odd indices in the other. Choosing pulses from only one of the two periods may cause different results depending on which of the two periods is selected.

It is important that the measurement instructions follow what we actually want to measure.

Defining a procedure that would cover both even- and odd-length arbitrary patterns is difficult. But we already have a well-defined method in clause 94 that is tailored to measure EOJ rather than polarity-related jitter. It is proposed to use that method, instead of the current definitions.

SuggestedRemedy
 Delete the first two paragraphs of 92.8.3.6.1.

Refer to the test pattern and measurement method defined in 94.3.12.8.2, or copy and modify it, with editorial license, here and in 93.8.1.8.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 92 SC 92.8.3.6.1 P 174 L 46 # 106
 Dawe, Piers IPtronics

Comment Type T Comment Status X

This says "The reference voltage for pulse width measurements is the mid-point between the positive pulse amplitude and the negative pulse amplitude" while above, 92.8.3.6 says "The voltage threshold for the measurement of BER or crossing times is the mid-point (0 V) of the AC-coupled differential signal." It would be better to be consistent. Also, for a slow signal as is allowed here, the shorter pulses shrink in height, biasing the threshold to reduce the apparent even-odd jitter; this creates a major error. Changing the emphasis also changes the apparent even-odd jitter with this definition. Instead, even-odd jitter can be found using an extension of the DDJ method in 85.8.3.8, so one measurement can provide two measured parameters. A definition should specify the pattern, although the method here is a convenient diagnostic. Incidentally "pulse level" would be more relevant than "pulse amplitude".

SuggestedRemedy

Replace the first paragraph with:
 with

Even-odd jitter is defined for PRBS9. A correct measurement of even-odd jitter requires that the period of the test pattern is an even number of bits, so the test pattern for the purpose of even-odd jitter measurement must be two periods of the PRBS9.

Replace the second paragraph with:

Even-odd jitter is defined to be the magnitude of the difference between the mean time of all even-numbered crossings and the mean time of all odd-numbered crossings (see Figure 85-6 for an example of crossing numbering).

Put the second paragraph first.

Consider adding an informative NOTE describing the method of measuring 8 bits of alternating polarity.

Give editor licence to improve the text.

Proposed Response Response Status O

CI 92 SC 92.8.3.6.4 P 175 L 19-2 # 278
 Li, Mike Altera

Comment Type TR Comment Status X

This paragraph on effective RJ is inaccurate, self-inconsistent, and confusion

SuggestedRemedy

Replace the text with the following new paragraph:

The effective random jitter (RJ) of a signal is defined as the difference between the TJ and effective deterministic jitter (DJ). Effective DJ is derived from the BER vs sampling time distribution. BER vs sampling time distribution can also be obtained from jitter probability distribution via integration. The estimation procedure is as follows.

- a) Convert the BER vs sampling distribution to Q vs sampling time distribution, via $Q(ts) = \sqrt{2} \operatorname{erf}^{-1}(1 - (1/TD) \operatorname{BER}(ts))$, where TD is the transition density and is assumed as 0.5, and erf^{-1} is inverse error function
- b) Measure the sampling time distance from Q(ts) distribution for $Q6 = 4.753$, and denote it as TJ6, repeat the similar measurement for $Q9 = 5.998$, and denote it as TJ9
- c) Effective DJ is calculated as $DJ = (Q9 \times TJ6 - Q6 \times TJ9) / (Q9 - Q6)$
- d) Effective RJ is calculated as $RJ = TJ - DJ$

Proposed Response Response Status O

CI 92 SC 92.8.4 P 175 L 42 # 193
 Ran, Adeo Intel

Comment Type ER Comment Status X

Missing space before "The", page break leaving an orphan line on next page, and missing period at end of sentence.

SuggestedRemedy

Add space, join orphan line to paragraph, add period.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 92 SC 92.8.4.2 P 176 L 46 # 68
 Anslow, Pete Ciena
 Comment Type E Comment Status X
 Equation 92-6 now has the frequency range within the curly brackets so stating the frequency range again below the equation is not needed and is inconsistent with the other equations of this type.
 SuggestedRemedy
 Delete "for 0.01 GHz <= f <= 19 GHz" from below Equation 92-6
 Proposed Response Response Status O

CI 92 SC 92.8.4.3.1 P 177 L 47 # 253
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 In Figure 92-7 there is no need to have Receivers in the test equipment.
 SuggestedRemedy
 Replace "4 Rx" with 4 Terminations (Rx).
 Proposed Response Response Status O

CI 92 SC 92.8.4.3.4 P 179 L 3 # 276
 Dudek, Mike QLogic
 Comment Type TR Comment Status X
 There is a sign issue in equation 92-7. Increasing values of attenuation are given by more positive values of a4, however this equation would decrease the value of a4 for faster risetimes.
 SuggestedRemedy
 Change from (Tr^2 - 19^2) to (19^2-Tr^2)
 Proposed Response Response Status O

CI 92 SC 92.8.4.3.5 P 179 L 13 # 254
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 We have changed the training pattern somewhat and this reference is now incorrect.
 SuggestedRemedy
 Change 72.6.10.2 to 92.7.12
 Proposed Response Response Status O

CI 92 SC 92.8.4.3.5 P 179 L 18 # 150
 Ran, Adeel Intel
 Comment Type TR Comment Status X
 Scrambled idle, like any data, is striped across the four lanes in a way that is not easily recoverable when looking at a single lane in the RX PMD. Also, generatuing a single-lane portion of scrambled idle requires a complex pattern generator.
 Using a PCS-oriented data pattern for BER testing at the PMD interface does not make architectural sense, and would require additional hardware in the PMA.
 For BER testing at the PMD, only PRBS31 should be used, and that would require the attached PMA to support PRBS31 checking.
 SuggestedRemedy
 Specify using PRBS31 as the BER test pattern.
 Add a requirement that a PMA attached to a 100GBASE-CR4 PMD must support the ability to check received PRBS31 test patterns (PRBS31_Rx_checker_ability, refer to 83.5.10).
 May be OBE if 4-lane, MAC-level FER test is adopted instead.
 Proposed Response Response Status O

CI 92 SC 92.8.4.5 P 179 L 28 # 194
 Ran, Adeel Intel
 Comment Type ER Comment Status X
 AC coupling is in the cable assembly, so this subclause is out of place. It should be under 92.10, where currently there is no mention of AC coupling at all.
 SuggestedRemedy
 Prune and graft.
 Note that there are references to this subclause, they should be updated.
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl **92A** SC **4** P **305** L **39** # **130**
 Ghiasi, Ali Broadcom

Comment Type **TR** Comment Status **X**
 Equation 92A-1 is not consistant with the TP0 to TP2 loss where coefficient SQRT(F) and f are about the same, but equation 92A-1 linear term is twice the SQRT term. Propose to use scale version of equation 92-4.

Same comment was submitted against D1.2 comment 222. Removing the connector loss which is only 1.2 dB will not result in the linear term of the host PCB to increase by factor of 2! I am trying to make the host PCB to be consistant with the TP0 to TP2a loss.

SuggestedRemedy

If equation 92-4 is multiplied by 0.7 then loss at 12.89 Ghz will be 6.8 dB
 $IL_{Prop} = 0.0565 + 0.4263 * \sqrt{f} + 0.4045 * f$ where f is from 0.01 to 18.75 GHz.

ghiasi_01_0113 will provide the supporting material

Proposed Response Response Status **O**

Cl **92A** SC **92A.2** P **305** L **18** # **165**
 Ran, Adeel Intel

Comment Type **E** Comment Status **X**
 Text points to 93.8.1, but the characteristics there refer to TP0a, not TP0.

Comment applies also to 92A.3 with TP5/TP5a instead.

SuggestedRemedy

Either change TP0 to TP0a, or change "are defined in 93.8.1" to "are the same as those defined in 93.8.1 for TP0a".

Proposed Response Response Status **O**

Cl **92A** SC **92A.5** P **307** L **25** # **246**
 Dudek, Mike QLogic

Comment Type **T** Comment Status **X**
 The 0.5m cable (minimum insertion loss) is no longer defined by max values of the polynomial coefficients. It is now given in Equation 92-11

SuggestedRemedy

Change "is the minimum 0.5m cable assembly insertion loss using Equation(92-8) and the maximum allowed values of the polynomial coefficients a1, a2, and a4 given in Table 92-11 corresponding to the minimum insertion loss at 12.8906 GHz." to "is the minimum 0.5m cable assembly insertion loss using Equation(92-11)

Proposed Response Response Status **W**

[CommentType not specified. Set to T.]

Cl **92A** SC **92A.5** P **307** L **9** # **272**
 Dudek, Mike QLogic

Comment Type **T** Comment Status **X**
 The Maximum insertion loss of the mated test fixture is contained in Equation 92-26 not Equation 92-27. Also using the maximum insertion loss is not really valid because the test results are to be adjusted based on any deviation from actual printed circuit board loss from the nominal loss of the test boards. Also we have the Editors note on Page 189 pointing out that the Mated test fixture loss is 4.11dB at 12.8906GHz (which is between the minimum and maximum loss.

The same problem exists for the minimum loss on line 31

SuggestedRemedy

Change this definition from "is the maximum insertion loss of the mated test fixture using Equation(92-27)" to "is the nominal insertion loss of the mated test fixture using Equation new"

Add Equation new. $IL_{matedTF}(f)(nom) = 0.114 * \sqrt{f} + 0.2869 * f$. (Note that this equation has 4.11dB loss at 12.8906 GHz and is scaled from the minimum loss equation 92-27).

Make the same change on line 31 (pointing to the same new equation).

Delete the editors note on page 189.

Proposed Response Response Status **O**

Cl **92A** SC **92A.7** P **308** L **41** # **274**
 Dudek, Mike QLogic

Comment Type **T** Comment Status **X**
 The ILD of the channel is being specified as exactly the same as that of the cable (equations 92-13 and 92-14) leaving nothing for the host. Also the channel performance is much better specified by the COM,

SuggestedRemedy

Delete subclause 92A.7

Proposed Response Response Status **O**

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 92A SC 92A.8 P 309 L 12 # 273
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 As it says in the editor's note the COM value should match that in 93.9.1
 SuggestedRemedy
 Change the COM value to 4dB and delete the editor's note.
 Proposed Response Response Status O

CI 92A SC 92A.8 P 309 L 15 # 227
 Brown, Matthew Applied Micro
 Comment Type T Comment Status X
 The editor's note points out that the 3 dB COM value is already obsolete. The value in 93.9.1 was updated to 4 dB to allow for a change in the channel model used by COM.
 SuggestedRemedy
 Change the recommended COM value from 3 dB to 4 dB.
 Proposed Response Response Status O

CI 92A SC 92A.8 P 309 L 17 # 96
 Healey, Adam LSI Corporation
 Comment Type T Comment Status X
 The lower limit on COM for the TP0 to TP5 channel does not agree with Clause 93. They are intended to be the same.
 SuggestedRemedy
 Align Annex 92A and Clause 93 COM requirements.
 Proposed Response Response Status O

CI 93 SC 8.1.1 P 217 L 19 # 135
 Ghiasi, Ali Broadcom
 Comment Type TR Comment Status X
 Transition time min is defiend by asserting preset control to disable EQ.
 In cases pacakge having large ISI the min rise time can be circumvented
 SuggestedRemedy
 Repalce note b with "Transmit equalization is adjusted to get 0 dB de-emphasis at TP0a the control
 Proposed Response Response Status O

CI 93 SC 8.1.1 P 217 L 32 # 121
 Ghiasi, Ali Broadcom
 Comment Type TR Comment Status X
 Random jitter is defined wihotut defining if the limit p-p and/or how many sigma
 SuggestedRemedy
 Assuming the definition is at BER 1E-12 or 14 sigma for p-p, please add sigma to the random jitter
 Proposed Response Response Status O

CI 93 SC 8.1.1 P 217 L 32 # 123
 Ghiasi, Ali Broadcom
 Comment Type TR Comment Status X
 Total jitter is defined wihotut defining if the limit p-p and/or how many sigma
 SuggestedRemedy
 Assuming the definition is at BER 1E-12 or 14 sigma for p-p, please add sigma to the random jitter.
 This comment maybe overtaken if we exclude random jitter from Total Jitter
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 93 SC 8.1.1 P 217 L 33 # 118
 Ghiasi, Ali Broadcom

Comment Type TR Comment Status X

Current transmitter output allows total jitter excluding DDJ to be 0.28 UI. In cases transmitter have very low RJ then TJ which in this case can be all PJ could approach 0.28 UI, which will be more harmful to the transmitter.

Current draft is incomplete as no test method has been provided to measure total jitter excluding DDJ, current test method would require real time scope with long record.

Comment 321 was submitted on D1.1 but without consensus to make the change

SuggestedRemedy

Due to lack of test method and the fact total jitter could end up to be all PJ the proposed resolution is to replace Total jitter excluding DDJ with "Total Jitter excluding DDJ and Random Jitter" which can easily be measured by capturing PRBS9 waveform per test method of 85.8.3.3.

Replace 0.28 UI with 0.15 UI for value of Total Jitter Excluding DDJ and Random Jitter

Proposed Response Response Status O

Cl 93 SC 8.1.1 P 218 L 24 # 27
 Le Cheminant, Greg Agilent Technologies

Comment Type T Comment Status X

Identical to comment made on 92.8.3. Entire test system response, not just the filter, should be 33 GHz bandwidth. Thomson, not Thompson

SuggestedRemedy

Replace with: A test system with a fourth-order Bessel-Thomson low-pass response (-3dB at 33 GHz) is to be used for all transmitter signal measurements

Proposed Response Response Status O

Cl 93 SC 8.1.4 P 219 L 39 # 129
 Ghiasi, Ali Broadcom

Comment Type TR Comment Status X

Transmitter return loss mask is unrealistic with low frequency too loose and high frequency too tight. Comment was also submitted against D1.2 comment 229, with response that this output is at TP0a and suggested equation was at TP2 so these equations can be different. However in case with min channel loss the HCB loss washes the degradation due to MDI connector, generally speaking the RL will improve for the case host channel loss is increased. They could be different but current equation 93-2 is unrealistic and not clear where it came from!

SuggestedRemedy

Proposed to use equation 92-5
 $12 - 0.5 * f$ from 0.01 to 8 GHz
 $5.65 - 9.71 * \log_{10}(f/14)$ from 8 to 19 GHz

See ghiasi_01_0113

Proposed Response Response Status O

Cl 93 SC 8.1.4 P 219 L 39 # 127
 Ghiasi, Ali Broadcom

Comment Type TR Comment Status X

Transmitter output return loss is unclear at what point is measured

SuggestedRemedy

Transmitter output return loss is measured at TP0a

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 93 SC 8.1.4 P 219 L 40 # 132
 Ghiasi, Ali Broadcom

Comment Type TR Comment Status X

Transmitter output return loss has unrealistic shape and high frequency is too tight and limit stop at low a frequency.

See comment 230 against D1.2

SuggestedRemedy

Propose to use EQ 92-1 from section 92.8.3.2 as I assume these are the same chip anyway
 $RL = 12 - 0.5f$ from $0.05 = f = 8$
 $= 5.65 - 9.71 \log(f / 14) 8 \leq f \leq 25$ GHz(dB)(92-1)

see ghiasi_01_0113

Proposed Response Response Status O

CI 93 SC 8.2.1 P 224 L 24 # 128
 Ghiasi, Ali Broadcom

Comment Type TR Comment Status X

Receiver return loss mask is unrealistic with low frequency too loose and high frequency too tight. Comment was also submitted against D1.2 comment 230, with response that this output is at TP0a and suggested equation was at TP2 so these equation can be different. However in case with min channel loss the HCB loss washes the degradation due to MDI connector, generally speaking the RL will improve for the case host channel loss is increased. They could be different but current equation 93-2 is unrealistic and not clear where it came from!

SuggestedRemedy

Proposed to use equation 92-5
 $12 - 0.5 * f$ from 0.01 to 8 GHz
 $5.65 - 9.71 * \log_{10}(f/14)$ from 8 to 19 GHz

see ghiasi_01_0113

Proposed Response Response Status O

CI 93 SC 8.2.2 P 225 L 49 # 139
 Ghiasi, Ali Broadcom

Comment Type TR Comment Status X

There is interest to make the return loss for CL93 and 94 the same and also stated by the editor in comment 325 against D1.2. Instead of making CL93 and 94 identical during last comment resolution cycle we end up removing differential to common mode conversion from CL93 instead of removing common mode

SuggestedRemedy

Remove common mode return loss limit of 93-8

Proposed Response Response Status O

CI 93 SC 8.2.2 P 225 L 49 # 137
 Ghiasi, Ali Broadcom

Comment Type TR Comment Status X

There is interest to make the return loss for CL93 and 94 the same and also stated by the editor in comment 325 against D1.2. Resolution to comment 325 indicate the TBD is to be replaced with proposed limit given in comment 325 but somehow differential to common mode conversion was removed from CL93 but still exist in CL94

SuggestedRemedy

Please add differential to common mode conversion in CL93 per equation 94-17 but with limit extended to 19 GHz

$25 - 20 * (f/13.89)$ from 0.05 to 6.95 GHz
 15 GHz from 6.95 GHz to 13 GHz

Proposed Response Response Status O

CI 93 SC 93.1 P 210 L 40 # 263
 Dudek, Mike QLogic

Comment Type T Comment Status X

With the FEC bypassed the Phy will not operate at a BER of $1e-12$ when the specified (worst case channel) in 93.9 is used.

SuggestedRemedy

Change "the channel specified in 93.9" to "a channel with better performance than the worst case specifications in 93.9"

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 93 SC 93.5 P 211 L 43 # 264
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 With the Transcoding and FEC encoding I don't think that PCS lanes always tranverse the same physical lane with or without skew.
 SuggestedRemedy
 Delete the sentence "The Skew variation must also be limited"
 Proposed Response Response Status O

Cl 93 SC 93.8.1.8 P 223 L 37 # 105
 Dawe, Piers IPtronics
 Comment Type T Comment Status X
 92.8.3.6 has a paragraph about jitter measurement filter and voltage threshold that applies here also.
 SuggestedRemedy
 Add a sentence incorporating it by reference.
 Proposed Response Response Status O

Cl 93 SC 93.8.1.3 P 219 L 26 # 89
 Healey, Adam LSI Corporation
 Comment Type T Comment Status X
 When the transmitter is disabled, it shall meet the requirements of 93.8.1 within TBD ns of the transmitter being enabled. TBD should be replaced with a value.
 SuggestedRemedy
 Replace "TBD ns" with 1 microsecond. Update PICS TC12 accordingly.
 Proposed Response Response Status O

Cl 93 SC 93.8.1.8 P 223 L 41 # 99
 Dawe, Piers IPtronics
 Comment Type E Comment Status X
 Use standards language.
 SuggestedRemedy
 Change "is characterized using the procedure defined in" to "is defined in", three times in this subclause.
 Proposed Response Response Status O

Cl 93 SC 93.8.1.4 P 219 L 39 # 104
 Dawe, Piers IPtronics
 Comment Type T Comment Status X
 I'm assuming this return loss spec is under review.
 To control echoes on short channels adequately, the return loss spec must extend to a frequency where the echo is adequately attenuated by something else (e.g. a filter in the receiver). If the spec stops at 13 GHz, reflections at 13.1 GHz would dominate.
 This applies to IC-to-IC links and also, as an IC that meets the 100GBASE-KR4 specification should be suitable for use in 100GBASE-CR4, to IC-to-cable echoes in 100GBASE-CR4, even if the cable has significant loss. Note that 100GBASE-CR4 specifies host return loss 10 MHz to 19 GHz and cable return loss 50 MHz to 19 GHz, so an implementer would have to deliver adequate performance up to 19 GHz for CR4 anyway.
 The equivalent OIF spec goes up to the signalling rate.
 SuggestedRemedy
 The new limit should extend to at least 15 GHz, preferably to 19 GHz.
 Proposed Response Response Status O

Cl 93 SC 93.8.2.2 P 225 L 18 # 107
 Dawe, Piers IPtronics
 Comment Type T Comment Status X
 Please don't waste the reader's (and editor's) time.
 I've made this a technical comment in case we want different limits for transmitter and receiver.
 SuggestedRemedy
 If it is intended that receiver input return loss limit will be the same as transmitter output return loss, just refer back to Equation (93-2) and Figure 93-6.
 Remove other unnecessary repetition in clauses 92-94.
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 93 SC 93.8.2.3 P 226 L 32 # 37
 Ben-Artzi, Liav Marvell
 Comment Type T Comment Status X
 Table 93-7 and the 100GBase-KR4 interference tolerance test lacks a correlation to the channel operating margin methodology.
 SuggestedRemedy
 Will supply a presentation.
 Proposed Response Response Status O

CI 93 SC 93.8.2.3 P 226 L 38 # 35
 Mellitz, Richard Intel Corporation
 Comment Type TR Comment Status X
 omit test 2 and test 3
 make test similar to clause 94
 SuggestedRemedy
 In table 93-7
 1)replace the BER at MAC or simile . i.e. value = 1e-12
 2) add rss DFE line to table
 make it optional to test with a minimally compliant transmitter so link training can be achieved.
 3) convert jitter etc to broad band noise calibration target.
 include procedure from clause 94.
 Proposed Response Response Status O

CI 93 SC 93.9.1 P 227 L 9 # 240
 Kochuparambil, Beth Cisco Systems
 Comment Type T Comment Status X
 It has not yet been proven that <=4dB COM channels align with passing 10E-12 TX/RX operation. I have concerns that the 4dB COM limits backplane channels beyond what is reasonable; continued analysis on this topic would also be beneficial.
 SuggestedRemedy
 See Kochuparambil_01_0113
 Proposed Response Response Status O

CI 93 SC 93.9.1 P 228 L 20 # 277
 Dudek, Mike QLogic
 Comment Type TR Comment Status X
 The minimum values of the pre-cursor and post-cursor coefficients in the COM table 93-8 do not match the required pre-cursor and post-cursor in 93.8.1.6.5
 SuggestedRemedy
 Change the minimum pre-cursor from -0.18 to -0.22 and change the minimum post-cursor from -0.38 to -0.6
 Proposed Response Response Status O

CI 93 SC 93A.1.2 P 312 L 8 # 29
 Moore, Charles Avago Technologies
 Comment Type T Comment Status X
 Equations 93A-3 and 93A-4 are the opposite sign of the normal definition of reflection coefficient. I think that is due to our misinterpreting benartsi_3bj_01a_1112 slide 6. As a result I think that we are leaving out an important phase term.
 SuggestedRemedy
 Either correct sign of 93A-3 and 93A-4 or find out from Liav what he intended and do that.
 Proposed Response Response Status O

CI 93A SC 93A.1 P 310 L 15 # 97
 Healey, Adam LSI Corporation
 Comment Type T Comment Status X
 The editor's note states that a separate informative annex will be added with a sample implementation when the content of Annex 93A stabilizes. In the meantime, it would be helpful to provide pointers to existing sample implementations.
 SuggestedRemedy
 Include a link to the Task Force "tools" page that points to a sample implementation of the COM calculation.
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 93a SC 93a.1.2 P 312 L 18 # 38
 Ben-Artzi, Liav Marvell
 Comment Type T Comment Status X
 The return loss equation for TP0/TP5 as described in Eq: 93a-3,4,5 and table 93a-2 is not coherent with the measured return loss at TP0a/TP5a as described in equations 93-2, 93-7, 94-5, 94-15 as well as with cable return loss as described at equations: 92-1 and 92-5.
 SuggestedRemedy
 will supply a presentation
 Proposed Response Response Status O

Cl 93a SC 93A.1.2 P 312 L 18 # 36
 Mellitz, Richard Intel Corporation
 Comment Type TR Comment Status X
 equation 93a-5 cannot be easily amended with new data and preserve causality and passivity.
 see presentation
 SuggestedRemedy
 Use new equation for Z derived from a fitting similar clause 93A.2 for a very small length of transmission line and termination.
 see presentation
 Proposed Response Response Status O

Cl 93A SC 93A.1.5 P 314 L 45 # 30
 Mellitz, Richard Intel Corporation
 Comment Type TR Comment Status X
 In equation(93A-16) σ_{isi}^2 vanishes when N is large and large number of h_{isi} terms are zero.
 SuggestedRemedy
 change: $\sigma_{isi}^2 = \sigma_x^2 * \sum(H_{isi}^2(n))$
 Proposed Response Response Status O

Cl 93A SC 93A.1.5 P 314 L 46 # 28
 Moore, Charles Avago Technologies
 Comment Type ER Comment Status X
 In equation 93A-16 σ_{ISI}^2 is supposed to be the total ISI not the average.
 Also in equation 93A-28, σ_m^2 also should be total interference, not average, although this is not significant.
 SuggestedRemedy
 In equation 93A-16 delete "N" in denominator
 also
 In equation 93A-28 delete "N" in denominator
 Proposed Response Response Status W
 [Clause specified as 94A. Changed to 93A.]

Cl 93A SC 93A.1.6.2 P 316 L 12 # 31
 Mellitz, Richard Intel Corporation
 Comment Type TR Comment Status X
 If equation (93A-24) is discretely evaluated the integral will be equal to the number of samples.
 SuggestedRemedy
 Add a note in the $P_g(y)$ is to be normalized so that the integral = 1
 Proposed Response Response Status O

Cl 94 SC 3.10.6.4 P 260 L 11 # 17
 Slavick, Jeff Avago Technologies
 Comment Type T Comment Status X
 Allowing for multiple tap change requests to be made simultaneously complicates the response behavior of the PMD when the change takes a given tap to or beyond its operating range. It also highly complicates the logic needed to deal with these circumstances (both at the edge, and in the center of the EQ range), and what was applied and was not applied is when a MIN/MAX response is given is dependent upon the link partner implementation, thus it's unknown. Which can cause interoperability issues.
 SuggestedRemedy
 Change "Coefficient increment and decrement update requests must not be sent in combination with initialize or preset."
 to
 "A tap coefficient increment or decrement update request must not be sent in combination with initialize, preset or other tap coefficient update requests."
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 94 SC 3.10.6.4 P 260 L 9 # 16
 Slavick, Jeff Avago Technologies
 Comment Type T Comment Status X
 Allowing for Coefficient change requests to "trickle" in may cause interoperability issues since different designs will respond to the trickle in different manners.
 SuggestedRemedy
 Change "for that tap is not_updated." to "for all taps is not_updated."
 Proposed Response Response Status O

Cl 94 SC 3.12.5 P 270 L 51 # 24
 Le Cheminant, Greg Agilent Technologies
 Comment Type E Comment Status X
 I believe that "...where bits 1 to 9 are the run of 9 zeros." was intended to read "...where bits 1 to 9 are the run of 9 ones". This is what the previous text implies, and a PRBS9 pattern cannot have a run of 9 zeroes (unless it is inverted).
 SuggestedRemedy
 replace word 'zeros' with 'ones' as indicated.
 Proposed Response Response Status O

Cl 94 SC 3.12.1 P 268 L 19 # 131
 Ghiasi, Ali Broadcom
 Comment Type TR Comment Status X
 Repalce TBD for rise and fall times
 SuggestedRemedy
 Scale value of CL92/93 by factor of 2 so repalce the TBD with rise time of 16 ps
 Proposed Response Response Status O

Cl 94 SC 3.12.8 P 274 L 32 # 133
 Ghiasi, Ali Broadcom
 Comment Type TR Comment Status X
 Due to complexity of KP4 reciver allowing tracking up to Fbaud/2500 over burden the reciver when low cost oscilaltor exist to tigthen the TX loop BW
 SuggestedRemedy
 Propose to use Fbaud/10000 or 1.36 MHz for the KP4 CDR loop BW
 Proposed Response Response Status O

Cl 94 SC 3.12.1 P 268 L 19 # 122
 Ghiasi, Ali Broadcom
 Comment Type TR Comment Status X
 Transition time min is defiend by asserting preset control to disable EQ.
 In cases pacakge having large ISI the min rise time can be circumvented
 SuggestedRemedy
 Repalce note b with "Transmit equalization is adjusted to get 0 dB de-emphasis at TP0a the control
 Proposed Response Response Status O

Cl 94 SC 3.13.1 P 276 L 54 # 140
 Ghiasi, Ali Broadcom
 Comment Type TR Comment Status X
 Add standalone reciver tracking and interefence test with sinousiodal jitter
 SuggestedRemedy
 The unstress jitter tolernace test is as the following:
 Test patern is PRBS31 each lane must operate with BER 1E-8 or better.
 The applied stress is sinousiodal stress of
 25 KHz with p-p jitter of 5 UI
 125 KHz with p-p jitter of 1 UI
 See ghiasi_01_0113
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 94 SC 3.13.2 P 276 L 32 # 138
 Ghiasi, Ali Broadcom

Comment Type TR Comment Status X

Comment 215 against D1.2 was accepted where it suggest replacing burdening common mode return loss with common mode to differential mode return loss. The comment was accepted in principel and the diferential to common mode limited were added, but the burdening common mode return for the receiver is still in the draft

SuggestedRemedy

Please remove common mode specification equation 94-16

Proposed Response Response Status O

Cl 94 SC 94.2.1 P 240 L 22 # 218
 Brown, Matthew Applied Micro

Comment Type T Comment Status X

The editor's note points out that the behavior in response to tx_mode and rx_mode must be defined.

SuggestedRemedy

Define the PMA behavior in response to rx_mode and tx_mode. A proposal will be provided.

Proposed Response Response Status O

Cl 94 SC 94.2.1 P 240 L 22 # 94
 Healey, Adam LSI Corporation

Comment Type T Comment Status X

The editor's note highlights that the functional behavior of a Clause 94 PMA that supports the optional Energy Efficient Ethernet (EEE) capability is undefined. Also see 94.2.3 and 94.2.5.

SuggestedRemedy

Define the Clause 94 PMA behavior for the optional EEE capability.

Proposed Response Response Status O

Cl 94 SC 94.2.12 P 249 L 39 # 90
 Healey, Adam LSI Corporation

Comment Type T Comment Status X

In Table 94-4, the register numbers for PMA overhead control and status are TBD.

SuggestedRemedy

Define the register numbers.

Proposed Response Response Status O

Cl 94 SC 94.2.12 P 249 L 39 # 228
 Brown, Matthew Applied Micro

Comment Type T Comment Status X

MDIO status and control register fields have been specified for the PMA overhead, but specific MDIO register address is TBD. The registers are annotated in Table 94-4 and Table 94-5.

SuggestedRemedy

Provide specific MDIO register address for each of the PMA OH register fields.

Proposed Response Response Status O

Cl 94 SC 94.2.2 P L # 217
 Brown, Matthew Applied Micro

Comment Type E Comment Status X

Each sub-section under 94.2.2, except 94.2.2.3, refers the PMA in general rather than specifically the transmit portion.

SuggestedRemedy

Modify references the "the PMA" to "the PMA transmit process" at the following locations:
 page 242, line 42
 page 243, line 3
 page 243, line 50
 page 244, line 40
 page 245, line 8
 page 245, line 30
 page 245, line 48

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 94 SC 94.2.2.4 P 243 L 52 # 144
 Ran, Adeel Intel
 Comment Type TR Comment Status X
 Overhead frame size is 348 termination blocks.
 SuggestedRemedy
 Change 384 to 348.
 Proposed Response Response Status O

CI 94 SC 94.2.3 P 246 L 4 # 219
 Brown, Matthew Applied Micro
 Comment Type T Comment Status X
 The editor's note points out that the PMA transmit EEE behavior must be defined.
 SuggestedRemedy
 Define the PMA EEE behavior. A proposal will be provided.
 Proposed Response Response Status O

CI 94 SC 94.2.5 P 247 L 24 # 220
 Brown, Matthew Applied Micro
 Comment Type T Comment Status X
 The editor's note points out that the PMA receive EEE behavior must be defined.
 SuggestedRemedy
 Define the PMA receiver EEE behavior. A proposal will be provided.
 Proposed Response Response Status O

CI 94 SC 94.2.9 P 248 L 4 # 230
 Brown, Matthew Applied Micro
 Comment Type T Comment Status X
 The PMA local loopback is mandatory, not optional. It is therefore not necessary to indicate whether the loopback is supported or not. However, since there is by default an MDIO local loopback ability status bit, this bit should be always set to one for this PMA.
 SuggestedRemedy
 In line 4 on page 248, insert the following sentence...
 "The Local_loopback_ability status variable shall always be set to 1."
 Proposed Response Response Status O

CI 94 SC 94.3.11.1 P 265 L 1 # 265
 Dudek, Mike QLogic
 Comment Type T Comment Status X
 It would be better to use the same names for these fields as are used in Figure 94-8
 SuggestedRemedy
 Change "and the control and status fields" to "and the coefficient update and status report fields"
 Proposed Response Response Status O

CI 94 SC 94.3.11.1.10 P 267 L 15 # 221
 Brown, Matthew Applied Micro
 Comment Type T Comment Status X
 The editor's note points out that that the diagram is intended to show a transition at any phase alignment offset (PAO), but the PRBS13 pattern is relevant to PAO = 0.
 SuggestedRemedy
 Update the diagram to correct this. A proposal will be provided.
 Proposed Response Response Status O

CI 94 SC 94.3.11.1.10 P 267 L 17 # 95
 Healey, Adam LSI Corporation
 Comment Type T Comment Status X
 The editor's note states that the PRBS13 sequence in Figure 94-9 is based on a PAO of zero and the sequence will be different for other PAO values. This clarification is relevant even after final publication (at which point the editor's note is removed).
 SuggestedRemedy
 Incorporate this information into subclause text or figure or generalize the figure so that it is correct regardless of PAO value. Delete the editor's note.
 Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 94 **SC 94.3.11.1.3** **P 266** **L 5** # **233**
 Brown, Matthew Applied Micro
Comment Type T **Comment Status X**
 As specified in 94.3.11.1.9, the "receiver ready" status field always indicate 1.
SuggestedRemedy
 In Table 94-13, in the description column for "receiver ready" replace the text with "Always set to 1."
Proposed Response **Response Status O**

Cl 94 **SC 94.3.11.1.6** **P 266** **L** # **232**
 Brown, Matthew Applied Micro
Comment Type T **Comment Status X**
 The PMA/PMD transmitter cannot differentiate between WAKE and REFRESH modes since tx_mode indicates only ALERT and DATA for both. The EEE mode indication is therefore not usable.
SuggestedRemedy
 Remove the EEE state bit from the ALERT frame status field.
 Delete section 94.3.11.1.6.
 In Table 94-13, indicate cells 17:16 as being reserved.
Proposed Response **Response Status O**

Cl 94 **SC 94.3.12** **P 268** **L 10** # **266**
 Dudek, Mike QLogic
Comment Type T **Comment Status X**
 The Differential Peak maximum voltage with transmitter enabled has different values in Table 94-14 (1110mV) and in section 94.3.12.3 (1200mV). Also this value should be at least as large as twice the steady-state voltage Vf max (600mV) in Table 94-14 and 94.3.12.6.2
SuggestedRemedy
 Make them consistent. I suggest the value in Table 94-14 is changed from 1110mV to 1200mV.
Proposed Response **Response Status O**

Cl 94 **SC 94.3.12** **P 268** **L 19** # **216**
 Brown, Matthew Applied Micro
Comment Type T **Comment Status X**
 In Table 94-14, the value for minimum transition time is TBD.
SuggestedRemedy
 Provide a value for minimum transition time. A proposal on the subject is expected.
Proposed Response **Response Status W**
 [CommentType not specified. Set to T.]

Cl 94 **SC 94.3.12.3** **P 269** **L 47** # **267**
 Dudek, Mike QLogic
Comment Type T **Comment Status X**
 There is no reason to allow the output voltage with EEE to be larger than the Tx disabled output voltage
SuggestedRemedy
 Change 35mV to 30mV to match the value in Table 94-14.
Proposed Response **Response Status O**

Cl 94 **SC 94.3.12.5** **P 270** **L 35** # **91**
 Healey, Adam LSI Corporation
Comment Type T **Comment Status X**
 Editor's note states that suitable pattern, methodology, and values for [minimum] transition time are needed.
SuggestedRemedy
 Define pattern, methodology, and values. Update PICS TC16 accordingly.
Proposed Response **Response Status O**

Cl 94 **SC 94.3.12.5** **P 270** **L 36** # **222**
 Brown, Matthew Applied Micro
Comment Type T **Comment Status X**
 The editor's note points out that pattern, methodology, and value are required for transition time. Specifically, a lower bound on transition time is required.
SuggestedRemedy
 Provide pattern, methodology, and value. A proposal will be provided.
Proposed Response **Response Status O**

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 94 SC 94.3.12.6.2 P 272 L 50 # 229
Brown, Matthew Applied Micro

Comment Type T Comment Status X

The peak value of p(k) should be increased to enforce faster transition time at the transmitter. It is reasonable to expect that the transition time should be similar to that achievable by a PAM2 transmitter. In other words, the assumed transmitter bandwidth may be doubled and the peak value of p(k) can be derived on this basis. The current transmitter bandwidth assumption is $0.375 \cdot fb$.

SuggestedRemedy

Select a value for peak value of p(k) such that worst case transmitter bandwidth is $0.75 \cdot fb$.

Proposed Response Response Status O

Cl 94 SC 94.3.12.6.2 P 272 L 50 # 268
Dudek, Mike QLogic

Comment Type T Comment Status X

The Peak value in table 94-14 should match the Peak value listed in this sub-clause.

SuggestedRemedy

Make them match. I suggest Change $0.85 \cdot Vf$ to $0.8 \cdot Vf$ here.

Proposed Response Response Status O

Cl 94 SC 94.3.12.9 P 275 L 24 # 113
Healey, Adam LSI Corporation

Comment Type T Comment Status X

The subclause heading "Transmitter output noise and distortion" and the name of the parameter defined therein "signal to noise and distortion ratio (SNDR)" seem to be incorrect since the reference to 94.3.12.6.1 (which refers to 85.8.3.3.4) returns an averaged waveform. It is unclear what form of "noise" is included in the measurement since uncorrelated noise and jitter will be significantly attenuated by averaging.

SuggestedRemedy

Change subclause heading to "Transmitter distortion" and change the parameter name to "signal to distortion ratio (SDR)". For step 2, change "output noise and distortion error" to "output distortion error".

Proposed Response Response Status O

Cl 94 SC 94.3.12.9 P 275 L 29 # 114
Healey, Adam LSI Corporation

Comment Type T Comment Status X

The RMS distortion error is computed for each phase $m = \{1, 2, \dots, M\}$ and the maximum value is used to compute SNDR. It unclear why all phases should be considered since a practical receiver will sample close to the center of the eye and distortion around the transitions will not be seen. Given that an averaged waveform is the basis for the SNDR measurement, EOJ is likely to be the major source of distortion around the transitions but this parameter is bounded separately. Note that it can be shown that the 19 dB SNDR requirement cannot be satisfied if EOJ is 3% (maximum allowed value).

SuggestedRemedy

Constrain the computation of RMS distortion error to a window spanning no more than $[-0.25, 0.25]$ UI relative to some a nominal sampling point near the eye center.

Proposed Response Response Status O

Cl 94 SC 94.3.13.3 P 276 L 40 # 109
Dawe, Piers IPtronics

Comment Type TR Comment Status X

Transmitter jitter is measured after a high-pass jitter filter. The receiver must be able to tolerate low frequency jitter, and the spec must require it. This could be enforced by including low frequency jitter in the receiver interference tolerance specification or by a separate jitter tolerance specification. The latter seems easier. A 2-point spec as used in e.g. 40GBASE-SR4 could be used (just two jitter frequencies rather than a mask).

SuggestedRemedy

Add a low frequency jitter tolerance specification to each of clauses 92, 93, 94, as a separate item (not part of receiver interference tolerance, but possibly using the same high loss channel). Make consistent with the transmitter jitter specs, in particular the 3 dB frequency of the jitter measurement filter used for transmitter output jitter measurement.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

Cl 94 SC 94.3.13.3 P 276 L 43 # 223
Brown, Matthew Applied Micro

Comment Type T Comment Status X

The editor's note points out that the channel parameters for the receiver interference tolerance test must be provided. Parameters are required for a low loss and a high loss channel.

SuggestedRemedy

Provide the channel parameters for each of the target channels. A proposal on this subject is expected.

Proposed Response Response Status O

Cl 94 SC 94.3.13.3 P 277 L 6 # 32
Mellitz, Richard Intel Corporation

Comment Type TR Comment Status X

remove Maximum BER without FEC and Maximum FER with FEC lines see presentation for more details

SuggestedRemedy

replace the BER at MAC or simile . i.e. value = 1e-12

Proposed Response Response Status O

Cl 94 SC 94.3.13.3 P 277 L 6 # 33
Mellitz, Richard Intel Corporation

Comment Type TR Comment Status X

each test channel should have certian amount of specified reflections

SuggestedRemedy

Add rss DFE line and value. Test 2 add rss dfe of 0.025 Test 1 add rss dfe 0.15

Proposed Response Response Status O

Cl 94 SC 94.3.13.3 P 277 L 8 # 20
Moore, Charles Avago Technologies

Comment Type TR Comment Status X

Many TBD's in Table 94-17 make spec technically incomplete. Also Assumed values a parameters are dimensionless gain (loss is negative) as a function of frequency in Hz. Elsewhere in the spec we use dB of loss and frequency in GHz. Should change to be consistent.

SuggestedRemedy

in Table 94-17
Change:
"COM"
to
"COM, including effects of added Gaussian white noise"

change COM values for Test 1 and Test 2 both to 1.5
change Insertion loss at 6.875 GHz for Test 1 to 12

change
"Real part of a_0 min"
to
"a_0 max"
change a_0 values for Test 1 and Test 2 to 1 and 2 respectively
add units for a_0 to dB

change
"Real part of a_1 min"
to
"a_1 max"
change a_1 values for Test 1 and Test 2 to 1.6 and 3.8 respectively
change units for a_1 to dB*GHz^-1/2
(gives 4.2 dB and 10 dB at Nyquist)

change
"Real part of a_2 min"
to
"a_2 max"
change a_2 values for Test 1 and Test 2 to 1.6 and 4.2 respectively
(gives 11 dB and 28.9 dB at Nyquist)
change units for a_2 to dB*GHz^-1

change
"Real part of a_4 min"
to
"a_4 max"
change a_2 values for Test 1 and Test 0.03 to 0.065 and 4.2 respectively
(gives 1.4 dB and 3.1 dB at Nyquist)
change units for a_4 to dB*GHz^-2

In note c of Table 94-17, change both instances of maximum to minimum.

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

In Annex 93A.2 page 317 make it clear the frequency "f" is given in GHz.

Proposed Response Response Status **O**

Cl 94 SC 94.3.13.4 P 277 L 30 # 270
 Dudek, Mike QLogic

Comment Type **T** Comment Status **X**

The Sine interferer and 1G PRBS source do not provide significant advantages over the Gaussian Noise Source and have disadvantages due to their heavy weighting to specific outputs (dual dirac like) and in the case of the Sine interferer single frequency. It is better to just use the Gaussian Noise Source.

SuggestedRemedy

On line 30 delete "1G PRBS source, sine interferer". Also delete them from Fig 94-14. Also Change item 2) of 94.3.13.4.2 to say "interference source", item 5 "interferer" and item 6 "level".

Proposed Response Response Status **O**

Cl 94 SC 94.3.13.4 P 277 L 33 # 269
 Dudek, Mike QLogic

Comment Type **T** Comment Status **X**

The Gaussian White Noise Source is intended to emulate more than the crosstalk noise

SuggestedRemedy

Change "..the crosstalk noise of a...." to "...the crosstalk noise and unequalizable signal distortions of a...."

Proposed Response Response Status **O**

Cl 94 SC 94.3.13.4 P 278 L 20 # 34
 Mellitz, Richard Intel Corporation

Comment Type **TR** Comment Status **X**

Include details reviewed in the "Clause 94 Interference tolerance ad-hoc" see presentation which includes inclusion of SNR to form a minimally compliant transmitter.

SuggestedRemedy

replace figure 94-14 and update/merge 94.3.13.4.2 Test method with presentation

Proposed Response Response Status **O**

Cl 94 SC 94.3.13.4.1 P 277 L 32 # 19
 Moore, Charles Avago Technologies

Comment Type **T** Comment Status **X**

The test channel Gaussian white noise source is not well speced. It cannot be ideally white an Gaussian. Need limits.

SuggestedRemedy

Add to 94.3.13.4.1:

The noise, measured at TP5A, due to the test channel Gaussian white noise source must have a crest factor at least 4 and be flat to within +/-3dB from 0.5 GHz to 6.875 GHz with the noise spectra density at 6.875 GHz no more than 1.5 dB below its maximum value. The added white Gaussian noise is the RMS value of the noise over the frequency range from 0 to 6.875 GHz.

Proposed Response Response Status **W**

[CommentType not specified. Set to T.]

Cl 94 SC 94.3.13.4.1 P 278 L 26 # 224
 Brown, Matthew Applied Micro

Comment Type **T** Comment Status **X**

The editor's note points out several limitations of the currently specified test setup.

SuggestedRemedy

Enhance the test setup to address the limitations. A proposal to address this editor's note is expected.

Proposed Response Response Status **O**

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 94 SC 94.3.13.4.2 P 278 L 41 # 21
 Moore, Charles Avago Technologies

Comment Type TR Comment Status X

step 1) of the test says:

"Determine the COM of the test channel using the method in Annex 93A. Adjust the test channel Gaussian white noise level to achieve the COM target in Table 94-17."

But nowhere is the effect of added Gaussian white noise on COM defined.

SuggestedRemedy

In Annex 93A most likely in 93A.1.6, define

$$H_{np} = H_{TP5A-TP5}(f) * H_r(f) * H_{ctl}(f)$$

with

$$H_{TP5A-TP5}(f) = 10^{(-0.07 * (f/12.89 \text{ GHz}))}$$

define

$$\text{Gain}_{noise} = \text{sqrt}(\text{integ}(|H_{np}|^2) \text{ from } 0 \text{ to } fb/2)$$

change 93A-23 to

$$\sigma_G = \text{sqrt}((A_s * \sigma_{RJ})^2 + \sigma_r^2 + \sigma_{noise}^2)$$

$$\sigma_{noise} = \text{WGN}_{TP5A} * \text{Gain}_{noise}$$

where WGN_TP5A is added white Gaussian noise at TP5A.

Proposed Response Response Status O

CI 94 SC 94.3.4 P 252 L 27 # 245
 Dudek, Mike QLogic

Comment Type T Comment Status X

With the Transcoding and FEC encoding I don't think that PCS lanes always tranverse the same physical lane with or without skew.

SuggestedRemedy

Delete the sentence "The Skew variation must also be limited"

Proposed Response Response Status W

[CommentType not specified. Set to T.]

CI 94 SC 94.3.6.2 P 254 L 38 # 231
 Brown, Matthew Applied Micro

Comment Type T Comment Status X

The transmitter coefficient are set to the values determine via the start-up protocol for any EEE state other than QUIET, not just DATA and ALERT. And for QUIET mode the transmitter is disabled, so the coefficient values are irrelevant.

SuggestedRemedy

Change "When tx_mode is DATA or ALERT" to "Regardless of tx_mode, ".

Proposed Response Response Status O

CI 94 SC 94.4.1 P 279 L 13 # 225
 Brown, Matthew Applied Micro

Comment Type T Comment Status X

The editor's note points out that a_dd and sigma_g should be reconciled with crjrms, cdj, and sndr.

SuggestedRemedy

Reconcile the noted parameters. A presentation is expected on this subject.

Proposed Response Response Status O

CI 94 SC 94.4.1 P 279 L 18 # 226
 Brown, Matthew Applied Micro

Comment Type T Comment Status X

The editor's note points out that the required COM value of 4 dB includes allocation for receiver package penalty and transmitter step size.

It is important for consistent interpretation that the scope of the COM value be clearly defined.

SuggestedRemedy

Add text and/or table that explains the penalties taken into consideration by the specified COM value. A proposal will be provided.

Proposed Response Response Status O

IEEE P802.3bj D1.3 100 Gb/s Backplane and Copper Cable 4th Task Force review comments

CI 94 SC 94.4.1 P 280 L 20 # 271
Dudek, Mike QLogic

Comment Type T Comment Status X

The minimum values of the pre-cursor and post-cursor coefficients in the COM table 94-18 do not match the required pre-cursor and post-cursor in 94.3.12.6.6 and the summary table 94-14.

SuggestedRemedy

Make them consistent. I suggest Changing the minimum pre-cursor from -0.18 to -0.22 and change the minimum post-cursor from -0.38 to -0.6 in table 94-18.

Proposed Response Response Status O