

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >		
Title	Clarifications for AAS Zone		
Date Submitted	2005-5-3		
Source(s)	Dave Pechner, Doug Dahlby, Asaf Matatyaou, Arvind Raghavan	ArrayComm Inc.	dpechner@arraycomm.com
Re:	IEEE P802_Cor1_D2		
Abstract	This contribution introduces clarifications for making allocations in an AAS zone in the OFDMA PHY		
Purpose	Adopt into P802.16d/D5 corrigenda		
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.		
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.		
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < mailto:chair@wirelessman.org > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < http://ieee802.org/16/ipr/patents/notices >.		

Clarifications for AAS Zone Allocations

Dave Pechner, Doug Dahlby, Asaf Matatyaou, Arvind Raghavan

1 Issues with the AAS Zone

- 1) The preamble modifier type should be included in the AAS IE()'s.
- 2) The PRBS_ID was added to the STC_DL_ZONE_IE. It should be added to the AAS_DL_IE() for consistency.

2 Outline of proposed solution

- 1) Add preamble modifier type to AAS_UL_IE() and AAS_DL_IE()
- 2) Add PRBS_ID field to AAS_DL_IE()

3 Proposed Text Changes

[Replace table 278 "AAS_DL_IE()" with the following:]

Syntax	Size	Notes
AAS_DL_IE() {		
Extended DIUC	4 bits	AAS = 0x02
Length	4 bits	Length = 0x03
OFDMA Symbol Offset	8 bits	Denotes the start of the zone (counting from the frame preamble and starting from 0)
Permutation	3 bits	0b000 = PUSC permutation 0b001 = FUSC permutation 0b010 = Optional FUSC permutation 0b011 = adjacent-subcarrier permutation 0b1xx = reserved
DL PermBase	6 bits	
Downlink_preamble_config	2 bits	0b00 - 0 symbols 0b01 - 1 symbols 0b10 - 2 symbols 0b11 - 3 symbols
Downlink Preamble type	1 bit	0 – Frequency shifted preamble is used in this DL AAS zone 1 – Time shifted preamble is used in this DL AAS zone
PRBS_ID	2 bits	Refer to 8.4.9.4.1
Reserved	2 bits	Shall be set to zero
}		

[Modify the first paragraph of 8.4.4.4 as follows:]

After decoding the DL_Frame_Prefix message within the FCH, the SS has the knowledge of how many and which subchannels are allocated to the PUSC segment. In order to observe the allocation of the subchannels in the downlink as a contiguous allocation block, the subchannels shall be renumbered. The renumbering,

for the first PUSC zone, shall start from the FCH subchannels (renumbered to values 0...11), then continue numbering the subchannels in a cyclic manner to the last allocated subchannel and from the first allocated subchannel to the FCH subchannels. Figure 221 gives an example of such renumbering for segment 1. For other PUSC zones, in which use all SC indicator is set to '1', renumbering shall be performed starting from subchannel $(N_{subchannels}/3)*PRBS_ID$, where PRBS ID is specified in the STC_DL_Zone_IE or AAS_DL_IE(). For other PUSC zones, in which use all SC indicator is set to '0', the renumbering shall be the same as in the first PUSC zone.

[Modify the text on Page 144, line 30 as follows:]

b5..b4 = Set to the segment number + 1 as indicated by the frame preamble in the first downlink zone and the 2 LSBs of PRBS_ID as indicated by the STC_DL_Zone_IE() or AAS_DL_IE() in the other downlink zones. Set to the two MSBs of UL_PermBase in the uplink.

[Replace table 293 “AAS_UL_IE()” with the following:]

Syntax	Size	Notes
AAS_UL_IE() {		
Extended UIUC	4 bits	AAS = 0x02
Length	4 bits	Length = 0x03
Permutation	2 bits	0b00 = PUSC permutation 0b01 = Optional PUSC permutation 0b10 = adjacent-subcarrier permutation 0b11 = reserved
UL_PermBase	7 bits	
OFDMA Symbol Offset	8 bits	Denotes the start of the zone (counting from the frame preamble and starting from 0)
Uplink_preamble_config	2 bits	0b00 - 0 symbols 0b01 - 1 symbols 0b10 - 2 symbols 0b11 - 3 symbols
Uplink Preamble type	1 bit	0 – Frequency shifted preamble is used in this UL AAS zone 1 – Time shifted preamble is used in this UL AAS zone
Reserved	4 bits	Shall be set to zero
}		