

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Encoding of the GPS time in the LBS-ADV message	
Date Submitted	2008-09-11	
Source(s)	Erik Colban, Lei Wang, Kenneth Stanwood, Yair Bourlas NextWave Wireless*	Voice: E-mail: ecolban@nextwave.com ; lwang@nextwave.com ; kstanwood@nextwave.com ybourlas@nextwave.com
		*< http://standards.ieee.org/faqs/affiliationFAQ.htm > >
Re:	802.16 Rev2 Sponsor Ballot	
Abstract	This contribution proposes a correction and improvement of the encoding of the GPS time in the LBS-ADV message.	
Purpose	To be discussed and adopted by 802.16 Rev2.	
Notice	<i>This document does not represent the agreed views of the IEEE 802.16 Working Group or any of its subgroups. It represents only the views of the participants listed in the "Source(s)" field above. It is offered as a basis for discussion. It is not binding on the contributor(s), who reserve(s) the right to add, amend or withdraw material contained herein.</i>	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy	The contributor is familiar with the IEEE-SA Patent Policy and Procedures: < http://standards.ieee.org/guides/bylaws/sect6-7.html#6 > and < http://standards.ieee.org/guides/opman/sect6.html#6.3 >. Further information is located at < http://standards.ieee.org/board/pat/pat-material.html > and < http://standards.ieee.org/board/pat >.	

Encoding of the GPS time in the LBS-ADV message

Erik Colban, Ken Stanwood, Lei Wang, Yair Bourlas

NextWave Wireless

1 Introduction

The GPS Time TLV (11.21.4), which is used to signal GPS time in the LBS-ADV message, does not signal the GPS time in the most efficient way.

The TLV uses 12 bits to signal the GPS seconds modulo 2048 [*sic*] and 28 bits to signal GPS second fraction. An immediate improvement would be to recognize that 12 bits may express an integer modulo 4096 and change the modulus from 2048 to 4096, or reduce the number of bits used to express the number of seconds by 1. When this TLV was introduced into the standard, the assumption was that the SS's clock is sufficiently accurate to determine the time within an hour (3600 seconds) and, thus, the SS would be able to determine the exact number of GPS seconds if the seconds were signaled modulo 4096. We believe that this assumption is lax, and that we can assume that the SS is capable of determining time within an accuracy of a few seconds using its internal clock only. Therefore, we propose that the BS should signal GPS time modulo m , where m is on the order of 1 minute.

Before this TLV got accepted into the standard, two solutions were considered. In the first solution, the BS signals the GPS time of the frame in which the LBS-ADV message is transmitted. In the other solution, which is currently in the standard, the BS signals the GPS time of when it transmitted frame 0 of the current epoch. The second solution was chosen because it was simplest to implement in the BS. In the first solution the BS updates the value of the GPS time TLV every time it is transmitted, whereas in the second solution, the BS updates the value fields in the TLV when the frame number wraps around. We observe that if the BS signals the GPS time modulo the frame number wraparound period (i.e., $2^{24} \times T_f$, where T_f is the frame duration) or modulo any divisor of the frame number wraparound period, the BS would not necessarily need to update the value field of the GPS time TLV when the frame number wraps around. Note that a second does not divide the wrap-around period if $T_f = 5$ ms. Therefore, we propose that the BS should signal GPS time modulo $2^{14} \times T_f$, (i.e., the modulus is 81.92 seconds when $T_f = 5$ ms).

Further, we observe that 28 bits for the fraction of GPS seconds allows one to express the time with a resolution of approximately 3.73 ns ($2^{-28} \cong 3.73 \times 10^{-9}$). The LBS-ADV message is used by BSs that are synchronized with reference to the GPS pulse per second (see 8.2.7.1.1). A BS will signal values close to multiples of T_f . For instance, a system profile may typically require the BS to start frame transmission within 1 microsecond (μ s) from time t , where t is a multiple of T_f . Therefore, we propose to signal the GPS time as a pair of integers (n, k) , where $0 \leq n < 2^{14}$ signals time in units of T_f modulo $2^{14} \times T_f$, and $-2^9 < k < 2^9$ signals a signed adjustment in units of 2 ns (i.e., the maximum adjustment is approximately $\pm 1 \mu$ s). The number k is signaled using 10 bits and two's complement notation. In total, the GPS time is signaled using 24 bits, and the accuracy is signaled using 8 bits as currently specified in the standard.

Example:

Assume that the frame duration is 5 ms. The MS' internal clock shows 11:59:59 PM AOE, on September 11th, 2008, when it receives the LBS-ADV message. This time translates to GPS time 1221220799 (Ref.

http://www.mapshots.com/tools/gps_time.asp). The LBS-ADV message is transmitted in frame 12345678 and signals the pair (3100, -303). When the LBS-ADV message is transmitted, the GPS time is $(3100 + 12345678 + N \times 2^{14}) \times 5\text{ms} - 303 \times 2\text{ns} + \epsilon$, where ϵ is bounded by the accuracy. Assuming that the MS' internal clock is accurate within 81 seconds, the number N is calculated as follows:

$$N = \left\lceil \frac{1221220799 \times 200 - 3100 - 12345678}{2^{14}} \right\rceil = 14906727$$

The GPS time at the BS when the LBS-ADV message was transmitted was $1221220819.729999394 + \epsilon$. (The MS' internal clock is almost 21 seconds too slow.)

2 Suggested Changes in Rev2/D6a

2.1 Remedy - Part 1

[On page 1332, line 36, modify section 11.21.4 as follows:]

11.21.4 GPS Time TLV

This TLV shall be used to provide the GPS time.

Name	Type	Length (bytes)	Value
GPS Time	4	64	See Table 609

Table 609—Contents of the GPS Time TLV

Field	Size (bits)	Description
GPS time in units of frame duration Second	142 bits	GPS time, expressed in units of frame duration T_f, second, modulo 2^{14} 2048
GPS frame transmission time offset Second fraction	1028 bits	GPS second fraction A signed integer expressing the offset between the OFDMA transmission time and an integer multiple of T_f , expressed in units of 2 nanoseconds (ns). This integer is encoded in two's complement notation. The value 0x200 signals that the offset in absolute value is greater than $(2^9 - 1) \times 2$ ns.
GPS time accuracy	8 bits	GPS Time Accuracy For unsigned integer values 0x00-0x3F: $\log_2(\text{Time error in pico seconds})$.

The GPS Time TLV informs the receiving MS of the precise time at which the BS's First Frame of the current epoch has been transmitted, which the MS may use to calibrate its own internal clock in reference to the GPS time standard. The GPS Time TLV is used if the BS's frame time is synchronized with the GPS clock. This may be particularly valuable for determining GPS satellite signal search windows in mobiles equipped to detect GPS satellites. GPS ~~second and second fraction~~ ~~frame transmission time offset~~ allows the MS to use DL Frame arrival times as timing signals aligned with GPS time. GPS Time Accuracy aids the MS in estimating how much error with respect to GPS time the BS may have when using this calibration.