

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Downlink HARQ for transparent RS	
Date Submitted	2007-05-07	
Source(s)	Junichi Suga Fujitsu Laboratories Ltd. KamikodaNACKa 4-1-1, Kawasaki, 211-8588, Japan	Voice: +81-44-754-2811 Fax: +81-44-754-2786 Email: suga.junichi@jp.fujitsu.com
	Michiharu NACKamura Fujitsu Laboratories LTD 5-5, Hikarinooka Yokosuka, Japan. 239-0847	Voice: +81-46-839-5371 Fax: +81-46-839-5560 Email: michi@labs.fujitsu.com
	Haihong Zheng, Yousuf Saifullah, Shashikant Maheshwari Nokia 6000 Connection Drive, Irving, TX	Voice: 972 894 5000 Fax: Email: haihong.1.zheng@nokia.com shashikant.maheshwai@nokia.com Yousuf.saifullah@nokia.com
	Aik Chindapol Nikolaj Marchenko Jimmy Chui Siemens Corporate Research Princeton, NJ, USA	Voice: +1 609 734 3364 Fax: +1 609 734 6565 Email: aik.chindapol@siemens.com
	Kyu Ha Lee Samsung Thales San 14, Nongseo-Dong, Giheung-Gu, Yongin, Gyeonggi-Do, Korea 449-712	Voice: +82-31-280-9917 Fax: +82-31-280-1562 Email: kyuha.lee@samsung.com
	Suchang Chae ETRI 161, Gajeong-Dong, Yuseong-Gu, Daejeon, Korea 305-350	Voice: +82-42-860-6642 Fax: +82-42-861-1966 Email: schae@etri.re.kr
	David Comstock, Huawei Technologies No.98, Lane91, Eshan Road, Shanghai, P.R.C	Voice: +1 858 735 9382 Email: dcomstock@huawei.com

Youngbin Chang
 Samsung Electronics Co., Ltd.
 416 Maetan-3, Suwon, 442-600,
 Korea

Voice: +82-31-279-5519
 Email: yb.chang@samsung.com

Rakesh Taori
 Samsung Advanced Institute of
 Technology
 C.P.O. Box 1142, Seoul, 100-611,
 Korea

Voice: +82-31-280-9635
 Email: rakesh.taori@samsung.com

Eugene Visotsky
 Motorola, Inc.
 1301 E. Algonquin Road
 Schaumburg, IL 60196

eugenev@motorola.com

Jeffrey Z. Tao, Koon Hoo Teo,
 Jinyun Zhang
Mitsubishi Electric Research Lab
 201 Broadway
 Cambridge, MA 02139 USA

Voice: 617-621- $\{7557,7527\}$
 Fax: 617-621-7550
{tao, teo, jzhang}@merl.com

Arnaud Tonnerre
 THALES COMMUNICATIONS,
 FRANCE

arnaud.tonnerre@fr.thalesgroup.com
 Voice: +33 1 46 13 2850

Djamal-Eddine Meddour
 FRANCE TELECOM, FRANCE

djamal.meddour@orange-ft.com

Yong Sun
 Toshiba Research Europe Limited
 32 Queen Square
 Bristol BS1 4ND
 UK

Sun@toshiba-trel.com
 Tel. no.: +441179060749

Re: Call for Technical Proposals regarding IEEE Project P802.16j (IEEE 802.16j-07/007r2)

Abstract This contribution proposes a procedure for handling retransmission of downlink HARQ for transparent RS.

Purpose Add proposed spec changes in P802.16j Baseline Document

Notice This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.

Release The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.

**Patent
Policy and
Procedures**

The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures <<http://ieee802.org/16/ipr/patents/policy.html>>, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair <<mailto:chair@wirelessman.org>> as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site <<http://ieee802.org/16/ipr/patents/notices>>.

Downlink HARQ for transparent RS

1. Specific text changes

[Insert new sub-clause 6.3.17.5.1]

6.3.17.5.1 DL HARQ for Transparent RS

[Insert new sub-clause 6.3.17.5.1.1]

6.3.17.5.1.1 RS Hop-by-Hop HARQ

When MR-BS or RS sends a HARQ sub-burst to MS through RS, the RS shall receive the HARQ sub-burst from the MR-BS for relaying the burst to the MS. If the RS receives the HARQ sub-burst correctly, then the RS sends an ACK signal to the MR-BS and saves it for the event that there may be a retransmission to MS. Subsequently, the RS forwards the sub-burst to the MS. If the RS does not receive the HARQ sub-burst successfully, the RS shall send a NACK signal to the MR-BS. Upon receiving the NACK from the RS, the MR-BS shall retransmit the HARQ sub-burst to the RS. When HARQ sub-burst is successfully received at RS, MS-BS request RS to transmit HARQ sub-burst. When the MR-BS receives a NACK from the MS, the MR-BS notifies the RS to retransmit the HARQ sub-burst to the MS, and the RS shall retransmit the stored HARQ sub-burst to the MS.

[Insert new sub-clause 6.3.17.5.1.2]

6.3.17.5.1.2 RS assisted HARQ

In a case where the MR-BS sends a HARQ sub-burst to the MS directly, the MR-BS informs the RS that it needs to monitor that particular transmission by Compact DL-MAP MONITOR IE and also allocate HARQ ACK region allocation IE on the relay link for sending ACK/NACK from RS. The RS, having information on the downlink resource allocations sent in the DL-MAP for the MS and Compact DL-MAP MONITOR IE, monitors the HARQ sub-burst transmission sent to MS by MR-BS directly and attempts to decode it. When the RS receives the HARQ sub-burst correctly, the RS saves it for a possible retransmission.

When MR-BS receives ACK/NACK from MS directly, MR-BS informs RS to reply ACK/NACK signal after RS receives the HARQ sub-burst. In this case, MR-BS receives ACK/NACK from RS and MS separately. When MR-BS receives NACK from both RS and MS, MR-BS retransmits the HARQ sub-burst. If MR-BS receives ACK from RS and NACK from MS, MS-BS makes the RS retransmits the HARQ sub-burst.

MR-BS may also configure RS to listen the ACK/NACK from the MS using Compact DL-MAP MONITOR IE. After the RS receives ACK/NACK from the MS, the RS replies using an encoded ACK/NACK defined in Table xxx through ACK channel prepared by MR-BS. RS shall clear the HARQ sub-burst depending upon the ACK/NACK information received from MS. If the RS received the HARQ sub-burst correctly and receives a NACK from MS, the RS replies the C_2 to MR-BS. In this case, the MR-BS requests the RS to retransmit the HARQ sub-burst saved at the RS. When the RS fails to receive the HARQ sub-burst and receives a NACK from the MS, the RS sends a NACK to the MR-BS. Then the MR-BS retransmits the burst by itself. When the RS receives an ACK from MS then irrespective of whether RS receives the HARQ sub-burst correctly or not, the RS replies ACK to the MR-BS. RS will send the encoded ACK/NACK in the UL ACKCH according to the order of CID in the compact DL-MAP MONITOR IE.

6.3.2.3.43.4 HARQ control IE

[Insert new field in table 94 (HARQ control IE format) as indicated:]

<u>Syntax</u>	<u>Size</u>	<u>Notes</u>
<u>RSH</u>	<u>1 bit</u>	<u>0 = RS-assisted HARQ is enabled</u> <u>1 = RS-assisted HARQ is disabled</u>

[Insert new subclause 6.3.2.3.43.6.10 and add table:]

6.3.2.3.43.6.10 Compact DL-MAP MONITOR IE

In RS-assisted relay case, MR-BS sends the Compact DL-MAP MONITOR IE to RS. The Compact DL-MAP MONITOR IE provides the list of CIDs of the MS whose transmissions need to be monitored in the DL part of the current frame and relayed in the next frame to the MS.

<u>Syntax</u>	<u>Size</u>	<u>Notes</u>
<u>Compact DL-MAP IE() {</u>		
<u> <u>DL-MAP Type = 7</u></u>	<u>3 bits</u>	
<u> <u>DL-MAP subtype</u></u>	<u>5 bits</u>	
<u> <u>N_CID_encoded</u></u>	<u>4 bits</u>	<u>Number of CIDs for which RS uses the encoded ACK/NACK</u>
<u> <u>N_CID_direct</u></u>	<u>4 bits</u>	<u>Number of CIDs for which RS uses the direct feedback</u>
<u> <u>For(i=0; i<N_CID_encoded + N_CID_direct; i++) {</u></u>		
<u> <u>RCID IE(i)</u></u>	<u>16 bits</u>	<u>The CIDs of the connections that RS shall monitor in the current frame</u>
<u> <u>}</u></u>		
<u>}</u>		

N_CID_encoded

This field specifies the number of CIDs to use the encoded ACK/NACK among CIDs list in this IE. The CIDs from the beginning of the list to the value of this field use the encoded ACK/NACK.

N_CID_direct

This field specifies the number of CIDs to use the direct ACK/NACK among CIDs list in this IE. The CIDs from the N_CID_encoded to the end of the list use the direct ACK/NACK.

8.4.5.4.13 UL ACK channel

[Insert the following text and add table:]

When MR-BS receives the ACK/NACK signal from MS through RS in the RS-assisted relay case, the new sequences based on Table 301a is used. RS notifies the status of HARQ sub-burst at both RS and MS with the encoded ACK/NACK signal defined in the table xxx. When RS receive ACK signal from MS then irrespective of whether RS receives the HARQ sub-burst correctly or not, the RS replies ACK to the MR-BS.

Table xxx: ACK / NACK Encoding

<u>Link Distance/Depth</u>	<u>ACK/NACK 1-bit symbol</u>	<u>Vector Indices per Tile Tile(0), Tile(1), Tile(2)</u>	<u>Code #</u>
<u>Any Distance</u>	<u>0 (ACK)</u>	<u>0, 0, 0</u>	<u>C₀</u>
<u>1</u>	<u>1 (NACK)</u>	<u>1, 1, 1</u>	<u>C₁</u>
<u>2</u>	<u>1 (NACK)</u>	<u>2, 2, 2</u>	<u>C₂</u>
<u>3</u>	<u>1 (NACK)</u>	<u>3, 3, 3</u>	<u>C₃</u>
<u>4</u>	<u>1 (NACK)</u>	<u>4, 4, 4</u>	<u>C₄</u>
<u>5</u>	<u>1 (NACK)</u>	<u>5, 5, 5</u>	<u>C₅</u>
<u>6</u>	<u>1 (NACK)</u>	<u>6, 6, 6</u>	<u>C₆</u>
<u>7</u>	<u>1 (NACK)</u>	<u>7, 7, 7</u>	<u>C₇</u>

2. References

- [1] C802.16j-06_132, "Relaying methods proposal for 802.16j"
- [2] C802.16j-06_266r1, "Relay-Assisted Hybrid ARQ"
- [3] C802.16j-06_197r1, "HARQ with Relays"
- [4] C802.16j-07_002r1, "DL HARQ with Relays"
- [5] C802.16j-07_029, "UL HARQ with Relays"