

# Major Comments to D1.2

Yuanqiu Luo

March 19, 2020

# Group A: 10GBASE-BR40

- Align 10BGASE-BR40 specs with industry defacto numbers
- Contribution “Nering\_3cp\_1\_2001.pdf” in Jan 2020
- Commented by Ray Nering

# Proposed changes by Ray (1)

## Comment #110

Table 158-6—10GBASE-BRx transmit characteristics

Description	10GBASE-BR10	10GBASE-BR20	10GBASE-BR40	10GBASE-BR40+	Unit
Signaling speed (nominal)		10.3125			GBd
Signaling speed variation from nominal (max)		± 100			ppm
10GBASE-BRx-D center wavelength (range)		1320 to 1340			nm
10GBASE-BRx-U center wavelength (range)		1260 to 1280			nm
Side Mode Suppression Ratio (min)		30			dB
Average launch power (max)	0.5	5.4	<del>-0.6</del> 5	4.6	dBm
Average launch power <sup>a</sup> (min)	-8.2	0.4	<del>-6.6</del> -2.7	-1.4	dBm
Launch power (min) in OMA minus TDP <sup>b</sup>	-6.2	2.4	<del>-4.6</del> -0.5	0.6	dBm
Optical Modulation Amplitude <sup>c</sup> (min)	-5.2	3.4	<del>-3.6</del> 0.3	1.6	dBm
Transmitter and dispersion penalty (max)	3.2		<del>3.0</del> 2.6		dB
Average launch power of OFF transmitter <sup>d</sup> (max)		-30			dBm
Extinction ratio (min)	3.5		<del>3</del> 5.5		dB
RIN <sub>12</sub> OMA (max)		-128			dB/Hz

Suggested new values

+3	+6
-3	0
-1	+1
0	+2
2.6	2.6

# Proposed changes by Ray (2)

## Comment #111

Table 158-7—10GBASE-BRx receive characteristics

Description	10GBASE-BR10	10GBASE-BR20	10GBASE-BR40	10GBASE-BR40+	Unit
Signaling speed (nominal)		10.3125			GBd
Signaling speed variation from nominal (max)		± 100			ppm
10GBASE-BRx-D center wavelength (range)		1320 to 1340			nm
10GBASE-BRx-U center wavelength (range)		1260 to 1280			nm
Average receive power <sup>a</sup> (max)	0.5	5.4	<del>-5.6</del> -9	-5.6	<del>dBm</del>
Average receive power <sup>b</sup> (min)	-14.4	-14.4	<del>-24.4</del> -21.2	-24.4	<del>dBm</del>
Maximum receive power (for damage)	4.0	4.0	4.0	4.0	<del>dBm</del>
Receiver sensitivity (max) in OMA <sup>c</sup>	-12.6	-12.6	<del>-22.6</del> -19	-22.6	<del>dBm</del>
Receiver Reflectance (max)	-12	-26	-26	-26	dB
Stressed receiver sensitivity (max) in OMA <sup>d,e</sup>	-10.3	-10.3	<del>-20.3</del> -16.8	-20.3	<del>dBm</del>
Vertical eye closure penalty <sup>f</sup> (min)	2.2	2.7	2.7	2.7	dB
Stressed eye jitter <sup>g</sup> (min)		0.3			UI pk-pk
Receive electrical 3 dB upper cutoff frequency (max)		12.3			<del>GHz</del>

**Suggested new values**

<b>-7</b>	<b>-4</b>
<b>-21.2</b>	<b>-23.2</b>
<b>-19</b>	<b>-21</b>
<b>-16.8</b>	<b>-18.8</b>

# Group B: 25GBASE-BR40

- Reuse 25GBASE-ER spec for 25GBASE-BR40
- Commented by Tom Palkert

# Proposed changes by Tom (1)

## Comment #89

**Table 159-6—25GBASE-BRx transmit characteristics**

Description	25GBASE-BR10	25GBASE-BR20	25GBASE-BR40	25GBASE-BR40+	Unit
Signaling rate (range)		25.78125 ± 100 ppm			GB d
25GBASE-BRx-D center wavelength (range)	1320 to 1340		1306 to 1322		nm
25GBASE-BRx-U center wavelength (range)	1260 to 1280		1281 to 1297		nm
Side-mode suppression ratio (SMSR), (min)		30			dB
Average launch power (max)	2	0	<del>3</del> 6	8	dBm
Average launch power <sup>a</sup> (min)	-7	-6	-3	2	dBm

Editor's question:  
How to adjust  
average launch  
power (min) and  
other columns in  
the table?

# Proposed changes by Tom (2)

## Comments #90, 91

Table 159-7—25GBASE-BRx receive characteristics					
Description	25GBASE-BR10	25GBASE-BR20	25GBASE-BR40	25GBASE-BR40+	Unit
Signaling rate (range)		25.78125 ± 100 ppm			GB d
25GBASE-BRx-D center wavelength (range)	1320 to 1340		1306 to 1322		nm
25GBASE-BRx-U center wavelength (range)	1260 to 1280		1281 to 1297		nm
Damage threshold <sup>a</sup> (min)	3	1	<del>-1</del> -3	-1	dBm
Average receive power (max)	2	0	<del>-2</del> -4	-2	dBm
Average receive power <sup>b</sup> (min)	-13.3		-21		dBm
Receive power (OMA), (max)	2.2		-4		dBm
Receiver reflectance (max)		<del>-2</del> -6			dB
Receiver sensitivity (OMA) <sup>c</sup> , (max)	-12		-19		dBm
Stressed receiver sensitivity (OMA) <sup>d</sup> , (max)	-9.5		-16.5		dBm
Conditions of stressed receiver sensitivity test					
Stressed eye closure <sup>e</sup>		2.5			dB

Editor's question:  
How to adjust other  
columns in the table?

# Group C: 50GBASE-BR40

- Reuse 50GBASE-ER spec for 50GBASE-BR40
- Commented by Tom Palkert and Ruoxu Wang



# Proposed changes by Tom and Ruoxu (1)

## Comments #92, 93, 112

Table 160-7—50GBASE-BRx receive characteristics

Description	50GBASE-BR10	50GBASE-BR20	50GBASE-BR40	50GBASE-BR40+	Unit
Signaling rate (range)		26.5625 ± 100 ppm			<del>GBd</del>
Modulation format		PAM4			—
50GBASE-BRx-D center wavelengths (range)	1320 to 1340		1306 to 1322		nm
50GBASE-BRx-U center wavelengths (range)	1260 to 1280		1281 to 1297		nm
Damage threshold <sup>a</sup>	5.2	4.6	<del>2.6</del> -2.4	2.6	<del>dBm</del>
Average receive power (max)	4.2	3.6	<del>1.6</del> -3.4	1.6	<del>dBm</del>
Average receive power <sup>b</sup> (min)	-10.8		-17.6		<del>dBm</del>
Receive power (OMA <sub>outer</sub> ) (max)	4		-2.6		<del>dBm</del>
Receiver reflectance (max)		-26			dB

Editor's question:  
How to adjust other  
columns in the table?

# Proposed changes by Ruoxu (2), Comment #113

Suggested remedy:

Table 160-10 should be modified as Table 159-10. The channel insertion loss should be 10dB in 40km cases. And add a footnote: Channel insertion loss (min) may be implemented with an optical attenuator.

**Table 160–10—Optical fiber and cable characteristics**

Description	Value	Unit
Nominal fiber specification wavelength	1310	nm
Cabled optical fiber attenuation (max)	0.43 <sup>a</sup> or 0.5 <sup>b</sup>	dB/km
Zero dispersion wavelength ( $\lambda_0$ )	$1300 \leq \lambda_0 \leq 1324$	nm
Dispersion slope (max) ( $S_0$ )	0.093	ps/nm <sup>2</sup> km

<sup>a</sup>The 0.43 dB/km at 1304.5 nm attenuation for optical fiber cables is derived from Appendix I of ITU-T G.695.

<sup>b</sup>The 0.5 dB/km attenuation is provided for Outside Plant cable as defined in ANSI/TIA 568-C.3. Using 0.5 dB/km may not support operation 10 km for 50GBASE-BR40.

**Table 159–10—Fiber optic cabling (channel) characteristics**

Description	Type B1.1, B1.3 SMF								Unit
Nominal wavelength	1270	1289			1330	1314			nm
Operating distance (max)	10	20	40	40+	10	20	40	40+	km
Channel insertion loss (max) <sup>a,b,c</sup>	6.2	15	18	23	6.2	15	18	23	dB
Channel insertion loss (min)	0	0	5	10	0	0	5	10	dB
Dispersion (max)	See Table 158–9								ps/nm
Dispersion (min)									ps/nm
DGD_max <sup>d</sup>	8	10.3			8	10.3			ps
Optical return loss	21								dB

<sup>a</sup>Channel insertion losses include cable, connectors, and splices.

<sup>b</sup>These channel insertion loss numbers are based on the nominal wavelength.

<sup>c</sup>Operating distances used to calculate channel insertion loss are those listed in this table.

<sup>d</sup>DGD\_max is the maximum differential group delay that the system must tolerate.

**Editor's question:**

**This changes BR40 loss range from 5~18 dB into 10~18 dB. Do we agree? How to update the Tx and Rx tables?**

**Note that Table 158-10 also uses 5 dB as the 40km min loss.**