

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Format of R-MAP within RS-Zone	
Date Submitted	2007-04-26	
Source(s)	<p>Hang Zhang, Peiyong Zhu, Mo-Han Fong, Wen Tong, David Steer, Gamini Senarath, Derek Yu, Mark Naden, G.Q. Wang</p> <p>Nortel 3500 Carling Avenue Ottawa, Ontario K2H 8E9</p> <p>Kanchei (Ken) Loa, Yi-Hsueh Tsai, Shiann-Tsong Sheu, Hua-Chiang Yin, Chih-Chiang Hsieh, Yung-Ting Lee, Frank C.D. Tsai, Heng-Iang Hsu, Youn-Tai Lee</p> <p>Institute for Information Industry 8F, No. 218, Sec. 2, Dunhua S. Rd., Taipei City 106, Taiwan, ROC.</p>	<p>Voice: +1 613 7631315 [mailto:wentong@nortel.com]</p> <p>[mailto:pyzhu@nortel.com]</p> <p>loa@nmi.iii.org.tw</p>
Re:	A response to a Call for Technical Proposal, http://www.ieee802.org/16/relay/docs/80216j-07_007r2.pdf	
Abstract	R-MAP in RS_Zone is used for a parent station (MR-BS or RS) to signal the resource assignment in the RS_Zone. This contribution propose the format of R-MAP in RS_Zone.	
Purpose	To incorporate the proposed text into the P802.16j Baseline Document (IEEE 802.16j-06/026r2)	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or	

Procedures applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair <<mailto:chair@wirelessman.org>> as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site <<http://ieee802.org/16/ipr/patents/notices>>.

R-MAP Within RS_Zone

Hang Zhang, Peiyong Zhu, Mo-Han Fong, Wen Tong, David Steer, Gamini Senarath, Derek Yu, Mark Naden,
G.Q. Wang

Nortel

Kanchei (Ken) Loa, Yi-Hsueh Tsai, Shiann-Tsong Sheu, Hua-Chiang Yin, Chih-Chiang Hsieh, Yung-Ting Lee,
Frank C.D. Tsai, Heng-Iang Hsu, Youn-Tai Lee

Institute for Information Industry

1. Introduction

R-MAP in RS_Zone is used for a parent station (MR-BS or RS) to signal the resource assignment in the RS_Zone. This contribution is addressing the format of R-MAP in RS_Zone.

2. Proposal

As agreed in the session #46, resource assignment will be done by R-MAP. Theoretically, we can use the similar format of DL-MAP/UL-MAP as defined in IEEE802.16e-2005 for R-MAP. However, this is not very efficient since some fields in compressed DL-MAP and UL-MAP messages are redundant. The table below shows these fields.

<u>Field in Compressed DL-MAP</u>	<u>Bits</u>	<u>Required for R-MAP</u>	<u>Comments</u>
Compressed map indicator	3	No	R-MAP always immediately follows the R-FCH
UL-MAP appended	1	No	Can identify DL or UL IE by R-MAP type value (see proposed text)
MAP message length	11	yes	
PHY synchronization field	32	No	Info known during RS initial network entry
DCD count	8	No	DCD count mainly for MS during initial network entry and sleep mode MS and idle mode MS
Operator ID	8	No	Known during initial network entry
Sector ID	8	No	Known during initial network entry
No. OFDM symbol	8	No	Used to indicate the DL duration only if a dynamic DL RS_Zone

			duration change is supported
DL IE count	8	Yes	May reduce to 6 bits to indicate the number of R-MAP IE
DL IE for loop	Variable	yes	
<u>Field in Compressed UL-MAP</u>	<u>Bits</u>	<u>Required for R-MAP</u>	<u>Comments</u>
UCD count	8	No	UCD count mainly for MS during initial network entry and sleep mode MS and idle mode MS
Allocation Start Time	32	No	Assuming a fixed frame delay
No. OFDM symbol	8	No	Assuming a fixed boundary between DL and UL sub-frame
UL IE for loop	Variable	yes	
Total saving	17 byte		

By introducing the new R-MAP format, the total saving is 17 bytes (152 bits). Due to this reason, we propose to introduce new R-MAP format within DL RS_Zone.

3. Proposed text change

+++++ Start Text +++++
[Modify title of 8.4.5.9 as indicated]

8.4.5.9 R-MAP Message

[Insert the following text in subclause 8.4.5.9]

This message is used to signal the resource assignments and other control information contained in the relay zones transmitted by an MR-BS or RS. This message shall be sent in the first transmitted DL relay_zone. This message shall immediately follow the R-FCH and shall not be preceded by a MAC header and message type field. The modulation and coding rate for the R-MAP message are indicated in the R-FCH. The message format is shown in Table xxx.

Table XXX. R-MAP Message Format.

Syntax	Size	Notes
<u>Length</u>	11	<u>Length of R-MAP</u>
<u>R-MAP format {</u>		
<u>Number of IEs</u>	<u>6 bits</u>	<u>Indicates the number of IEs included</u>

<u>For (i = 0; i < Number of IEs; i++) {</u>		
<u> R-MAP IE</u>	<u>Variable</u>	
<u> }</u>		
<u>}</u>		

[\[Add new subclause 8.4.5.9.1\]](#)

8.4.5.9.1 R-MAP IE

R-MAP IE format is shown in Table XXX.

Table XXX. R-MAP IE format

<u>Syntax</u>	<u>Size</u>	<u>Notes</u>
<u>R-MAP IE ()</u>		
<u>Reduced CID</u>	<u>8 bits</u>	<u>Reduced RS basic CID</u>
<u>IE Type</u>	<u>6 bits</u>	
<u>If (IE type == (000000-001111)) {</u>		
<u> DL-MAP IE ()</u>	<u>Variable</u>	<u>DIUC 0-15. CID within DL-MAP IE is removed</u>
<u>If (IE type == (010000- 011111)) {</u>		
<u> UL-MAP IE ()</u>	<u>Variable</u>	<u>UIUC 0-15. CID within UL-MAP IE is removed</u>
<u>Else {</u>		
<u> R-link specific IE }</u>	<u>Variable</u>	
<u>}</u>		

The R-MAP IE type values are shown in Table XXX.

Table R-MAP IE type values.

<u>R-MAP IE type</u>	<u>Usage</u>
<u>0-15</u>	<u>OFDMA DL-MAP IE ()</u>
<u>16-31</u>	<u>OFDMA UL_MAP IE ()</u>
<u>33-63</u>	<u>Reserved for R-link specific IEs</u>

R-link specific IE format is shown in Table XXX.

Table R-link specific IE.

<u>Syntax</u>	<u>Size</u>	<u>Notes</u>
<u>R-link specific IE ()</u>		
<u> Length</u>	<u>6 bits</u>	<u>In bytes</u>

<u>IE specific data</u>	<u>Variable</u>	
<u>↓</u>		