

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Changes on DL-MAP_IE() in 802.16d/D3 OFDMA-PHY	
Date Submitted	2003-09-11	
Source(s)	Chulsik Yoon, Soonyong Lim, Kunmin Yeo, Jaeheung Kim, Byunghan Ryu ETRI 161 Gajeong-Dong, Yuseong-Gu, Daejeon, Korea	Voice: +82-42-860-6826 Fax: +82-42-860-6732 mailto: csyoon@etri.re.kr
Re:	This is a response to a Call for Comments IEEE 802.16e-03/18 on IEEE 802.16e-03/07r3	
Abstract	This document contains suggestions to the improvement of the power saving efficiency and the lessening the processing burdens on the DL-bursts in OFDMA-PHY.	
Purpose	The document is submitted for review by 802.16d &802.16e Working Group members.	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < mailto:chair@wirelessman.org > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < http://ieee802.org/16/ipr/patents/notices >.	

Changes on DL-MAP_IE() in 802.16e OFDMA-PHY

Chulsik Yoon, Soonyong Lim, Kunmin Yeo, Jaeheung Kim, Byunghan Ryu
ETRI

1. Background

In IEEE 802.16 DL bursts only discriminate the burst profiles configuring the bursts, but not specific to the SSs. Thus in TDM mode of operation, each SSs virtually should decode every DL bursts to draw out the data addressed to the SS. This is not the problem in the application of Fixed Wireless, where SSs may not be supplied by the battery power. For the mobile SSs which are basically battery powered, that is the serious shortcomings.

In the other PHY-modes except the OFDMA-PHY in 802.16a and 802.16e, the DL bursts are strictly ordered by the robustness of the physical burst profiles, from the most robust burst profile to the least robust burst profile; the SS should decode the DL bursts up to the operational burst profiles. Since the DL resources are allocated by rectangles of subchannels and symbols pair in OFDMA-PHY, the strict order of modulation levels by their robustness is not guaranteed. Thus each SS should decode the unwanted DL data bursts before it can validate the PDU header addressed to it. That causes the extra power consumption and imposes a burden in the receiver blocks, especially in the mobile environment for 802.16e.

Therefore, we suggest an alternative to the DL-MAP_IE to include the basic CIDs or broadcast CID of the addressed MSSs in the OFDMA-PHY for 802.16e. It should be subjected to the mobile specific environment only, not for the fixed wireless environments which can be supplied by the power lines. The suggested idea can help the corresponding MSSs to decode the specified DL bursts only and save their battery power during the remaining parts of the receiving periods.

MSSs can only decode the specified DL bursts only addressed by their basic CIDs or broadcast CID. We can reduce the additional overhead by addressing only the broadcast CID for the DL burst configured by broadcast messages and unicast messages, because the MSSs should decode the corresponding burst containing the broadcast messages whether the DL burst contains their basic CIDs or not.

Although this contribution intend to apply to mobile specific case only, but for the backward compatibility we propose to include the CIDs in DL-MAP_IE in OFDMA-PHY as an optional field.

2. Proposed changes in IEEE 802.16d and 802.16e OFDMA-PHY

[in 8.5.5.2]

Replace

Table 217-OFDMA DL-MAP_Information_Element format

Syntax	Size	Notes
DL_MAP_Information_Element() {		
DIUC	4 bits	
If (DIUC == 15) {		
Extended DIUC dependent IE	Variable	AAS_DL_IE()
} else {		

OFDM Symbol Offset	8 bits	
Subchannel Offset	5 bits	
Boosting	3 bits	000: normal (not boosted); 001: +6dB; 010: -6dB; 011: +9dB; 100: +3dB; 101: -3dB; 110: -9dB; 111: -12dB;
No. OFDM Symbols	8 bits	
No. Subchannels	5 bits	
Mini_Subchannel_index	3 bits	000 – no mini subchannels used; 001 – mini subchannel 1 is allocated; 010 – mini subchannel 2 is allocated; 011 – mini subchannel 3 is allocated; 100 – mini subchannel 4 is allocated; 101 – mini subchannel 5 is allocated; 110, 111 – reserved.
}		

To

Table 217-OFDMA DL-MAP_Information_Element format

Syntax	Size	Notes
DL_MAP_Information_Element() {		
DIUC	4 bits	
If (DIUC == 15) {		
Extended DIUC dependent IE	Variable	AAS_DI_IE()
} else {		
OFDM Symbol Offset	8 bits	
Subchannel Offset	5 bits	
Boosting	3 bits	000: normal (not boosted); 001: +6dB; 010: -6dB; 011: +9dB; 100: +3dB; 101: -3dB; 110: -9dB; 111: -12dB;
No. OFDM Symbols	8 bits	
No. Subchannels	5 bits	
Mini_Subchannel_index	3 bits	000 – no mini subchannels used; 001 – mini subchannel 1 is allocated; 010 – mini subchannel 2 is allocated; 011 – mini subchannel 3 is allocated; 100 – mini subchannel 4 is allocated; 101 – mini subchannel 5 is allocated; 110, 111 – reserved.
if (CID use is enabled by burst profile) {		
Number of CID Elements <i>m</i>	8 bits	Number <i>m</i> of Broadcast CID, Multicast CIDs, and Basic CIDs configuring the DL burst.
for (<i>i</i> = 0, <i>i</i> < <i>m</i> ; <i>i</i> ++) {		
CID	16 bits	Basic CIDs, Multicast CIDs, or Broadcast CID
}		
}		
}		

[Insert the following after the definition of Mini_Subchannel_index:]

CID

Represent the assignment of the IE to a Basic CIDs, Multicast CIDs, or Broadcast CID. The value is only present in an IE if the burst profile associated with the DIUC value specifies that CID usage is enabled.

[Insert the row at the end of Table 261]

Table 261 – DCD Channel Encodings –OFDMA-PHY

Name	Type	Length	Value
CID_In_DL_IE	29	1	0 – CID does not appear in DL-MAP_IE(default) 1 – CID does appear in DL-MAP_IE 2..255 - Reserved