

## 48. Physical Coding Sublayer (PCS) and Physical Medium Attachment (PMA) sublayer, type 10GBASE-X

Change rows in Link Status section as shown in Table 48-3:

### 48.2.4 Ordered\_sets and special code-groups

Table 48–1—Defined ordered\_sets and special code-groups

Code	Ordered_Set	Number of code-groups	Encoding
	<b>Link Status</b>		
Q	Sequence ordered_set	4	/K28.4/Dx.y/Dx.y/Dx.y/ <sup>a</sup>
LF	Local Fault signal	4	/K28.4/D0.0/D0.0/D1.0/
RF	Remote Fault signal	4	/K28.4/D0.0/D0.0/D2.0/
LINT	Link Interruption signal	4	/K28.4/D0.0/D0.0/D3.0/
Qrsvd	Reserved	4	!  LF   and !  RF   and !  LINT

<sup>a</sup>Dx.y/ indicates any data code-group.