

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 00 SC P L # 290
 Lo, William Marvell Semiconducto

Comment Type TR Comment Status A

- Auto-Neg register reference
- Split off BASE-T1 registers into its own register space
- Rename some registers to be more specific to BASE-T1

SuggestedRemedy

See Lo_McClellan_3bp_01a_0315.pdf page 18 for editing instructions

Response Response Status C

ACCEPT.

CI 00 SC P L # 331
 Bob Grow RMG Consulting

Comment Type TR Comment Status D

Clauses 22, 34 and 35 include statements that are in conflict with the proposed use of Clause 45 registers and the MDIO interface to access them. The GMII as specified in Std 802.3 includes use of the management interface specified in Clause 22. The attached file includes proposed text changes to avoid P802.3bp specifications that will introduce ambiguities into clause.

SuggestedRemedy

Detailed changes in file. If agreement on changes can be reached between P802.3bp, P802.3bx and P802.3bv, the Maintenance TF will likely accept the change for inclusion in the P802 revision project.
 The proposed text changes will need to be supplemented by changes to PICS, certainly for Clause 22 possibly for Clause 35

Proposed Response Response Status Z

REJECT.

This comment was WITHDRAWN by the commenter.

The Task Force agrees with the proposed changes as suggested by commenter. However, since the comment affects multiple projects, changes should be submitted into Revision project (P802.3bx).

CI 00 SC 0 P 1 L 1 # 261
 Regev, Alon Ixia

Comment Type ER Comment Status A

links do not work (they seem to have the command "Go to a page in another document", with the document name "Frame\Frame\P8023bp_C97", rather than going to a section within the draft document itself).

SuggestedRemedy

fix links

Response Response Status C

ACCEPT.

TOC is affected.

CI 00 SC 0 P 10 L 1 # 262
 Regev, Alon Ixia

Comment Type ER Comment Status A

The page numbers in the table of contents are mostly wrong. For example, the page number listed for section 97.6 is 74, but section 97.6 is actually on page 89.

The sections listed in the table of contents do not match the actual sections in the draft (for example, the table of contents has a whole section for 97.3.8, but there is no section 97.3.8 in the main text).

SuggestedRemedy

Regenerate the table of contents.

Response Response Status C

ACCEPT.

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 45 SC 45 P 25 L 1 # 286
 Lo, William Marvell Semiconducto

Comment Type TR Comment Status A Clause 45
 Clause 45 needs text

SuggestedRemedy

See Lo_McClellan_3bp_01a_0315.pdf pages 1, 2, 3, 4, 5, 7, 8, 9, 11, 12, 13, 14, 15, 16, 17 for text and editing instructions.

This also takes care of tu_3bp_01a_0215.pdf page 8 that was inadvertently left out of D1.30

Response Response Status C
 ACCEPT.

Instructions for changes to Clause 97 and moving registers from Clause 97 to new Clause 45 included in the referenced document.

Cl 78 SC 78.1.3.3.1 P 26 L 7 # 259
 Regev, Alon Ixia

Comment Type E Comment Status A
 "1000BASE-T1 PHY" should be just "1000BASE-T1" (as the who list is a list of PHYs).

SuggestedRemedy

change "1000BASE-T1 PHY" to "1000BASE-T1"

Response Response Status C
 ACCEPT.

Cl 78 SC Table 78-2 P 27 L 21 # 204
 Jim, Graba Broadcom Corporation

Comment Type TR Comment Status A
 The entries for Ts, Tq, and Tr maximums are TBD.

SuggestedRemedy

Replace Ts max TBD with 3.6.
 Replace Tq max TBD with 84.96.
 Replace Tr max with 1.44.

Response Response Status C
 ACCEPT.

Cl 79 SC 97.3.2.2.8 P 44 L 11 # 274
 Regev, Alon Ixia

Comment Type E Comment Status A
 "Interframe" is hyphenated in all other locations in the draft.

SuggestedRemedy

Change "Interframe" to "Inter-frame"

Response Response Status C
 ACCEPT.

Cl 97 SC 97.1 P 29 L 10 # 212
 Tu, Mike Broadcom

Comment Type ER Comment Status A
 There is no "PLD" sublayer. It should be "PMD" sublayer.

SuggestedRemedy

Change line 10 from

"... the PCS, PMA, and PLD sublayers ..."

to

"... the PCS, PMA, and PMD sublayers ..."

Response Response Status C
 ACCEPT.

Cl 97 SC 97.1.1 P 29 L 27 # 260
 Regev, Alon Ixia

Comment Type E Comment Status A
 per David Law, it is preferred not to include Objectives in the clauses as this complicates the maintenance (if in the long term a clause needs to be modified in a way that is not consistent with the original objectives).

Key information from the objectives should be included in the subclauses that describe the operation of 1000BASE-T1, without specifying them as "objectives".

SuggestedRemedy

Remove section 97.1.1.

Response Response Status C
 ACCEPT.

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 97 SC 97.1.1 P 29 L 27 # 298
 McClellan, Brett Marvell
 Comment Type T Comment Status A
 Sections 97.1.1 to 97.1.6, excluding 97.1.3.4 have no text.
 SuggestedRemedy
 I will submit a text proposal.
 Response Response Status C
 ACCEPT IN PRINCIPLE.
 Use regev_3bp_01_0315.pdf

CI 97 SC 97.1.2 P 29 L 33 # 256
 Regev, Alon Ixia
 Comment Type T Comment Status A
 Brett & I are providing baseline text for the missing front matter. I'm not sure if a comment (or just a presentation) is needed, but I'm filing the comment to make sure.
 SuggestedRemedy
 Provided in separate document.
 Response Response Status C
 ACCEPT IN PRINCIPLE.
 Use regev_3bp_01_0315.pdf

CI 97 SC 97.1.3.4 P 30 L 19 # 273
 Regev, Alon Ixia
 Comment Type T Comment Status A
 The word "normal" has multiple meanings in the draft including:
 1. PHY control is in SEND_DATA state (tx_mode = SEND_N).
 2. PHY is not in LPI mode.
 3. link_status=OK
 4. not in a test mode
 There is no definition of "normal" in the draft.
 While sometimes the meaning is clear, in some instances the meaning of "normal" is left up to interpretation.

SuggestedRemedy
 Use "non-test mode" to refer to non-test modes. Use the term "Normal power mode" to refer to the non-LPI mode. Use "tx_mode is set to SEND_N" to refer to the PHY control state. Use "link_status is OK" when refering to link state. Use a more specific description for other uses. Here are the detailed changes:
 Page 30, line 19:
 Replace "normal" with "normal power mode"
 Page 32, line 40:
 Replace "in normal mode." with "where frames can be exchanged with the link partner (i.e not in auto-negotiation, synchronization, or training modes)."
 Page 39, line 16:
 Replace "When the transmit channel is in normal mode," with "In normal transmit mode, when PMA_TXMODE.indication message has the value SEND_N,"
 Page 39, line 31:
 Replace "the PMA_TXMODE.indication message has the value SEND_N, and" with "when PMA_TXMODE.indication message has the value SEND_N,"
 Page 39, line 41:
 Replace "After reaching the normal mode of operation," with "Once PMA_TXMODE.indication has the value of SEND_N,"
 Page 46, line 45:
 Replace "When the transmit channel is operating in normal mode," with "When PMA_TXMODE.indication has the value of SEND_N,"
 Page 47, line 32:
 Replace "When the PHY is not in the normal state," with "When PMA_TXMODE.indication does not have the value of SEND_N,"
 Page 47, line 44:

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Replace "normal operational" with "normal power"

Page 48, line 46:
Replace "normal" with "normal power mode"

Page 48, line 50: addressed via separate comment as this section needs additional editing.

Page 52, line 34:
Replace "normal" with "normal power"

Page 52, line 37:
Replace "normal" with "normal power"

Page 54, line 47:
Replace "normal" with "normal power"

Page 67, line 8:
Replace "normal data transmission" with "frame transmission to the link partner by"

Page 67, line 37:
Replace "Failure of the underlying receive channel typically causes the PMA's clients to suspend normal operation." with "Failure of the underlying receive channel causes the PMA to set link_status to FAIL, which in turn causes the PMA's clients to stop exchanging frames and restart auto-negotiation (if enabled) or synchronization (if auto-negotiation is not enabled)."

Page 73, line 16:
Replace "Normal operation" with "Normal (non-test mode) operation"

Page 73, line 17:
Replace "normal mode" with "linked mode"

Page 74, line 2:
Replace "normal mode" with "Normal (non-test) mode"

Page 74, line 52:
Replace "normal" with "non-test"

Page 75, line 7:
Replace "normal" with "normal (non-test)"

Page 78, line 48:
Replace "are in the normal mode of operation" with "have established link (link_status is set to OK)"

Page 79, line 1:
Replace "are in the normal mode of operation" with "have established link (link_status is set to OK)"

Page 79, line 11:
Replace "normal" with "normal power mode"

Page 79, line 12:
Replace "normal" with "normal power"

Page 92, line 42:
Replace "normal operation." with "normal operation(when PMA_TXMODE.indication message has the value SEND_N and not in low power mode)."

Page 103, line 30:
Replace "normal operation" with "normal operation (when PMA_TXMODE.indication message has the value SEND_N and not in low power mode)"

Page 104, line 14:
Replace "normal operation" with "normal operation (when PMA_TXMODE.indication message has the value SEND_N and not in low power mode)"

Page 104, line 33:
Replace "normal operation" with "normal operation (when PMA_TXMODE.indication message has the value SEND_N and not in low power mode)"

Page 104, line 40:
Replace "normal operation" with "normal operation (when PMA_TXMODE.indication message has the value SEND_N and not in low power mode)"

Response *Response Status* **C**
ACCEPT IN PRINCIPLE.

Use "non-test mode" to refer to non-test modes. Use the term "Normal power mode" to refer to the non-LPI mode. Use "data mode" to refer to the PHY control state. Use "link_status is OK" when referring to link state. Use a more specific description for other uses.

Here are the detailed changes:

Page 30, line 19:
"normal" with "normal power mode"

Page 32, line 40:
Replace "This value is continuously asserted when transmission of sequences of symbols representing a GMII data stream in normal mode." With "This value is continuously asserted during transmission of sequences of symbols representing a GMII data stream in data mode."

Page 39, line 16:
Replace "normal mode" with "data mode"

Page 39, line 31:

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Replace "In the normal mode of operation, the PMA_TXMODE.indication message has the value SEND_N," with "In the data mode of operation, the PMA_TXMODE.indication message has the value SEND_N"

Page 39, line 41:
Replace " normal mode" with "data mode"

Page 46, line 45:
Replace " normal mode" with "data mode"

Page 47, line 32:
Replace "When the PHY is not in the normal state," with "When the PMA_TXMODE.indication message does not have the value of SEND_N,"

Page 47, line 44:
Replace "normal operational" with "normal power"

Page 48, line 46:
Replace "normal" with "normal power mode"

Page 48, line 50: addressed via separate comment as this section needs additional editing.

Page 52, line 34:
Replace "normal" with "normal power"

Page 52, line 37:
Replace "normal" with "normal power"

Page 54, line 47:
Replace "normal" with "normal power"

Page 67, line 8:
Replace "normal data transmission" with "frame transmission to the link partner by"

Page 67, line 37:
Replace "Failure of the underlying receive channel typically causes the PMA's clients to suspend normal operation." with "Failure of the underlying receive channel causes the PMA to set link_status to FAIL, which in turn causes the PMA's clients to stop exchanging frames and restart the auto-negotiation (if enabled) or synchronization (if auto-negotiation is not enabled) process."

Page 73, line 16:
Replace "Normal operation" with "Normal (non-test mode) operation"

Page 73, line 17:
Replace "normal mode" with "linked mode"

Page 74, line 2:
Replace "normal mode" with "Normal (non-test) mode"

Page 74, line 52:
Replace "normal" with "non-test"

Page 75, line 7:
Replace "normal" with "normal (non-test)"

Page 78, line 48:
Replace "are in the normal mode of operation" with "have established link (link_status is set to OK)"

Page 79, line 1:
Replace "are in the normal mode of operation" with "have established link (link_status is set to OK)"

Page 79, line 11:
Replace "normal" with "normal power mode"

Page 79, line 12:
Replace "normal" with "normal power"

Page 92, line 42:
Replace "during normal operation." with "during normal power operation in the data mode."

Page 103, line 30:
Replace "during normal operation" with " during normal power operation in the data mode"

Page 104, line 14:
Replace "during normal operation" with " during normal power operation in the data mode"

Page 104, line 33:
Replace "during normal operation" with " during normal power operation in the data mode"

Page 104, line 40:
Replace "during normal operation" with " during normal power operation in the data mode"

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 97 SC 97.1.3.4 P 30 L 21 # 263
 Regev, Alon Ixia

Comment Type TR Comment Status A

In section 97.1.3.4, it states that "Support for EEE capability is advertised during Auto-Negotiation."

The EEE capability is now exchanged in during training in Oct9<7> (containing the bit EEEen). In section 97.4.2.5.9, it states that the optional EEE capability shall only be enabled if both PHYs set the capability bit EEEen=1.

SuggestedRemedy

Change "Support for EEE capability is advertised during Auto-Negotiation." to "Support for EEE capability is advertised during Training."

Response Response Status C

ACCEPT IN PRINCIPLE.

Adding reference to where it is specified:

Change

"Support for EEE capability is advertised during Auto-Negotiation."

to

"Support for EEE capability is advertised during Training. See 97.4.2.5.5 for details."

CI 97 SC 97.1.3.4 P 30 L 21 # 220
 Tu, Mike Broadcom

Comment Type TR Comment Status A

The 1000BASE-T1 EEE capability is now advertised via training mode InfoField, instead of autoneg messages.

SuggestedRemedy

Change line 21 from

"Support for EEE capability is advertised during Auto-Negotiation."

to

"Support for EEE capability is advertised via InfoField during the startup sequence. See 97.4.2.5.5 for details."

Response Response Status C

ACCEPT IN PRINCIPLE.

See comment #263

CI 97 SC 97.11 P 109 L 18 # 281
 Lo, William Marvell Semiconducto

Comment Type T Comment Status A

Need to specify a latency bit time

SuggestedRemedy

Change TBD to 7200.

I don't know if group needs further discussion. I'm throwing a number of two RS frames out here to see if anyone objects - either too short or too long.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change "TBD BT" to "7200 bit time"

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 SC 97.2 P 30 L 50 # 221
 Tu, Mike Broadcom

Comment Type TR Comment Status A
 The Technology Dependent Interface is specified in either Clause 97.6 or Clause 98.

SuggestedRemedy

Change line 50 from

"...the Technology Dependent Interface is specified in Clause 98."

to

"...the Technology Dependent Interface is specified in Clause 98 or 97.6."

Response Response Status C

ACCEPT IN PRINCIPLE.

Since it is specified in both of these locations, "and" is more appropriate here.

Change line 50 from

"...the Technology Dependent Interface is specified in Clause 98."

to

"...the Technology Dependent Interface is specified in 97.6 and in Clause 98."

Cl 97 SC 97.2 P 33 L 1 # 300
 McClellan, Brett Marvell

Comment Type T Comment Status A Figure 97-1

figure 97-1: the dotted line primitives don't match the text primitives.

SuggestedRemedy

replace in figure 97-1

PMA_LPIMODE.indication replace with PMA_PCS_RX_LPI_STATUS.request

PMA_LPIREQ.request replace with PMA_PCS_TX_LPI_STATUS.request

remove from figure 97-1:

PMA_REMLPIREQ.request

PMA_UPDATE.indication

PMA_REMUPDATE.request

Response Response Status C

ACCEPT.

See also comment #241

Cl 97 SC 97.2 P 33 L 2 # 230
 Tu, Mike Broadcom

Comment Type TR Comment Status A Figure 97-1

In Figure 97-1 the Technology Dependent Interface should include the forced mode case. Refer to Figure 97-14 that has been discussed and agreed upon by the task force.

SuggestedRemedy

In Figure 97-1, on top of the figure, change

"Technology Dependent Interface (Clause 98)"

to

"Technology Dependent Interface (Clause 98 or 97.6)"

Response Response Status C

ACCEPT IN PRINCIPLE.

Preference is to reference subclause first and Clause later.

In Figure 97-1, on top of the figure, change

"Technology Dependent Interface (Clause 98)"

to

"Technology Dependent Interface (97.6 or Clause 98)"

Cl 97 SC 97.2 P 33 L 2 # 251
 Regev, Alon Ixia

Comment Type E Comment Status R Figure 97-1

As autonegotiation is optional, in Figure 97-1, PMA_LINK.request and PMA_LINK.indication should have dashed lines instead of solid lines in the signals.

SuggestedRemedy

In figure 97-1, use dashed lines for the signals PMA_LINK.request and PMA_LINK.indication.

Response Response Status C

REJECT.

PMA_LINK.request and PMA_LINK.indication are not optional and used in the synchronization machine.

Note this is a technical comment!

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 **SC 97.2.1** **P 31** **L 4** # **222**
 Tu, Mike Broadcom

Comment Type **TR** **Comment Status** **A**

In forced mode the Technology Dependent Interface is specified in Clause 97.6.

SuggestedRemedy
 Change line 4 from

"across the Technology Dependent Interface as specified in Clause 98:"

to

"across the Technology Dependent Interface as specified in Clause 98 or 97.6:"

Response **Response Status** **C**

ACCEPT IN PRINCIPLE.

Preference is to list subclause first

Change line 4 from

"across the Technology Dependent Interface as specified in Clause 98:"

to

"across the Technology Dependent Interface as specified in 97.6 or Clause 98:"

Cl 97 **SC 97.2.1.1** **P 31** **L 12** # **224**
 Tu, Mike Broadcom

Comment Type **TR** **Comment Status** **A**

In forced mode the PMA_LINK.request primitive is specified by 97.6 PHY Link Synchronization.

SuggestedRemedy
 Change line 12 and 13 from

"This primitive allows the Auto-Negotiation algorithm to enable and disable operation of the PMA as specified in 98.4.2"

to

"This primitive allows the Auto-Negotiation or the PHY Link Synchronization algorithm to enable and disable operation of the PMA as specified in 98.4.2 or 97.6."

Response **Response Status** **C**

ACCEPT IN PRINCIPLE.

Change line 12 and 13 from

"This primitive allows the Auto-Negotiation algorithm to enable and disable operation of the PMA as specified in 98.4.2"

to

"This primitive allows the Auto-Negotiation or the PHY Link Synchronization algorithm to enable and disable operation of the PMA, as specified in 98.4.2 and 97.6, respectively."

Cl 97 **SC 97.2.1.1** **P 31** **L 13** # **223**
 Tu, Mike Broadcom

Comment Type **TR** **Comment Status** **R**

Clause 98.4.2 does not exist.

SuggestedRemedy
 Define 98.4.2. See McClellan_3bp_nn_0315.pdf.

Response **Response Status** **C**

REJECT.

Contribution did not exist at the time the comment was reviewed.

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 97 SC 97.2.1.1 P 31 L 21 # 265
 Regev, Alon Ixia

Comment Type T Comment Status A

Description of DISABLE & ENABLE states of link_control are not clear and not consistent with the way they are defined in other clauses.

SuggestedRemedy

Replace
 "DISABLE PHY processes are disabled. This allows the Auto-Negotiation algorithm to determine how to configure the link"

with
 "DISABLE Used by the Auto-Negotiation algorithm to disable PHY processing while Auto-Negotiation is sending or receiving DME pages. This allows the Auto-Negotiation algorithm to determine how to configure the link"

Replace
 "EENABLE Used by Auto-Negotiation to turn control over to the PHY for data processing functions."

With
 "ENABLE Used by Auto-Negotiation to enable the PHY for data processing functions.

Response Response Status C

ACCEPT IN PRINCIPLE.

Change "Auto-Negotiation algorithm" to "Auto-Negotiation process" globally

Replace
 "DISABLE PHY processes are disabled. This allows the Auto-Negotiation algorithm to determine how to configure the link"

with
 "DISABLE Used by the Auto-Negotiation algorithm to disable PHY processing while the Auto-Negotiation process is sending or receiving DME pages. This allows the Auto-Negotiation process to determine how to configure the link"

Replace
 "EENABLE Used by Auto-Negotiation to turn control over to the PHY for data processing functions."

With
 "ENABLE Used by the Auto-Negotiation process to enable the PHY for data processing functions.

CI 97 SC 97.2.1.1.1 P 31 L 21 # 225
 Tu, Mike Broadcom

Comment Type TR Comment Status A

Need to include forced mode case.

SuggestedRemedy

Change line 21 from

"... PHY processes are disabled. This allows the Auto-Negotiation"

to

"... PHY processes are disabled. This allows the Auto-Negotiation or PHY Link Synchronization"

Response Response Status C

ACCEPT IN PRINCIPLE.

See comment #265

CI 97 SC 97.2.1.1.1 P 31 L 23 # 226
 Tu, Mike Broadcom

Comment Type TR Comment Status A

Need to include forced mode case

SuggestedRemedy

Change line 23 from

"...Used by Auto-Negotiation to turn control..."

to

"...Used by Auto-Negotiation or PHY Link Synchronization to turn control..."

Response Response Status C

ACCEPT IN PRINCIPLE.

See comment #265

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl **97** *SC* **97.2.1.1.2** *P* **31** *L* **28** # **227**
 Tu, Mike Broadcom

Comment Type **TR** *Comment Status* **A**
 Need to include forced mode case.

SuggestedRemedy
 Change line 28 from

"Auto-Negotiation generates this primitive to indicate a change in link_control as described in Clause 98."

to

"Auto-Negotiation or PHY Link Synchronization generates this primitive to indicate a change in link_control as described in Clause 98 or 97.6."

Response *Response Status* **C**
 ACCEPT IN PRINCIPLE.

Preference is to list subclause first

Change line 28 from

"Auto-Negotiation generates this primitive to indicate a change in link_control as described in Clause 98."

to

"Auto-Negotiation or PHY Link Synchronization generates this primitive to indicate a change in link_control as described in 97.6 or Clause 98."

Cl **97** *SC* **97.2.1.1.3** *P* **31** *L* **32** # **266**
 Regev, Alon Ixia

Comment Type **T** *Comment Status* **A**
 The description of the effect of receipt of the PMA_LINK.request(link_control) primitive is incomplete. While this primitive affects the PMA Link Monitor function, it also affects the PMA PHY Control function.

SuggestedRemedy
 Replace
 "This primitive affects operation of the PMA Link Monitor function as defined in 97.4.2.6."

With
 "This primitive affects operation of the PMA Link Monitor function as defined in 97.4.2.6 and the PMA PHY Control function as defined in 97.4.2.5."

Response *Response Status* **C**
 ACCEPT IN PRINCIPLE.

Adding missing articles

Replace
 "This primitive affects operation of the PMA Link Monitor function as defined in 97.4.2.6."

With
 "This primitive affects the operation of the PMA Link Monitor function as defined in 97.4.2.6 and the PMA PHY Control function as defined in 97.4.2.5."

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 SC 97.2.1.2 P 31 L 37 # 228
 Tu, Mike Broadcom

Comment Type TR Comment Status A
 PMA_LINK.indication is specified in 98.4.1, instead of 28.2.6.1. Also need to include forced mode case.

SuggestedRemedy
 Change line 37 from

"...28.2.6.1. This primitive informs the PCS, PMA PHY Control function, and the Auto-Negotiation algorithm..."

to

"...98.4.1. This primitive informs the PCS, PMA PHY Control function, and the Auto-Negotiation or PHY Link Synchronization algorithm..."

Response Response Status C
 ACCEPT IN PRINCIPLE.

Change line 37 from

"...28.2.6.1. This primitive informs the PCS, PMA PHY Control function, and the Auto-Negotiation algorithm..."

to

"...98.4.1. This primitive informs the PCS, PMA PHY Control function, and the Auto-Negotiation or PHY Link Synchronization process..."

Cl 97 SC 97.2.1.2 P 31 L 37 # 299
 McClellan, Brett Marvell

Comment Type T Comment Status A
 incorrect reference to 28.2.6.1.

SuggestedRemedy
 change 28.2.6.1 to 98.4.1

Response Response Status C
 ACCEPT.

See comment #228

Cl 97 SC 97.2.1.2.2 P 31 L 54 # 238
 Regev, Alon Ixia

Comment Type T Comment Status A
 "When Generated" for PMA_LINK.indication (link_status) states "The PMA generates this primitive to indicate a change in link_status in compliance with the state diagram given in Figure 97.5". This should be Figure 97-21.

SuggestedRemedy
 Change "Figure 97.5" to "Figure 97-21"

Response Response Status C
 ACCEPT.

Cl 97 SC 97.2.1.2.2 P 31 L 54 # 229
 Tu, Mike Broadcom

Comment Type TR Comment Status A
 The state diagram is shown in Figure 97-21, instead of Figure 97-5.

SuggestedRemedy
 Change line 54 from

"...given in Figure 97.5."

to

"...given in Figure 97.21."

Response Response Status C
 ACCEPT IN PRINCIPLE.

See comment #238

CI 97 SC 97.2.1.2.3 P 32 L 3 # 240
 Regev, Alon Ixia

Comment Type T Comment Status A

The effect of receipt of PMA_LINK.indication (link_status) is specified as "The effect of receipt of this primitive is specified in 97.4.1.", but there is no text in 97.4.1 that specifies the effect of receipt of link_status.

SuggestedRemedy

Replace
 "The effect of receipt of this primitive is specified in 97.4.1."

With
 "The effect of receipt of this primitive is specified in 98.4.1"

Response Response Status C
 ACCEPT.

CI 97 SC 97.2.2 P 33 L 1 # 241
 Regev, Alon Ixia

Comment Type T Comment Status A Figure 97-1

The PMA service interface signals is Table 97-1 do not match the text in 97.2.2. The text is correct, and the figure is wrong.

Figure 97-1 also references the two connections to the balanced pair cabling as "MDI-" and "MDI+" whereas in the PMA subclause they are labeled "BI_DA-" and "BI_DA+". The MDI subclause does not refer to these by name.

SuggestedRemedy

In Figure 97-1, make the following changes:

Delete the arrows with the labels PMA_RESET.indication, PMA_LPIMODE.indication, PMA_LPIREQ.request, PMA_REMLPIREQ.request, PMA_UPDATE.indication, and PMA_REMUPDATE.request.

Add a line from PCS to PMA, with an arrowhead on the PMA side with the line labeled "PMA_PCSSTATUS.request(pcs_status)". This line should be where PMA_RESET.indication is in the existing drawing.

Add a dashed line from PCS to PMA, with an arrowhead on the PMA side with the line labeled "PMA_PCS_RX_LPI_STATUS.request". This dashed line should be where PMA_LPIMODE.indication is in the current drawing.

Add a dashed line from PCS to PMA, with an arrowhead on the PMA side with the line labeled "PMA_PCS_TX_LPI_STATUS.request". This dashed line should be where PMA_LPIREQ.request is in the current drawing.

Change the text "MDI-" to "BI_DA-".

Change the text "MDI+" to "BI_DA+".

Response Response Status C
 ACCEPT IN PRINCIPLE.

In Figure 97-1, make the following changes:

Delete the arrows with the labels PMA_LPIMODE.indication, PMA_LPIREQ.request, PMA_REMLPIREQ.request, PMA_UPDATE.indication, and PMA_REMUPDATE.request.

Add a line from PCS to PMA, with an arrowhead on the PMA side with the line labeled "PMA_PCSSTATUS.request(pcs_status)". This line should be under the existing PMA_RESET.indication.

Add a dashed line from PCS to PMA, with an arrowhead on the PMA side with the line labeled "PMA_PCS_RX_LPI_STATUS.request". This dashed line should be where PMA_LPIMODE.indication is in the current drawing.

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Add a dashed line from PCS to PMA, with an arrowhead on the PMA side with the line labeled "PMA_PCS_TX_LPI_STATUS.request". This dashed line should be where PMA_LPIREQ.request is in the current drawing.

Change Figure 97-14 as follows:
 Change the text "BI_DA-" to "MDI-".
 Change the text "BI_DA+" to "MDI+".

See also comment #300

Cl 97 SC 97.2.2 P37 L 5 # 301

McClellan, Brett Marvell

Comment Type T Comment Status A Figure 97-1

primitive PMA_RESET.indication in figure 97-1 is not defined

SuggestedRemedy

insert primitive definition for PMA_RESET.indication before 97.2.2.9

97.2.2.9 PMA_RESET.indication

This primitive is used to pass the PMA Reset function to the PCS (pcs_reset=ON) when reset is enabled.

The PMA_RESET.indication primitive can take on one of two values:

TRUE Reset is enabled.

FALSE Reset is not enabled.

97.2.2.9.1 When generated

The PMA Reset function is executed as described in 97.4.2.1.

97.2.2.9.2 Effect of receipt

The effect of receipt of this primitive is specified in 97.4.2.1.

Response Response Status C

ACCEPT IN PRINCIPLE.

Changes per suggested remedy. In 97.2.2 (page 32 line 17) add PMA_RESET.indication to the end of the list.

Cl 97 SC 97.2.2.1.1 P32 L 41 # 213

Tu, Mike Broadcom

Comment Type ER Comment Status R

SEND_I is not defined in 1000BASE-T1.

SuggestedRemedy

Remove "SEND_I" and the corresponding descriptions in line 41 and 42.

Response Response Status C

REJECT.

SEND_I is defined in 97.4.4.1 and used in Figure 97-20.

Cl 97 SC 97.2.2.1.1 P32 L 42 # 294

McClellan, Brett Marvell

Comment Type E Comment Status A

incomplete sentence.

SuggestedRemedy

add "is to take place."

Response Response Status C

ACCEPT.

Cl 97 SC 97.2.2.10 P37 L 30 # 275

Regev, Alon Ixia

Comment Type T Comment Status A Figure 97-1

tx_lpi_active is not actually used by the PMA (at least not in the draft). It is not whown in Figure 97-14 and is not referenced anywhere in the PMA.

Theoretically the PMA could use this to power down the transmitter, but there is no mention of this in the PMA text.

SuggestedRemedy

Page 32, line 24:

Remove the line "PMA_PCS_TX_LPI_STATUS.request (tx_lpi_active)"

Page 33:

Remove (or do not add) PMA_PCS_TX_LPI_STATUS.request from Figure 97-1 (yes I'm aware that this is contradicotry to another comment where I requested to add this signal to this figure).

Delete subclause 97.2.2.10 and all its subclauses

Response Response Status C

ACCEPT IN PRINCIPLE.

Add tx_lpi_active to Figure 97-14 as follows: add a dashed line (it is optional) arrow from the top of the diagram to the PMA TRANSMIT block with the an arrowhead on the PMA TRANSMIT side and PMA RECEIVE side. label the line as "tx_lpi_active".

Change rx_lpi_active to dashed line.

CI 97 SC 97.2.2.10 P 37 L 32 # 250
Regev, Alon Ixia

Comment Type T Comment Status A

PMA_PCS_TX_LPI_STATUS.request (tx_lpi_active) is generated by the PCS transmit function, not the PCS receive function

SuggestedRemedy

Change
"When the PHY supports the EEE capability this primitive is generated by the PCS receive function to indicate the status of the transmit link at the local PHY."

To:
"When the PHY supports the EEE capability this primitive is generated by the PCS transmit function to indicate the status of the transmit link at the local PHY."

Response Response Status C
ACCEPT.

CI 97 SC 97.2.2.10 P 37 L 35 # 249
Regev, Alon Ixia

Comment Type E Comment Status A

The draft states that PMA_PCS_TX_LPI_STATUS.request (tx_lpi_active) is generated by the PCS Transmit state diagram in Figure 97-12, but this is not true. Figure 97-12 uses tx_lpi_active as an input.

The generation of tx_lpi_active is actually described in 97.3.5 and 97.3.6.2.2.

SuggestedRemedy

On page 37, line 35:
Delete "The parameter is generated by the PCS Transmit state diagram in Figure 97-12."

On Page 37, line 49,
Change
"The PCS generates PMA_PCS_TX_LPI_STATUS.request messages to indicate a change in the tx_lpi_active variable as determined by the transmit state diagram in Figure 97-12."

To
"The PCS generates PMA_PCS_TX_LPI_STATUS.request messages to indicate a change in the tx_lpi_active variable as described in 97.3.5 and 97.3.6.2.2."

Response Response Status C
ACCEPT.

CI 97 SC 97.2.2.2 P 33 L 45 # 242
Regev, Alon Ixia

Comment Type T Comment Status A

The PMA_CONFIG.indication states that "MASTER-SLAVE configuration is determined during Auto-Negotiation", but this is not true when Auto-Negotiation is not used.

SuggestedRemedy

Replace "MASTER-SLAVE configuration is determined during Auto-Negotiation (Clause 98). The result of this negotiation is provided to the PMA."

With
"If Auto-Negotiation is enabled, PMA_CONFIG MASTER-SLAVE configuration is determined during Auto-Negotiation (Clause 98) and the result of this negotiation is provided to the PMA. If Auto-Negotiation is not enabled, PMA_CONFIG MASTER-SLAVE configuration is pre-determined to be Master or Slave via management control during initialization or via default hardware set-up"

Response Response Status C
ACCEPT IN PRINCIPLE.

With minor editorial revisions

Replace

"MASTER-SLAVE configuration is determined during Auto-Negotiation (Clause 98). The result of this negotiation is provided to the PMA."

With

"If the Auto-Negotiation process is enabled, PMA_CONFIG MASTER-SLAVE configuration is determined during Auto-Negotiation (Clause 98) and the result is provided to the PMA. If the Auto-Negotiation process is not enabled, PMA_CONFIG MASTER-SLAVE configuration is pre-determined to be Master or Slave via management control during initialization or via default hardware set-up."

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 SC 97.2.2.2 P 33 L 46 # 231
 Tu, Mike Broadcom

Comment Type TR Comment Status A

In forced mode the MASTER-SLAVE configuration is pre-determined.

SuggestedRemedy

Change line 45-47 from

"... MASTER-SLAVE configuration is determined during Auto-Negotiation (Clause 98). The result of this negotiation is provided to the PMA."

to

"... MASTER-SLAVE configuration is either preconfigured or determined during Auto-Negotiation (Clause 98), in which case the result of this negotiation is provided to the PMA."

Response Response Status C

ACCEPT IN PRINCIPLE.

See comments #242

Cl 97 SC 97.2.2.4.1 P 34 L 48 # 243
 Regev, Alon Ixia

Comment Type E Comment Status A

In clause 40, there were 4 pairs and 4 symbols were received on each clock cycle. In clause 97, we only have 1 pair, but we still have wording left over from clause 40 that seems to indicate simultaneous receive of symbols. As this is not the case, we need to edit the phrasing

SuggestedRemedy

Replace

"During reception the PMA_UNITDATA.indication simultaneously conveys to the PCS via the parameter rx_symb the values of the symbols detected on the MDI."

With

"During reception the PMA_UNITDATA.indication conveys to the PCS via the parameter rx_symb the value of the symbols detected on the MDI during each cycle of the recovered clock. Each symbol can have the value of -1, 0, of +1."

Response Response Status C

ACCEPT IN PRINCIPLE.

With minor editorial changes

Replace

"During reception the PMA_UNITDATA.indication simultaneously conveys to the PCS via the parameter rx_symb the values of the symbols detected on the MDI."

With

"During reception the PMA_UNITDATA.indication conveys to the PCS via the parameter rx_symb the value of symbols detected on the MDI during each cycle of the recovered clock."

CI 97 SC 97.2.2.7.3 P 36 L 31 # 244
Regev, Alon Ixia

Comment Type T Comment Status A

Not all effects of receipt of PMA_RXSTATUS.indication (loc_rcvr_status) are specified

SuggestedRemedy

Replace
"The effect of receipt of this primitive is specified in Figure 97–20 and in 97.3.2.3 and 97.4.5.2."

With "The effect of receipt of this primitive is specified in Figure 97–20 and in 97.3.2.3, 97.4.2.5, and 97.4.5"

Response Response Status C

ACCEPT IN PRINCIPLE.

Replace
"The effect of receipt of this primitive is specified in Figure 97–20 and in 97.3.2.3 and 97.4.5.2."

With "The effect of receipt of this primitive is specified in Figure 97–20, 97.3.2.3, 97.4.2.5, and 97.4.5"

CI 97 SC 97.2.2.8 P 36 L 38 # 245
Regev, Alon Ixia

Comment Type T Comment Status A

Section 97.2.2.8 states that "The criterion for setting the parameter rem_rcvr_status is left to the implementor. It can be based, for example, on asserting rem_rcvr_status is NOT_OK until loc_rcvr_status is OK and then asserting the detected value of rem_rcvr_status after proper PCS Receive decoding is achieved."

This is contradictory to other parts of the clause that indicate that "This variable is received in the loc_rcvr_status bit in the InfoField from the remote PHY".

SuggestedRemedy

Replace
"The criterion for setting the parameter rem_rcvr_status is left to the implementor. It can be based, for example, on asserting rem_rcvr_status is NOT_OK until loc_rcvr_status is OK and then asserting the detected value of rem_rcvr_status after proper PCS Receive decoding is achieved."

with

"rem_rcvr_status is set to the value received in the loc_rcvr_status bit in the InfoField from the remote PHY. rem_rcvr_status is set to NOT_OK if the PCS has not decoded a valid InfoField from the remote PHY."

Response Response Status C

ACCEPT IN PRINCIPLE.

With minor editorial fixes

Replace

"The criterion for setting the parameter rem_rcvr_status is left to the implementor. It can be based, for example, on asserting rem_rcvr_status is NOT_OK until loc_rcvr_status is OK and then asserting the detected value of rem_rcvr_status after proper PCS Receive decoding is achieved."

with

"The parameter rem_rcvr_status is set to the value received in the loc_rcvr_status bit in the InfoField from the remote PHY. The rem_rcvr_status is set to NOT_OK if the PCS has not decoded a valid InfoField from the remote PHY."

CI 97 SC 97.2.2.8.2 P 36 L 53 # 247
Regev, Alon Ixia

Comment Type T Comment Status A

The PCS generates PMA_REMRXSTATUS.request messages to indicate a change in rem_rcvr_status based on decoding InfoField messages received from the remote PHY during training; not directly on the basis of signals received at the MDI.

SuggestedRemedy

Replace
"The PCS generates PMA_REMRXSTATUS.request messages to indicate a change in rem_rcvr_status on the basis of signals received at the MDI."

With
"The PCS generates PMA_REMRXSTATUS.request messages to indicate a change in rem_rcvr_status based on the PCS decoding the loc_rcvs_status bit in InfoField messages received from the remote PHY during training."

Response Response Status C

ACCEPT.

CI 97 SC 97.2.2.9 P 37 L 10 # 248
Regev, Alon Ixia

Comment Type T Comment Status A

The draft states that PMA_PCS_RX_LPI_STATUS.request (rx_lpi_active) is generated by the PCS Receive state diagram in Figure 97-13, but this is not true. Figure 97-13 uses rx_lpi_active as an input.

The generation of rx_lpi_active is actually described in 97.3.2.3 and in 97.3.6.2.2.

SuggestedRemedy

On page 37, line 10:
Delete "The parameter is generated by the PCS Receive state diagram in Figure 97-13."

On Page 37, line 23,
Change
"The PCS generates PMA_PCS_RX_LPI_STATUS.request messages to indicate a change in the rx_lpi_active variable as determined by the receive state diagram in Figure 97-13."

To
"The PCS generates PMA_PCS_RX_LPI_STATUS.request messages to indicate a change in the rx_lpi_active variable as described in 97.3.2.3 and 97.3.6.2.2."

Response Response Status C

ACCEPT.

CI 97 SC 97.3 P 38 L 27 # 253
Regev, Alon Ixia

Comment Type T Comment Status A

"PMA_UNITDATA.indication(rx_symb_vector)" (used in the PCS subclause) is not consistent with "PMA_UNITDATA.indication(rx_symb)" (used elsewhere in Clause 97). As this only contains one symbol, it should not be called "_vector".

"PMA_UNITDATA.request(tx_symb_vector)" (used in the PCS subclause) is not consistent with "PMA_UNITDATA.request(tx_symb)" (used elsewhere in Clause 97). As this only contains one symbol, it should not be called "_vector".

SuggestedRemedy

change all instances of "rx_symb_vector" to "rx_symb".

change all instances of "tx_symb_vector" to "tx_symb".

Response Response Status C

ACCEPT.

There are a total of 5 entries in the whole draft that need to be changed.

CI 97 SC 97.3.2 P 38 L 40 # 214
Tu, Mike Broadcom

Comment Type ER Comment Status A

In Figure 97-2, "tx_symb_vector" and "rx_symb_vector" should be replaced by "tx_symb" and "rx_symb" respectively. See Clause 97.2.2.3.1 and 97.2.2.4.1.

SuggestedRemedy

In Figure 97-2,

Change "PMA_UNITDATA.request(tx_symb_vector)" to
"PMA_UNITDATA.request(tx_symb)".

Change "PMA_UNITDATA.indication(rx_symb_vector)" to
"PMA_UNITDATA.indication(rx_symb)".

Response Response Status C

ACCEPT IN PRINCIPLE.

See comment #253.

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 97 SC 97.3.2.2 P 39 L 18 # 186
 Remein, Duane Huawei

Comment Type TR Comment Status A

An OAM9 symbol is not defined or described anywhere that I could find (based on whole reader search for OAM9).

Note: This may be contained in 97.7 but that section does not use the term OAM9.

SuggestedRemedy

Add editors note that a description of OAM9 is needed.

If the description in 97.7 applies than replace "OAM symbol" with "OAM9 symbol" as appropriate (note there is a stray OAM symbol pg 52 lin 32).

Response Response Status C

ACCEPT IN PRINCIPLE.

Change all instances of "OAM9 symbol" to "OAM symbol" to remain consistent with 97.7.1

Next, change all other instances of OAM9 in the draft to OAM - they are mostly in Figures: 97-3, 97-4, 97-5

CI 97 SC 97.3.2.2 P 39 L 33 # 232
 Tu, Mike Broadcom

Comment Type TR Comment Status A

The 81B bits after 80/81 encoding goes to the RS FEC first, then scrambled by PCS scrambler.

SuggestedRemedy

Change line 33 to 35 from

"During transmission, the 81B bits are scrambled by the PCS using a PCS scrambler. During data encoding PCS Transmit utilizes a RS frame encoder, then frames are encoded into a sequence of PAM3 symbols and transferred to the PMA."

to

"During transmission, 45 blocks of the 81B bits shall be aggregated, encoded by a RS frame encoder, and then scrambled by a PCS scrambler. During data encoding PCS Transmit frames shall be encoded into a sequence of PAM3 symbols and transferred to the PMA."

Response Response Status C

ACCEPT IN PRINCIPLE.

Change line 33 to 35 from

"During transmission, the 81B bits are scrambled by the PCS using a PCS scrambler. During data encoding PCS Transmit utilizes a RS frame encoder, then frames are encoded into a sequence of PAM3 symbols and transferred to the PMA."

to

"During transmission, 45 81B blocks shall be aggregated, encoded by a RS frame encoder, and then scrambled by a PCS scrambler. During data encoding PCS Transmit frames shall be encoded into a sequence of PAM3 symbols and transferred to the PMA."

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 97 SC 97.3.2.2.10 P 36 L 30 # 322
 Thomas Lindner BMW

Comment Type T Comment Status A
 Page 36; 97.3.2.2.10 Transmit process line 30

SuggestedRemedy
 tx-coded<80:0> is not passed to the scrambler, at first it is Aggregate to 45 81B blocks, plus OAM9, then passed to the Reed Solomon FEC Encoder and then passed to the scrambler.

Change to 0x01 (is already in the comment list)

Response Response Status C
 ACCEPT IN PRINCIPLE.

Location changed to page 44, line 39 - commenter used D1.2 for reference.

Change

"a vector tx_coded<80:0>, which is passed to the scrambler"

to

"a vector tx_coded<80:0>, which is aggregated with 45 81B blocks and OAM, then passed to the Reed Solomon FEC Encoder and then finally passed to the scrambler."

CI 97 SC 97.3.2.2.10 P 44 L 27 # 270
 Regev, Alon Ixia

Comment Type T Comment Status A
 Error control codes are only sent when both TX_EN & TX_ER are asserted

SuggestedRemedy
 Replace "The Error is sent when TX_ER is asserted."

With "The Error control code is sent when TX_ER and TX_EN are both asserted."

Response Response Status C
 ACCEPT.

CI 97 SC 97.3.2.2.10 P 44 L 28 # 271
 Regev, Alon Ixia

Comment Type T Comment Status A
 References to undefined function definitions R_BLOCK_TYPE and T_BLOCK_TYPE.

SuggestedRemedy
 Remove the sentence "See R_BLOCK_TYPE and T_BLOCK_TYPE function definitions in 97.3.6.2.4 for further information."

Response Response Status C
 ACCEPT.

CI 97 SC 97.3.2.2.11 P 37 L 38 # 323
 Thomas Lindner BMW

Comment Type T Comment Status R
 Page 37 97.3.2.2.11 RS encoder line 38

SuggestedRemedy
 Change to 3654

Response Response Status C
 REJECT.

Comment is actually against page 45 line 47 - commenter used D1.2 for reference. The number is already correct today. No changes to draft needed.

CI 97 SC 97.3.2.2.12 P 38 L 1/7 # 324
 Thomas Lindner BMW

Comment Type ER Comment Status R
 Page 38 97.3.2.2.12 PCS scrambler line 1 and line 7

Same function-name for Slave and Master GS-Polynome.

SuggestedRemedy
 Change to $GM(x) = 1 + x^4 + x^{15}$
 Change to $GS(x) = 1 + x^{11} + x^1$

Response Response Status C
 REJECT.

Both equations are numbered and not referenced in text by name. No change needed.

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 97 SC 97.3.2.2.12 P 38 L 13-2 # 325
 Thomas Lindner BMW
 Comment Type ER Comment Status A
 Page 38 97.3.2.2.12 PCS scrambler Figure 97-7—MASTER and SLAVE PCS scramblers line 13..24
 SuggestedRemedy
 Add missing arrows around the "+" sign and into S0 block
 Response Response Status C
 ACCEPT.
 Page 46, line 18 - commenter was using D1.2 for reference.

CI 97 SC 97.3.2.2.12 P 44 L 48 # 207
 Shen, BZ Broadcom
 Comment Type TR Comment Status A
 The (450,406) FEC code is not a cyclic code, since it is a shortened code from a length 511 RS code.
 SuggestedRemedy
 Change line 48 and 49 from
 "The FEC code used for 1000BASE-T1 links is a linear cyclic block code—the Reed-Solomon code (450,406) over the Galois Field of GF(2⁹)—a code operating on 9 bit symbols,..."
 to
 "The FEC code used for 1000BASE-T1 links is a shortened Reed-Solomon (450,406) code over the Galois Field GF(2⁹)—a code operating on 9 bit symbols,..."
 Response Response Status C
 ACCEPT.

CI 97 SC 97.3.2.2.12 P 45 L 12 # 206
 Shen, BZ Broadcom
 Comment Type ER Comment Status R
 The entire paragraph from line 12 to 14 and Figure 97-6 are redundant, since the parity calculation is already defined in Equation 97-2.
 SuggestedRemedy
 Remove entire paragraph from line 12 to 14, and remove Figure 97-6.
 Response Response Status C
 REJECT.
 These statements actually add mandatory requirements. Equation is illustrative only. The very same definition is used in other locations in 802.3

CI 97 SC 97.3.2.2.12 P 45 L 23 # 330
 Brown, Thomas Vitesse Semiconducto
 Comment Type TR Comment Status A
 The data feeding the RS Encoder is listed as D449 ... D45
 The data should be D405...D0
 SuggestedRemedy
 The data input on Figure 97-6 should be D405 ... D0
 Response Response Status C
 ACCEPT.

CI 97 SC 97.3.2.2.12 P 45 L 23 # 208
 Shen, BZ Broadcom
 Comment Type TR Comment Status A
 In Figure 97-6, indices of the input to the divider is wrong.
 SuggestedRemedy
 Change Figure 97-6 input to the divider from
 "D449, D448, ..., D46, D45"
 to
 "D405, D404, ..., D1, D0"
 Response Response Status C
 ACCEPT.
 See comment #330

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 97 SC 97.3.2.2.13 P 46 L 18 # 233
 Tu, Mike Broadcom

Comment Type **TR** Comment Status **A**

The scrambler runs continuously on both payload bits and RS parity check bits.

SuggestedRemedy

Change line 18 and 19 from

"...The scrambler is run continuously on all payload bits."

to

"...The scrambler is run continuously on all RS frame output bits."

Response Response Status **C**

ACCEPT.

CI 97 SC 97.3.2.2.13 P 46 L 18 # 211
 Tu, Mike Broadcom

Comment Type **E** Comment Status **A**

The statement needs clarifications. Add a note that the seeds are exchanged via InfoField during startup sequence.

SuggestedRemedy

Change the first sentence from

"The initial seed values for the MASTER and SLAVE are left to the implementor."

to

"The initial seed values for the MASTER and SLAVE scramblers are left to the implementor. The seed values shall be non-zero and shall be transmitted during the InfoField exchange. See Clause 97.4.2.5.5."

Response Response Status **C**

ACCEPT IN PRINCIPLE.

This is a technical comment!

Change the first sentence from

"The initial seed values for the MASTER and SLAVE are left to the implementor."

to

"The initial seed values for the MASTER and SLAVE scramblers are left to the implementor. The seed values shall be non-zero and shall be transmitted during the InfoField exchange. (See 97.4.2.5.5)"

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 97 SC 97.3.2.2.16 P 47 L 40 # 279
 Regev, Alon Ixia

Comment Type T Comment Status A

The sentence "When the lpi_tx_mode variable takes the value REFRESH the PMA maps the scrambler output into PAM3" is not clear.

SuggestedRemedy

Change
 "When the lpi_tx_mode variable takes the value REFRESH the PMA maps the scrambler output into PAM3"

To:
 "When the lpi_tx_mode variable takes the value REFRESH, the PCS passes zero data encoded through PCS data path (through the RS encoder, scrambler, and 3B2T mapper) to the PMA via the PMA_UNITDATA.request primitive."

Response Response Status C

ACCEPT IN PRINCIPLE.

Change
 "When the lpi_tx_mode variable takes the value REFRESH the PMA maps the scrambler output into PAM3"

To:
 "When the lpi_tx_mode variable takes the value REFRESH, the PCS passes zero data encoded through PCS data path to the PMA via the PMA_UNITDATA.request primitive."

CI 97 SC 97.3.2.2.2 P 40 L 27 # 236
 Steven, Chen Broadcom

Comment Type ER Comment Status A

The added "LSB" notation in OAM9 symbol is confusing with previous 81B block.

SuggestedRemedy

Remove the newly added "LSB" within the OAM9 block. Change it to a text with arrow at the bottom of the OAM9 block, similar to the "TXB<80>" notation at line 23.

Response Response Status C

ACCEPT.

CI 97 SC 97.3.2.2.4 P 42 L 4 # 272
 Regev, Alon Ixia

Comment Type T Comment Status A

When representing the 81B blocks, figures 97-5 and 97-7 use a bit ordering of H (header), 0, 1, ... 79, whereas the block definition in 97.3.2.2.2 and 97.3.2.2.5 define this as TXB<0:80>.

SuggestedRemedy

In Figure 97-5, Replace H,0..79 with 0..80 in each of the 3 instances in the top row of blocks.

In Figure 97-7, Replace "H" with "0", "0" with "1", "1" with "2", "7" with "8", "8:16" with "9:17", and "71:79" with "72:80"

Response Response Status C

ACCEPT.

CI 97 SC 97.3.2.2.6 P 43 L 28 # 268
 Regev, Alon Ixia

Comment Type E Comment Status A

Control Codes should not be labeled as "(recommended)" as their use is not optional.

SuggestedRemedy

remove the "(recommended)"

Response Response Status C

ACCEPT.

This is a technical comment!

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 SC 97.3.2.2.6 P 43 L 30 # 267
 Regev, Alon Ixia

Comment Type T Comment Status A

The text does not correctly map the GMII to control code mapping for cases where TX_ER is asserted but TX_EN is not asserted.

SuggestedRemedy

Change
 "When TX_ER is asserted, the 1000BASE-T1 PCS will convey an Error symbol in the 80B81B block code."

To
 "When TX_ER and TX_EN are both asserted, the 1000BASE-T1 PCS will convey an Error symbol in the 80B81B block code."

Response Response Status C

ACCEPT IN PRINCIPLE.

Change
 "When TX_ER is asserted, the 1000BASE-T1 PCS will convey an Error symbol in the 80B81B block code."

To
 "When TX_ER and TX_EN are both asserted, the 1000BASE-T1 PCS conveys an Error symbol in the 80B81B block code."

Cl 97 SC 97.3.2.2.6 P 43 L 47 # 269
 Regev, Alon Ixia

Comment Type T Comment Status A

Use the values for the control codes for "Assert Low Power Idle" currently in the draft (control code value 101) as baseline text.

SuggestedRemedy

Accept as baseline the control code value of 101 for Assert Low Power Idle.

Remove italics on "101", "Assert Low Power Idle", and "Assert Low Power Idle"

Response Response Status C

ACCEPT.

Cl 97 SC 97.3.2.2.6 P 43 L 47 # 283
 Lo, William Marvell Semiconducto

Comment Type E Comment Status A

Remove italics font in 101 row

SuggestedRemedy

See above

Response Response Status C

ACCEPT.

See comment #269

Cl 97 SC 97.3.2.2.8 P 44 L 13 # 182
 Remein, Duane Huawei

Comment Type E Comment Status A

This statement is not clear: "They shall not be added while data is being received" received from where; GMII or PMA? My assumption is GMII as this section discusses PCS TX.

SuggestedRemedy

Add "from the GMII" so the statement reads:
 "They shall not be added while data is being received from the GMII"

Response Response Status C

ACCEPT IN PRINCIPLE.

It is questionable whether this statement is needed altogether. Suggest to remove "They shall not be added while data is being received"

This is a technical comment!

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 SC 97.3.2.2.9 P 44 L 23 # 205
 Jim, Graba Broadcom Corporation

Comment Type TR Comment Status A

"If EEE is not supported, then LP_IDLE isn't a valid control character." should be removed. Allowing LP_IDLE to be a valid control character makes for a simpler PHY implementation without compromising performance.

The ramification is if the PHYs don't advertise EEE and the GMII asserts the low power idle condition the PHY shall transmit normal data across the MDI encoded with LPI_IDLEs to the link partner PHY. There will be no quiet or refreshes during this condition.

SuggestedRemedy

Remove the paragraph, "If EEE is not supported, then LP_IDLE isn't a valid control character."

Response Response Status C

ACCEPT IN PRINCIPLE.

Change

"If EEE is not supported, then LP_IDLE isn't a valid control character."

to

"If EEE is not supported, then LP_IDLE shall be converted to IDLE."

Cl 97 SC 97.3.2.3 P 48 L 35 # 280
 Regev, Alon Ixia

Comment Type T Comment Status A

The signal indicating transitions to/from LPI rx mode is PMA_PCS_RX_LPI_STATUS.request(rx_lpi_active) which is defined in 97.2.2.9.

SuggestedRemedy

Change "97.3.9" to "97.2.2.9"

Response Response Status C

ACCEPT IN PRINCIPLE.

See comment #302

Cl 97 SC 97.3.2.3 P 48 L 35 # 201
 Jim, Graba Broadcom Corporation

Comment Type ER Comment Status A

Reference to non-existent subclause. The transition indication is described in the following paragraph so there is no need to reference a subclause.

SuggestedRemedy

Strike "using signals defined in 97.3.9"

Response Response Status C

ACCEPT IN PRINCIPLE.

See comment #302.

Cl 97 SC 97.3.2.3 P 48 L 35 # 302
 McClellan, Brett Marvell

Comment Type T Comment Status A

wrong cross reference

SuggestedRemedy

change 97.3.9 to 97.3.6

Response Response Status C

ACCEPT.

CI 97 SC 97.3.2.3.1 P 48 L 50 # 254
 Regev, Alon Ixia

Comment Type T Comment Status A

The paragraph describing Rx PCS Frame and block synchronization is unclear. It is unclear what "normal" mode is, when it is entered, and when synchronization occurs.

SuggestedRemedy

Replace

"When the receive channel is operating in normal mode, the frame and block synchronization function receives data via PAM3 PMA_UNITDATA.request primitive. It shall form a PAM3 stream from the primitive by concatenating requests in order from rx_data<0> to rx_data<2699> (see Figure 97-4). It obtains block_lock to the RS frames during the PAM2 training pattern using synchronization bits provided in the training sequence. The 81-bit blocks are extracted based on their location in the RS frame."

With

"Block and frame lock begins when the PMA PHY control is in the TRAINING state and the PMA has set loc_rcvr_status to OK, signaling reliable operation of the receive link for the local PHY and reliable acquisition of the descrambler state. Block lock is obtained by locking to inverted bit pattern that occurs in the first bit of partial RS FEC frames (180 bits) and signaling the lock by asserting block_lock. Frame lock uses the location of the InfoField which is found in the first 96 bits of the last (15th) partial RS FEC frame in each block as well as the partial frame count (PFC24) found in each InfoFrame to lock to the RS FEC frames. See 97.4.2.5 for details about this process.

Once block and frame locking has occurred and the link partner has transitioned from transmitting PAM2 to PAM3, the PCS Frame and block synchronization receives data via the PMA PMA_UNITDATA.request primitive and forms a stream from the primitive by concatenating requests in order from rx_data<0> to rx_data<2699> (see Figure 97-4) using the frame & block locks previously obtained. The 81-bit blocks are extracted based on their location in the RS frame."

Response Response Status C

ACCEPT IN PRINCIPLE.

On Page 48, Line 52:

Replace

"It obtains block_lock to the RS frames during the PAM2 training pattern using synchronization bits provided in the training sequence. The 81-bit blocks are extracted based on their location in the RS frame."

With

"It obtains block lock to the RS frames during the PAM2 training pattern using synchronization bits provided in the training sequence."

On page 48, line 28:

Change

"The PMA training sequence includes 1 bit pattern every 180 PAM2 symbols, which is aligned with the PCS Partial RS frame boundary. When the PCS Synchronization process is synchronized to this pattern, block_lock is asserted."

To

"The PMA training sequence includes 1 bit pattern every 180 PAM2 symbols, which is aligned with the PCS Partial RS frame boundary, as well as an InfoField which is inserted in the 15th PCS Partial RS frame. When the PCS Synchronization process is synchronized to the RS frame boundary using this pattern, block_lock is asserted."

On page 48, line 50:

Change

"When the receive channel is operating in normal mode,"

to

"When the receive channel is operating in data mode,"

CI 97 SC 97.3.2.3.1 P 48 L 51 # 277
 Regev, Alon Ixia

Comment Type T Comment Status A

as this is the Rx path, "PMA_UNITDATA.request" is wrong. It should be "PMA_UNITDATA.indication"

SuggestedRemedy

Change "PMA_UNITDATA.request" to "PMA_UNITDATA.indication"

Response Response Status C

ACCEPT IN PRINCIPLE.

See comment #254

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 97 SC 97.3.3 P 49 L 16 # 215
 Tu, Mike Broadcom

Comment Type ER Comment Status A

Test mode 7 is defined in sub-clause 97.5.2, instead of 97.5.4.

SuggestedRemedy

Change end of line 16 from

"This mode is further described as test mode 7 in 97.5.4."

to

"This mode is further described as test mode 7 in 97.5.2."

Response Response Status C
 ACCEPT.

CI 97 SC 97.3.3 P 49 L 16 # 255
 Regev, Alon Ixia

Comment Type T Comment Status A

Test mode 7 is described in subclause 97.5.2 (not 97.5.4)

SuggestedRemedy

change "97.5.4" to "97.5.2"

Response Response Status C
 ACCEPT.

See comment #215

CI 97 SC 97.3.4 P 50 L 6 # 184
 Remein, Duane Huawei

Comment Type ER Comment Status A

Figure 97-9 difficult to read due to small size, there is no need for this small font size. IEEE Style Manual requires a font size of 8 pt min (Table 1), 6 pt. is allowed in figures but text should then be all caps (see Figure 1).

This also applies to the following figures:

Figure 97-20, Figure 97-36, Figure 97-38, Figure 97-39, Figure 97-40, Figure 98-3, Figure 98-7, Figure 98-11, Figure 98-12, Figure 98-13, Figure 98-14, Figure 97A-1, Figure 97A-2, Figure 97B-1 and possibly others.

Editor may also want to check equations (free standing Eq should use FrameMaker Med sized eq.)

SuggestedRemedy

Enlarge the figures so the min. font size is maintained.

Response Response Status C
 ACCEPT IN PRINCIPLE.

Most figures are still in a state of flux and come from different sources, making it hard to control font size.

CI 97 SC 97.3.4 P 50 L 6 # 183
 Remein, Duane Huawei

Comment Type E Comment Status A

There appears to be some stray text in the Figure 97-9 title (Scrn)

SuggestedRemedy

Remove stray text

Response Response Status C
 ACCEPT.

CI 97 SC 97.3.4.1 P 11 L 9 # 329
 Brown, Thomas Vitesse Semiconducto

Comment Type ER Comment Status A

The table on contents at line 9: Generation of San

SuggestedRemedy

Change to:

Generation of Sn

Response Response Status C
 ACCEPT IN PRINCIPLE.
 Update TOC

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 SC 97.3.4.3 P 50 L 43 # 209
 Tu, Mike Broadcom

Comment Type E Comment Status A
 The polynomials have been defined in 97.3.4. Perhaps it is better to refer to Equation 97-5 and 97-6.

SuggestedRemedy
 Change line 43 and 44 from

"the MASTER PHY shall employ the receiver descrambler generator polynomial $g^M(x)=1+x^{20}+x^{33}$ and the SLAVE PHY shall employ the receiver descrambler generator polynomial $g^S(x)=1+x^{13}+x^{33}$."

to

"the MASTER PHY shall employ the receiver descrambler generator polynomial same as Equation 97-6 and the SLAVE PHY shall employ the receiver descrambler generator polynomial same as Equation 97-5."

Response Response Status C
 ACCEPT.

Cl 97 SC 97.3.5.2 P 52 L 22 # 203
 Jim, Graba Broadcom Corporation

Comment Type T Comment Status A
 This line refers to "transmitters". This clause requires only one transmitter.

SuggestedRemedy
 Change transmitters to transmitter.

Response Response Status C
 ACCEPT.

Cl 97 SC 97.3.5.3 P 52 L 33 # 202
 Jim, Graba Broadcom Corporation

Comment Type ER Comment Status A
 The OAM position is described twice.

SuggestedRemedy
 Delete the paragraph that begins on line 33.

Response Response Status C
 ACCEPT.

Cl 97 SC 97.3.5.3 P 52 L 33 # 278
 Regev, Alon Ixia

Comment Type E Comment Status A
 The paragraph "The OAM symbol is XOR'ed with the scrambler stream at the same relative position to the RS boundaries as it occupies during normal mode." seems to repeat a subset of the information contained in the following paragraph and can be deleted.

SuggestedRemedy
 Delete the paragraph "The OAM symbol is XOR'ed with the scrambler stream at the same relative position to the RS boundaries as it occupies during normal mode."

Response Response Status C
 ACCEPT.

See comment #202

Cl 97 SC 97.3.6.2.4 P 55 L 7 # 252
 Regev, Alon Ixia

Comment Type T Comment Status A
 "DECODE(rx_symb_vector<81:0>)" shoud be "DECODE(rx_coded<81:0>)"

SuggestedRemedy
 change "DECODE(rx_symb_vector<81:0>)" to "DECODE(rx_coded<81:0>)"

Response Response Status C
 ACCEPT.

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 97 SC 97.4.1 P 60 L 5 # 239
 Regev, Alon Ixia

Comment Type E Comment Status A

The PMA functional specifications still contains "(TBD)" and "(to be confirmed)" text, but these are not needed (as the referenced text is provided and correct).

SuggestedRemedy

Replace
 "The PMA couples messages from a PMA service interface specified in 97.2.2 (TBD) to the 1000BASE-T1 baseband medium, specified in 97.5 (to be confirmed).

The interface between PMA and the baseband medium is the Medium Dependent Interface (MDI), which is specified in 97.8 (TBD)."

With
 "The PMA couples messages from a PMA service interface specified in 97.2.2 to the 1000BASE-T1 baseband medium, specified in 97.5.

The interface between PMA and the baseband medium is the Medium Dependent Interface (MDI), which is specified in 97.8."

Response Response Status C

ACCEPT IN PRINCIPLE.

See comment #295

CI 97 SC 97.4.1 P 60 L 5 # 295
 McClellan, Brett Marvell

Comment Type E Comment Status A

Cross references are correct

SuggestedRemedy

delete "TBD" on line 5, "to be confirmed" on line 6, and "TBD" on line 9

Response Response Status C

ACCEPT.

CI 97 SC 97.4.2 P 67 L 51 # 305
 McClellan, Brett Marvell

Comment Type T Comment Status A

In November, the task force adopted a EEE refresh monitor.
 "The receiver shall force a retrain if Refresh is unreliably detected within a moving window of 50 Q/R cycles (4.32ms)."
 But there is no text for this item.

SuggestedRemedy

Add a new section prior to 97.4.2.7 Clock Recovery function.
 "97.4.2.7 Refresh Monitor function
 The Refresh monitor is required for PHYs that support the EEE capability. The Refresh monitor operates when the PHY is in the LPI receive mode. The receiver shall force a retrain if Refresh is unreliably detected within a moving window of 50 Q/R cycles (4.32ms)."

Response Response Status C

ACCEPT IN PRINCIPLE.

With extra emphasis on first statement being an optional requirement

Add a new section prior to 97.4.2.7 Clock Recovery function.
 "97.4.2.7 Refresh Monitor function
 A 1000BASE-T1 PHY supporting the EEE capability shall implement the Refresh monitor function. The Refresh monitor operates when the PHY is in the LPI receive mode. The receiver shall force a retrain if Refresh is unreliably detected within a moving window of 50 Q/R cycles (4.32ms)."

CI 97 SC 97.4.2.1 P 61 L 9 # 303
 McClellan, Brett Marvell

Comment Type T Comment Status A

wrong cross reference

SuggestedRemedy

change 97.3.6.2.2 to to 98.5.1

Response Response Status C

ACCEPT.

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 SC 97.4.2.2 P 61 L 24 # 296
 McClellan, Brett Marvell

Comment Type E Comment Status A
 cross reference to 97.5.3.3 is correct

SuggestedRemedy
 delete TBD on line 24 and 27.

Response Response Status C
 ACCEPT IN PRINCIPLE.
 delete TBD on line 24 and 27 and insert line cross-references

Cl 97 SC 97.4.2.2 P 61 L 25 # 276
 Regev, Alon Ixia

Comment Type E Comment Status A
 "MASTER/SLAVE" should be "MASTER-SLAVE"

SuggestedRemedy
 change "MASTER/SLAVE" to "MASTER-SLAVE"

Response Response Status C
 ACCEPT.

Cl 97 SC 97.4.2.5 P 62 L 51 # 304
 McClellan, Brett Marvell

Comment Type T Comment Status A
 wrong cross reference

SuggestedRemedy
 Page 62 line 51:change "Figure 97-18" to "Figure 97-20"
 Page 63 line 1: change "Figure 97-18" to "Figure 97-20"

Response Response Status C
 ACCEPT.

Cl 97 SC 97.4.2.5 P 63 L 9 # 210
 Tu, Mike Broadcom

Comment Type E Comment Status A
 Remove informative comments (<1msec) on line 9.

SuggestedRemedy
 Remove informative comments "<1msec)" on line 9.

Response Response Status C
 ACCEPT.

Cl 97 SC 97.4.2.5.10 P 67 L 20 # 288
 Lo, William Marvell Semiconducto

Comment Type TR Comment Status A
 Section needs new table after register movement

SuggestedRemedy
 Remove table 97-9 as that is moved per Lo_McClellan_3bp_01a_0315.pdf page 4.
 Insert new table as 97-9 as sentence as shown in Lo_McClellan_3bp_01a_0315.pdf page 6

Response Response Status C
 ACCEPT IN PRINCIPLE.

Implement comment #286 that takes care of these changes as well.

Cl 97 SC 97.4.2.5.10 P 67 L 20 # 218
 Tu, Mike Broadcom

Comment Type ER Comment Status A
 Name of the table is incorrect. It should be "Link Partner Training Registers" as shown in page 9 of "tu_3bp_01a_0215.pdf".

Also there is a missing table for "Training Registers". See page 8 of "tu_3bp_01a_0215.pdf".

SuggestedRemedy
 1. Change line 20 to "Table 97-xx -- Link Partner Training Registers".
 2. Add a new table based on page 8 of "tu_3bp_01a_0215.pdf".

Response Response Status C
 ACCEPT IN PRINCIPLE.

Implement change 1

Change 2 is taken care of in comment #286

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 97 SC 97.4.2.5.5 P 65 L 12 # 216
 Tu, Mike Broadcom

Comment Type ER Comment Status A
 There is a typo. "SO (sent last)" should be "S0 (sent last)". Change capital character "O" to number "0".

SuggestedRemedy
 Change line 12 from
 "...contains bits S14 (sent first) to SO (sent last) to..."
 to
 "...contains bits S14 (sent first) to S0 (sent last) to..."

Response Response Status C
 ACCEPT.

CI 97 SC 97.4.2.5.5 P 65 L 14 # 234
 Tu, Mike Broadcom

Comment Type TR Comment Status A
 The scrambler is shown in Figure 97-8, instead of Figure 97-7.

SuggestedRemedy
 Change line 14 from
 "state of the scrambler in Figure 97-7 shall be S14:S0..."
 to
 "state of the scrambler in Figure 97-8 shall be S14:S0..."

Response Response Status C
 ACCEPT.

Make sure that the link is live (now it is just text)

CI 97 SC 97.4.2.5.5 P 65 L 15 # 235
 Tu, Mike Broadcom

Comment Type TR Comment Status A
 The data mode scrambler starts when the partial frame counter equals to the received DataSwPFC24. The original text saying it starts when DataSwPFC24=0 is incorrect.

SuggestedRemedy
 Change line 15 from
 "...DataSwPFC24 = 0, see 97.4.2.5.6."
 to
 "...the partial frame counter equals to the DataSwPFC24 value, see 97.4.2.5.6".

Response Response Status C
 ACCEPT.

CI 97 SC 97.4.2.5.5 P 65 L 18 # 217
 Tu, Mike Broadcom

Comment Type ER Comment Status A
 There is a typo. "0ct" should be "Oct". Change number "0" to capital character "O".

SuggestedRemedy
 Change line 18 from
 "The remaining 7-bit 0ct10<7:1> shall be user configurable register."
 to
 "The remaining 7-bit Oct10<7:1> shall be user configurable register."

Response Response Status C
 ACCEPT.

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 **SC 97.4.2.5.5** **P 65** **L 18** # **292**
 Lo, William Marvell Semiconducto

Comment Type **T** **Comment Status** **A**
 Red highlight to 97.4.2.5.10 is correct.

SuggestedRemedy
 Remove highlight
 New text in Lo_McClellan_3bp_01a_0315.pdf in particular page 6 make this ok.

Response **Response Status** **C**
 ACCEPT.
 This will be updated once Clause 45 registers are placed in the draft

Cl 97 **SC 97.4.2.5.8** **P 65** **L 48** # **237**
 Steven, Chen Broadcom

Comment Type **TR** **Comment Status** **A**
 In Figure 97-16, the Auto-Negotiation Page Data does not apply here.

SuggestedRemedy
 In Figure 97-16, replace "Auto-Negotiation Page Data" with "Oct4 through Oct10".

Response **Response Status** **C**
 ACCEPT.

Cl 97 **SC 97.4.4.1** **P 69** **L 44** # **246**
 Regev, Alon Ixia

Comment Type **E** **Comment Status** **A**
 Make it clear that rem_rcvr_status shall be set to NOT_OK if the PCS has not decoded a valid InfoField from the remote PHY.

SuggestedRemedy
 Replace
 "This variable is received in the loc_rcvr_status bit in the InfoField from the remote PHY."

 With
 "This variable is received in the loc_rcvr_status bit in the InfoField from the remote PHY.
 This variable is set to NOT_OK if the PCS has not decoded a valid InfoField from the remote PHY."

Response **Response Status** **C**
 ACCEPT.

 Note this is a technical comment!

Cl 97 **SC 97.4.4.1** **P 69** **L 54** # **219**
 Tu, Mike Broadcom

Comment Type **ER** **Comment Status** **R**
 SEND_I is no longer defined in 1000BASE-T1.

SuggestedRemedy
 Remove line 54 "SEND_I" and the descriptions on line 54 of page 69, and line 1 on page 70.

Response **Response Status** **C**
 REJECT.

 See comment #213

Cl 97 **SC 97.5.2** **P 73** **L 6** # **293**
 Lo, William Marvell Semiconducto

Comment Type **T** **Comment Status** **A**
 Need to specify register location

SuggestedRemedy
 Change
 3-bit control register
 to
 3-bit control in register 1.2308.15:13

 The detailed text is already incorporated in
 Lo_McClellan_3bp_01a_0315.pdf page 5

Response **Response Status** **C**
 ACCEPT IN PRINCIPLE.

 Change
 3-bit control register
 to
 control register 1.2308.15:13

 The detailed text is already incorporated in
 Lo_McClellan_3bp_01a_0315.pdf page 5

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 **SC 97.5.2** **P 73** **L 6** # **307**
 McClellan, Brett Marvell
Comment Type **T** **Comment Status** **A**
 doesn't specify which register controls the test modes
SuggestedRemedy
 change "setting a 3-bit control register"
 to "setting 1.2308.15:13" per the proposal in Lo_McClellan_3bp_01a_0315.pdf
Response **Response Status** **C**
 ACCEPT IN PRINCIPLE.

 change "setting a 3-bit control register"
 to "setting the control register 1.2308.15:13" per the proposal in
 Lo_McClellan_3bp_01a_0315.pdf

Cl 97 **SC 97.5.2** **P 74** **L 53** # **257**
 Regev, Alon Ixia
Comment Type **T** **Comment Status** **A**
 There is a disagreement between the description of test mode 5 in table 79-10 where it states "normal operation in Idle mode" and the description on page 74, line 53, where it states "with data set to zero".

 "Idle mode" implies that you are transmitting an idle or sequence (a sequence of "normal Inter-Frame" control codes).

 "data set to zero" implies that the the input to the PCS is valid zero data (so the encoded 81B data would be all zeroes)
SuggestedRemedy
 change "with data set to zero" to "with data set to normal Inter-Frame idle signals"
Response **Response Status** **C**
 ACCEPT.

Cl 97 **SC 97.5.2** **P 75** **L 9** # **327**
 Brown, Thomas Vitesse Semiconducto
Comment Type **ER** **Comment Status** **A**
 The phrase, "Any no zero data"

 Should be "Any non zero"
SuggestedRemedy
 Change "Any no zero" to "Any non zero"
Response **Response Status** **C**
 ACCEPT IN PRINCIPLE.

 Change "Any no zero" to "Any non-zero"

Cl 97 **SC 97.5.3.1** **P 77** **L 24** # **197**
 Chini, Ahmad Broadcom
Comment Type **TR** **Comment Status** **A**
 The droop requirement does not match MDI RL requirement.
SuggestedRemedy
 Change the requirement to "less than 10%"
Response **Response Status** **C**
 ACCEPT.

Cl 97 **SC 97.5.3.3** **P 79** **L 24** # **195**
 Chini, Ahmad Broadcom
Comment Type **ER** **Comment Status** **A**
 There are two closed paranthesis used.
SuggestedRemedy
 Remove the extra paranthesis (also in line 29)
Response **Response Status** **C**
 ACCEPT.

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 **SC 97.5.3.3** **P 79** **L 29** # **196**
 Chini, Ahmad Broadcom

Comment Type **TR** **Comment Status** **A**
 Lower PSD limit defined for frequencies above 40MHz does not match MDI RL requirement

SuggestedRemedy
 Modify Equation (97-13) to start from 10MHz. Also modify Figure 97-28 to reflect the same.

Response **Response Status** **C**
 ACCEPT IN PRINCIPLE.
 Modify Equation (97-13) to start from 10MHz.
 Use updated Figure 97-28 per
http://www.ieee802.org/3/bp/public/mar15/chini_3bp_01_0315.pdf

Cl 97 **SC 97.5.6.2** **P 83** **L 45** # **312**
 DiMinico, Christopher MC Communications

Comment Type **T** **Comment Status** **A**
 incorrect equation reference. Remove equation TBD. TBD was provided to ensure comment review of equation. No changes requested in ballot cycles.

SuggestedRemedy
 (1)Correct equation reference (97-17). (2)Remove TBD. TBD was provided to ensure comment review of equation. No changes requested in ballot cycle.

Response **Response Status** **C**
 ACCEPT.

Cl 97 **SC 97.5.6.2.2** **P 84** **L 40** # **313**
 DiMinico, Christopher MC Communications

Comment Type **T** **Comment Status** **A**
 Remove TBD. TBD was provided to ensure comment review of equation. No changes requested in ballot cycles.

SuggestedRemedy
 Remove TBD. TBD was provided to ensure comment review of equation. No changes requested in ballot cycles.

Response **Response Status** **C**
 ACCEPT.

Cl 97 **SC 97.5.6.2.4** **P 85** **L 25** # **194**
 Mitsuru, Iwaoka Yokogawa Electric Cor

Comment Type **T** **Comment Status** **A**
 Test method for coupling attenuation is not specified.

SuggestedRemedy
 1) Add the following two documents to the 1.3 Normative references.

 IEC 62153-4-14:2012, Metallic communication cable test methods - Part 4-14: Electromagnetic compatibility (EMC) - Coupling attenuation of cable assemblies (Field conditions) absorbing clamp method

 2) Insert the following text at the end of 97.5.6.2.4
 The coupling attenuation is tested as specified in IEC 62153-4-14.

Response **Response Status** **C**
 ACCEPT.

Cl 97 **SC 97.5.6.2.4** **P 85** **L 34** # **314**
 DiMinico, Christopher MC Communications

Comment Type **T** **Comment Status** **A**
 Currently no automotive applications characterized for E4.

SuggestedRemedy
 Remove column E4 in Table 97-12—Coupling attenuation Type B link segment and in Table 97-13—Electromagnetic classifications Type B link segment

Response **Response Status** **C**
 ACCEPT.

Cl 97 **SC 97.5.6.3.1** **P 86** **L 12** # **315**
 DiMinico, Christopher MC Communications

Comment Type **T** **Comment Status** **A**
 Stated 802.3bp objective includes "Maintain a bit error ratio (BER) of less than or equal to 10^-10 at the MAC/PLS service interface"

SuggestedRemedy
 Remove "specified in TBD".

Response **Response Status** **C**
 ACCEPT.

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 **SC 97.5.6.3.3** **P 87** **L 26** # **316**
 DiMinico, Christopher MC Communications
Comment Type T **Comment Status A**
 Stated 802.3bp objective includes "Maintain a bit error ratio (BER) of less than or equal to 10⁻¹⁰ at the MAC/PLS service interface"
SuggestedRemedy
 Remove "specified in TBD"
Response **Response Status C**
 ACCEPT.

Cl 97 **SC 97.5.6.4.1** **P 88** **L 38** # **310**
 DiMinico, Christopher MC Communications
Comment Type T **Comment Status A**
 Stated 802.3bp objective includes "Maintain a bit error ratio (BER) of less than or equal to 10⁻¹⁰ at the MAC/PLS service interface"
SuggestedRemedy
 Remove "specified in TBD"
Response **Response Status C**
 ACCEPT.

Cl 97 **SC 97.5.6.4.3** **P 89** **L 14** # **311**
 DiMinico, Christopher MC Communications
Comment Type T **Comment Status A**
 Stated 802.3bp objective includes "Maintain a bit error ratio (BER) of less than or equal to 10⁻¹⁰ at the MAC/PLS service interface"
SuggestedRemedy
 Remove "specified in TBD"
Response **Response Status C**
 ACCEPT.

Cl 97 **SC 97.5.6.4.3** **P 89** **L 32** # **317**
 DiMinico, Christopher MC Communications
Comment Type T **Comment Status A**
 Remove TBD's. TBDs were provided to ensure comment review of equation. No changes requested in ballot cycles.
SuggestedRemedy
 Remove the three TBDs
Response **Response Status C**
 ACCEPT.

Cl 97 **SC 97.6.1.1** **P 90** **L 25** # **285**
 Lo, William Marvell Semiconducto
Comment Type T **Comment Status A**
 Tighten up send_s_sigdet
SuggestedRemedy
 Add the following sentence.
 This variable shall be set FALSE no later than 400ns after the signal goes quiet on the MDI.
Response **Response Status C**
 ACCEPT IN PRINCIPLE.

Add the following sentence.
 This variable shall be set FALSE no later than 1 us after the signal goes quiet on the MDI.

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

CI 97 SC 97.6.1.1 P 90 L 31 # 306
 McClellan, Brett Marvell

Comment Type T Comment Status A

SEND_S is used within the PHY Link Synchronization state machines, but the SEND_S signal is supposedly generated by the PCS.
 Nowhere in the PCS text is there any definition for the SEND_S signal. Further, the PMA_TXMODE.indication (tx_mode) primitive definition in 97.2.2.1.1 does not include SEND_S as a defined value.

SuggestedRemedy

In 97.2.2.1.1 add this definition
 SEND_S: This value is continuously asserted for transmission of 255 PN sequences generated by: $x^8+x^4+x^3+x^2+1$ for Master and $x^8+x^6+x^5+x^4+1$ for Slave.

We need a text contribution to define SEND_S signaling within the PCS.

Response Response Status C

ACCEPT IN PRINCIPLE.

Replace text in 97.6, and 97.6.1.1 with text included in "McClellan_3bp_01b_0315_SEND_S_text_proposal.pdf".

Make sure that 400ns in send_s_sigdet is changed to 1 us

Make changes in 97.6.2: Change instances of "tx_mode" to "sync_tx_mode"

CI 97 SC 97.6.1.1 P 90 L 33 # 297
 McClellan, Brett Marvell

Comment Type E Comment Status A

grammar

SuggestedRemedy

change "This value is continuously asserted when transmission" to "This value is continuously asserted for transmission"

Response Response Status C

ACCEPT.

CI 97 SC 97.6.1.1 P 90 L 6 # 287
 Lo, William Marvell Semiconducto

Comment Type TR Comment Status A

config referenced to wrong section

SuggestedRemedy

change 98.5.1 to 97.4.4.1

Response Response Status C

ACCEPT.

CI 97 SC 97.7 P 91 L 34 # 289
 Lo, William Marvell Semiconducto

Comment Type TR Comment Status A

- OAM register reference changes
- Replace all TBDs with actual register addresses
 - Move registers to clause 45
 - Update all OAM register references to clause 45

SuggestedRemedy

See Lo_McClellan_3bp_01a_0315.pdf page 10 for editing instructions

Response Response Status C

ACCEPT.

CI 97 SC 97.7.1 P 92 L 1 # 193
 Mitsuru, Iwaoka Yokogawa Electric Cor

Comment Type T Comment Status A

In 97.1.1 (Definitions), a term "OAM symbol" is defined. However, other terms "OAM9 symbol" and "OAM frame symbol" are used to specify same thing. They should be unified.

SuggestedRemedy

Replace "OAM9 symbol" and "OAM frame symbol" with "OAM symbol" throughout the draft.
 Replace "OAM9" with "OAM" in Figure 97-3, 97-4, and 97-5.
 Replace "OAM9" with "OAM symbol" in 97.3.5.3.

Response Response Status C

ACCEPT IN PRINCIPLE.

See comment #186 for some of changes needed. Change also all instances of "OAM frame symbol" with "OAM symbol"

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl 97 **SC 97.7.2.2.3** **P 93** **L 25** # **326**
 Brown, Thomas Vitesse Semiconducto
Comment Type **T** **Comment Status** **A**
 re-link with in 2 to 4 ms
SuggestedRemedy
 change with in to within
Response **Response Status** **C**
 ACCEPT.

Cl 97 **SC 97.7.3.1.2** **P 98** **L 48** # **264**
 Regev, Alon Ixia
Comment Type **E** **Comment Status** **A**
 "byte" should be "octet"
SuggestedRemedy
 change all occurrences of "byte" to "octet" in the draft
Response **Response Status** **C**
 ACCEPT.

Cl 97 **SC 97.8.2.1** **P 107** **L 46** # **328**
 Brown, Thomas Vitesse Semiconducto
Comment Type **ER** **Comment Status** **A**
 characteristic impedance of 100 Q
SuggestedRemedy
 replace with
 characteristic impedance of 100 Ohms
Response **Response Status** **C**
 ACCEPT.

Cl 97 **SC Figure 97-2** **P 38** **L 42** # **198**
 Jim, Graba Broadcom Corporation
Comment Type **E** **Comment Status** **R**
 The optional quality of rx_lpi_active isn't explained.
SuggestedRemedy
 Place a note in this figure saying:
 rx_lpi_active is only required for the EEE capability.
Response **Response Status** **C**
 REJECT.

The dashed box around this signal already implies the very same thing. This is a markup typical for any signals required by operational EEE capability.

Cl 97 **SC Table 97-1** **P 43** **L 47** # **199**
 Jim, Graba Broadcom Corporation
Comment Type **E** **Comment Status** **A**
 The row starting with 101 is italicized.
SuggestedRemedy
 Change the row's font to be the same style as the other entries in the table.
Response **Response Status** **C**
 ACCEPT.
 See comment #269

Cl 97 **SC Table 97-4** **P 52** **L 14** # **200**
 Jim, Graba Broadcom Corporation
Comment Type **E** **Comment Status** **A**
 Constant is on the left side of the equation while the other entries in this table and Table 97-3 have them on the right side of the equation.
SuggestedRemedy
 Change
 lpi_quiet_time <= mod(v, lpi_qr_time)
 to
 mod(v, lpi_qr_time) => lpi_quiet_time
Response **Response Status** **C**
 ACCEPT.
 This change has questionable value

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl **97.10** SC **97.10.1** P **108** L **50** # **192**
 Matola, Larry Delphi

Comment Type **TR** Comment Status **A**
 Proposed baseline text for section 97.10.1 General Safety

SuggestedRemedy

97.10.1General Safety
 Motor vehicle equipment implementations in this clause shall conform to all applicable local or national motor vehicle standards or as agreed to between the customer and supplier All equipment subject to this clause that is not used in automotive applications shall conform to IEC 60950-1 for IT applications, or for-non IT applications, the relevant local or national codes.

Response Response Status **C**
 ACCEPT IN PRINCIPLE.

Use hajduczenia_3bp_01_0315.pdf

Cl **97.10** SC **97.10.2** P **109** L **1** # **187**
 Matola, Larry Delphi

Comment Type **TR** Comment Status **A**
 Baseline text for section 97.10.2 Network Safety

SuggestedRemedy

97.10.2Network Safety
 All cabling and equipment shall be installed in a workman like manor, mechanically and electrically secure. The designer is urged to consult the relevant local, national, and international safety regulations to ensure compliance with appropriate requirements. In automotive applications all cabling shall be routed to provide maximum protection by the vehicle sheet metal and structural components. As an example SAE J1292, Automobile, Truck-Tractor, Trailer, and Motor Coach Wiring, can be referred to for general recommendations and guidelines. Several other documents may also be considered as providing motor vehicle guidance, e.g. ISO 14229 Road Vehicles-Unified Diagnostic Services and ISO 15764 Road Vehicles-Extended data Link Security.

Response Response Status **C**
 ACCEPT IN PRINCIPLE.

Use hajduczenia_3bp_01_0315.pdf

Cl **97.10** SC **97.10.3** P **109** L **5** # **188**
 Matola, Larry Delphi

Comment Type **TR** Comment Status **A**
 Proposed baseline text for subclause 97.10.3.1

SuggestedRemedy

97.10.3.1 Environmental Stresses
 The 1000BASE T-1 PHY was originally designed to operate in the automotive environment. All equipment in this clause shall conform to the potential environmental stresses described in ISO 16750 with respect to their mounting location or as agreed to between the customer and supplier. ISO 16750 is a 5-part specification with the Environmental loads defined as follows:

- ? Part 1: General
- ? Part 2: Electrical loads
- ? Part 3: Mechanical loads
- ? Part 4: Climatic loads
- ? Part 5: Chemical loads

Automotive environmental conditions are generally more severe than those found in many commercial environments. The targeted application environment(s) require careful analysis prior to implementation.

Response Response Status **C**
 ACCEPT IN PRINCIPLE.

Use hajduczenia_3bp_01_0315.pdf

Cl **97.10** SC **97.10.3** P **109** L **5** # **189**
 Matola, Larry Delphi

Comment Type **TR** Comment Status **A**
 Proposed baseline text for section 97.10.3.2

SuggestedRemedy

97.10.3.2 Electromagnetic Compatibility
 A system integrating the 1000BASE T-1 PHY shall comply with all applicable local and national codes, or as agreed to between the customer and supplier, for the limitation of electromagnetic interference. CISPR 25 test methods have been defined to measure the EMC cperformance of the PHY in terms of RF immunity and RF emission. Generally, motor vehicle EMC requirements are defined by CISPER 25 (radiated Emissions) and ISO 11452 (Radiated Immunity); however, exact test setup and test limit values may be adapted by each customer.

Response Response Status **C**
 ACCEPT IN PRINCIPLE.

Use hajduczenia_3bp_01_0315.pdf

Approved Responses

IEEE P802.3bp D1.3 1000BASE-T1 PHY 4th Task Force review comments

Cl **97.8.** SC **97.8.2.3** P **108** L **17** # **190**
 Matola, Larry Delphi

Comment Type **TR** Comment Status **A**

Short circuits of any wire to any wire...
 Vehicles can be subjected to the connection of a reversed battery when an auxiliary starting device is used. It is routine in some areas to use + 24 volts in these devices. With the advent of 42 volt electrical systems in the near future +/-50 volts is not an unlikely scenario.

SuggestedRemedy

Revise up to 50 V to +/-50 V

Response Response Status **C**

ACCEPT.

Cl **97A** SC **97A.2** P **141** L **19** # **318**
 DiMinico, Christopher MC Communications

Comment Type **T** Comment Status **A**

Remove and replace TBDs in subclause 97A.2.

SuggestedRemedy

Delete: (TBD length) in "The 1000BASE-T1 link segment (TBD length)" two instances.
 Change: (1, 5, TBD) to 10 mm
 Change: (3, 15, TBD) at least 30 mm

Delete sentence: The test fixtures used in the measurement conform to the test fixture specifications in clause TBD.

Align figures with text revisions;
 Figure 97A-1—4-port test setup
 Figure 97A-2—3-port common mode conversion loss measurement
 Change distance to the edge of the GND plane from 200mm to >/= 30mm.
 Note 3 in both drawings should also change accordingly.
 Change distances between meanders to >/= 30mm.

Response Response Status **C**

ACCEPT.

Cl **97B** SC **97B.1.1** P **143** L **19** # **321**
 DiMinico, Christopher MC Communications

Comment Type **T** Comment Status **A**

In 97B.1.1 Alien crosstalk test configurations remove 3 TBDs

SuggestedRemedy

In 97B.1.1 Alien crosstalk test configurations remove 3 TBDs.

Response Response Status **C**

ACCEPT.

Cl **97B** SC **97B.1.1** P **143** L **25** # **319**
 DiMinico, Christopher MC Communications

Comment Type **T** Comment Status **A**

Remove TBD's. TBDs were provided to ensure comment review of equation. No changes requested in ballot cycles.

SuggestedRemedy

Remove three TBDs in 97B.1.1

Response Response Status **C**

ACCEPT.

See also comment #321

Cl **97B** SC **97B.3** P **144** L **35** # **320**
 DiMinico, Christopher MC Communications

Comment Type **T** Comment Status **A**

Remove TBD's. TBDs were provided to ensure comment review of equation. No changes requested in ballot cycles.

SuggestedRemedy

Remove 3 TBDs and in 97B.3 and Figure 97B-4—Cable bundle in 4-around-1 configuration

Response Response Status **C**

ACCEPT IN PRINCIPLE.

Remove TBDs in 97B.3
 TBD in Figure 97B-2 and Figure 97B-3 to be marked in RED - reference or numeric value is needed.
 Mark TBD in title of 97B-1 in RED - title is missing.

Cl **97B.1** SC **97B.1.1** P **143** L **25** # **191**
 Matola, Larry Delphi

Comment Type **TR** Comment Status **A**

Currently temperature and humidity have (TBD) next to the values in line 25. The values inline 25 are referenced in section 1 of ISO 16750 part 1 as general test conditions and can be found in section 7.2 of that document. Since that document is referenced in section 97.10 Environmental Conditions I propose removing TBDs.

SuggestedRemedy

Remove TBD and fix values.

Response Response Status **C**

ACCEPT.

See also comment #321

Cl **98** SC **98.1.2** P **115** L **10** # **258**
 Regev, Alon Ixia

Comment Type **T** Comment Status **A**

The draft states "PMD is not specified for 1000BASE-T1". This is not true. The PMD is defined in terms of electrical characteristics, EMC tests, etc.

SuggestedRemedy

Delete the line "PMD is not specified for 1000BASE-T1"

Response Response Status **C**

ACCEPT.

Cl **98** SC **98.2.1.1.3** P **118** L **36** # **291**
 Lo, William Marvell Semiconducto

Comment Type **TR** Comment Status **A**

The DME scheme has evolved and the text is no longer accurate.

SuggestedRemedy

- 1) Change heading from "Sync Header and Manchester violation delimiter" to "DME page Delimiters"
- 2) Remove yellow highlighting - text is correct.
- 3) Change "The page end is followed by a DME violation delimiter." to "The page end is followed by a dummy zero."
- 4) Change "A violation is signaled as shown in Figure 98-7." to "An example of the delimiters as shown in Figure 98-7".
- 5) Change figure 98-7 title to "DME Page"

Response Response Status **C**

ACCEPT IN PRINCIPLE.

- 1) Change heading from "Sync Header and Manchester violation delimiter" to "DME page Delimiters"
- 2) Remove yellow highlighting - text is correct.
- 3) Change "The page end is followed by a DME violation delimiter." to "The page end is followed by a dummy zero."
- 4) Change "A violation is signaled as shown in Figure 98-7." to "An example of the delimiters is shown in Figure 98-7."
- 5) Change figure 98-7 title to "DME Page"

