

33.2.8.5 Continuous output current capability in the POWER_ON state

For Type 1 and Type 2 PSEs, $I_{\text{Port-2P}}$ is defined in 33.1.32-5.4. For Type 3 and Type 4 PSEs, $I_{\text{Port-2P}}$ and $I_{\text{Port-2P-other}}$ are the currents on the pairs with the same polarity of the two pairsets and are defined in Equation (33–5) and in Equation (33–6).

$$I_{\text{Port-2P}} = \left\{ \begin{array}{l} I_{\text{Port-2P-pri}} \text{ for the Primary Alternative} \\ I_{\text{Port-2P-sec}} \text{ for the Secondary Alternative} \end{array} \right\}_A \quad (33-5)$$

$$I_{\text{Port-2P-other}} = \left\{ \begin{array}{l} I_{\text{Port-2P-sec}} \text{ for the Primary Alternative} \\ I_{\text{Port-2P-pri}} \text{ for the Secondary Alternative} \end{array} \right\}_A \quad (33-6)$$

where

$I_{\text{Port-2P-pri}}$ is the output current sourced by the Primary Alternative, defined in 33.2.5.9
 $I_{\text{Port-2P-sec}}$ is the output current sourced by the Secondary Alternative, defined in 33.2.5.9

I_{Port} is the total current on both pairs with the same polarity and is defined in Equation (33–7).

$$I_{\text{Port}} = \{I_{\text{Port-2P}} + I_{\text{Port-2P-other}}\}_A \quad (33-7)$$

PSEs shall be able to source $I_{\text{Con-2P}}$, the current the PSE supports on each powered pairset, as specified in Equation (33–8).

$$I_{\text{Con-2P}} = \left\{ \begin{array}{ll} P_{\text{Class}}/V_{\text{PSE}} & \text{when in 2-pair mode} \\ \min(I_{\text{Con}} - I_{\text{Port-2P-other}}, I_{\text{Con-2P-umb}}) & \text{when 4-pair powering a single-signature PD} \\ P_{\text{Class-2P}}/V_{\text{PSE}} & \text{when 4-pair powering a dual-signature PD} \end{array} \right\}_A \quad (33-8)$$

where

P_{Class} is P_{Class} as defined in [Equation \(33-2\)Table 33-13](#)
 $P_{\text{Class-2P}}$ is $P_{\text{Class-2P}}$ as defined in [Equation \(33-3\)Table 33-13](#)
 V_{PSE} is the voltage at the PSE PI as defined in 33.1.3
 I_{Con} is the total current a PSE is able to source as defined in Equation (33–9)
 $I_{\text{Con-2P-umb}}$ is the current a PSE is able to source on a pairset due to unbalance as defined in Table 33–18
 $I_{\text{Port-2P-other}}$ is the output current on the other pairset as defined in Equation (33–6).

~~$I_{\text{Con-2P}}$ is the current the PSE supports on each powered pairset and is defined by Equation (33–8). I_{Con} is the total current of both pairs with the same polarity that a Type 3 and Type 4 PSE supports, when powering a single-signature PD in 4-pair mode. I_{Con} is defined in Equation (33–9). $I_{\text{Con-2P-umb}}$ is the maximum current a Type 3 or Type 4 PSE supports over one of the pairs of same polarity under maximum unbalance condition (see 33.2.8.5.1) in the POWER_ON state, when powering a single-signature PD in 4-pair mode.~~

When powering a single-signature PD over 4 pairs, a Type 3 or Type 4 PSE supports:

- A total current of I_{Con} , defined in Equation (33–9), over both pairs with the same polarity

- A minimum current of $I_{\text{Con-2P-umb}}$ over one of the pairs of the same polarity under maximum unbalance condition (see 33.2.8.5.1) in the POWER ON state.

$$I_{\text{Con}} = \left\{ \frac{P_{\text{Class}}}{V_{\text{PSE}}} \right\}_A \quad (33-9)$$

The PSE shall support the AC current waveform parameter $I_{\text{Peak-2P}}$, defined in Equation (33-104), on each powered pairset while within the operating voltage range of $V_{\text{Port-PSE-2P}}$, for a minimum of $T_{\text{CUT-2P}}$ and a duty cycle of at least 5%.

$$I_{\text{Peak-2P}} = \left\{ \begin{array}{ll} I_{\text{Peak}} & \text{when in 2-pair mode} \\ \min(I_{\text{Peak}} - I_{\text{Port-2P-other}}, I_{\text{Peak-2P-umb}}) & \text{when 4-pair powering a single-signature PD} \\ \frac{V_{\text{PSE}} - \sqrt{V_{\text{PSE}}^2 - 4 \times R_{\text{Chan-2P}} \times P_{\text{Peak-PD-2P}}}}{2 \times R_{\text{Chan-2P}}} & \text{when 4-pair powering a dual-signature PD} \end{array} \right\}_A \quad (33-104)$$

where

- I_{Peak} is the total peak current of the powered pairs a PSE supports per Equation (33-~~1311~~)
- $I_{\text{Port-2P-other}}$ is the output current on the other pairset as defined in Equation (33-6).
- $I_{\text{Peak-2P-umb}}$ is the minimum current due to unbalance effects a PSE must support on a pairset as defined in Equation (33-~~1244~~).
- V_{PSE} is the voltage at the PSE PI as defined in 33.1.3
- $R_{\text{Chan-2P}}$ is the pairset loop resistance; this parameter has a worst-case value of R_{Ch} defined in 33.1.3. R_{Ch} is defined in Table 33-1.
- $P_{\text{Peak-PD-2P}}$ is the total peak power a dual-signature PD may draw per its Class on a pairset; see Table 33-30

I_{Peak} , defined in Equation (33-~~1011~~), is the total current of the powered both pairs with the same polarity that a PSE supports, as defined in Equation (33-10), when powering either in a PD over 2-pairs or 4-pair powering a single-signature PD over 4 pairs.

$$I_{\text{Peak}} = \left\{ \frac{V_{\text{PSE}} - \sqrt{V_{\text{PSE}}^2 - 4 \times R_{\text{Chan}} \times P_{\text{Peak-PD}}}}{2 \times R_{\text{Chan}}} \right\}_A \quad (33-~~1011~~)$$

where

- V_{PSE} is the voltage at the PSE PI as defined in 33.1.3
- R_{Chan} is the channel loop resistance as defined in 33.1.3
- $P_{\text{Peak-PD}}$ is the total peak power a PD may draw for its Class; see Table 33-30

$I_{\text{Peak-2P-umb}}$, defined in Equation (33-12), is the minimum current due to unbalance effects that a PSE supports on a pairset, as defined by Equation (33-11), when powering a single-signature PD over 4-pair.

$$I_{\text{Peak-2P-umb}} = \left\{ (1 + K_{I_{\text{Peak}}}) \times \frac{I_{\text{Peak}}}{2} \right\}_A$$

(33-~~1244~~)

where

KIPeak The value of KIPeak, defined in Equation (33-~~1342~~), is based on a curve fit and is dimensionless

IPeak is the total peak current a PSE supports per Equation (33-~~1140~~)

$$K_{I_{peak}} = \left\{ \begin{array}{ll} \min(0.214 \times (R_{chan-2P})^{-0.363}, 0.331) & \text{for Class 5} \\ \min(0.199 \times (R_{chan-2P})^{-0.350}, 0.304) & \text{for Class 6} \\ \min(0.180 \times (R_{chan-2P})^{-0.335}, 0.270) & \text{for Class 7} \\ \min(0.176 \times (R_{chan-2P})^{-0.347}, 0.260) & \text{for Class 8} \end{array} \right\} \quad (33-~~1342~~)$$

*Editing Instruction: Add new top row to KIpeak
Equation with values:
1 *Classes 0-4**

where

RChan-2P is the channel DC loop resistance per pairset, as defined in 33.1.3. RChan-2P has a minimum value of 0.2 Ω when used in Equation (33-~~1342~~).

~~The Alternatively, an over-margined worst case~~-value of IPeak-2P-unb_z ~~is~~ IPeak-2P-unb_{max} ~~which~~ is defined by Equation (33-~~1413~~). IPeak-2P-unb_{max} is used in <New Iunb section> to define Iunb for Type 3 and Type 4 PSEs.

$$I_{Peak-2P_unb_max} = \{I_{LIM-2P} - 0.002\}_A \quad (33-~~1413~~)$$

where

ILIM-2P is the ILIM-2P min value per pairset for the PSE, as defined in Table 33-18