

CI 149 SC 149.7.1.4 P172 L36 # 2

DiBiaso, Eric TE Connectivity

Comment Type T Comment Status A Coupling attenuation

The coupling attenuation equation (149-24) references Fmax (line 36 & 41) as its maximum Frequency. Fmax is defined as 4000 x S, where S equals 1/4, 1/2, or 1 corresponding to 2.5Gbps, 5.0Gbps, or 10Gbps, respectively. However, Figure 149-45 on page 173 plots the coupling attenuation showing a maximum frequency of 5500MHz.

SuggestedRemedy

Similar to the crosstalk limits in 149.7.2.1 & 149.7.2.2, I recommend replacing the 2 instances of Fmax with 4000MHz in the coupling attenuation equation.

Frequency limits of equation (149-24) would then be:

30 <= f <= 750 MHz
750 <= f <= 4000 MHz
where f is the frequency in MHz; 30 <= f <= 4000

Figure 149-45 should also be modified to show a max Frequency of 4000MHz instead of 5500MHz.

Response Response Status C

ACCEPT IN PRINCIPLE.

This comment does not apply to the substantive changes between IEEE P802.3ch D2.1 and D2.2 or the unsatisfied negative comments from earlier ballots. Hence it is not within the scope of the recirculation ballot.

However, the change suggested has identified an error in the draft, and the proposed response is a substantive change which fixes an inconsistency in the draft between the equations and the graph.

This also makes the maximum frequency of the coupling attenuation consistent with that of the coupling parameters between the link segments.

P172 L37 & P172 L41, Change "Fmax" to "4000"

P173 L3, Change Figure 149-45 to have a max frequency of 4000 MHz instead of 5500 MHz.

CI 45 SC 45.2.1.192.1 P35 L44 # 15

Tu, Mike Broadcom

Comment Type T Comment Status A EZ

Register bit 1.2309.15 is PMA/PMD reset. But this statement refers to 149.3.2.1, which is PCS reset.

SuggestedRemedy

On page 35, line 44, change the reference from 149.3.2.1 to 149.4.2.1.

Response Response Status C

ACCEPT.

This comment does not apply to the substantive changes between IEEE P802.3ch D2.1 and D2.2 or the unsatisfied negative comments from earlier ballots. Hence it is not within the scope of the recirculation ballot.

However, the change suggested has identified an error in the draft, and the proposed response is a substantive change which fixes the cross reference to point to the correct subclause.

CI 45 SC 45.2.1.195.3 P39 L50 # 1

Wienckowski, Natalie General Motors

Comment Type T Comment Status A EZ

The Precoder registers and text were modified in D2.2, but there is still a reference in D2.2 to register bits that were deleted.

SuggestedRemedy

Delete: In normal operation, this value shall mirror the value in the MultiGBASE-T1 PMA control register bits 1.2309.10:9. P57 L17: Also, delete PICS MM227 as the "shall" has been removed.

Response Response Status C

ACCEPT.

CI 45 SC 45.2.1.195.3 P39 L51 # 4

Tu, Mike Broadcom

Comment Type T Comment Status A EZ

Control register bits 1.2309.10:9 do not exist.

SuggestedRemedy

Delete the last sentence of this paragraph.

Response Response Status C

ACCEPT.

Cl 45 SC 45.2.1.196.4 P41 L 51 # 6

Tu, Mike Broadcom

Comment Type T Comment Status A EZ

The transmit jitter tests are specified in both 149.5.2.3.1 and 149.5.2.3.2. Recommend to refer to both, or simply refer to 149.5.2.3.

SuggestedRemedy

Option 1. Change "149.5.2.3.1" to "149.5.2.3".

Option 2. Change "See 149.5.2.3.1 for more information." to "See 149.5.2.3.1 and 149.5.2.3.2 for more information."

Response Response Status C

ACCEPT IN PRINCIPLE.

Change "149.5.2.3.1" to "149.5.2.3".

Cl 45 SC 45.2.1.198 P42 L 36 # 8

Tu, Mike Broadcom

Comment Type T Comment Status A EZ

Typos in Table 45-155g. 1.2314 should be 1.2315 on the first column.

SuggestedRemedy

Change the first column of Table 45-155g from "1.2314.xx:yy" to "1.2315.xx:yy".

Response Response Status C

ACCEPT.

Cl 45 SC 45.2.1.199.1 P42 L 49 # 9

Tu, Mike Broadcom

Comment Type E Comment Status A EZ

Title of the subclause should match with the name of register bits.

SuggestedRemedy

Change line 49 to "45.2.1.199.1 MultiGBASE-T1 user defined data (1.2316.15:0)".

Response Response Status C

ACCEPT.

Cl 45 SC 45.2.1.200.1 P43 L 25 # 10

Tu, Mike Broadcom

Comment Type E Comment Status A EZ

Title of the subclause should match with the name of register bits.

SuggestedRemedy

Change line 25 to: "45.2.1.200.1 MultiGBASE-T1 link partner user defined data (1.2317.15:0)".

Response Response Status C

ACCEPT.

Cl 149 SC 149.1.3 P80 L 11 # 12

Tu, Mike Broadcom

Comment Type T Comment Status A EZ

The EEE capability advertisement is described in 149.4.2.4.5.

SuggestedRemedy

Change the reference from 149.3.2.2.22 to 149.4.2.4.5.

Response Response Status C

ACCEPT.

This comment does not apply to the substantive changes between IEEE P802.3ch D2.1 and D2.2 or the unsatisfied negative comments from earlier ballots. Hence it is not within the scope of the recirculation ballot.

However, the change suggested has identified an error in the draft, and the proposed response is a substantive change which fixes the cross reference to point to the correct subclause.

Cl 149 SC 149.1.3 P 80 L 25 # 13

Tu, Mike Broadcom

Comment Type T Comment Status A EZ

PMA functionality is described in 149.4, not 149.2.

SuggestedRemedy

Change the reference from 149.2 to 149.4.

Response Response Status C

ACCEPT.

This comment does not apply to the substantive changes between IEEE P802.3ch D2.1 and D2.2 or the unsatisfied negative comments from earlier ballots. Hence it is not within the scope of the recirculation ballot.

However, the change suggested has identified an error in the draft, and the proposed response is a substantive change which fixes the cross reference to point to the correct subclause

Cl 149 SC 149.1.3.3 P 81 L 30 # 14

Tu, Mike Broadcom

Comment Type T Comment Status A EZ

EEE capability is embedded in Infocfield octet 10 bit 6.

SuggestedRemedy

Change "(Octet 9 bit 7)" to "(Octet 10 bit 6)"

Response Response Status C

ACCEPT.

This comment does not apply to the substantive changes between IEEE P802.3ch D2.1 and D2.2 or the unsatisfied negative comments from earlier ballots. Hence it is not within the scope of the recirculation ballot.

However, the change suggested has identified an error in the draft, and the proposed response is a substantive change which fixes the reference to the EEE capability bit which was changed in D2.1.

Cl 149 SC 149.3.2.1 P 93 L 47 # 11

Tu, Mike Broadcom

Comment Type T Comment Status A EZ

The PCS reset control register bit is 3.2322.15, not 1.2309.15.

SuggestedRemedy

On page 93, 149.3.2.1, line 47, change from "1.2309.15" to "3.2322.15".

Response Response Status C

ACCEPT.

This comment does not apply to the substantive changes between IEEE P802.3ch D2.1 and D2.2 or the unsatisfied negative comments from earlier ballots. Hence it is not within the scope of the recirculation ballot.

However, the change suggested has identified an error in the draft, and the proposed response is a substantive change which fixes the reference to the PCS reset bit which currently refers to the PMA reset bit.

Cl 149 SC 149.3.2.2 P 94 L 40 # 22

McCiellan, Brett Marvell Semiconductor

Comment Type E Comment Status A EZ

grammar

SuggestedRemedy

change 'encoder' to 'encoders'

Response Response Status C

ACCEPT.

This comment does not apply to the substantive changes between IEEE P802.3ch D2.1 and D2.2 or the unsatisfied negative comments from earlier ballots. Hence it is not within the scope of the recirculation ballot.

However, the change suggested has identified an error in the draft, and the proposed response is a non-substantive editorial change which improves clarity.

Cl 149 SC 149.3.2.2 P94 L48 # 23

McClellan, Brett Marvell Semiconductor

Comment Type E Comment Status A EZ

typo

SuggestedRemedy

change "RS-FE" to "RS-FEC"

Response Response Status C

ACCEPT.

This comment does not apply to the substantive changes between IEEE P802.3ch D2.1 and D2.2 or the unsatisfied negative comments from earlier ballots. Hence it is not within the scope of the recirculation ballot.

However, the change suggested has identified an error in the draft, and the proposed response is a non-substantive editorial change which improves clarity.

Cl 149 SC 149.3.2.2.3 P96 L17 # 19

McClellan, Brett Marvell Semiconductor

Comment Type E Comment Status A EZ

Tx_coded should be tx_coded
Rx_coded should be rx_coded

SuggestedRemedy

Change occurrences of "Tx_coded" to "tx_coded"
Change occurrences of "Rx_coded" to "rx_coded"

Response Response Status C

ACCEPT.

Cl 149 SC 149.3.2.2.18 P104 L45 # 20

McClellan, Brett Marvell Semiconductor

Comment Type E Comment Status A EZ

A and B are missing subscript 'n' that was added in 149.3.2.2.19

SuggestedRemedy

change "A" to "A_n"
change "B" to "B_n" with _n indicating a subscript

Response Response Status C

ACCEPT.

Cl 149 SC 149.5.1 P161 L46 # 3

Tu, Mike Broadcom

Comment Type T Comment Status A EZ

Register bits 1.2309.10:9 do not exist.It should be 1.2313.10:9.

SuggestedRemedy

Change from: "... by the value set in register 1.2309:10:9, ..."
To: "... by the value set in register 1.2313.10:9, ...".

Response Response Status C

ACCEPT.

Cl 149 SC 149.5.2.4 P165 L21 # 18

den Besten, Gerrit NXP Semiconductors

Comment Type E Comment Status A EZ

LPSD: The L seems smaller than the other characters

SuggestedRemedy

Fix the size of the L

Response Response Status C

ACCEPT.

This comment does not apply to the substantive changes between IEEE P802.3ch D2.1 and D2.2 or the unsatisfied negative comments from earlier ballots. Hence it is not within the scope of the recirculation ballot.

However, the change suggested has identified an error in the draft, and the proposed response is a non-substantive editorial change which improves clarity.

Cl 149 SC 149.7.1.3.2 P171 L8 # 21

McClellan, Brett Marvell Semiconductor

Comment Type E Comment Status A EZ

In Figure 149-54 N=1 and N=0 are not aligned to the associated RL curves.

SuggestedRemedy

In Figure 149-54 move N=1 and N=0 to be aligned to the associated RL curves.

Response Response Status C

ACCEPT.

Cl 45 SC 45.2.1.197 P 42 L 4 # 7

Tu, Mike Broadcom

Comment Type E Comment Status R OOS_Reject

Use "MultiGBASE-T1", instead of "MultiGBASE-T1 set". According to 149.1.1, "the nomenclature MultiGBASE-T1 is used to describe specifications that apply to the 2.5GBASE-T1, 5GBASE-T1, and 10GBASE-T1 PHYs."

SuggestedRemedy

1. Page 42, line 3: Change from: "... at the slicer input for the PMAs in the MultiGBASE-T1 set." To: "... at the slicer input for the MultiGBASE-T1 PMAs."

2. Page 62, Clause 78.5, line 18 to 25: Change all occurrences of "... the PHY in the MultiGBASE-T1 set ..." to "... the MultiGBASE-T1 PHY ...".

Response Response Status C

REJECT.

This comment does not apply to the substantive changes between IEEE P802.3ch D2.1 and D2.2 or the unsatisfied negative comments from D2.0. Hence it is not within the scope of the recirculation ballot. In addition, this proposal does not fix an error in the draft.

In addition, the nomenclature defined locally in clause 149 doesn't apply to clause 45, while that shorthand is convenient for clause 149 specifications which apply to all three PHYs in that clause, the global definition in clause 1.4 applies generally, and the existing text is consistent with that usage.

Cl 104 SC 104.4.6.3 P 68 L 52 # 16

den Besten, Gerrit NXP Semiconductors

Comment Type T Comment Status R OOS_Reject

The PoDL ripple is somewhat ambiguously defined as the text descriptions only talks about measuring ripple with certain high-pass filters. The table mentions 1kHz-10MHz. If this is the measurement bandwidth, the measurement with 10MHz high-pass becomes actually a fairly narrow bandpass measurement around 10MHz. This also implies there is no constraint on the PoDL ripple beyond 10MHz. I've understood that the assumption is that there will no be significant ripple beyond 10MHz, but unfortunately the specification does not constrain that. A ripple at higher frequencies is very undesirable, so a note that PoDL circuitry shall not produce any significant ripple beyond 10MHz seems useful.

SuggestedRemedy

Add a note to this paragraph of the PoDL clause: The induced voltage ripple at the MDI of PoDL circuits beyond 10MHz shall be negligible to avoid degradation of signal reception.

Response Response Status C

REJECT.

This comment does not apply to the substantive changes between IEEE P802.3ch D2.1 and D2.2 or the unsatisfied negative comments from D2.0. Hence it is not within the scope of the recirculation ballot. In addition, this proposal does not fix an error in the draft.

The Suggested Remedy does not provide a technically complete solution. Notes are informative only and cannot state normative requirements. Additionally "negligible voltage ripple" cannot be a normative requirement as it provides no testable metric for voltage ripple.

Commenter may wish to resubmit this comment at Standards Association ballot.

The commenter may also wish to submit a Maintenance request for Clause 104 to add similar requirements for ripple voltage at other communication rates.

Cl 149 SC 149.5.2.2 P 163 L 47 # 17

den Besten, Gerrit

NXP Semiconductors

Comment Type T Comment Status R OOS_Reject

The linearity test of BASE-T1 PHYs have previously been based on transmission of a sequence in combination with a sinewave signal that is injected from the outside to account for the full-duplex communication on the link. In March it was argued that this method was not useful and there there are better and simpler methods for specifying linearity that could be borrowed from other specs. This resulted into a method borrowed from a unidirectional SERDES spec, which happens to refer to multiple other clauses too. This method is arguably not simpler than the previously used method. But even more importantly this new method does not account for the full-duplex behavior. The received signal significantly extends the signal range on the MDI. When linearity is only measured when the TX is transmitting, but there is no signal received at the same time, such a test is not adequate IMO to address the problem.

SuggestedRemedy

Suggest to use a similar linearity test method as used for 100BASE-T1 and 1000BASE-T1, that is, with an external sinewave superpositioned on top of the transmitted signal. This method ensures that linearity is tested over the appropriate output signal range that can occur for full duplex communication. Alternatively it can be considered if this test can be skipped, because the imposed linearity requirements of the transceiver to ensure reliable data transfer might be tighter than the currently included 'unidirectional SERDES-borrowed' test.

Response Response Status C

REJECT.

This comment does not apply to the substantive changes between IEEE P802.3ch D2.1 and D2.2 or the unsatisfied negative comments from D2.0. Hence it is not within the scope of the recirculation ballot. In addition, this proposal does not fix an error in the draft.

The Suggested Remedy does not include a specific change the commenter would like to see made to the draft.

Commenter may wish to resubmit this comment, with a specific solution, at initial Standards Association ballot.

Cl 45 SC 45.2.1.196 P 41 L 17 # 5

Tu, Mike

Broadcom

Comment Type T Comment Status R Precoder

Table 45-155e defines the test mode control register bits. The test mode 3 transmit precoder setting is always controlled by register bits 1.2313.10:9. There is no need to define a "Local transmitter precoder override" bit.

Also change the name from "Local transmit precoder setting" to "Test mode transmit precoder setting" to clarify the purpose of these control register bits.

SuggestedRemedy

1. In Table 45-155e, delete the row "1.2313.11".
2. In Table 45-155e, change the first column of the row "1.2313.12" from "1.2313.12" to "1.2313.12:11".
3. In Table 45-155e, change the Name of 1.2313.10:9 to "Test mode transmit precoder setting".
4. Delete 45.2.1.196.2.
5. Change page 41 line 39 to 45 to the following:
"45.2.1.196.3 Test mode transmit precoder setting (1.2313.10:9)
In Test mode 3, bits 1.2313.10:9 control the precoder setting of the local transmitter, as defined in 149.3.2.2.20. During normal operation, the precoder is set according to the value of PrecoderSel received from the link partner, and bits 1.2313.10:9 are ignored."

Response Response Status C

REJECT.

The ability to locally override the transmitted precoder was left in on purpose. If you do not have access to the remote PHY, because link doesn't come up, you may need it for troubleshooting. When the link doesn't come up, it could, for example, be because of an error in how precoder settings are controlled. Requiring that they be set by the remote PHY in all cases limits debuggability.

If these changes are made, the ability to locally control the transmitter will be linked to the very limited and specialized transmit sequences in test mode 3. The ability to locally control the precoder is needed for any more extensive debug. Stripping out this control serves no useful purpose, hides functionality, and reduces debug control for interoperability.