

IEC/IEEE 60802 Contribution – Time Sync Informative Annex

Version 01 – July 2023

David McCall (Intel Corporation)

<Are the correct terms: Grandmaster; PTP Relay Instance, Relay Instance, Relay; End Station?>

1. Overview

IEC/IEEE 60802 (this specification) enables a network of compliant devices to achieve a time synchronisation accuracy, at the application level, of 1 μ s over 100 network hops. To achieve this, it allocates the overall error budget of 1 000 ns as described in Table 1.

Table 1: Time Synchronisation Error Budget

Network Aspect	Error Type	Network-Level Error Budget (ns)	Normative or Informative?
All PTP Instances	Constant Time Error	200	Normative
	Dynamic Time Error	600	
All PTP Links	Constant Time Error	200	Informative
	Dynamic Time Error	0	

<What about the error budget going from the ClockSource to ClockTimeTransmitter? And from the ClockTimeReceiver to ClockTarget?>

A chain of 1 Grandmaster, 99 Relays and 1 End Station (100 network hops) that all comply with the normative requirements of sections 6.2.2 and 6.2.3 will generate a network-level Time Error at or below the Error Budget for All PTP Instances.

Section 2 describes the principles of operation this specification assumes.

Section 3 provides information on the more novel normative requirements.

The principles of operation include the use of regular crystal oscillators (XOs) as opposed to more accurate, stable and costly options such as temperature-compensated crystal oscillators (TCXOs). The use of XOs means that some of the normative requirements are difficult or impossible to meet without employing algorithms that track Neighbor Rate Ratio drift and Rate Ratio drift and compensate for consequent errors in calculating Rate Ratio and Correction Field. Section 4 of this annex provides examples of algorithms that may be used for this purpose, and which have been shown to enable compliance with the normative requirements.

Note that implementations which employ TCXOs or other more accurate, stable oscillators will still need to employ algorithms to track and compensate for errors due to clock drift in neighboring and/or Grandmaster instances that use XOs.

There is no normative requirement to use the algorithms described in section 4; an implementation may employ alternative algorithms provided the normative requirements are met. However, care should be taken when deploying a network whose instances employ a mix of different algorithms. Section 4 describes the potential risks. It is left as an exercise for implementers to mitigate the risks and ensure alternative algorithms continue to deliver the network-level performance.

This specification does not include normative requirements for PTP Links, but section 2 describes network-level characteristics that need to meet, including some examples of using common PTP Link characteristics, in order to ensure the relevant error budget is not exceeded and 1 μ s time synchronisation accuracy is maintained.

This specification’s normative requirements regarding instance-level error generation are novel, necessitated by the need to ensure not just an overall level of dTE generation at each node, but also the performance of drift tracking and error compensation algorithms and the amount of dTE generation due to timestamp error versus clock drift (as the algorithms are employed to mitigate the latter, but cannot mitigate the former). Section 5 describes an approach to testing the normative requirements. It is not, however, the only viable approach, and the description is not a test specification.

2. Principles of Operation

Achieving 1 μ s time synchronisation accuracy across 100 network hops involves managing the accumulation of errors in the Precise Origin Timestamp + Correction Field and the Rate Ratio as they are passed, via Sync or Follow_Up messages, down the chain of PTP instances and are then used by the End Station to keep its ClockTarget in line with the ClockSource at the Grandmaster. All significant errors can ultimately be traced back to one of two sources: timestamp error or clock drift. The selection of PTP protocol parameters often involves trading off one source of error against the other. This specification requires PTP protocol configurations, and assumes the use of mechanisms (algorithms), that reduce dTE due to timestamp error but would also – without additional measures – increase dTE due to clock drift to the point where the latter exceeds the allocated error budget. However, this specification also includes additional measures to minimise some sources of dTE due to clock drift and mechanisms to track and compensate for errors from other sources to a sufficient degree that the error budget is not exceeded.

The specific protocol configurations and other measures, along with their intended effects, are described in Table 2.

Table 2: Protocol configurations & other measures to achieve dTE budget

Configuration or Measure	Description and Intended Effect(s)
Sync Interval 125 ms	Effects: <ol style="list-style-type: none"> <li data-bbox="578 1591 1417 1654">1. Calibrate balance between dTE from timestamp error vs error due to clock drift. <li data-bbox="578 1663 1417 1755">2. Keep below acceptable limits the need to rely on accurate Rate Ratio estimation for keeping ClockTarget in line with ClockSource between arrival of Sync messages.

<p>Drift_Tracking TLV - syncEgressTimestamp</p>	<p>Description: <Is this needed?></p> <p>Effect: Enables calculation of NRR using Sync message timestamps, which eliminates error due to NRR clock drift that would otherwise occur between calculation of NRR using Pdelay_Resp messages and their use during Sync message processing (i.e. calculation of updated Correction Field and Rate Ratio values)</p>
<p>NRR Smoothing</p>	<p>Description: Algorithm to use timestamps from multiple past Sync messages when estimating NRR.</p> <p>Effect: Reduce the amount of error in the estimate of NRR due to timestamp error while increasing the amount of error due to clock drift.</p>
<p>NRR Drift Tracking & Compensation</p>	<p>Description: Algorithm to use timestamps from multiple past Sync messages to estimate NRR drift then apply compensation to correct for consequent errors in NRR smoothing calculation.</p> <p>Effect: Mitigate the effect of errors due to clock drift when calculating and using the estimated NRR.</p>
<p>Drift_Tracking TLV – rateRatioDrift</p>	<p>Description: Carries estimate of Rate Ratio drift rate from one node to the next.</p> <p>Effect: Allows each node to estimate its own Rate Ratio drift rate by combining the incoming Rate Ratio drift rate with the local estimate of NRR drift rate.</p>
<p>RR Drift Compensation</p>	<p>Description: Algorithm that uses the estimate of RR drift rate to compensate for that drift, adjusting the estimated RR over time according to the drift rate.</p> <p>Effect: For Relay Instances, minimises errors in the Correction Field caused by Rate Ratio drift. For End Stations, minimises errors in keeping ClockTarget in line with ClockSource between arrival of Sync messages.</p>
<p>Sync Interval Consistency</p>	<p>Description: This specification requires tighter control of the interval between Sync messages generated at the Grandmaster than the defaults in IEEE 802.1AS-2020.</p> <p>Effect: Errors due to clock drift at Relay Instances have a tendency to cancel out. A clock drift which generates a positive error in NRR measurement on receipt of a Sync message generates a negative error in NRR measurement at the next node. The degree of cancellation is dependant on the consistency of the intervals over which NRR is measured at subsequent nodes.</p>

	<Is this still necessary given that Sync Interval messages are inherently more consistent node-to-node, varying only according to differences in Residence Time?>
Pdelay Interval Consistency	<Should we add this back in given the conversation on 13 th July 2023, i.e. where NRR based on Pdelay_Resp messages may be used when NRR based on Sync messages is not available, e.g. at startup or after a reconfiguration?>
Mean Residence Time	<p>Description: This specification defines an average Residence Time requirement, where the average is significantly lower than the default maximum Residence Time in IEEE 802.1AS-2020.</p> <p>Effect: The amount of error in the Correction Field at the End Station due to clock drift is proportional to the cumulative meanLinkDelay and residenceTime experienced by a Sync message during transit from the Grandmaster to the End Station. Specifying a lower average residenceTime reduces this source of error.</p>

2.1. Grandmaster Implementation

<Behaviour when Local Clock is Clock Source and when it the two are different. rateRatio and rateRatioDrift may not be zero in transmitted Sync/Sync_Followup. ClockSource behaviour when in steady state and during transition when being driven externally to align with another domain.>

2.2. Splitting, Joining and Aligning Time Domains

<Material from 6.2.5 and 6.2.13>

3. Notes on Normative Requirements and PTP Link Recommendations

3.1. Oscillator Requirements

Clock drift at the Grandmaster causes greater dTE than the same amount of clock drift at a Relay Instance or the End station. This specification therefore requires tighter limits on maximum fractional frequency offset for an oscillator at the Grandmaster than at other instances.

This specification does not place requirements on operational temperature range or other environmental factors. The required oscillator behaviour is delivered across whatever operational conditions a device claims it is compliant.

3.2. Timestamp Granularity Error

<Dependant on upcoming discussion. If necessary, this section will explain why Timestamp Granularity Error is expected to average to zero.>

3.3. Dynamic Timestamp Error

<PHY delay variability equals Dynamic Timestamp Error and must therefore be reduced to a level where normative requirements on preciseOriginTimestamp + correctionField can be met>

3.4. Grandmaster Error Generation Requirements

Table 12 sets normative requirements for error generation at a Grandmaster that ensure the relevant fields in the Sync and Sync_Followup messages it transmits are sufficiently accurate to deliver the <guaranteed? promised?> network-level time sync performance.

- preciseOriginTimestamp + correctionField
 - Timestamp Error
- rateRatioDrift
 - Performance of rateRatioDrift measurement
- rateRatio
 - Performance of rateRatio measurement
- syncEgressTimestamp
 - Timestamp Error

3.5. PTP Relay Instance

Table 13 sets normative requirements for error generation at a PTP Relay Instance that ensure the relevant fields in the Sync and Sync_Followup messages it transmits as part of Sync processing are sufficiently accurate to deliver the <guaranteed? promised?> network-level time sync performance.

- preciseOriginTimestamp + correctionField
 - Measurement of Residence Time
- rateRatioDrift
 - Performance of NRR drift measurement when there is no NRR drift
 - Performance of NRR drift measurement when there is NRR drift
- rateRatio
 - Performance of rateRatio calculation when there is no RR drift
 - Performance rateRatio calculation and error compensation when there is RR drift due to GM clock drift (incoming rateRatioDrift field)
 - Performance of rateRatio calculation and error compensation when there is RR drift due to Local Clock drift (NRR drift measurement)
- syncEgressTimestamp
 - TimestampError

3.6. End Station

Table 14 sets normative requirements for error generation at a PTP Relay Instance that ensure the relevant fields in the Sync and Sync_Followup messages it transmits as part of Sync processing are sufficiently accurate to deliver the <guaranteed? Promised?> network-level time sync performance.

- Performance of ClockTarget generation when there is no clock drift.
- Performance of ClockTarget generation when there is RateRatio drift due to GM clock drift. (incoming rateRatioDrift field)
- Performance of ClockTarget generation when there is RateRatio drift due to Local Clock drift. (NRRdrift measurement)

4. Example Algorithms

<Imported from "[60802 Time Sync - Monte Carlo and Time Series Simulation Configuration Including NRR and RR Drift Tracking & Error Compensation v3](#)" but adjusted to use mNRRcompNAP 8 and mNRRsmoothing 4>

5. Approach to Testing Normative Requirements

<Import from "60802 Time Sync – Rate Ratio Drift Tracking & Error Compensation" with adjustment for use of RRdriftTracking field and additional text to explain test approach>