

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Clarifications for FBSS and MDHO	
Data Submitted	2007-03-13	
Source(s)	Aeri Lim, Samsung Electronics Co.	Voice: +82-31-279-5694 Fax: +82-31-279-4609 ari.lim@samsung.com
Re:	P80216/Cor2/D2	
Abstract	The document contains suggestions on the clarification of FBSS and MDHO	
Purpose	Adoption of proposed changes into P80216/Cor2/D2	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16	
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard. "Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < mailto:chiar@wirelessman.org > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < http://ieee802.org/16/ipr/patents/notices >.	

Clarifications for FBSS and MDHO

Introduction

In 802.16e-2005, when a FBSS capable MS completes the initial network entry to a BS, the MS considers the serving BS as Anchor BS. In addition, when the MS has an empty Diversity Set, TEMP_BSID in MOB_MSHO-REQ shall be set to zero.

This means that, a MS initializes the Diversity Set and TEMP_BSID of Anchor BS shall be set to 0 after it completes initial network entry.

The Diversity Set is maintained only when a MS switches Anchor BS with FBSS/MDHO procedure. If a MS enters a BS with the procedure except Anchor BS update for MDHO/FBSS defined in 6.3.22.3.4, the Diversity Set shall be initialized in a MS and a BS.

Proposed changes to P80216/Cor2/D2

6.3.22.3.2 FBSS decision and initiation

Change the subclause as indicated:

The BS supporting FBSS shall broadcast the DCD message that includes the H_Add Threshold and H_Delete Threshold.

These thresholds may be used by the FBSS capable MS to determine if MOB_MSHO-REQ should be sent to request ~~switching to another Anchor BS or~~ changing Diversity Set. When mean CINR of an active BS in the current diversity set is less than H_Delete Threshold, the MS may send MOB_MSHO-REQ to request dropping this BS from the diversity set; when mean CINR of a neighbor BS is higher than H_Add Threshold, the MS may send MOB_MSHO-REQ to request adding this neighbor BS to the diversity set. In each case, Anchor BS responds with MOB_BSHO-RSP with updated Diversity Set.

After the MS completes the initial network entry, re-entry procedure or the handover procedure defined in 6.3.22.2, the BS automatically becomes an Anchor BS. Also, the Diversity Set is initialized and TEMP_BSID of the Anchor BS is set to zero. However, the TEMP_BSID and Diversity Set shall be maintained when Anchor BS switching defined in 6.3.22.3.4 occurs.