

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Calculating the Non-pre-assigned DL/UL Radio Resources	
Date Submitted	2007-03-13	
Source(s)	Peretz Feder – Alcatel-Lucent Phillip Barber - Huawei Honghai Zhang – Alcatel-Lucent	pfeder@alcatel-lucent.com pbarber@broadbandmobiletech.com hozhang@alcatel-lucent.com
Re:	IEEE 802.16 Session #48	
Abstract	This contribution proposes the updates of IEEE 802.16g D8 document in order to calculate the Non-pre-assigned DL/UL radio resources.	
Purpose	Update 802.16g draft: calculate the Non-pre-assigned DL/UL radio resources.	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < http://ieee802.org/16/ipr/patents/policy.html >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < mailto:chair@wirelessman.org > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < http://ieee802.org/16/ipr/patents/notices >.	

Calculating the Non-pre-assigned DL/UL Radio Resources

Peretz Feder -Alcatel-Lucent
Honghai Zhang – Alcatel-Lucent
Phillip Barber - Huawei

1. Introduction

Currently in 802.16g/D8, it is not clear how to calculate the Non-pre-assigned DL or UL radio resources. This contribution resolves these issues.

2. Proposed Text Change

Remedy 1:

Add two constant parameters for the window size over which the Non-pre-assigned DL or UL radio resources are calculated.

[Add the following entries to Table 342]:

Table 342 Parameters and Constants

Systems	Name	Time references	Minimum Value	Default Value	Maximum Value
MS, BS	DL_radio_resources_window_size	The number of frames over which the Non-pre-assigned DL radio resources are calculated.		200	
MS, BS	UL_radio_resources_window_size	The number of frames over which the Non-pre-assigned UL radio resources are calculated.		200	

Remedy 2:

In order to factor the loading information when determining the target BS for initial entry and handover, the radio loading condition is provided in the DCD message.

[Add to table 358 – DCD channel encoding the following entry]:

Name	Type (1 Byte)	Length	Value	PHY Scope
Non-pre-assigned DL radio resources	23	1	Indicates the average percentage of non-pre-assigned physical radio resources for DL where averaging shall take place over a time interval which shall be a configurable value (with a default value of the last 200 frames) common to all BS within an operator network. Non-pre-assigned physical radio resources shall be defined as the set of subchannels and/or symbols within a radio frame, which are not used by any non-best-effort service flow class as identified by either the uplink grant scheduling type or the data delivery service as	All

		<p>identified in the service flow encodings. The average shall be taken over a non-overlapping time interval defined by the DL_radio_resources_window_size parameter (Table 342) that shall be configurable and common to all BSs within an operator network.</p> <p>0x00: 0% 0x01 : 1%, ..., 0x64 : 100% 0x65 - 0xFE : reserved, 0xFF indicates no information available</p>	
--	--	--	--

(Note to the editor: Non-pre-assigned- DL radio message was introduced in the SB02 phone CBR session)

Remedy 4:

In order to factor the loading information when determining the target BS for initial entry and handover the radio loading condition is provided in the UCD message.

[Add to table 349 – UCD common channel encoding the following entry]:

Name	Type (1 Byte)	Length	Value
Non-pre-assigned UL radio resources	24	1	<p>Indicates the average percentage of non-pre-assigned physical radio resources for UL where averaging shall take place over a time interval which shall be a configurable value (with a default value of the last 200 frames) common to all BS within an operator network. Non-pre-assigned physical radio resources shall be defined as the set of subchannels and/or symbols within a radio frame, which are not used by any non-best-effort service flow class as identified by either the uplink grant scheduling type or the data delivery service as identified in the service flow encodings. The average shall be taken over a non-overlapping time interval defined by the UL_radio_resources_window_size parameter (Table 342) that shall be configurable and common to all BSs within an operator network.</p>

			<p>0x00: 0% 0x01 : 1%, ..., 0x64 : 100% 0x65 - 0xFE : reserved, 0xFF indicates no information available</p>
--	--	--	---