

Project	<b>IEEE 802.16 Broadband Wireless Access Working Group</b> < <a href="http://ieee802.org/16">http://ieee802.org/16</a> >
Title	<b>H-ARQ for DIUC/UIUC</b>
Date Submitted	<b>2004-08-18</b>
Source(s)	Geunhwi Lim, Wonil Roh, Yong Chang, <a href="mailto:geunhwi.lim@samsung.com">geunhwi.lim@samsung.com</a> Hong Sung Chang, JungWon Kim, TaeWon Kim Samsung Electronics Co. Ltd.
Re:	
Abstract	<b>Change H-ARQ MAP_IE for proper operation of H-ARQ</b>
Purpose	Adoption of proposed changes into P802.16e /D4-2004
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures (Version 1.0) < <a href="http://ieee802.org/16/ipr/patents/policy.html">http://ieee802.org/16/ipr/patents/policy.html</a> >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, if there is technical justification in the opinion of the standards-developing committee and provided the IEEE receives assurance from the patent holder that it will license applicants under reasonable terms and conditions for the purpose of implementing the standard."  Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < <a href="mailto:r.b.marks@ieee.org">mailto:r.b.marks@ieee.org</a> > as early as possible, in written or electronic form, of any patents (granted or under application) that may cover technology that is under consideration by or has been approved by IEEE 802.16. The Chair will disclose this notification via the IEEE 802.16 web site < <a href="http://ieee802.org/16/ipr/patents/notices">http://ieee802.org/16/ipr/patents/notices</a> >.

## 1 Introduction

Even though the current system defines H-ARQ operation and DIUC/UIUC in physical layer, there is no support of the operation in the H-ARQ MAP. Hence, we propose a text change for H-ARQ MAP.

For the backward compatibility problem, this change can't be applied to the system that uses FFT size of 2048.

## 2 Proposed Text

*In page 28, Line 8, Section 6.3.2.3.43, add the following text.*

### 6.3.2.3.43.8 H-ARQ support for DIUC/UIUC

Apply following change to the IEEE 802.16-REVd/D4-2004 for the proper operation of H-ARQ with DIUC/UIUC.

*[In page 107, Line 30, change the following text]*

**Table 87—Compact\_DL-MAP IE types**

Compact DL-MAP Type	Description
0	Diversity
1	Band AMC
2	Safety
3	DIUC <a href="#">Diversity</a>
4	Format Configuration IE
5	H-ARQ ACK BITMAP IE
6	<del>Reserved</del> <a href="#">DIUC AMC</a>
7	Extension

**Table 88—Compact\_UL-MAP IE types**

Compact UL-MAP Type	Description
0	Normal subchannel
1	Band AMC
2	Safety
3	UIUC <a href="#">Diversity</a>
4	H-ARQ Region IE
5	CQI Region IE
6	<del>Reserved</del> <a href="#">UIUC AMC</a>
7	Extension

*[In page 107, Line 30, change the following text]*

**Table 89—Format configuration [DL-MAP](#) IE**

Syntax	Size	Notes
<a href="#">Format Configuration</a> Compact_DL-MAP IE() {		
DL-MAP Type = 4	3 bits	<del>Format</del> Configuration <a href="#">Compact DL-MAP</a> IE
New Format Indication	1 bits	0 = Use the format configured by the latest Format Configuration <a href="#">Compact DL-MAP</a> IE

		1 = New format
if (New Format Indication == 1) {		
CID Type	2 bits	00 = Normal CID 01 = RCID11 (default) 10 = RCID7 11 = RCID3
Safety Pattern	<del>4</del> 5 bits	
Subchannel type for Band AMC	2 bit	See Band AMC specification (8.4.6.3). 00 = Default type (default) 01 = 1x6 type 10 = 2x3 type 11 = 3x2 type
Max Logical Bands	2 bits	0 = 3 bands, 1 = 6 bands, 2 = 12 bands (default) 3 = 24 bands
No. Symbols for Broadcast	4 <del>5</del> bits	No. Symbol, (default = 0)
No. Symbols for DL Band AMC	4 <del>6</del> bits	No. Symbol, (default = 0)
No. Symbols for UL Band AMC	4 <del>6</del> bits	No. Symbol, (default = 0)
}		
}		

[In page 116, Line 45, change the following text]

6.3.2.3.43.6.4 **DIUC Compact DL-MAP IE for DIUC subchannel**

Table 97—**H-ARQ DIUC Compact DL-MAP IE format for DIUC subchannel**

Syntax	Size	Notes
<b>DIUC Compact DL-MAP IE () {</b>	-	-
<b>Compact DL-MAP Type = 3</b>	3 bits	DIUC type
Reserved	1 bits	
DIUC	4 bits	See DIUC section
if(DIUC == 15) {		
Extended DIUC dependent IE	variable	
} else {		
RCID_IE	variable	
<del>No. Subchannels Duration</del>	8 bits	<del>The number of subchannels allocated by the IE in OFDMA slots (see 8.4.3.1)</del>
<b>Repetition Coding Indication</b>	2 bits	0b00 - No repetition coding 0b01 - Repetition coding of 2 used 0b10 - Repetition coding of 4 used 0b11 - Repetition coding of 6 used
<b>H-ARQ Control IE</b>	variable	
<b>CQICH Control IE</b>	variable	
}		

[In page 118, Line 1, change the following text]

6.3.2.3.43.6.6 [Extension Compact DL-MAP IE](#) ~~for extension~~

**Table 99—H-ARQ [Extension Compact DL-MAP IE](#) format ~~for extension~~**

Syntax	Size	Notes
<a href="#">Extension Compact DL-MAP IE ()</a> {	-	-
<a href="#">Compact DL-MAP Type</a> = 7	3 bits	
<a href="#">Extended DIUC Indicator</a>	1 bits	0 = Sub-type 1 = <a href="#">Extended DIUC</a>
if ( <a href="#">Extended DIUC Indicator</a> = 1)		
<a href="#">DIUC</a>	4 bits	
else		
DL-MAP sub-type	54 bits	Extension sub-type
Length	4 bits	Length of the IE in Bytes
Payload	Variable	Sub-type dependent payload
}		

[In page 118, add the following text]

6.3.2.3.43.6.7 [DIUC AMC Compact DL-MAP IE](#)

**Table 99a —[DIUC AMC Compact DL-MAP IE](#) format**

Syntax	Size	Notes
<a href="#">DIUC AMC Compact DL-MAP IE ()</a> {		
<a href="#">Compact DL-MAP Type</a> = 6	3 bits	
Reserved	1 bit	
<a href="#">RCID IE</a>	variable	
<a href="#">DIUC</a>	4 bits	
<a href="#">Repetition Coding Indication</a>	2 bits	0b00 - <a href="#">No repetition coding</a> 0b01 - <a href="#">Repetition coding of 2 used</a> 0b10 - <a href="#">Repetition coding of 4 used</a> 0b11 - <a href="#">Repetition coding of 6 used</a>
Reserved	2 bits	
Nband	Nb-Band bits	<a href="#">Number of bands</a> , 0 = use <a href="#">BITMAP</a> instead
if(Nband == 0){		
<a href="#">Band BITMAP</a>	Nb-BITMAP bits	n-th LSB is 1 if n-th band is selected
}else {		
for (i=0;i<Nband ; i++)		
<a href="#">Band Index</a>	Nb-Index bits	<a href="#">Band selection</a> .
}		
<a href="#">Allocation Mode</a>	2 bit	<a href="#">Indicates the subchannel allocation mode</a> . 00 = same number of subchannels for the selected bands 01 = different number of subchannels for the selected bands 10 = reserved

		<a href="#">11 = reserved</a>
<a href="#">Reserved</a>	<a href="#">2 bits</a>	
<a href="#">if(Allocation Mode == 00){</a>		
<a href="#">Duration</a>	<a href="#">8 bits</a>	
<a href="#">} else if( Allocation Mode == 01){</a>		
<a href="#">for (i=0;i&lt; band count :i++){</a>	-	<a href="#">If Nband is 0, band count is the number of '1' in Band BITMAP. Otherwise band count is Nband.</a>
<a href="#">Duration</a>	<a href="#">8 bits</a>	
<a href="#">}</a>	-	
<a href="#">}</a>		
<a href="#">H-ARQ Control IE</a>	<a href="#">variable</a>	
<a href="#">COICH Control IE</a>	<a href="#">variable</a>	
<a href="#">}</a>	-	

[In page 121, Line 50, change the following text]

**6.3.2.3.43.7.4 UIUC Compact DL-MAP IE for UIUC subchannel**

**Table 103—H-ARQ UIUC Compact DL-MAP IE format for UIUC subchannel**

Syntax	Size	Notes
UIUC Compact UL-MAP_IE () {	-	-
Compact UL-MAP Type = 3	3 bits	UIUC type
Reserved	1 bits	
UIUC	4 bits	
<a href="#">if(UIUC == 12) {</a>		
<a href="#">OFDMA Symbol offset</a>	<a href="#">8 bits</a>	
<a href="#">Subchannel offset</a>	<a href="#">7 bits</a>	
<a href="#">No. OFDMA Symbols</a>	<a href="#">7 bits</a>	
<a href="#">No. Subchannels</a>	<a href="#">7 bits</a>	
<a href="#">Ranging Method</a>	<a href="#">2 bits</a>	<a href="#">0b00 - Initial Ranging over two symbols</a> <a href="#">0b01 - Initial Ranging over four symbols</a> <a href="#">0b10 - BW Request/Periodic Ranging over one symbol</a> <a href="#">0b11 - BW Request/Periodic Ranging over three symbols</a>
<a href="#">reserved</a>	<a href="#">1 bit</a>	<a href="#">Shall be set to zero</a>
<a href="#">} else if (UIUC == 14) {</a>		
<a href="#">CDMA Allocation_IE()</a>	<a href="#">32 bits</a>	
<a href="#">} else if (UIUC == 15) {</a>		
<a href="#">Extended UIUC dependent IE</a>	<a href="#">variable</a>	
<a href="#">} else {</a>		
<a href="#">RCID_IE</a>	<a href="#">variable</a>	
<del><a href="#">No. Subchannels</a></del> <a href="#">Duration</a>	<a href="#">8 bits</a>	<del>The number of subchannels allocated by the IE</del> <a href="#">In OFDMA slots (see 8.4.3.1)</a>

<a href="#">Repetition Coding Indication</a>	2 bits	0b00 - No repetition coding 0b01 - Repetition coding of 2 used 0b10 - Repetition coding of 4 used 0b11 - Repetition coding of 6 used
<a href="#">H-ARQ Control IE</a>	variable	
}		
}		

[In page 121, Line 50, add the following text]

**6.3.2.3.43.7.7 UIUC AMC Compact DL-MAP IE**

**Table 104—UIUC AMC Compact DL-MAP IE format**

Syntax	Size	Notes
<a href="#">UIUC AMC Compact UL-MAP IE () {</a>	-	-
<a href="#">UL-MAP Type = band</a>	3 bits	<a href="#">UIUC AMC</a>
<a href="#">Reserved</a>	1 bit	
<a href="#">RCID IE</a>	variable	
<a href="#">UIUC</a>	4 bits	<a href="#">Number of encapsulate packet</a>
<a href="#">Repetition Coding Indication</a>	2 bits	0b00 - No repetition coding 0b01 - Repetition coding of 2 used 0b10 - Repetition coding of 4 used 0b11 - Repetition coding of 6 used
<a href="#">Reserved</a>	2 bits	
<a href="#">Nband</a>	Nb-Band bits	<a href="#">Indicates the number of selected bands.</a> 0 = BITMAP indicates the number and offset of selected bands
<a href="#">if(Nband == 0){</a>	-	-
<a href="#">Band BITMAP</a>	Nb-BITMAP bits	<a href="#">n-th LSB is 1 if n-th band is selected</a>
<a href="#">}else {</a>		
<a href="#">for (i=0;i&lt;Nband;i++)</a>	-	-
<a href="#">Band Index</a>	Nb-Index bits	<a href="#">Band selection.</a>
<a href="#">}</a>	-	-
<a href="#">Allocation Mode</a>	2 bits	<a href="#">Indicates the subchannel allocation mode.</a> 00 = same number of subchannels for the selected bands 01 = different number of subchannels for the selected bands 10 = reserved 11 = reserved
<a href="#">Reserved</a>	2 bits	
<a href="#">if( Allocation Mode == 0){</a>		
<a href="#">Duration</a>	8 bits	
<a href="#">} else if( Allocation Mode == 1){</a>		
<a href="#">for (i=0;i&lt; band count ;i++){</a>		<a href="#">If Nband is 0, band count is the number of '1' in Band BITMAP.</a> <a href="#">Otherwise band count is Nband.</a>
<a href="#">Duration</a>	8 bits	<a href="#">Number of subchannels per band</a>
<a href="#">}</a>		

<u>}</u>		
<u>H-ARQ Control IE</u>	<u>variable</u>	
<u>}</u>	<u>-</u>	<u>-</u>

[In page 124, Line 12, change the following text]

6.3.2.3.43.7.7 Extension Compact UL-MAP IE ~~for extension~~

**Table 106—H-ARQ Compact UL-MAP IE format ~~for extension~~**

Syntax	Size	Notes
<u>Extension</u> Compact UL-MAP_IE () {	-	-
<u>Compact</u> UL-MAP Type = 7	3 bits	
<u>Extended UIUC Indicator</u>	1 bits	<u>0 = Sub-type</u> <u>1 = Extended UIUC</u>
<u>if (Extended UIUC Indicator = 1)</u>		
<u>UIUC</u>	4 bits	
<u>else</u>		
UL-MAP sub-type	<del>5</del> 4 bits	Extension sub-type
Length	4 bits	Length of the IE in Bytes
Payload	Variable	Sub-type dependent payload
}		

**References:**

[1] IEEE P802.16-REVd/D5-2004 Draft IEEE Standards for local and metropolitan area networks part 16: Air interface for fixed broadband wireless access systems