

Project	IEEE 802.16 Broadband Wireless Access Working Group < <a href="http://ieee802.org/16">http://ieee802.org/16</a> >
Title	Changes to DL-MAP-IE and UL-MAP-IE to Support AMC Subchannel in OFDMA PHY
Date Submitted	2004-05-13
Source(s)	Haiming Huang, Kemin Li, Titus Lo Walbell Technologies, Inc., USA <a href="mailto:tlo@walbell.com">tlo@walbell.com</a> Jaehyeong Kim, Anuj Puri, Jun Shen Posdata Corporation, S. Korea Voice: +425-451-8278
Re:	IEEE P802.16e/D2-2004
Abstract	This document suggests changes in TGd Draft Document IEEE 802.16e-D2 to provide an optional mechanism to indicate different burst profile within one DL/UL-MAP-IE for AMC subchannel configuration in OFDMA PHY.
Purpose	The proposed option makes it possible to specify different burst profiles within one DL-MAP-IE or UL-MAP-IE to provide efficient use of subchannels.
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures < <a href="http://ieee802.org/16/ipr/patents/policy.html">http://ieee802.org/16/ipr/patents/policy.html</a> >, including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair < <a href="mailto:chair@wirelessman.org">mailto:chair@wirelessman.org</a> > as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site < <a href="http://ieee802.org/16/ipr/patents/notices">http://ieee802.org/16/ipr/patents/notices</a> >.

# Changes to DL-MAP-IE and UL-MAP-IE to Support AMC Subchannel in OFDMA PHY

*Haiming Huang, Kemin Li, Titus Lo*

*Walbell Technologies, Inc.*

*Jaehyeong Kim, Anuj Puri, Jun Shen*

*Posdata Corporation*

## 1. Motivation

This document suggests changes to TGe Draft Document IEEE 802.16e-D2 to provide an optional mechanism to indicate different burst profiles within one DL/UL-MAP-IE for AMC subchannel configuration in OFDMA PHY.

As specified in 8.4.6.3 of TGd Draft Document IEEE 802.16d-D4, the AMC subchannel configuration is used as an option in the OFDMA subchannel construction. Given the AMC subchannel configuration, a specific burst profile may enable efficient utilization of a particular subchannel. The proposed option makes it possible to specify different burst profiles within one DL-MAP-IE or UL-MAP-IE.

## 2. Specific Changes Suggested to TGe Draft Document IEEE P802.16e-D2

[Insert the following after 8.4.5.3.7 on page 72]

### 8.4.5.3.8 AMC-DL-MAP-IE

In the DL-MAP, a BS may transmit  $DIUC = 15$  with the AMC-DL-MAP-IE() to indicate a DL-MAP allocation for a connection with different DIUCs.

**Table xxx – AMC-DL-MAP-IE Message Format**

Syntax	Size	Notes
AMC-DL-MAP-IE() {		
Extended DIUC	4 bits	AMC-DL-MAP = 0x05
Length	8 bits	Length in bytes of the following field
AMC region information {	Variable	
if (INC_CID == 1) {		The DL-MAP starts with INC_CID = 0. INC_CID is toggled between 0 and 1 by the CID-SWITCH_IE() (8.4.5.3.7)
N_CID	8 bits	Number of CIDs assigned for this IE
for (n=0; n<N_CID; n++) {		
CID	16 bits	
}		
}		
OFDMA symbol offset	10 bits	
Subchannel offset	5 bits	
Boosting	3 bits	
No. OFDMA symbols	9 bits	
No. Subchannels	5 bits	
for (n = 0; n < No. Subchannels; n++) {		
DIUC	4 bits	
}		
}		
}		

[Insert the following after 8.4.5.3.9 on page 73]

#### 8.4.5.4.3.10 AMC-UL-MAP-IE

In the UL-MAP, a BS may transmit UIUC = 15 with the AMC-UL-MAP-IE() to indicate a UL-MAP allocation for a connection with different UIUCs.

**Table xxx – AMC-UL-MAP-IE Message Format**

Syntax	Size	Notes
AMC-UL-MAP-IE() {		
Extended UIUC	4 bits	AMC-UL-MAP = 0x04
Length	8 bits	Length in bytes of the following field
AMC region information {	Variable	
OFDMA symbol offset	10 bits	
Subchannel offset	5 bits	
Boosting	3 bits	
No. OFDMA symbols	9 bits	
No. Subchannels	5 bits	
for (n = 0; n < No. Subchannels; n++) {		
UIUC	4 bits	
}		
}		
}		