

Project	IEEE 802.16 Broadband Wireless Access Working Group < http://ieee802.org/16 >	
Title	Changes of Reference Symbol Offset for Rotating Pilots in O-FUSC and AMC subchannels	
Date Submitted	2005-03-09	
Source(s)	Jiho Jang, Jeong-Heon Kim, Seungjoo Maeng, Jaeho Jeon	jiho.jang@samsung.com
	<p>Samsung Electronics Co., Ltd. Dong Suwon P.O.Box 105 416, Maetan-3dong, Yeongtong-gu, Suwon-city, Gyeonggi-do, Korea 442-600</p>	
Re:	IEEE P802.16e/D6	
Abstract	Changes of Reference Symbol Offset for Rotating Pilots in O-FUSC and AMC subchannels	
Purpose	Adopting of proposed method into P802.16e	
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.	
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.	
Patent Policy and Procedures	<p>The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures (Version 1.0) <http://ieee802.org/16/ipr/patents/policy.html>, including the statement "IEEE standards may include the known use of patent(s), including patent applications, if there is technical justification in the opinion of the standards-developing committee and provided the IEEE receives assurance from the patent holder that it will license applicants under reasonable terms and conditions for the purpose of implementing the standard."</p> <p>Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair <mailto:r.b.marks@ieee.org> as early as possible, in written or electronic form, of any patents (granted or under application) that may cover technology that is under consideration by or has been approved by IEEE 802.16. The Chair will disclose this notification via the IEEE 802.16 web site <http://ieee802.org/16/ipr/patents/notices>.</p>	

Changes of Reference Symbol Offset for Rotating Pilots in O-FUSC and AMC subchannels

1. Introduction

In the current standard (IEEE 802.16e/D6), the positions of pilot tones for optional FUSC (O-FUSC) and AMC subchannels are rotated with the symbol index value which is referred to the first symbol of the frame, i.e. preamble. Then the pattern of pilot tones may vary according to the start symbol offset of each zone for O-FUSC or AMC.

The fixed pattern of pilot tones regardless of the start symbol offset of each zone can be helpful for easy implementation of subscribers, but there is no performance degradation. In this contribution, the reference symbol offset for rotating pilots in O-FUSC and AMC subchannels is changed to be the very first symbol of each zone.

2. Suggested Text Changes

(1) Make changes in Table 312a, Table 312b, and Table 312c (from page 383, line 1 to page 384, line 28) as follows:

Table 312a—1024-FFT OFDMA downlink carrier allocations – Optional FUSC

Parameters	Value	Comments
Number of DC Subcarriers	1	
Number of Guard Subcarriers, Left	80	
Number of Guard Subcarriers, Right	79	
Number of Used Subcarriers(N_{used}) (Including all possible allocated pilots and the DC subcarrier)	865	
Number of Pilot Subcarriers	96	
Pilot Subcarrier Index	$9k+3m+1$ for $k=0,1\dots95$ and $m=[\text{symbol index}] \bmod 3$	Symbol of index 0 in pilot subcarrier index should be the first symbol of the frame zone .
Number of Data Subcarriers	768	
Number of Data Subcarriers per Subchannel	48	

Table 312b—512-FFT OFDMA downlink carrier allocations – Optional FUSC

Parameters	Value	Comments
Number of DC Subcarriers	1	
Number of Guard Subcarriers, Left	40	
Number of Guard Subcarriers, Right	39	
Number of Used Subcarriers(N_{used}) (Including all possible allocated pilots and the DC subcarrier)	433	
Number of Pilot Subcarriers	48	
Pilot Subcarrier Index	$9k+3m+1$ for $k=0,1\dots47$ and $m=[\text{symbol index}] \bmod 3$	Symbol of index 0 in pilot subcarrier index should be the first symbol of the frame zone .
Number of Data Subcarriers	384	

Number of Data Subcarriers per Subchannel	48	
---	----	--

Table 312c—128-FFT OFDMA FUSC downlink carrier allocations – Optional FUSC

Parameters	Value	Comments
Number of DC Subcarriers	1	
Number of Guard Subcarriers, Left	10	
Number of Guard Subcarriers, Right	9	
Number of Used Subcarriers (N_{used}) (Including all possible allocated pilots and the DC subcarrier)	109	
Number of Pilot Subcarriers	12	
Pilot Subcarrier Index	$9k+3m+1$ for $k=0,1\dots11$ and $m=[\text{symbol index}] \bmod 3$	Symbol of index 0 in pilot subcarrier index should be the first symbol of the frame zone .
Number of Data Subcarriers	96	
Number of Data Subcarriers per Subchannel	48	

(2) Make changes in Table 316a, Table 316b, and Table 316c (from page 400, line 20 to page 401, line 65) as follows:

Table 316a—1024-FFT OFDMA AMC subcarrier allocations

Parameter	Value	Notes
Number of DC Subcarriers	1	
Number of Guard Subcarriers, Left	80	
Number of Guard Subcarriers, Right	79	
Number of Used Subcarriers (N_{used}) (including all possible allocated pilots and the DC subcarrier)	865	
Number of Pilot Subcarriers	96	
Pilot Subcarrier Index	$9k+3m+1$ for $k=0,1\dots95$ and $m=[\text{symbol index}] \bmod 3$	Symbol of index 0 in pilot subcarrier index should be the first symbol of the frame zone .
Number of Data Subcarriers	768	
Number of Bands	24	
Number of Bins per Band	4	
Number of Data Subcarriers per Subchannel	48	

Table 316b—512-FFT OFDMA AMC subcarrier allocations

Parameter	Value	Notes
Number of DC Subcarriers	1	
Number of Guard Subcarriers, Left	40	
Number of Guard Subcarriers, Right	39	
Number of Used Subcarriers (N_{used}) (including all possible allocated pilots and the DC subcarrier)	433	
Number of Pilot Subcarriers	48	
Pilot Subcarrier Index	$9k+3m+1$ for $k=0,1\dots47$ and $m=[\text{symbol index}] \bmod 3$	Symbol of index 0 in pilot subcarrier index should be the first symbol of the frame zone .
Number of Data Subcarriers	384	

Number of Bands	12	
Number of Bins per Band	4	
Number of Data Subcarriers per Subchannel	48	

Table 316c—128-FFT OFDMA AMC subcarrier allocations

Parameter	Value	Notes
Number of DC Subcarriers	1	
Number of Guard Subcarriers, Left	10	
Number of Guard Subcarriers, Right	9	
Number of Used Subcarriers (N_{used}) (including all possible allocated pilots and the DC subcarrier)	109	
Number of Pilot Subcarriers	12	
Pilot Subcarrier Index	$9k+3m+1$ for $k=0,1\dots 11$ and $m=[\text{symbol index}]$ mod 3	Symbol of index 0 in pilot subcarrier index should be the first symbol of the frame zone .
Number of Data Subcarriers	96	
Number of Bands	3	
Number of Bins per Band	4	
Number of Data Subcarriers per Subchannel	48	