

Project	<b>IEEE 802.16 Broadband Wireless Access Working Group</b> < <a href="http://ieee802.org/16">http://ieee802.org/16</a> >	
Title	<b>Uplink HARQ for transparent RS</b>	
Date Submitted	<b>2007-3-5</b>	
Source(s)	Junichi Suga Fujitsu Laboratories Ltd. Kamikodanaka 4-1-1, Kawasaki, 211-8588, Japan	Voice: +81-44-754-2811 Fax: +81-44-754-2786 Email: <a href="mailto:suga.junichi@jp.fujitsu.com">suga.junichi@jp.fujitsu.com</a>
	Michiharu Nakamura Fujitsu Laboratories LTD 5-5, Hikarinooka Yokosuka, Japan. 239-0847	Voice: +81-46-839-5371 Fax: +81-46-839-5560 Email: <a href="mailto:michi@labs.fujitsu.com">michi@labs.fujitsu.com</a>
	Haihong Zheng, Yousuf Saifullah, Shashikant Maheshwari Nokia 6000 Connection Drive, Irving, TX	Voice: 972 894 5000 Fax: Email: <a href="mailto:haihong.1.zheng@nokia.com">haihong.1.zheng@nokia.com</a> <a href="mailto:shashikant.maheshwai@nokia.com">shashikant.maheshwai@nokia.com</a> <a href="mailto:Yousuf.saifullah@nokia.com">Yousuf.saifullah@nokia.com</a>
	Aik Chindapol Nikolaj Marchenko Jimmy Chui Siemens Corporate Research Princeton, NJ, USA	Voice: +1 609 734 3364 Fax: +1 609 734 6565 Email: <a href="mailto:aik.chindapol@siemens.com">aik.chindapol@siemens.com</a>
	Kyu Ha Lee Samsung Thales San 14, Nongseo-Dong, Giheung-Gu, Yongin, Gyeonggi-Do, Korea 449-712	Voice: +82-31-280-9917 Fax: +82-31-280-1562 Email: <a href="mailto:kyuha.lee@samsung.com">kyuha.lee@samsung.com</a>
	Suchang Chae ETRI 161, Gajeong-Dong, Yuseong-Gu, Daejeon, Korea 305-350	Voice: +82-42-860-6642 Fax: +82-42-861-1966 Email: <a href="mailto:schae@etri.re.kr">schae@etri.re.kr</a>
	David Comstock, Huawei Technologies No.98, Lane91, Eshan Road, Shanghai, P.R.C	Voice: +1 858 735 9382 Email: <a href="mailto:dcomstock@huawei.com">dcomstock@huawei.com</a>
	Youngbin Chang Samsung Electronics Co., Ltd.	Voice: +82-31-279-5519 Email: <a href="mailto:yb.chang@samsung.com">yb.chang@samsung.com</a>

416 Maetan-3, Suwon, 442-600,  
Korea

Rakesh Taori  
Samsung Advanced Institute of  
Technology  
C.P.O. Box 1142, Seoul, 100-611,  
Korea

Voice: +82-31-280-9635

Email: [rakesh.taori@samsung.com](mailto:rakesh.taori@samsung.com)

---

Re:	Call for Technical Proposals regarding IEEE Project P802.16j (IEEE 802.16j-07/007r2)
Abstract	This contribution proposes a procedure for handling retransmission of uplink HARQ for transparent RS.
Purpose	Add proposed spec changes in P802.16j Baseline Document
Notice	This document has been prepared to assist IEEE 802.16. It is offered as a basis for discussion and is not binding on the contributing individual(s) or organization(s). The material in this document is subject to change in form and content after further study. The contributor(s) reserve(s) the right to add, amend or withdraw material contained herein.
Release	The contributor grants a free, irrevocable license to the IEEE to incorporate material contained in this contribution, and any modifications thereof, in the creation of an IEEE Standards publication; to copyright in the IEEE's name any IEEE Standards publication even though it may include portions of this contribution; and at the IEEE's sole discretion to permit others to reproduce in whole or in part the resulting IEEE Standards publication. The contributor also acknowledges and accepts that this contribution may be made public by IEEE 802.16.
Patent Policy and Procedures	The contributor is familiar with the IEEE 802.16 Patent Policy and Procedures <a href="http://ieee802.org/16/ipr/patents/policy.html">http://ieee802.org/16/ipr/patents/policy.html</a> , including the statement "IEEE standards may include the known use of patent(s), including patent applications, provided the IEEE receives assurance from the patent holder or applicant with respect to patents essential for compliance with both mandatory and optional portions of the standard." Early disclosure to the Working Group of patent information that might be relevant to the standard is essential to reduce the possibility for delays in the development process and increase the likelihood that the draft publication will be approved for publication. Please notify the Chair <a href="mailto:chair@wirelessman.org">mailto:chair@wirelessman.org</a> as early as possible, in written or electronic form, if patented technology (or technology under patent application) might be incorporated into a draft standard being developed within the IEEE 802.16 Working Group. The Chair will disclose this notification via the IEEE 802.16 web site <a href="http://ieee802.org/16/ipr/patents/notices">http://ieee802.org/16/ipr/patents/notices</a> .

---

# Uplink HARQ for transparent RS

## 1. Introduction

This contribution introduces an uplink HARQ mechanism for transparent type of RS where the RS does not transmit a preamble, FCH and DL/ULMAP directly as shown Figure 1.

In order to reduce the resource for retransmission of HARQ bursts, the RS retransmits the HARQ burst instead of MS, if the RS has the correct HARQ burst.

In this contribution, we propose the procedure for HARQ transmission. We don't suggest the MAP allocation for HARQ burst and an ACK/NAK channel on relay-link.




Figure 1 transparent RS

## 2. Proposed Uplink HARQ procedure

For uplink HARQ, RS decodes a HARQ burst from MS and reports the status of HARQ burst by using ACK/NAK through ACK channel prepared by MR-BS. By the result of ACK channel, the MR-BS decides whether RS or MS retransmits the HARQ burst.

If RS decodes HARQ burst from MS correctly, the RS sends ACK signal to MR-BS. Then the MR-BS allocates bandwidth to RS to relay the HARQ burst. On the other hand, if RS fails to receive the HARQ burst from MS, the RS sends NAK signal to MR-BS. The MR-BS transmits the UL MAP to the MS to retransmit the burst and to the RS to report ACK or NAK.

Figure 2 shows the UL HARQ procedure. MR-BS allocates uplink resource for the MS to transmit HARQ burst and ACKCH for the RS by UL MAP. The RS transmits ACK/NAK signal to the MR-BS which indicates the result of decoding the HARQ burst from MS. If RS fails to receive the HARQ burst from MS, the RS sends NAK signal to MR-BS. Subsequently, the MR-BS requests MS to retransmits the HARQ burst and RS to send ACK/NAK of the retransmission. On the other hand, if RS received the HARQ burst correctly, the RS sends ACK signal to MR-BS. Then the MR-BS requests RS to relay the HARQ burst.




Figure 2 UL HARQ procedure for transparent RS

### 3. Specific text changes

[Insert new sub-clause 6.3.17.5.2]

#### 6.3.17.5.2 UL HARQ for two-hop transparent RS

When the MR-BS chooses to receive an HARQ sub-burst from the MS through the RS, it shall inform the RS and allocate UL transmission for the RS to relay the burst to the MR-BS. If an RS receives a HARQ sub-burst from an MS correctly, the RS saves it for any possible retransmission, and sends an ACK signal to the MR-BS using the ACK channel prepared by MR-BS. Then the MR-BS allocates bandwidth for the RS to relay the HARQ sub-burst. If the MR-BS receives ACK signal from the RS, it sends an ACK on HARQ ACK Bitmap IE to the MS directly. If the MR-BS cannot decode the sub-burst relayed by the RS correctly, the MR-BS sends a NAK to the RS and allocates bandwidth for the RS to retransmit the saved sub-burst. If an RS fails to receive the HARQ sub-burst from MS correctly, the RS sends a NAK signal to the MR-BS and the MR-BS sends a NAK to the MS. Subsequently, the MR-BS may request the MS to retransmit the HARQ sub-burst.

It is also possible for the MR-BS to receive the first transmission from an MS directly. In such a case, the MR-BS informs the RS using the Compact UL-MAP MONITOR IE that it needs to monitor the transmission. The RS, having the information on uplink resource allocations sent in the UL-MAP for the MS, monitors the HARQ sub-burst transmission sent by the MS to the MR-BS directly and attempts to decode it. When the RS receives the HARQ sub burst correctly, the RS saves it for a possible retransmission and sends an ACK to the MR-BS. On receiving the ACK from RS, MR-BS sends an ACK on HARQ ACK Bitmap IE to the MS directly. If the burst is received incorrectly at the RS the RS sends a NAK to MR BS. If MR-BS did not receive the HARQ sub-burst from the MS correctly and received a NAK from the RS, the MR-BS sends NAK on HARQ ACK Bitmap IE to the MS. Subsequently, the MR-BS may request the MS to retransmit the HARQ sub-burst.

*[Insert new subclause 6.3.2.3.43.6.11 and add table:]*

#### **6.3.2.3.43.6.11 UL HARQ for two-hop transparent RS**

The Compact UL-MAP MONITOR IE provides the list of CIDs of the MS whose transmissions need to be monitored in the UL part of the current frame and relayed in the next frame to the MS.

<u>Syntax</u>	<u>Size</u>	<u>Notes</u>
<u>Compact DL-MAP IE() {</u>		
<u>  UL-MAP Type = 7</u>	<u>3 bits</u>	
<u>  UL-MAP subtype</u>	<u>5 bits</u>	
<u>  Number of CIDs</u>	<u>4 bits</u>	<u>Number of CIDs in the IE</u>
<u>  For(i=0; i&lt;Number of CIDs; i++) {</u>		
<u>    CID(i)</u>	<u>16 bits</u>	<u>The CIDs of the connections that RS shall monitor in the current frame</u>
<u>  }</u>		
<u>}</u>		

#### **8.4.5.4.25 HARQ ACK region allocation IE**

*[Insert the following text at the end of the subclause]*

This IE may be used by MR-BS to define an ACK channel region on the R-UL to include one or more ACK channel(s) for RS.

RS receives HARQ UL sub-burst from MS for relaying to MR-BS at frame  $i$  shall transmit the ACK/NAK signal through the ACK Channel in the ACKCH region for UL MS data at frame  $(i+k)$ . The frame offset  $k$  is defined by the “HARQ ACK Delay for UL Burst for MR” field in the UCD message.

*[Insert the following table after table 302t]*

Table 302xx – HARQ ACKCH region allocation for UL MS Data IE

<u>Syntax</u>	<u>Size</u>	<u>Notes</u>
---------------	-------------	--------------

<u>HARQ ACKCH Region for UL Relay IE0 {</u>		
<u>Extended-2 UIUC</u>	<u>4 bits</u>	<u>0xYY</u>
<u>Length</u>	<u>8 bits</u>	<u>Length in bytes</u>
<u>OFDMA Symbol offset</u>	<u>8 bits</u>	
<u>Subchannel offset</u>	<u>7 bits</u>	
<u>No.OFDMA symbols</u>	<u>5 bits</u>	
<u>No.subchannels</u>	<u>4 bits</u>	
<u>}</u>		

#### 4. References

- [1] C802.16j-06\_132, "Relaying methods proposal for 802.16j"
- [2] C802.16j-06\_266r1, "Relay-Assisted Hybrid ARQ"
- [3] C802.16j-06\_197r1, "HARQ with Relays"
- [4] C802.16j-07\_002r1, "DL HARQ with Relays"
- [5] C802.16j-07\_029, "UL HARQ with Relays"